



Manage broadcast domains

ONTAP 9.14.1 REST API reference

NetApp

May 23, 2024

Table of Contents

Manage broadcast domains	1
Network Ethernet broadcast-domains endpoint overview	1
Retrieve broadcast domains for the entire cluster	11
Create a new broadcast domain	17
Delete a broadcast domain	22
Retrieve broadcast domain details	24
Update broadcast domain properties	29

Manage broadcast domains

Network Ethernet broadcast-domains endpoint overview

Overview

A broadcast domain is a collection of Ethernet ports that have layer 2 connectivity. They are used to determine which Ethernet ports can host interfaces of various types. The broadcast domain REST API allows you to retrieve, create, modify, and delete broadcast domains. The broadcast domain APIs do not manage port membership. To add a port to a broadcast domain or to move a port to a different broadcast domain, use PATCH /network/ethernet/ports/<uuid>.</uuid>

Retrieving network Ethernet broadcast domain information

The broadcast domains GET API retrieves and displays relevant information pertaining to the broadcast domains configured in the cluster. The API retrieves the list of all broadcast domains configured in the cluster, or a specific broadcast domain.

Examples

Retrieving all broadcast domains in the cluster

The following output shows the list of all broadcast domains configured in a cluster.

```
# The API:  
/api/network/ethernet/broadcast-domains  
  
# The call:  
curl -X GET "https://<mgmt-ip>/api/network/ethernet/broadcast-domains" -H  
"accept: application/hal+json"  
  
# The response:  
{  
  "records": [  
    {  
      "uuid": "6970c2a9-f34f-11e8-8373-005056bb6b85",  
      "name": "Cluster",  
      "ipspace": {  
        "uuid": "6267eff8-f34f-11e8-8373-005056bb6b85",  
        "name": "Cluster",  
        "_links": {  
          "self": {  
            "href": "/api/network/ipspaces/6267eff8-f34f-11e8-8373-  
005056bb6b85"
```

```

        }
    },
},
"ports": [
{
    "uuid": "626b4d19-f34f-11e8-8373-005056bb6b85",
    "name": "e0a",
    "node": {
        "name": "examplecluster-node01"
    },
    "_links": {
        "self": {
            "href": "/api/network/ethernet/ports/626b4d19-f34f-11e8-8373-005056bb6b85"
        }
    }
},
{
    "uuid": "626b77b9-f34f-11e8-8373-005056bb6b85",
    "name": "e0b",
    "node": {
        "name": "examplecluster-node01"
    },
    "_links": {
        "self": {
            "href": "/api/network/ethernet/ports/626b77b9-f34f-11e8-8373-005056bb6b85"
        }
    }
},
],
"mtu": 9000,
"_links": {
    "self": {
        "href": "/api/network/ethernet/broadcast-domains/6970c2a9-f34f-11e8-8373-005056bb6b85"
    }
}
},
{
    "uuid": "6972416c-f34f-11e8-8373-005056bb6b85",
    "name": "Default",
    "ipspace": {
        "uuid": "5f650349-f34f-11e8-8373-005056bb6b85",
        "name": "Default",
        "_links": {

```

```

    "self": {
        "href": "/api/network/ipspaces/5f650349-f34f-11e8-8373-
005056bb6b85"
    }
},
"ports": [
{
    "uuid": "626bae19-f34f-11e8-8373-005056bb6b85",
    "name": "e0c",
    "node": {
        "name": "examplecluster-node01"
    },
    "_links": {
        "self": {
            "href": "/api/network/ethernet/ports/626bae19-f34f-11e8-8373-
005056bb6b85"
        }
    }
},
{
    "uuid": "626bd677-f34f-11e8-8373-005056bb6b85",
    "name": "e0d",
    "node": {
        "name": "examplecluster-node01"
    },
    "_links": {
        "self": {
            "href": "/api/network/ethernet/ports/626bd677-f34f-11e8-8373-
005056bb6b85"
        }
    }
}
],
"mtu": 1500,
"_links": {
    "self": {
        "href": "/api/network/ethernet/broadcast-domains/6972416c-f34f-
11e8-8373-005056bb6b85"
    }
}
},
"num_records": 2,
"_links": {
    "self": {

```

```
        "href": "/api/network/ethernet/broadcast-domains?fields=*"  
    }  
}  
}
```

Retrieving a specific broadcast domain

The following output shows the response returned when a specific broadcast domain is requested. The system returns an error if there is no broadcast domain with the requested UUID.

```
# The API:  
/api/network/ethernet/broadcast-domains/{uuid}  
  
# The call:  
curl -X GET "https://<mgmt-ip>/api/network/ethernet/broadcast-  
domains/4475a2c8-f8a0-11e8-8d33-005056bb986f/?fields=*" -H "accept:  
application/hal+json"  
  
# The response:  
{  
  "uuid": "4475a2c8-f8a0-11e8-8d33-005056bb986f",  
  "name": "Cluster",  
  "ipspace": {  
    "uuid": "3e518ed5-f8a0-11e8-8d33-005056bb986f",  
    "name": "Cluster",  
    "_links": {  
      "self": {  
        "href": "/api/network/ipspaces/3e518ed5-f8a0-11e8-8d33-005056bb986f"  
      }  
    }  
  },  
  "ports": [  
    {  
      "uuid": "3e539a62-f8a0-11e8-8d33-005056bb986f",  
      "name": "e0a",  
      "node": {  
        "name": "examplecluster-node01"  
      },  
      "_links": {  
        "self": {  
          "href": "/api/network/ethernet/ports/3e539a62-f8a0-11e8-8d33-  
005056bb986f"  
        }  
      }  
    }  
  ]  
}
```

```

    }
},
{
  "uuid": "3e53c94a-f8a0-11e8-8d33-005056bb986f",
  "name": "e0b",
  "node": {
    "name": "examplecluster-node01"
  },
  "_links": {
    "self": {
      "href": "/api/network/ethernet/ports/3e53c94a-f8a0-11e8-8d33-005056bb986f"
    }
  }
}
],
"mtu": 9000,
"_links": {
  "self": {
    "href": "/api/network/ethernet/broadcast-domains/4475a2c8-f8a0-11e8-8d33-005056bb986f/"
  }
}
}

```

Retrieving all broadcast domains with a specific name

The following output shows the response returned when broadcast domains with a specific name in any IPspace are requested.

```

# The API:
/api/network/ethernet/broadcast-domains

# The call:
curl -X GET "https://10.224.87.121/api/network/ethernet/broadcast-
domains/?name=bd1" -H "accept: application/hal+json"

# The response:
{
  "records": [
    {
      "uuid": "66b607e5-4bee-11e9-af6a-005056bb13c0",
      "name": "bd1",
      "_links": {
        "self": {
          "href": "/api/network/ethernet/broadcast-domains/66b607e5-4bee-
11e9-af6a-005056bb13c0"
        }
      }
    }
  ],
  "num_records": 1,
  "_links": {
    "self": {
      "href": "/api/network/ethernet/broadcast-domains/?name=bd1"
    }
  }
}

```

Retrieving the broadcast domains for an IPspace

The following output shows the response returned when the broadcast domains for a specified IPspace are requested.

```

# The API:
/api/network/ethernet/broadcast-domains

# The call:
curl -X GET "https://10.224.87.121/api/network/ethernet/broadcast-
domains/?ipspace.name=Cluster&fields=*" -H "accept: application/hal+json"

# The response:

```

```
{
  "records": [
    {
      "uuid": "ae69070c-4bed-11e9-af6a-005056bb13c0",
      "name": "Cluster",
      "ipspace": {
        "uuid": "ac466a88-4bed-11e9-af6a-005056bb13c0",
        "name": "Cluster",
        "_links": {
          "self": {
            "href": "/api/network/ipspaces/ac466a88-4bed-11e9-af6a-005056bb13c0"
          }
        }
      },
      "ports": [
        {
          "uuid": "acd67884-4bed-11e9-af6a-005056bb13c0",
          "name": "e0a",
          "node": {
            "name": "examplecluster-node-1"
          },
          "_links": {
            "self": {
              "href": "/api/network/ethernet/ports/acd67884-4bed-11e9-af6a-005056bb13c0"
            }
          }
        },
        {
          "uuid": "ace1a36f-4bed-11e9-af6a-005056bb13c0",
          "name": "e0b",
          "node": {
            "name": "examplecluster-node-1"
          },
          "_links": {
            "self": {
              "href": "/api/network/ethernet/ports/ace1a36f-4bed-11e9-af6a-005056bb13c0"
            }
          }
        }
      ],
      "mtu": 1500,
      "_links": {
        "self": {

```

```
        "href": "/api/network/ethernet/broadcast-domains/ae69070c-4bed-  
11e9-af6a-005056bb13c0"  
    }  
}  
}  
]  
,"num_records": 1,  
"_links": {  
    "self": {  
        "href": "/api/network/ethernet/broadcast-  
domains/?ipspace.name=Cluster&fields=*"  
    }  
}
```

Creating network Ethernet broadcast domains

You can use the POST API to create broadcast domains.

Example

Creating a new broadcast domain

The following example shows how to create a broadcast domain with a name of 'bd1' and an MTU of 1500.

```
# The API:  
/api/network/ethernet/broadcast-domains  
  
# The call:  
curl -X POST "https://<mgmt-ip>/api/network/ethernet/broadcast-  
domains?return_records=true" -H "accept: application/hal+json" -d '{  
"name": "bd1", "mtu": 1500 }'  
  
# The response:  
{  
  "num_records": 1,  
  "records": [  
    {  
      "name": "bd1",  
      "mtu": 1500,  
      "_links": {  
        "self": {  
          "href": "/api/network/ethernet/broadcast-domains/"  
        }  
      }  
    }  
  ]  
}
```

Updating network Ethernet broadcast domains

You can use the PATCH API to update the attributes of broadcast domains.

Examples

Updating the name and MTU of a specific broadcast domain

The following example shows how the PATCH request changes the broadcast domain name to 'bd2' and the broadcast domain MTU to 9000.

```
# The API:  
/api/network/ethernet/broadcast-domains/{uuid}  
  
# The call:  
curl -X PATCH "https://<mgmt-ip>/api/network/ethernet/broadcast-  
domains/6cde03b2-f8a2-11e8-8d33-005056bb986f/" -d '{ "name": "bd2", "mtu":  
9000 }'  
{  
}
```

Updating the IPspace of a specific broadcast domain

The following example shows how the PATCH request changes the IPspace of a broadcast domain to 'ipspace2'.

```
# The API:  
/api/network/ethernet/broadcast-domains/{uuid}  
  
# The call:  
curl -X PATCH "https://<mgmt-ip>/api/network/ethernet/broadcast-  
domains/c6fe2541-61f4-11e9-a66e-005056bbe83e" -d '{ "ipspace" : { "name" :  
"ipspace2" } }'  
{  
}
```

Deleting network Ethernet broadcast domains

You can use the DELETE API to delete a broadcast domain from the cluster configuration.

Example

Deleting a specific broadcast domain

The following DELETE request deletes a broadcast domain.

```
# The API:  
/api/network/ethernet/broadcast-domains/{uuid}  
  
# The call:  
curl -X DELETE "https://<mgmt-ip>/api/network/ethernet/broadcast-  
domains/6cde03b2-f8a2-11e8-8d33-005056bb986f/"
```

Retrieve broadcast domains for the entire cluster

GET /network/ethernet/broadcast-domains

Introduced In: 9.6

Retrieves a collection of broadcast domains for the entire cluster.

Related ONTAP commands

- network port broadcast-domain show

Parameters

Name	Type	In	Required	Description
uuid	string	query	False	Filter by uuid
ports.uuid	string	query	False	Filter by ports.uuid
ports.name	string	query	False	Filter by ports.name
ports.node.name	string	query	False	Filter by ports.node.name
mtu	integer	query	False	Filter by mtu <ul style="list-style-type: none"> • Min value: 68
ipspace.uuid	string	query	False	Filter by ipspace.uuid
ipspace.name	string	query	False	Filter by ipspace.name
name	string	query	False	Filter by name

Name	Type	In	Required	Description
fields	array[string]	query	False	Specify the fields to return.
max_records	integer	query	False	Limit the number of records returned.
return_records	boolean	query	False	<p>The default is true for GET calls. When set to false, only the number of records is returned.</p> <ul style="list-style-type: none"> Default value: 1
return_timeout	integer	query	False	<p>The number of seconds to allow the call to execute before returning. When iterating over a collection, the default is 15 seconds. ONTAP returns earlier if either max records or the end of the collection is reached.</p> <ul style="list-style-type: none"> Min value: 0 Default value: 1 Max value: 120
order_by	array[string]	query	False	Order results by specified fields and optional [asc]

Response

```
Status: 200, Ok
```

Name	Type	Description
_links	_links	
num_records	integer	Number of records
records	array[broadcast_domain]	

Example response

```
{  
    "_links": {  
        "next": {  
            "href": "/api/resourcelink"  
        },  
        "self": {  
            "href": "/api/resourcelink"  
        }  
    },  
    "num_records": 1,  
    "records": {  
        "_links": {  
            "self": {  
                "href": "/api/resourcelink"  
            }  
        },  
        "ipspace": {  
            "_links": {  
                "self": {  
                    "href": "/api/resourcelink"  
                }  
            },  
            "name": "exchange",  
            "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
        },  
        "mtu": 1500,  
        "name": "bd1",  
        "ports": {  
            "_links": {  
                "self": {  
                    "href": "/api/resourcelink"  
                }  
            },  
            "name": "elb",  
            "node": {  
                "name": "node1"  
            },  
            "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
        },  
        "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
    }  
}
```

Error

Status: Default, Error

Name	Type	Description
error	returned_error	

Example error

```
{
  "error": {
    "arguments": {
      "code": "string",
      "message": "string"
    },
    "code": "4",
    "message": "entry doesn't exist",
    "target": "uuid"
  }
}
```

Definitions

See Definitions

href

Name	Type	Description
href	string	

_links

Name	Type	Description
next	href	
self	href	

_links

Name	Type	Description
self	href	

ipspace

Applies to both SVM and cluster-scoped objects. Either the UUID or name is supplied on input.

Name	Type	Description
_links	_links	
name	string	IPspace name
uuid	string	IPspace UUID

node

Name	Type	Description
name	string	Name of node on which the port is located.

ports

Port UUID along with readable names

Name	Type	Description
_links	_links	
name	string	
node	node	
uuid	string	

broadcast_domain

Set of ports that will receive a broadcast Ethernet packet from any of them

Name	Type	Description
_links	_links	
ipspace	ipspace	Applies to both SVM and cluster-scoped objects. Either the UUID or name is supplied on input.
mtu	integer	Maximum transmission unit, largest packet size on this network
name	string	Name of the broadcast domain, scoped to its IPspace
ports	array[ports]	Ports that belong to the broadcast domain
uuid	string	Broadcast domain UUID

error_arguments

Name	Type	Description
code	string	Argument code
message	string	Message argument

returned_error

Name	Type	Description
arguments	array[error_arguments]	Message arguments
code	string	Error code
message	string	Error message
target	string	The target parameter that caused the error.

Create a new broadcast domain

POST /network/ethernet/broadcast-domains

Introduced In: 9.6

Creates a new broadcast domain.

Required properties

- name - Name of the broadcast-domain to create.
- mtu - Maximum transmission unit (MTU) of the broadcast domain.

Recommended optional properties

- ipspace.name or ipspace.uuid - IPspace the broadcast domain belongs to.

Default property values

If not specified in POST, the following default property values are assigned:

- ipspace - *Default*

Related ONTAP commands

- network port broadcast-domain create

Parameters

Name	Type	In	Required	Description
return_records	boolean	query	False	<p>The default is false. If set to true, the records are returned.</p> <ul style="list-style-type: none">• Default value:

Request Body

Name	Type	Description
_links	_links	
ipspace	ipspace	Applies to both SVM and cluster-scoped objects. Either the UUID or name is supplied on input.

Name	Type	Description
mtu	integer	Maximum transmission unit, largest packet size on this network
name	string	Name of the broadcast domain, scoped to its IPspace
ports	array[ports]	Ports that belong to the broadcast domain
uuid	string	Broadcast domain UUID

Example request

```
{  
    "_links": {  
        "self": {  
            "href": "/api/resourcelink"  
        }  
    },  
    "ipspace": {  
        "_links": {  
            "self": {  
                "href": "/api/resourcelink"  
            }  
        },  
        "name": "exchange",  
        "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
    },  
    "mtu": 1500,  
    "name": "bd1",  
    "ports": {  
        "_links": {  
            "self": {  
                "href": "/api/resourcelink"  
            }  
        },  
        "name": "elb",  
        "node": {  
            "name": "node1"  
        },  
        "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
    },  
    "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
}
```

Response

Status: 201, Created

Headers

Name	Description	Type
Location	Useful for tracking the resource location	string

Error

Status: Default

ONTAP Error Response Codes

Error Code	Description
1377267	The specified IPspace does not exist.
1377596	The Cluster IPspace cannot contain more than one broadcast domain. Modifying the system IPspace Cluster is not supported.
1966460	The provided MTU was either too large or too small.
1967082	The specified ipspace.name does not match the IPspace name of ipspace.uuid.
1967102	A POST operation might have left the configuration in an inconsistent state. Check the configuration.
53281982	The specified broadcast domain name is reserved by the system.

Also see the table of common errors in the [Response body](#) overview section of this documentation.

Name	Type	Description
error	returned_error	

Example error

```
{  
  "error": {  
    "arguments": {  
      "code": "string",  
      "message": "string"  
    },  
    "code": "4",  
    "message": "entry doesn't exist",  
    "target": "uuid"  
  }  
}
```

Definitions

See Definitions

href

Name	Type	Description
href	string	

_links

Name	Type	Description
self	href	

ipspace

Applies to both SVM and cluster-scoped objects. Either the UUID or name is supplied on input.

Name	Type	Description
_links	_links	
name	string	IPspace name
uuid	string	IPspace UUID

node

Name	Type	Description
name	string	Name of node on which the port is located.

ports

Port UUID along with readable names

Name	Type	Description
_links	_links	
name	string	
node	node	
uuid	string	

broadcast_domain

Set of ports that will receive a broadcast Ethernet packet from any of them

Name	Type	Description
_links	_links	

Name	Type	Description
ipspace	ipspace	Applies to both SVM and cluster-scoped objects. Either the UUID or name is supplied on input.
mtu	integer	Maximum transmission unit, largest packet size on this network
name	string	Name of the broadcast domain, scoped to its IPspace
ports	array[ports]	Ports that belong to the broadcast domain
uuid	string	Broadcast domain UUID

error_arguments

Name	Type	Description
code	string	Argument code
message	string	Message argument

returned_error

Name	Type	Description
arguments	array[error_arguments]	Message arguments
code	string	Error code
message	string	Error message
target	string	The target parameter that caused the error.

Delete a broadcast domain

`DELETE /network/ethernet/broadcast-domains/{uuid}`

Introduced In: 9.6

Deletes a broadcast domain.

Related ONTAP commands

- network port broadcast-domain delete

Parameters

Name	Type	In	Required	Description
uuid	string	path	True	Broadcast domain UUID

Response

```
Status: 200, Ok
```

Error

```
Status: Default
```

ONTAP Error Response Codes

Error Code	Description
1967103	A broadcast domain with ports cannot be deleted.

Also see the table of common errors in the [Response body](#) overview section of this documentation.

Name	Type	Description
error	returned_error	

Example error

```
{
  "error": {
    "arguments": {
      "code": "string",
      "message": "string"
    },
    "code": "4",
    "message": "entry doesn't exist",
    "target": "uuid"
  }
}
```

Definitions

See Definitions

error_arguments

Name	Type	Description
code	string	Argument code
message	string	Message argument

returned_error

Name	Type	Description
arguments	array[error_arguments]	Message arguments
code	string	Error code
message	string	Error message
target	string	The target parameter that caused the error.

Retrieve broadcast domain details

GET /network/ethernet/broadcast-domains/{uuid}

Introduced In: 9.6

Retrieves details of a broadcast domain.

Related ONTAP commands

- network port broadcast-domain show

Parameters

Name	Type	In	Required	Description
uuid	string	path	True	Broadcast domain UUID
fields	array[string]	query	False	Specify the fields to return.

Response

Status: 200, Ok

Name	Type	Description
_links	_links	
ipspace	ipspace	Applies to both SVM and cluster-scoped objects. Either the UUID or name is supplied on input.
mtu	integer	Maximum transmission unit, largest packet size on this network
name	string	Name of the broadcast domain, scoped to its IPspace
ports	array[ports]	Ports that belong to the broadcast domain
uuid	string	Broadcast domain UUID

Example response

```
{  
  "_links": {  
    "self": {  
      "href": "/api/resourcelink"  
    }  
  },  
  "ipspace": {  
    "_links": {  
      "self": {  
        "href": "/api/resourcelink"  
      }  
    },  
    "name": "exchange",  
    "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
  },  
  "mtu": 1500,  
  "name": "bd1",  
  "ports": {  
    "_links": {  
      "self": {  
        "href": "/api/resourcelink"  
      }  
    },  
    "name": "elb",  
    "node": {  
      "name": "node1"  
    },  
    "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
  },  
  "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
}
```

Error

Status: Default, Error

Name	Type	Description
error	returned_error	

Example error

```
{  
  "error": {  
    "arguments": {  
      "code": "string",  
      "message": "string"  
    },  
    "code": "4",  
    "message": "entry doesn't exist",  
    "target": "uuid"  
  }  
}
```

Definitions

See Definitions

href

Name	Type	Description
href	string	

_links

Name	Type	Description
self	href	

ipspace

Applies to both SVM and cluster-scoped objects. Either the UUID or name is supplied on input.

Name	Type	Description
_links	_links	
name	string	IPspace name
uuid	string	IPspace UUID

node

Name	Type	Description
name	string	Name of node on which the port is located.

ports

Port UUID along with readable names

Name	Type	Description
_links	_links	
name	string	
node	node	
uuid	string	

error_arguments

Name	Type	Description
code	string	Argument code

Name	Type	Description
message	string	Message argument

returned_error

Name	Type	Description
arguments	array[error_arguments]	Message arguments
code	string	Error code
message	string	Error message
target	string	The target parameter that caused the error.

Update broadcast domain properties

PATCH /network/ethernet/broadcast-domains/{uuid}

Introduced In: 9.6

Updates the properties of a broadcast domain.

Related ONTAP commands

- network port broadcast-domain modify
- network port broadcast-domain rename
- network port broadcast-domain move

Parameters

Name	Type	In	Required	Description
uuid	string	path	True	Broadcast domain UUID

Request Body

Name	Type	Description
_links	_links	

Name	Type	Description
ipspace	ipspace	Applies to both SVM and cluster-scoped objects. Either the UUID or name is supplied on input.
mtu	integer	Maximum transmission unit, largest packet size on this network
name	string	Name of the broadcast domain, scoped to its IPspace
ports	array[ports]	Ports that belong to the broadcast domain
uuid	string	Broadcast domain UUID

Example request

```
{  
    "_links": {  
        "self": {  
            "href": "/api/resourcelink"  
        }  
    },  
    "ipspace": {  
        "_links": {  
            "self": {  
                "href": "/api/resourcelink"  
            }  
        },  
        "name": "exchange",  
        "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
    },  
    "mtu": 1500,  
    "name": "bd1",  
    "ports": {  
        "_links": {  
            "self": {  
                "href": "/api/resourcelink"  
            }  
        },  
        "name": "elb",  
        "node": {  
            "name": "node1"  
        },  
        "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
    },  
    "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
}
```

Response

Status: 200, Ok

Error

Status: Default

ONTAP Error Response Codes

Error Code	Description
1376484	Cannot change the MTU of a VLAN to be greater than the MTU of the port hosting it.
1377267	The specified IPspace does not exist.
1377269	Failed to lookup the specified IPspace.
1377560	Broadcast domain already exists in specified IPspace.
1377575	Remove associated subnets before deleting this broadcast domain.
1377605	Moving the system-generated broadcast domain to another IPspace is not supported.
1966460	The specified MTU is either too large or too small.
1967082	The specified ipspace.name does not match the IPspace name of ipspace.uuid.
1967150	The specified ipspace.uuid is not valid.
1967151	The specified ipspace.uuid and ipspace.name do not match.
1967152	Patching IPspace for a broadcast domain requires an effective cluster version of 9.7 or later.
53280884	The MTU of the broadcast domain cannot be modified on this platform.
53282013	Broadcast domain cannot be renamed because the name is reserved by the system.

Also see the table of common errors in the [Response body](#) overview section of this documentation.

Name	Type	Description
error	returned_error	

Example error

```
{  
  "error": {  
    "arguments": {  
      "code": "string",  
      "message": "string"  
    },  
    "code": "4",  
    "message": "entry doesn't exist",  
    "target": "uuid"  
  }  
}
```

Definitions

See Definitions

href

Name	Type	Description
href	string	

_links

Name	Type	Description
self	href	

ipspace

Applies to both SVM and cluster-scoped objects. Either the UUID or name is supplied on input.

Name	Type	Description
_links	_links	
name	string	IPspace name
uuid	string	IPspace UUID

node

Name	Type	Description
name	string	Name of node on which the port is located.

ports

Port UUID along with readable names

Name	Type	Description
_links	_links	
name	string	
node	node	
uuid	string	

broadcast_domain

Set of ports that will receive a broadcast Ethernet packet from any of them

Name	Type	Description
_links	_links	

Name	Type	Description
ipspace	ipspace	Applies to both SVM and cluster-scoped objects. Either the UUID or name is supplied on input.
mtu	integer	Maximum transmission unit, largest packet size on this network
name	string	Name of the broadcast domain, scoped to its IPspace
ports	array[ports]	Ports that belong to the broadcast domain
uuid	string	Broadcast domain UUID

error_arguments

Name	Type	Description
code	string	Argument code
message	string	Message argument

returned_error

Name	Type	Description
arguments	array[error_arguments]	Message arguments
code	string	Error code
message	string	Error message
target	string	The target parameter that caused the error.

Copyright information

Copyright © 2024 NetApp, Inc. All Rights Reserved. Printed in the U.S. No part of this document covered by copyright may be reproduced in any form or by any means—graphic, electronic, or mechanical, including photocopying, recording, taping, or storage in an electronic retrieval system—with prior written permission of the copyright owner.

Software derived from copyrighted NetApp material is subject to the following license and disclaimer:

THIS SOFTWARE IS PROVIDED BY NETAPP “AS IS” AND WITHOUT ANY EXPRESS OR IMPLIED WARRANTIES, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE, WHICH ARE HEREBY DISCLAIMED. IN NO EVENT SHALL NETAPP BE LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO, PROCUREMENT OF SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA, OR PROFITS; OR BUSINESS INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE) ARISING IN ANY WAY OUT OF THE USE OF THIS SOFTWARE, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE.

NetApp reserves the right to change any products described herein at any time, and without notice. NetApp assumes no responsibility or liability arising from the use of products described herein, except as expressly agreed to in writing by NetApp. The use or purchase of this product does not convey a license under any patent rights, trademark rights, or any other intellectual property rights of NetApp.

The product described in this manual may be protected by one or more U.S. patents, foreign patents, or pending applications.

LIMITED RIGHTS LEGEND: Use, duplication, or disclosure by the government is subject to restrictions as set forth in subparagraph (b)(3) of the Rights in Technical Data -Noncommercial Items at DFARS 252.227-7013 (FEB 2014) and FAR 52.227-19 (DEC 2007).

Data contained herein pertains to a commercial product and/or commercial service (as defined in FAR 2.101) and is proprietary to NetApp, Inc. All NetApp technical data and computer software provided under this Agreement is commercial in nature and developed solely at private expense. The U.S. Government has a non-exclusive, non-transferrable, nonsublicensable, worldwide, limited irrevocable license to use the Data only in connection with and in support of the U.S. Government contract under which the Data was delivered. Except as provided herein, the Data may not be used, disclosed, reproduced, modified, performed, or displayed without the prior written approval of NetApp, Inc. United States Government license rights for the Department of Defense are limited to those rights identified in DFARS clause 252.227-7015(b) (FEB 2014).

Trademark information

NETAPP, the NETAPP logo, and the marks listed at <http://www.netapp.com/TM> are trademarks of NetApp, Inc. Other company and product names may be trademarks of their respective owners.