



# Manage storage tape devices

ONTAP 9.14.1 REST API reference

NetApp  
May 23, 2024

# Table of Contents

- Manage storage tape devices ..... 1
  - Storage tape-devices endpoint overview ..... 1
  - Retrieve tape devices ..... 10
  - Retrieve a tape device ..... 19
  - Update a tape device ..... 25

# Manage storage tape devices

## Storage tape-devices endpoint overview

### Retrieving storage tape information

The storage tape GET API retrieves all of the tapes in the cluster.

### Examples

#### 1) Retrieving a list of tapes from the cluster

The following example returns the list of tapes in the cluster:

```
# The API:
/api/storage/tape-devices

# The call:
curl -X GET "https://<mgmt-ip>/api/storage/tape-devices" -H "accept:
application/hal+json"

# The response:
{
  "records": [
    {
      "node": {
        "uuid": "4083be52-5315-11eb-a839-00a0985ebbe7",
        "name": "st-8020-1-01",
        "_links": {
          "self": {
            "href": "/api/cluster/nodes/4083be52-5315-11eb-a839-
00a0985ebbe7"
          }
        }
      },
      "device_id": "2d.0",
      "_links": {
        "self": {
          "href": "/api/storage/tape-devices/4083be52-5315-11eb-a839-
00a0985ebbe7/2d.0"
        }
      }
    }
  ],
}
```

```

{
  "node": {
    "uuid": "4083be52-5315-11eb-a839-00a0985ebbe7",
    "name": "st-8020-1-01",
    "_links": {
      "self": {
        "href": "/api/cluster/nodes/4083be52-5315-11eb-a839-00a0985ebbe7"
      }
    }
  },
  "device_id": "2d.0L1",
  "_links": {
    "self": {
      "href": "/api/storage/tape-devices/4083be52-5315-11eb-a839-00a0985ebbe7/2d.0L1"
    }
  }
},
{
  "node": {
    "uuid": "4083be52-5315-11eb-a839-00a0985ebbe7",
    "name": "st-8020-1-01",
    "_links": {
      "self": {
        "href": "/api/cluster/nodes/4083be52-5315-11eb-a839-00a0985ebbe7"
      }
    }
  },
  "device_id": "qeg-tape-brocade2-8g:0.126",
  "_links": {
    "self": {
      "href": "/api/storage/tape-devices/4083be52-5315-11eb-a839-00a0985ebbe7/qeg-tape-brocade2-8g%3A0.126"
    }
  }
},
{
  "node": {
    "uuid": "4083be52-5315-11eb-a839-00a0985ebbe7",
    "name": "st-8020-1-01",
    "_links": {
      "self": {
        "href": "/api/cluster/nodes/4083be52-5315-11eb-a839-00a0985ebbe7"
      }
    }
  }
}

```

```

    }
  },
  "device_id": "stsw-broc6510-01:11.126",
  "_links": {
    "self": {
      "href": "/api/storage/tape-devices/4083be52-5315-11eb-a839-00a0985ebbe7/stsw-broc6510-01%3A11.126"
    }
  }
},
{
  "node": {
    "uuid": "4083be52-5315-11eb-a839-00a0985ebbe7",
    "name": "st-8020-1-01",
    "_links": {
      "self": {
        "href": "/api/cluster/nodes/4083be52-5315-11eb-a839-00a0985ebbe7"
      }
    }
  },
  "device_id": "stsw-broc6510-01:15.126",
  "_links": {
    "self": {
      "href": "/api/storage/tape-devices/4083be52-5315-11eb-a839-00a0985ebbe7/stsw-broc6510-01%3A15.126"
    }
  }
},
{
  "node": {
    "uuid": "4083be52-5315-11eb-a839-00a0985ebbe7",
    "name": "st-8020-1-01",
    "_links": {
      "self": {
        "href": "/api/cluster/nodes/4083be52-5315-11eb-a839-00a0985ebbe7"
      }
    }
  },
  "device_id": "stsw-broc6510-01:15.126L1",
  "_links": {
    "self": {
      "href": "/api/storage/tape-devices/4083be52-5315-11eb-a839-00a0985ebbe7/stsw-broc6510-01%3A15.126L1"
    }
  }
}

```

```

    }
  },
  {
    "node": {
      "uuid": "4083be52-5315-11eb-a839-00a0985ebbe7",
      "name": "st-8020-1-01",
      "_links": {
        "self": {
          "href": "/api/cluster/nodes/4083be52-5315-11eb-a839-00a0985ebbe7"
        }
      }
    },
    "device_id": "stsw-broc6510-01:22.126",
    "_links": {
      "self": {
        "href": "/api/storage/tape-devices/4083be52-5315-11eb-a839-00a0985ebbe7/stsw-broc6510-01%3A22.126"
      }
    }
  },
  {
    "node": {
      "uuid": "4083be52-5315-11eb-a839-00a0985ebbe7",
      "name": "st-8020-1-01",
      "_links": {
        "self": {
          "href": "/api/cluster/nodes/4083be52-5315-11eb-a839-00a0985ebbe7"
        }
      }
    },
    "device_id": "stsw-broc6510-01:23.126",
    "_links": {
      "self": {
        "href": "/api/storage/tape-devices/4083be52-5315-11eb-a839-00a0985ebbe7/stsw-broc6510-01%3A23.126"
      }
    }
  },
],
"num_records": 7,
"_links": {
  "self": {
    "href": "/api/storage/tape-devices"
  }
}

```

```
}  
}  
}
```

## 2) Retrieving a specific tape device from the cluster

The following example returns the requested tape device. If there is no tape with the requested UID, an error is returned.

```
# The API:  
/api/storage/tape-devices/{node.uuid}/{device_id}  
  
# The call:  
curl -X GET "https://<mgmt-ip>/api/storage/tape-devices/5f5275eb-5315-11eb-8ac4-00a0985e0dcf/2d.0" -H "accept: application/hal+json"  
  
# The response:  
{  
  "node": {  
    "uuid": "5f5275eb-5315-11eb-8ac4-00a0985e0dcf",  
    "name": "st-8020-1-02",  
    "_links": {  
      "self": {  
        "href": "/api/cluster/nodes/5f5275eb-5315-11eb-8ac4-00a0985e0dcf"  
      }  
    }  
  },  
  "device_id": "2d.0",  
  "type": "tape",  
  "description": "IBM LTO-6 ULT3580",  
  "alias": {  
    "name": "st7",  
    "mapping": "SN[1068000245]"  
  },  
  "aliases": [  
    {  
      "name": "st7",  
      "mapping": "SN[1068000245]"  
    }  
  ],  
  "wwnn": "5001697722ee0010",  
  "wwpn": "5001697722ee0011",  
  "serial_number": "1068000245",
```

```
"interface": "sas",
"device_state": "offline",
"formats": [
  "LTO-4/5 Native Density",
  "LTO-4/5 Compressed",
  "LTO-6 2.5TB",
  "LTO-6 6.25TB Compressed"
],
"storage_port": {
  "name": "2d"
},
"file_number": -1,
"block_number": -1,
"residual_count": 0,
"density": "low",
"device_names": [
  {
    "rewind_device": "rst0l",
    "no_rewind_device": "nrst0l",
    "unload_reload_device": "urst0l"
  },
  {
    "rewind_device": "rst0m",
    "no_rewind_device": "nrst0m",
    "unload_reload_device": "urst0m"
  },
  {
    "rewind_device": "rst0h",
    "no_rewind_device": "nrst0h",
    "unload_reload_device": "urst0h"
  },
  {
    "rewind_device": "rst0a",
    "no_rewind_device": "nrst0a",
    "unload_reload_device": "urst0a"
  }
],
"reservation_type": "off",
"_links": {
  "self": {
    "href": "/api/storage/tape-devices/5f5275eb-5315-11eb-8ac4-00a0985e0dcf/2d.0"
  }
}
}
```



---

## Updating a tape device

The tape PATCH API allows the tape device to be set online or offline, positioned, and given an alias.

---

### Examples

#### 1) Taking a tape device offline

The following example takes a tape device offline:

---

```
# The API:
/api/storage/tape-devices/{node.uuid}/{device_id}

# The call:
curl -X PATCH "https://<mgmt-ip>/api/storage/tape-devices/5f5275eb-5315-11eb-8ac4-00a0985e0dcf/2d.0" -H "accept: application/hal+json" -H "Content-Type: application/hal_json" -d '{"online": "false"}'

# The response:
{
  "job": {
    "uuid": "9e544626-306e-11ec-8c2e-00a098b81daa",
    "_links": {
      "self": {
        "href": "/api/cluster/jobs/9e544626-306e-11ec-8c2e-00a098b81daa"
      }
    }
  }
}
```

---

#### 2) Bringing a tape device online

The following example brings a tape device online:

---

```
# The API:
/api/storage/tape-devices/{node.uuid}/{device_id}

# The call:
curl -X PATCH "https://<mgmt-ip>/api/storage/tape-devices/5f5275eb-5315-11eb-8ac4-00a0985e0dcf/2d.0" -H "accept: application/hal+json" -H "Content-Type: application/hal_json" -d '{"online": "true"}'

# The response:
{
  "job": {
    "uuid": "9e544626-306e-11ec-8c2e-00a098b81daa",
    "_links": {
      "self": {
        "href": "/api/cluster/jobs/9e544626-306e-11ec-8c2e-00a098b81daa"
      }
    }
  }
}
```

### 3) Giving a tape device an alias

The following example assigns an alias to a tape device:

```
# The API:
/api/storage/tape-devices/{node.uuid}/{device_id}

# The call:
curl -X PATCH "https://<mgmt-ip>/api/storage/tape-devices/5f5275eb-5315-11eb-8ac4-00a0985e0dcf/2d.0" -H "accept: application/hal+json" -H "Content-Type: application/hal_json" -d '{"aliases": [{"name": "st0"}]}'

# The response:
{
}
```

### 4) Removing a tape device's aliases

The following example clears any aliases previously assigned to a tape device:

```
# The API:
/api/storage/tape-devices/{node.uuid}/{device_id}

# The call:
curl -X PATCH "https://<mgmt-ip>/api/storage/tape-devices/5f5275eb-5315-
11eb-8ac4-00a0985e0dcf/2d.0" -H "accept: application/hal+json" -H
"Content-Type: application/hal_json" -d '{"aliases": []}'

# The response:
{
}
```

---

## 5) Rewinding a tape device

The following example rewinds a tape device:

```
# The API:
/api/storage/tape-devices/{node.uuid}/{device_id}

# The call:
curl -X PATCH "https://<mgmt-ip>/api/storage/tape-devices/5f5275eb-5315-
11eb-8ac4-00a0985e0dcf/2d.0" -H "accept: application/hal+json" -H
"Content-Type: application/hal_json" -d '{"position": {"operation":
"rewind"}}'

# The response:
{
  "job": {
    "uuid": "9e544626-306e-11ec-8c2e-00a098b81daa",
    "_links": {
      "self": {
        "href": "/api/cluster/jobs/9e544626-306e-11ec-8c2e-00a098b81daa"
      }
    }
  }
}
```

---

## 6) Forwarding the tape five files

The following example moves the tape forward five file records:

```

# The API:
/api/storage/tape-devices/{node.uuid}/{device_id}

# The call:
curl -X PATCH "https://<mgmt-ip>/api/storage/tape-devices/5f5275eb-5315-11eb-8ac4-00a0985e0dcf/2d.0" -H "accept: application/hal+json" -H "Content-Type: application/hal_json" -d '{"position": {"operation": "fsf", "count": 5}}'

# The response:
{
  "job": {
    "uuid": "954c20d5-306e-11ec-8c2e-00a098b81daa",
    "_links": {
      "self": {
        "href": "/api/cluster/jobs/954c20d5-306e-11ec-8c2e-00a098b81daa"
      }
    }
  }
}

```

## Retrieve tape devices

GET /storage/tape-devices

**Introduced In:** 9.9

Retrieves a collection of tape devices.

### Related ONTAP commands

- `storage tape show`

### Learn more

- [DOC /storage/tape-devices](#)

### Parameters

Name	Type	In	Required	Description
density	string	query	False	Filter by density <ul style="list-style-type: none"> <li>• Introduced in: 9.11</li> </ul>

Name	Type	In	Required	Description
description	string	query	False	Filter by description
block_number	integer	query	False	Filter by block_number
reservation_type	string	query	False	Filter by reservation_type
file_number	integer	query	False	Filter by file_number
online	boolean	query	False	Filter by online  • Introduced in: 9.11
node.name	string	query	False	Filter by node.name
node.uuid	string	query	False	Filter by node.uuid
alias.name	string	query	False	Filter by alias.name
alias.mapping	string	query	False	Filter by alias.mapping
formats	string	query	False	Filter by formats
wwnn	string	query	False	Filter by wwnn
wwpn	string	query	False	Filter by wwpn
device_names.unload_reload_device	string	query	False	Filter by device_names.unload_reload_device
device_names.no_rewind_device	string	query	False	Filter by device_names.no_rewind_device
device_names.rewind_device	string	query	False	Filter by device_names.rewind_device
storage_port.name	string	query	False	Filter by storage_port.name

Name	Type	In	Required	Description
type	string	query	False	Filter by type
device_state	string	query	False	Filter by device_state
device_id	string	query	False	Filter by device_id
serial_number	string	query	False	Filter by serial_number
interface	string	query	False	Filter by interface
residual_count	integer	query	False	Filter by residual_count
aliases.name	string	query	False	Filter by aliases.name  • Introduced in: 9.11
aliases.mapping	string	query	False	Filter by aliases.mapping  • Introduced in: 9.11
fields	array[string]	query	False	Specify the fields to return.
max_records	integer	query	False	Limit the number of records returned.
return_records	boolean	query	False	The default is true for GET calls. When set to false, only the number of records is returned.  • Default value: 1

Name	Type	In	Required	Description
return_timeout	integer	query	False	<p>The number of seconds to allow the call to execute before returning. When iterating over a collection, the default is 15 seconds. ONTAP returns earlier if either max records or the end of the collection is reached.</p> <ul style="list-style-type: none"> <li>• Default value: 1</li> <li>• Max value: 120</li> <li>• Min value: 0</li> </ul>
order_by	array[string]	query	False	Order results by specified fields and optional [asc

## Response

Status: 200, Ok

Name	Type	Description
<a href="#">_links</a>	<a href="#">_links</a>	
num_records	integer	Number of records
records	array[ <a href="#">tape_device</a> ]	

## Example response

```
{
  "_links": {
    "next": {
      "href": "/api/resourcelink"
    },
    "self": {
      "href": "/api/resourcelink"
    }
  },
  "num_records": 1,
  "records": {
    "alias": {
      "mapping": "SN[10WT000933]",
      "name": "st6"
    },
    "aliases": {
      "mapping": "SN[10WT000933]",
      "name": "st6"
    },
    "block_number": 0,
    "density": "low",
    "description": "QUANTUM LTO-8 ULTRIUM",
    "device_id": "1a.0",
    "device_names": {
      "no_rewind_device": "nrst6l",
      "rewind_device": "rst6l",
      "unload_reload_device": "urst6l"
    },
    "device_state": "read_write_enabled",
    "file_number": 0,
    "formats": [
      "LTO-7 6TB",
      "LTO-7 15TB Compressed",
      "LTO-8 12TB",
      "LTO-8 30TB Compressed"
    ],
    "interface": "sas",
    "node": {
      "_links": {
        "self": {
          "href": "/api/resourcelink"
        }
      },
      "name": "node1",

```



```

    "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"
  },
  "position": {
    "count": 5,
    "operation": "rewind"
  },
  "reservation_type": "off",
  "residual_count": 0,
  "serial_number": "10WT00093",
  "storage_port": {
    "name": "2b"
  },
  "type": "tape",
  "wwnn": "500507631295741c",
  "wwpn": "500507631295741c"
}
}

```

## Error

Status: Default, Error

Name	Type	Description
error	<a href="#">returned_error</a>	

## Example error

```

{
  "error": {
    "arguments": {
      "code": "string",
      "message": "string"
    },
    "code": "4",
    "message": "entry doesn't exist",
    "target": "uuid"
  }
}

```

# Definitions

## See Definitions

href

Name	Type	Description
href	string	

\_links

Name	Type	Description
next	<a href="#">href</a>	
self	<a href="#">href</a>	

alias

Name	Type	Description
mapping	string	This field will no longer be supported in a future release. Use <code>aliases.mapping</code> instead.
name	string	This field will no longer be supported in a future release. Use <code>aliases.name</code> instead.

aliases

Name	Type	Description
mapping	string	Alias mapping.
name	string	Alias name.

device\_names

Name	Type	Description
no_rewind_device	string	Device name for no rewind.
rewind_device	string	Device name for rewind.
unload_reload_device	string	Device name for unload or reload operations.

\_links

Name	Type	Description
self	<a href="#">href</a>	

node

Name	Type	Description
<a href="#">_links</a>	<a href="#">_links</a>	
name	string	
uuid	string	

position

Name	Type	Description
count	integer	Number of times to run position operation.
operation	string	Position operation.

storage\_port

Name	Type	Description
name	string	Initiator port.

tape\_device

Name	Type	Description
<a href="#">alias</a>	<a href="#">alias</a>	
aliases	array[ <a href="#">aliases</a> ]	
block_number	integer	Block number.
density	string	Density.
description	string	
device_id	string	
device_names	array[ <a href="#">device_names</a> ]	
device_state	string	Operational state of the device.
file_number	integer	File number.
formats	array[string]	Tape cartridge format.

Name	Type	Description
interface	string	Device interface type.
node	<a href="#">node</a>	
online	boolean	
position	<a href="#">position</a>	
reservation_type	string	
residual_count	integer	Residual count of the last I/O operation.
serial_number	string	
storage_port	<a href="#">storage_port</a>	
type	string	Device type.
wwnn	string	World Wide Node Name.
wwpn	string	World Wide Port Name.

#### error\_arguments

Name	Type	Description
code	string	Argument code
message	string	Message argument

#### returned\_error

Name	Type	Description
arguments	array[ <a href="#">error_arguments</a> ]	Message arguments
code	string	Error code
message	string	Error message
target	string	The target parameter that caused the error.

## Retrieve a tape device

GET /storage/tape-devices/{node.uuid}/{device\_id}

**Introduced In:** 9.9

Retrieves a specific tape device.

## Related ONTAP commands

- `storage tape show`

## Learn more

- [DOC /storage/tape-devices](#)

## Parameters

Name	Type	In	Required	Description
node.uuid	string	path	True	Node UUID
device_id	string	path	True	Device ID
fields	array[string]	query	False	Specify the fields to return.

## Response

Status: 200, Ok

Name	Type	Description
alias	<a href="#">alias</a>	
aliases	array[ <a href="#">aliases</a> ]	
block_number	integer	Block number.
density	string	Density.
description	string	
device_id	string	
device_names	array[ <a href="#">device_names</a> ]	
device_state	string	Operational state of the device.
file_number	integer	File number.
formats	array[string]	Tape cartridge format.

<b>Name</b>	<b>Type</b>	<b>Description</b>
interface	string	Device interface type.
node	<a href="#">node</a>	
online	boolean	
position	<a href="#">position</a>	
reservation_type	string	
residual_count	integer	Residual count of the last I/O operation.
serial_number	string	
storage_port	<a href="#">storage_port</a>	
type	string	Device type.
wwnn	string	World Wide Node Name.
wwpn	string	World Wide Port Name.

## Example response

```
{
  "alias": {
    "mapping": "SN[10WT000933]",
    "name": "st6"
  },
  "aliases": {
    "mapping": "SN[10WT000933]",
    "name": "st6"
  },
  "block_number": 0,
  "density": "low",
  "description": "QUANTUM LTO-8 ULTRIUM",
  "device_id": "1a.0",
  "device_names": {
    "no_rewind_device": "nrst6l",
    "rewind_device": "rst6l",
    "unload_reload_device": "urst6l"
  },
  "device_state": "read_write_enabled",
  "file_number": 0,
  "formats": [
    "LTO-7 6TB",
    "LTO-7 15TB Compressed",
    "LTO-8 12TB",
    "LTO-8 30TB Compressed"
  ],
  "interface": "sas",
  "node": {
    "_links": {
      "self": {
        "href": "/api/resourcelink"
      }
    },
    "name": "node1",
    "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"
  },
  "position": {
    "count": 5,
    "operation": "rewind"
  },
  "reservation_type": "off",
  "residual_count": 0,
  "serial_number": "10WT00093",
  "storage_port": {
```



```
    "name": "2b"
  },
  "type": "tape",
  "wwnn": "500507631295741c",
  "wwpn": "500507631295741c"
}
```

## Error

Status: Default, Error

Name	Type	Description
error	<a href="#">returned_error</a>	

## Example error

```
{
  "error": {
    "arguments": {
      "code": "string",
      "message": "string"
    },
    "code": "4",
    "message": "entry doesn't exist",
    "target": "uuid"
  }
}
```

## Definitions

## See Definitions

### alias

Name	Type	Description
mapping	string	This field will no longer be supported in a future release. Use aliases.mapping instead.
name	string	This field will no longer be supported in a future release. Use aliases.name instead.

### aliases

Name	Type	Description
mapping	string	Alias mapping.
name	string	Alias name.

### device\_names

Name	Type	Description
no_rewind_device	string	Device name for no rewind.
rewind_device	string	Device name for rewind.
unload_reload_device	string	Device name for unload or reload operations.

### href

Name	Type	Description
href	string	

### \_links

Name	Type	Description
self	<a href="#">href</a>	

### node

Name	Type	Description
_links	<a href="#">_links</a>	

Name	Type	Description
name	string	
uuid	string	

position

Name	Type	Description
count	integer	Number of times to run position operation.
operation	string	Position operation.

storage\_port

Name	Type	Description
name	string	Initiator port.

error\_arguments

Name	Type	Description
code	string	Argument code
message	string	Message argument

returned\_error

Name	Type	Description
arguments	array[ <a href="#">error_arguments</a> ]	Message arguments
code	string	Error code
message	string	Error message
target	string	The target parameter that caused the error.

## Update a tape device

PATCH /storage/tape-devices/{node.uuid}/{device\_id}

Introduced In: 9.11

Updates a specific tape device.

## Related ONTAP commands

- `storage tape alias-set`
- `storage tape alias-clear`
- `storage tape online`
- `storage tape offline`
- `storage tape position`

## Learn more

- [DOC /storage/tape-devices](#)

## Parameters

Name	Type	In	Required	Description
node.uuid	string	path	True	Node UUID
device_id	string	path	True	Device ID

Name	Type	In	Required	Description
return_timeout	integer	query	False	<p>The number of seconds to allow the call to execute before returning. When doing a POST, PATCH, or DELETE operation on a single record, the default is 0 seconds. This means that if an asynchronous operation is started, the server immediately returns HTTP code 202 (Accepted) along with a link to the job. If a non-zero value is specified for POST, PATCH, or DELETE operations, ONTAP waits that length of time to see if the job completes so it can return something other than 202.</p> <ul style="list-style-type: none"> <li>• Default value: 1</li> <li>• Max value: 120</li> <li>• Min value: 0</li> </ul>

## Request Body

Name	Type	Description
alias	<a href="#">alias</a>	
aliases	array[ <a href="#">aliases</a> ]	
block_number	integer	Block number.
density	string	Density.
description	string	
device_id	string	
device_names	array[ <a href="#">device_names</a> ]	

<b>Name</b>	<b>Type</b>	<b>Description</b>
device_state	string	Operational state of the device.
file_number	integer	File number.
formats	array[string]	Tape cartridge format.
interface	string	Device interface type.
node	<a href="#">node</a>	
online	boolean	
position	<a href="#">position</a>	
reservation_type	string	
residual_count	integer	Residual count of the last I/O operation.
serial_number	string	
storage_port	<a href="#">storage_port</a>	
type	string	Device type.
wwnn	string	World Wide Node Name.
wwpn	string	World Wide Port Name.

## Example request

```
{
  "alias": {
    "mapping": "SN[10WT000933]",
    "name": "st6"
  },
  "aliases": {
    "mapping": "SN[10WT000933]",
    "name": "st6"
  },
  "block_number": 0,
  "density": "low",
  "description": "QUANTUM LTO-8 ULTRIUM",
  "device_id": "1a.0",
  "device_names": {
    "no_rewind_device": "nrst6l",
    "rewind_device": "rst6l",
    "unload_reload_device": "urst6l"
  },
  "device_state": "read_write_enabled",
  "file_number": 0,
  "formats": [
    "LTO-7 6TB",
    "LTO-7 15TB Compressed",
    "LTO-8 12TB",
    "LTO-8 30TB Compressed"
  ],
  "interface": "sas",
  "node": {
    "_links": {
      "self": {
        "href": "/api/resourcelink"
      }
    },
    "name": "node1",
    "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"
  },
  "position": {
    "count": 5,
    "operation": "rewind"
  },
  "reservation_type": "off",
  "residual_count": 0,
  "serial_number": "10WT00093",
  "storage_port": {
```

```

    "name": "2b"
  },
  "type": "tape",
  "wwnn": "500507631295741c",
  "wwpn": "500507631295741c"
}

```

## Response

Status: 200, Ok

## Response

Status: 202, Accepted

## Error

Status: Default

### ONTAP Error Response Codes

Error Code	Description
11403264	Tape operation "<operation>\" failed on tape device \"<device_id>\". This may indicate tape reached end of data, a hardware error, an illegal request, an invalid name format, or an aborted command.</device_id></operation>
11403265	Tape operation "<operation>\" failed because it encountered an unexpected file mark on tape device \"<device_id>\".</device_id></operation>
11403266	Internal error. Unknown tape parameter for tape device "<device_id>\".</device_id>
11403267	Tape device "<device_id>\" is busy.</device_id>
11403268	No tape loaded for "<operation>\" operation on tape drive \"<device_id>\".</device_id></operation>
11403269	Tape device "<device_id>\" unknown.</device_id>
11403270	Tape alias name "<alias>\" already exists.</alias>
11403271	The format of the tape alias name "<alias>\" is invalid. Use \"st\" or \"mc\" followed by one or more digits.</alias>



Error Code	Description
11403273	Internal error. Tape alias name "<alias>" not saved.</alias>
11403274	Internal error. Tape alias operation "<operation>" for alias name "<alias>" failed.</alias></operation>
11403275	Tape alias name "<alias>" not found.</alias>
11403277	Tape device "<device_id>" is reserved by another host.</device_id>
11403278	Invalid count value specified with operation "<operation>". Valid values are from 0 to {1}.</operation>

Also see the table of common errors in the [Response body](#) overview section of this documentation.

Name	Type	Description
error	<a href="#">returned_error</a>	

### Example error

```
{
  "error": {
    "arguments": {
      "code": "string",
      "message": "string"
    },
    "code": "4",
    "message": "entry doesn't exist",
    "target": "uuid"
  }
}
```

### Definitions

## See Definitions

### alias

Name	Type	Description
mapping	string	This field will no longer be supported in a future release. Use aliases.mapping instead.
name	string	This field will no longer be supported in a future release. Use aliases.name instead.

### aliases

Name	Type	Description
mapping	string	Alias mapping.
name	string	Alias name.

### device\_names

Name	Type	Description
no_rewind_device	string	Device name for no rewind.
rewind_device	string	Device name for rewind.
unload_reload_device	string	Device name for unload or reload operations.

### href

Name	Type	Description
href	string	

### \_links

Name	Type	Description
self	<a href="#">href</a>	

### node

Name	Type	Description
_links	<a href="#">_links</a>	

Name	Type	Description
name	string	
uuid	string	

#### position

Name	Type	Description
count	integer	Number of times to run position operation.
operation	string	Position operation.

#### storage\_port

Name	Type	Description
name	string	Initiator port.

#### tape\_device

Name	Type	Description
alias	<a href="#">alias</a>	
aliases	array[ <a href="#">aliases</a> ]	
block_number	integer	Block number.
density	string	Density.
description	string	
device_id	string	
device_names	array[ <a href="#">device_names</a> ]	
device_state	string	Operational state of the device.
file_number	integer	File number.
formats	array[string]	Tape cartridge format.
interface	string	Device interface type.
node	<a href="#">node</a>	
online	boolean	
position	<a href="#">position</a>	

Name	Type	Description
reservation_type	string	
residual_count	integer	Residual count of the last I/O operation.
serial_number	string	
storage_port	<a href="#">storage_port</a>	
type	string	Device type.
wwnn	string	World Wide Node Name.
wwpn	string	World Wide Port Name.

#### error\_arguments

Name	Type	Description
code	string	Argument code
message	string	Message argument

#### returned\_error

Name	Type	Description
arguments	array[ <a href="#">error_arguments</a> ]	Message arguments
code	string	Error code
message	string	Error message
target	string	The target parameter that caused the error.

## Copyright information

Copyright © 2024 NetApp, Inc. All Rights Reserved. Printed in the U.S. No part of this document covered by copyright may be reproduced in any form or by any means—graphic, electronic, or mechanical, including photocopying, recording, taping, or storage in an electronic retrieval system—without prior written permission of the copyright owner.

Software derived from copyrighted NetApp material is subject to the following license and disclaimer:

THIS SOFTWARE IS PROVIDED BY NETAPP “AS IS” AND WITHOUT ANY EXPRESS OR IMPLIED WARRANTIES, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE, WHICH ARE HEREBY DISCLAIMED. IN NO EVENT SHALL NETAPP BE LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO, PROCUREMENT OF SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA, OR PROFITS; OR BUSINESS INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE) ARISING IN ANY WAY OUT OF THE USE OF THIS SOFTWARE, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE.

NetApp reserves the right to change any products described herein at any time, and without notice. NetApp assumes no responsibility or liability arising from the use of products described herein, except as expressly agreed to in writing by NetApp. The use or purchase of this product does not convey a license under any patent rights, trademark rights, or any other intellectual property rights of NetApp.

The product described in this manual may be protected by one or more U.S. patents, foreign patents, or pending applications.

LIMITED RIGHTS LEGEND: Use, duplication, or disclosure by the government is subject to restrictions as set forth in subparagraph (b)(3) of the Rights in Technical Data -Noncommercial Items at DFARS 252.227-7013 (FEB 2014) and FAR 52.227-19 (DEC 2007).

Data contained herein pertains to a commercial product and/or commercial service (as defined in FAR 2.101) and is proprietary to NetApp, Inc. All NetApp technical data and computer software provided under this Agreement is commercial in nature and developed solely at private expense. The U.S. Government has a non-exclusive, non-transferrable, nonsublicensable, worldwide, limited irrevocable license to use the Data only in connection with and in support of the U.S. Government contract under which the Data was delivered. Except as provided herein, the Data may not be used, disclosed, reproduced, modified, performed, or displayed without the prior written approval of NetApp, Inc. United States Government license rights for the Department of Defense are limited to those rights identified in DFARS clause 252.227-7015(b) (FEB 2014).

## Trademark information

NETAPP, the NETAPP logo, and the marks listed at <http://www.netapp.com/TM> are trademarks of NetApp, Inc. Other company and product names may be trademarks of their respective owners.