



# Manage FPolicy engine configuration

## REST API reference

NetApp  
February 10, 2026

This PDF was generated from [https://docs.netapp.com/us-en/ontap-restapi-96/manage\\_fpolicy\\_engine\\_configuration.html](https://docs.netapp.com/us-en/ontap-restapi-96/manage_fpolicy_engine_configuration.html) on February 10, 2026. Always check [docs.netapp.com](https://docs.netapp.com) for the latest.

# Table of Contents

Manage FPolicy engine configuration .....	1
Manage FPolicy engine configuration .....	1
Overview .....	1
Examples .....	1
Retrieves fpolicy engine configurations of all the engines for a specified svm ontap allows creation of cluster-level fpolicy engines that act as a template for all the svms belonging to the cluster these cluster-level fpolicy engines are also retrieved for the specified svm .....	6
Related ONTAP commands .....	7
Learn more .....	7
Parameters .....	7
Response .....	8
Error .....	9
Definitions .....	10
Creates an fpolicy engine configuration for a specified svm fpolicy engine creation is allowed only on data svms .....	12
Required properties .....	12
Recommended optional properties .....	13
Default property values .....	13
Related ONTAP commands .....	13
Learn more .....	13
Parameters .....	13
Request Body .....	13
Response .....	14
Error .....	15
Definitions .....	16
Deletes the fpolicy external engine configuration deletion of an fpolicy engine that is attached to one or more fpolicy policies is not allowed .....	18
Related ONTAP commands .....	18
Learn more .....	18
Parameters .....	18
Response .....	19
Error .....	19
Definitions .....	20
Retrieves a particular fpolicy engine configuration of a specified svm a cluster-level fpolicy engine configuration cannot be retrieved for a data svm .....	20
Related ONTAP commands .....	20
Learn more .....	20
Parameters .....	21
Response .....	21
Error .....	22
Definitions .....	23
Updates a specific fpolicy engine configuration of an svm modification of an fpolicy engine that is attached to one or more enabled fpolicy policies is not allowed .....	23

Related ONTAP commands . . . . .	23
Learn more . . . . .	23
Parameters . . . . .	24
Request Body . . . . .	24
Response . . . . .	25
Error . . . . .	25
Definitions . . . . .	26

# Manage FPolicy engine configuration

## Manage FPolicy engine configuration

### Overview

The FPolicy engine allows you to configure the external servers to which the file access notifications are sent. As part of FPolicy engine configuration, you can configure the server(s) to which the notification is sent, an optional set of secondary server(s) to which the notification is sent in the case of the primary server(s) failure, the port number for FPolicy application and the type of the engine, synchronous or asynchronous.

For the synchronous engine, ONTAP will wait for a response from the FPolicy application before it allows the operation. With an asynchronous engine, ONTAP proceeds with the operation processing after sending the notification to the FPolicy application. An engine can belong to multiple FPolicy policies.

### Examples

#### Creating an FPolicy engine

---

```

# The API:
POST /protocols/fpolicy/{svm.uuid}/engines

#The call:
curl -X POST "https://<mgmt-ip>/api/protocols/fpolicy/4f643fb4-fd21-11e8-
ae49-0050568e2c1e/engines/" -H "accept: application/json" -H "Content-
Type: application/json" -d "{ \"name\": \"engine0\", \"port\": 9876,
\"primary_servers\": [ \"10.132.145.22\", \"10.140.101.109\" ],
\"secondary_servers\": [ \"10.132.145.20\", \"10.132.145.21\" ], \"type\":
\"synchronous\"}"

# The response:
{
  "num_records": 1,
  "records": [
    {
      "name": "engine0",
      "primary_servers": [
        "10.132.145.22",
        "10.140.101.109"
      ],
      "secondary_servers": [
        "10.132.145.20",
        "10.132.145.21"
      ],
      "port": 9876,
      "type": "synchronous"
    }
  ]
}

```

## Creating an FPolicy engine with the minimum required fields

```

# The API:
POST /protocols/fpolicy/{svm.uuid}/engines

#The call:
curl -X POST "https://<mgmt-ip>/api/protocols/fpolicy/4f643fb4-fd21-11e8-
ae49-0050568e2c1e/engines/" -H "accept: application/json" -H "Content-
Type: application/json" -d "{ \"name\": \"engine0\", \"port\": 9876,
\"primary_servers\": [ \"10.132.145.22\", \"10.140.101.109\" ], \"type\":
\"synchronous\"}"

# The response:
{
  "num_records": 1,
  "records": [
    {
      "name": "engine0",
      "primary_servers": [
        "10.132.145.22",
        "10.140.101.109"
      ],
      "port": 9876,
      "type": "synchronous"
    }
  ]
}

```

---

## Retrieving an FPolicy engine configuration for a particular SVM

---

```

# The API:
GET /protocols/fpolicy/{svm.uuid}/engines

# The call:
curl -X GET "https://<mgmt-ip>/api/protocols/fpolicy/4f643fb4-fd21-11e8-
ae49-0050568e2c1e/engines/?fields=*&return_records=true&return_timeout=15"
-H "accept: application/json"

# The response:
{
  "records": [
    {
      "svm": {
        "uuid": "4f643fb4-fd21-11e8-ae49-0050568e2c1e",
        "name": "cifs",
        "primary_servers": [
          "10.20.20.10"
        ],
        "port": 9876,
        "type": "synchronous"
      },
      {
        "svm": {
          "uuid": "4f643fb4-fd21-11e8-ae49-0050568e2c1e",
          "name": "nfs",
          "primary_servers": [
            "10.23.140.64",
            "10.140.101.109"
          ],
          "secondary_servers": [
            "10.132.145.20",
            "10.132.145.22"
          ],
          "port": 9876,
          "type": "synchronous"
        }
      }
    ],
    "num_records": 2
  }
}

```

## Retrieving a specific FPolicy engine configuration for an SVM

```
# The Api:  
GET /protocols/fpolicy/{svm.uuid}/engines/{name}  
  
#The call:  
curl -X GET "https://<mgmt-ip>/api/protocols/fpolicy/4f643fb4-fd21-11e8-  
ae49-0050568e2c1e/engines/cifs?fields=*" -H "accept: application/json"  
  
# The response:  
{  
  "svm": {  
    "uuid": "4f643fb4-fd21-11e8-ae49-0050568e2c1e"  
,  
    "name": "cifs",  
    "primary_servers": [  
      "10.20.20.10"  
,  
      "port": 9876,  
      "type": "synchronous"  
  }  
}
```

## Updating an FPolicy engine for an SVM

```
# The API:  
PATCH /protocols/fpolicy/{svm.uuid}/engines/{name}  
  
# The call:  
curl -X PATCH "https://<mgmt-ip>/api/protocols/fpolicy/4f643fb4-fd21-11e8-  
ae49-0050568e2c1e/engines/cifs" -H "accept: application/json" -H "Content-  
Type: application/json" -d "{ \"port\": 6666, \"secondary_servers\": [  
  \"10.132.145.20\", \"10.132.145.21\" ], \"type\": \"synchronous\"}"
```

## Updating all the attributes of a specific FPolicy engine for an SVM

```

# The API:
PATCH /protocols/fpolicy/{svm.uuid}/engines/{name}

# The call:
curl -X PATCH "https://<mgmt-ip>/api/protocols/fpolicy/4f643fb4-fd21-11e8-
ae49-0050568e2c1e/engines/cifs" -H "accept: application/json" -H "Content-
Type: application/json" -d "{ \"port\": 9876, \"primary_servers\": [
\"10.132.145.20\", \"10.140.101.109\" ], \"secondary_servers\": [
\"10.132.145.23\", \"10.132.145.21\" ], \"type\": \"synchronous\"}"

```

## Deleting a specific FPolicy engine for an SVM

```

# The API:
DELETE /protocols/fpolicy/{svm.uuid}/engines/{name}

# The call:
curl -X DELETE "https://<mgmt-ip>/api/protocols/fpolicy/4f643fb4-fd21-
11e8-ae49-0050568e2c1e/events/cifs" -H "accept: application/json"

```

**Retrieves fpolicy engine configurations of all the engines for a specified svm ontap allows creation of cluster-level fpolicy engines that act as a template for all the svms belonging to the cluster these cluster-level fpolicy engines are also retrieved for the specified svm**

### related ontap commands

- `fpolicy policy external-engine show` [# learn more](#)
- `[doc /protocols/fpolicy/{svmuuid}/engines]` ([#docs-nas-protocols\\_fpolicy\\_{svmuuid}\\_engines](#))

`GET /protocols/fpolicy/{svm.uuid}/engines`

Retrieves FPolicy engine configurations of all the engines for a specified SVM. ONTAP allows creation of cluster-level FPolicy engines that act as a template for all the SVMs belonging to the cluster. These cluster-level FPolicy engines are also retrieved for the specified SVM.

## Related ONTAP commands

- `fpolicy policy external-engine show`

## Learn more

- [DOC /protocols/fpolicy/{svm.uuid}/engines](#)

## Parameters

Name	Type	In	Required	Description
svm.uuid	string	path	True	UUID of the SVM to which this object belongs.
primary_servers	string	query	False	Filter by primary_servers
type	string	query	False	Filter by type
name	string	query	False	Filter by name
secondary_servers	string	query	False	Filter by secondary_servers
port	integer	query	False	Filter by port
fields	array[string]	query	False	Specify the fields to return.
max_records	integer	query	False	Limit the number of records returned.
return_records	boolean	query	False	The default is true for GET calls. When set to false, only the number of records is returned.

Name	Type	In	Required	Description
return_timeout	integer	query	False	The number of seconds to allow the call to execute before returning. When iterating over a collection, the default is 15 seconds. ONTAP returns earlier if either max records or the end of the collection is reached.
order_by	array[string]	query	False	Order results by specified fields and optional [asc

## Response

Status: 200, Ok

Name	Type	Description
_links	<a href="#">_links</a>	
num_records	integer	Number of records
records	array[fpolicy_engine]	

## Example response

```
{  
  "_links": {  
    "next": {  
      "href": "/api/resourcelink"  
    },  
    "self": {  
      "href": "/api/resourcelink"  
    }  
  },  
  "records": [  
    {  
      "name": "fp_ex_eng",  
      "port": 9876,  
      "primary_servers": [  
        "10.132.145.20",  
        "10.140.101.109"  
      ],  
      "secondary_servers": [  
        "10.132.145.20",  
        "10.132.145.21"  
      ],  
      "type": "string"  
    }  
  ]  
}
```

## Error

Status: Default,

Name	Type	Description
error	error	

## Example error

```
{  
  "error": {  
    "arguments": [  
      {  
        "code": "string",  
        "message": "string"  
      }  
    ],  
    "code": "4",  
    "message": "entry doesn't exist",  
    "target": "uuid"  
  }  
}
```

## Definitions

## See Definitions

href

Name	Type	Description
href	string	

\_links

Name	Type	Description
next	<a href="#">href</a>	
self	<a href="#">href</a>	

fpolicy\_engine

The engine defines how ONTAP makes and manages connections to external FPolicy servers.

Name	Type	Description
name	string	Specifies the name to assign to the external server configuration.
port	integer	Port number of the FPolicy server application.
primary_servers	array[string]	
secondary_servers	array[string]	
type	string	<p>The notification mode determines what ONTAP does after sending notifications to FPolicy servers. The possible values are:</p> <ul style="list-style-type: none"><li>• synchronous - After sending a notification, wait for a response from the FPolicy server.</li><li>• asynchronous - After sending a notification, file request processing continues.<ul style="list-style-type: none"><li>◦ Default value: 1</li><li>◦ enum: ["synchronous", "asynchronous"]</li></ul></li></ul>

error\_arguments

Name	Type	Description
code	string	Argument code
message	string	Message argument

error

Name	Type	Description
arguments	array[error_arguments]	Message arguments
code	string	Error code
message	string	Error message
target	string	The target parameter that caused the error.

## Creates an fpolicy engine configuration for a specified svm fpolicy engine creation is allowed only on data svms

### required properties

- svmuuid - existing svm in which to create the fpolicy engine
- name - name of external engine
- port - port number of the fpolicy server application
- primary\_servers - list of primary fpolicy servers to which the node will send notifications **#** recommended optional properties
- secondary\_servers - it is recommended to configure secondary fpolicy server to which the node will send notifications when the primary server is down **#** default property values
- type - **synchronous** **#** related ontap commands
- fpolicy policy external-engine create **#** learn more
- [doc /protocols/fpolicy/{svmuuid}/engines][#docs-nas-protocols\_fpolicy\_{svmuuid}\_engines)

POST /protocols/fpolicy/{svm.uuid}/engines

Creates an FPolicy engine configuration for a specified SVM. FPolicy engine creation is allowed only on data SVMs.

### Required properties

- svm.uuid - Existing SVM in which to create the FPolicy engine.

- `name` - Name of external engine.
- `port` - Port number of the FPolicy server application.
- `primary_servers` - List of primary FPolicy servers to which the node will send notifications.

## Recommended optional properties

- `secondary_servers` - It is recommended to configure secondary FPolicy server to which the node will send notifications when the primary server is down.

## Default property values

- `type` - *synchronous*

## Related ONTAP commands

- `fpolicy policy external-engine create`

## Learn more

- [DOC /protocols/fpolicy/{svm.uuid}/engines](#)

## Parameters

Name	Type	In	Required	Description
<code>svm.uuid</code>	string	path	True	UUID of the SVM to which this object belongs.

## Request Body

Name	Type	Description
<code>name</code>	string	Specifies the name to assign to the external server configuration.
<code>port</code>	integer	Port number of the FPolicy server application.
<code>primary_servers</code>	array[string]	
<code>secondary_servers</code>	array[string]	

Name	Type	Description
type	string	<p>The notification mode determines what ONTAP does after sending notifications to FPolicy servers. The possible values are:</p> <ul style="list-style-type: none"> <li>• synchronous - After sending a notification, wait for a response from the FPolicy server.</li> <li>• asynchronous - After sending a notification, file request processing continues. <ul style="list-style-type: none"> <li>◦ Default value: 1</li> <li>◦ enum: ["synchronous", "asynchronous"]</li> </ul> </li> </ul>

## Example request

```
{
  "name": "fp_ex_eng",
  "port": 9876,
  "primary_servers": [
    "10.132.145.20",
    "10.140.101.109"
  ],
  "secondary_servers": [
    "10.132.145.20",
    "10.132.145.21"
  ],
  "type": "string"
}
```

## Response

```
Status: 201, Created
```

Name	Type	Description
_links	_links	
num_records	integer	Number of records
records	array[fpolicy_engine]	

## Example response

```
{  
  "_links": {  
    "next": {  
      "href": "/api/resourcelink"  
    },  
    "self": {  
      "href": "/api/resourcelink"  
    }  
  },  
  "records": [  
    {  
      "name": "fp_ex_eng",  
      "port": 9876,  
      "primary_servers": [  
        "10.132.145.20",  
        "10.140.101.109"  
      ],  
      "secondary_servers": [  
        "10.132.145.20",  
        "10.132.145.21"  
      ],  
      "type": "string"  
    }  
  ]  
}
```

## Error

Status: Default

### ONTAP Error Response Codes

Error Code	Description
9764885	The primary secondary server has a redundant IP address
9764953	The name of the FPolicy engine is "native" which is reserved by the system

Name	Type	Description
error	error	

## Example error

```
{  
  "error": {  
    "arguments": [  
      {  
        "code": "string",  
        "message": "string"  
      }  
    ],  
    "code": "4",  
    "message": "entry doesn't exist",  
    "target": "uuid"  
  }  
}
```

## Definitions

## See Definitions

### fpolicy\_engine

The engine defines how ONTAP makes and manages connections to external FPolicy servers.

Name	Type	Description
name	string	Specifies the name to assign to the external server configuration.
port	integer	Port number of the FPolicy server application.
primary_servers	array[string]	
secondary_servers	array[string]	
type	string	<p>The notification mode determines what ONTAP does after sending notifications to FPolicy servers. The possible values are:</p> <ul style="list-style-type: none"><li>• synchronous - After sending a notification, wait for a response from the FPolicy server.</li><li>• asynchronous - After sending a notification, file request processing continues.<ul style="list-style-type: none"><li>◦ Default value: 1</li><li>◦ enum: ["synchronous", "asynchronous"]</li></ul></li></ul>

### href

Name	Type	Description
href	string	

### \_links

Name	Type	Description
next	href	
self	href	

### error\_arguments

Name	Type	Description
code	string	Argument code
message	string	Message argument

error

Name	Type	Description
arguments	array[error_arguments]	Message arguments
code	string	Error code
message	string	Error message
target	string	The target parameter that caused the error.

## Deletes the fpolicy external engine configuration deletion of an fpolicy engine that is attached to one or more fpolicy policies is not allowed

### related ontap commands

- `fpolicy policy external-engine modify` # learn more
- `[doc /protocols/fpolicy/{svmuuid}/engines](#docs-nas-protocols_fpolicy_{svmuuid}_engines)`

`DELETE /protocols/fpolicy/{svm.uuid}/engines/{name}`

Deletes the FPolicy external engine configuration. Deletion of an FPolicy engine that is attached to one or more FPolicy policies is not allowed.

### Related ONTAP commands

- `fpolicy policy external-engine modify`

### Learn more

- [DOC /protocols/fpolicy/{svm.uuid}/engines](#)

### Parameters

Name	Type	In	Required	Description
svm.uuid	string	path	True	UUID of the SVM to which this object belongs.
name	string	path	True	

## Response

Status: 200, Ok

## Error

Status: Default

### ONTAP Error Response Codes

Error Code	Description
9764940	At least one FPolicy policy is using the FPolicy engine
9764887	The FPolicy engine is a cluster level FPolicy engine

Name	Type	Description
error	error	

### Example error

```
{
  "error": {
    "arguments": [
      {
        "code": "string",
        "message": "string"
      }
    ],
    "code": "4",
    "message": "entry doesn't exist",
    "target": "uuid"
  }
}
```

## Definitions

### See Definitions

error\_arguments

Name	Type	Description
code	string	Argument code
message	string	Message argument

error

Name	Type	Description
arguments	array[error_arguments]	Message arguments
code	string	Error code
message	string	Error message
target	string	The target parameter that caused the error.

## Retrieves a particular fpolicy engine configuration of a specified svm a cluster-level fpolicy engine configuration cannot be retrieved for a data svm

### related ontap commands

- `fpolicy policy external-engine show` [# learn more](#)
- [\[doc /protocols/fpolicy/{svmuuid}/engines\]\(#docs-nas-protocols\\_fpolicy\\_{svmuuid}\\_engines\)](#)

`GET /protocols/fpolicy/{svm.uuid}/engines/{name}`

Retrieves a particular FPolicy engine configuration of a specified SVM. A cluster-level FPolicy engine configuration cannot be retrieved for a data SVM.

### Related ONTAP commands

- `fpolicy policy external-engine show`

### Learn more

- [DOC /protocols/fpolicy/{svm.uuid}/engines](#)

## Parameters

Name	Type	In	Required	Description
svm.uuid	string	path	True	UUID of the SVM to which this object belongs.
name	string	path	True	
fields	array[string]	query	False	Specify the fields to return.

## Response

Status: 200, Ok

Name	Type	Description
name	string	Specifies the name to assign to the external server configuration.
port	integer	Port number of the FPolicy server application.
primary_servers	array[string]	
secondary_servers	array[string]	
type	string	<p>The notification mode determines what ONTAP does after sending notifications to FPolicy servers. The possible values are:</p> <ul style="list-style-type: none"> <li>• synchronous - After sending a notification, wait for a response from the FPolicy server.</li> <li>• asynchronous - After sending a notification, file request processing continues. <ul style="list-style-type: none"> <li>◦ Default value: 1</li> <li>◦ enum: ["synchronous", "asynchronous"]</li> </ul> </li> </ul>

## Example response

```
{  
  "name": "fp_ex_eng",  
  "port": 9876,  
  "primary_servers": [  
    "10.132.145.20",  
    "10.140.101.109"  
  ],  
  "secondary_servers": [  
    "10.132.145.20",  
    "10.132.145.21"  
  ],  
  "type": "string"  
}
```

## Error

Status: Default, Error

Name	Type	Description
error	error	

## Example error

```
{  
  "error": {  
    "arguments": [  
      {  
        "code": "string",  
        "message": "string"  
      }  
    ],  
    "code": "4",  
    "message": "entry doesn't exist",  
    "target": "uuid"  
  }  
}
```

## Definitions

### See Definitions

error\_arguments

Name	Type	Description
code	string	Argument code
message	string	Message argument

error

Name	Type	Description
arguments	array[error_arguments]	Message arguments
code	string	Error code
message	string	Error message
target	string	The target parameter that caused the error.

**Updates a specific fpolicy engine configuration of an svm modification of an fpolicy engine that is attached to one or more enabled fpolicy policies is not allowed**

### related ontap commands

- `fpolicy policy external-engine modify` [# learn more](#)
- [\[doc /protocols/fpolicy/{svm.uuid}/engines\]\(#docs-nas-protocols\\_fpolicy\\_{svm.uuid}\\_engines\)](#)

`PATCH /protocols/fpolicy/{svm.uuid}/engines/{name}`

Updates a specific FPolicy engine configuration of an SVM. Modification of an FPolicy engine that is attached to one or more enabled FPolicy policies is not allowed.

## Related ONTAP commands

- `fpolicy policy external-engine modify`

## Learn more

- [DOC /protocols/fpolicy/{svm.uuid}/engines](#)

## Parameters

Name	Type	In	Required	Description
svm.uuid	string	path	True	UUID of the SVM to which this object belongs.
name	string	path	True	

## Request Body

Name	Type	Description
port	integer	Port number of the FPolicy server application.
primary_servers	array[string]	
secondary_servers	array[string]	
type	string	<p>The notification mode determines what ONTAP does after sending notifications to FPolicy servers. The possible values are:</p> <ul style="list-style-type: none"> <li>• synchronous - After sending a notification, wait for a response from the FPolicy server.</li> <li>• asynchronous - After sending a notification, file request processing continues. <ul style="list-style-type: none"> <li>◦ Default value: 1</li> <li>◦ enum: ["synchronous", "asynchronous"]</li> </ul> </li> </ul>

## Example request

```
{  
  "port": 9876,  
  "primary_servers": [  
    "10.132.145.20",  
    "10.140.101.109"  
  ],  
  "secondary_servers": [  
    "10.132.145.20",  
    "10.132.145.21"  
  ],  
  "type": "string"  
}
```

## Response

Status: 200, Ok

## Error

Status: Default

### ONTAP Error Response Codes

Error Code	Description
9764922	The primary and secondary server has a redundant IP address
9764942	At least one FPolicy policy is using the FPolicy engine
9764886	FPolicy engine is a cluster-level FPolicy engine

Name	Type	Description
error	error	

## Example error

```
{  
  "error": {  
    "arguments": [  
      {  
        "code": "string",  
        "message": "string"  
      }  
    ],  
    "code": "4",  
    "message": "entry doesn't exist",  
    "target": "uuid"  
  }  
}
```

## Definitions

## See Definitions

### fpolicy\_engine

The engine defines how ONTAP makes and manages connections to external FPolicy servers.

Name	Type	Description
port	integer	Port number of the FPolicy server application.
primary_servers	array[string]	
secondary_servers	array[string]	
type	string	<p>The notification mode determines what ONTAP does after sending notifications to FPolicy servers. The possible values are:</p> <ul style="list-style-type: none"><li>• synchronous - After sending a notification, wait for a response from the FPolicy server.</li><li>• asynchronous - After sending a notification, file request processing continues.<ul style="list-style-type: none"><li>◦ Default value: 1</li><li>◦ enum: ["synchronous", "asynchronous"]</li></ul></li></ul>

### error\_arguments

Name	Type	Description
code	string	Argument code
message	string	Message argument

### error

Name	Type	Description
arguments	array[error_arguments]	Message arguments
code	string	Error code
message	string	Error message

Name	Type	Description
target	string	The target parameter that caused the error.

## Copyright information

Copyright © 2026 NetApp, Inc. All Rights Reserved. Printed in the U.S. No part of this document covered by copyright may be reproduced in any form or by any means—graphic, electronic, or mechanical, including photocopying, recording, taping, or storage in an electronic retrieval system—without prior written permission of the copyright owner.

Software derived from copyrighted NetApp material is subject to the following license and disclaimer:

THIS SOFTWARE IS PROVIDED BY NETAPP “AS IS” AND WITHOUT ANY EXPRESS OR IMPLIED WARRANTIES, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE, WHICH ARE HEREBY DISCLAIMED. IN NO EVENT SHALL NETAPP BE LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO, PROCUREMENT OF SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA, OR PROFITS; OR BUSINESS INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE) ARISING IN ANY WAY OUT OF THE USE OF THIS SOFTWARE, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE.

NetApp reserves the right to change any products described herein at any time, and without notice. NetApp assumes no responsibility or liability arising from the use of products described herein, except as expressly agreed to in writing by NetApp. The use or purchase of this product does not convey a license under any patent rights, trademark rights, or any other intellectual property rights of NetApp.

The product described in this manual may be protected by one or more U.S. patents, foreign patents, or pending applications.

**LIMITED RIGHTS LEGEND:** Use, duplication, or disclosure by the government is subject to restrictions as set forth in subparagraph (b)(3) of the Rights in Technical Data -Noncommercial Items at DFARS 252.227-7013 (FEB 2014) and FAR 52.227-19 (DEC 2007).

Data contained herein pertains to a commercial product and/or commercial service (as defined in FAR 2.101) and is proprietary to NetApp, Inc. All NetApp technical data and computer software provided under this Agreement is commercial in nature and developed solely at private expense. The U.S. Government has a non-exclusive, non-transferrable, nonsublicensable, worldwide, limited irrevocable license to use the Data only in connection with and in support of the U.S. Government contract under which the Data was delivered. Except as provided herein, the Data may not be used, disclosed, reproduced, modified, performed, or displayed without the prior written approval of NetApp, Inc. United States Government license rights for the Department of Defense are limited to those rights identified in DFARS clause 252.227-7015(b) (FEB 2014).

## Trademark information

NETAPP, the NETAPP logo, and the marks listed at <http://www.netapp.com/TM> are trademarks of NetApp, Inc. Other company and product names may be trademarks of their respective owners.