



# **Networking**

ONTAP 9.7 REST API reference

NetApp  
April 02, 2024

# Table of Contents

Networking . . . . .	1
Networking overview . . . . .	1
Manage broadcast domains . . . . .	3
Manage network Ethernet ports . . . . .	35
Manage FC network interfaces . . . . .	92
Retrieve FC port information . . . . .	143
Manage HTTP proxy configuration . . . . .	176
Manage BGP peer groups . . . . .	204
Manage network IP interfaces . . . . .	245
Manage network IP routes . . . . .	307
Manage network IP service policies . . . . .	336
Manage network IPspaces . . . . .	354

# Networking

## Networking overview

### Overview

The ONTAP networking APIs enable reporting on networking information, such as IPspaces, interfaces, routes, ports, service policies and broadcast domains. Some can also be used to manage networking.

---

### IPspaces

IPspaces enable you to configure a single ONTAP cluster so that it can be accessed by clients from more than one administratively separate network domain, even if those clients are using the same IP address subnet range. This allows for separation of client traffic for privacy and security.

An IPspace defines a distinct IP address space in which storage virtual machines (SVMs) reside. Ports and IP addresses defined for an IPspace are applicable only within that IPspace. A distinct routing table is maintained for each SVM within an IPspace, so that no cross-SVM or cross-IPspace traffic routing occurs.

---

### Ethernet

#### Broadcast Domains

A broadcast domain is a set of ports which would all receive a broadcast packet that is sent from any of the ports.

By accurately representing the physical network with an ONTAP broadcast domain, ONTAP ensures that IP interfaces are able to migrate to appropriate ports in case of failure. ONTAP also ensures that characteristics, such as MTU, stay matched across all ports of the broadcast domain.

A broadcast domain resides in an IPspace, and can be used by cluster-scoped or SVM-scoped IP interfaces in that IPspace. The scope of the broadcast domain's uniqueness is the IPspace it is in. You must create as many broadcast domains in an IPspace as there are IP subnets with interfaces in that IPspace.

Ports are mapped to an IPspace by assigning the port's broadcast domain.

#### Ports

A port is a physical or virtual Ethernet network device. Physical ports may be combined into Link Aggregation Groups (LAGs, or ifgrps), or divided into Virtual LANs (VLANs).

The GET and PATCH APIs are available for all port types. The POST and DELETE APIs are available for "lag" and "vlan" port types.

A given port can host zero or more IP interfaces.

A port exists in a broadcast domain and all ports within the same broadcast domain must have layer 2 network connectivity to one another. If a port within a broadcast domain goes down, any IP interfaces hosted by that port can fail over to other ports in the same broadcast domain.

## Fibre Channel

---

### Interfaces

Fibre Channel (FC) interfaces are the logical endpoints for Fibre Channel network connections to an SVM. A Fibre Channel interface provides Fibre Channel access to storage within the interface's SVM using either Fibre Channel Protocol (FCP) or Non-Volatile Memory Express over Fibre Channel (NVMe over FC).

The Fibre Channel interface REST API allows you to create, delete, update and discover Fibre Channel interfaces and obtain status information for Fibre Channel interfaces.

A Fibre Channel interface is created on a Fibre Channel port that is located on a cluster node. The Fibre Channel port must be specified to identify the location of the interface for a POST or PATCH that relocates an interface. You can identify the port by either supplying the node and port names or the port UUID.

### Ports

Fibre Channel ports are the physical ports of Fibre Channel adapters on ONTAP cluster nodes that can be connected to Fibre Channel networks to provide Fibre Channel network connectivity. A Fibre Channel port defines the location of a Fibre Channel interface within the ONTAP cluster.

The Fibre Channel port REST API allows you to discover Fibre Channel ports, obtain status information for Fibre Channel ports, and configure Fibre Channel port properties.

### Learn More

- *Fibre Channel Logins* found in both the SAN and NVMe sections. Fibre Channel logins represent connections formed by Fibre Channel initiators that have successfully logged in to ONTAP.
- 

## IP

### Interfaces

An interface (also referred to as a *LIF* in ONTAP documentation) represents a network access point to a node in a cluster. In other words, an interface is essentially an IPv4 or IPv6 address with associated attributes.

IP interfaces are configured on ports to send and receive communications over the network. The port that will host the interface can either be explicitly specified using node and/or port fields or implicitly specified using a broadcast domain.

The IPspace of the interface is required for cluster-scoped interfaces. The SVM owning the interface is required for SVM-scoped interfaces. These interfaces are in the SVM's IPspace.

The service policy of an interface defines what network services are provided by the interface.

### Routes

Routes indicate which IPv4 or IPv6 gateway to use to communicate with hosts that are not on the local subnet. Typically, an IP interface (or LIF) can only use a gateway if it has the same address family and is in the LIF's subnet.

It is important that every gateway address belongs to a physical or virtual router that has connectivity to the specified destination network.

SVM-scoped routes can only be used by IP interfaces of the specified SVM. Likewise, cluster-scoped routes can only be used by cluster-scoped IP interfaces in the specified IPspace.

## Service Policies

Service policies are named groupings that define what services are supported by an IP interface. These include both built-in service policies (for example: default-data-files or default-management) and custom service policies.

Service policies are scoped to either an SVM or IPspace.

---

# Manage broadcast domains

## Network Ethernet broadcast-domains endpoint overview

### Overview

A broadcast domain is a collection of Ethernet ports that have layer 2 connectivity. They are used to determine which Ethernet ports can host interfaces of various types. The broadcast domain REST API allows you to retrieve, create, modify, and delete broadcast domains. The broadcast domain APIs do not manage port membership. To add a port to a broadcast domain or to move a port to a different broadcast domain, use PATCH /network/ethernet/ports/<uuid>.</uuid>

### Retrieving network Ethernet broadcast domain information

The broadcast domains GET API retrieves and displays relevant information pertaining to the broadcast domains configured in the cluster. The API retrieves the list of all broadcast domains configured in the cluster, or a specific broadcast domain.

---

## Examples

### Retrieving all broadcast domains in the cluster

The following output shows the list of all broadcast domains configured in a cluster.

```
# The API:  
/api/network/ethernet/broadcast-domains  
  
# The call:  
curl -X GET "https://<mgmt-ip>/api/network/ethernet/broadcast-domains" -H  
"accept: application/hal+json"  
  
# The response:  
{  
"records": [  
]
```

```
{
  "uuid": "6970c2a9-f34f-11e8-8373-005056bb6b85",
  "name": "Cluster",
  "ipspace": {
    "uuid": "6267eff8-f34f-11e8-8373-005056bb6b85",
    "name": "Cluster",
    "_links": {
      "self": {
        "href": "/api/network/ipspaces/6267eff8-f34f-11e8-8373-005056bb6b85"
      }
    }
  },
  "ports": [
    {
      "uuid": "626b4d19-f34f-11e8-8373-005056bb6b85",
      "name": "e0a",
      "node": {
        "name": "examplecluster-node01"
      },
      "_links": {
        "self": {
          "href": "/api/network/ethernet/ports/626b4d19-f34f-11e8-8373-005056bb6b85"
        }
      }
    },
    {
      "uuid": "626b77b9-f34f-11e8-8373-005056bb6b85",
      "name": "e0b",
      "node": {
        "name": "examplecluster-node01"
      },
      "_links": {
        "self": {
          "href": "/api/network/ethernet/ports/626b77b9-f34f-11e8-8373-005056bb6b85"
        }
      }
    }
  ],
  "mtu": 9000,
  "_links": {
    "self": {
      "href": "/api/network/ethernet/broadcast-domains/6970c2a9-f34f-11e8-8373-005056bb6b85"
    }
  }
}
```

```

        }
    },
},
{
"uuid": "6972416c-f34f-11e8-8373-005056bb6b85",
"name": "Default",
"ipspace": {
    "uuid": "5f650349-f34f-11e8-8373-005056bb6b85",
    "name": "Default",
    "_links": {
        "self": {
            "href": "/api/network/ipspaces/5f650349-f34f-11e8-8373-
005056bb6b85"
        }
    }
},
"ports": [
{
    "uuid": "626bae19-f34f-11e8-8373-005056bb6b85",
    "name": "e0c",
    "node": {
        "name": "examplecluster-node01"
    },
    "_links": {
        "self": {
            "href": "/api/network/ethernet/ports/626bae19-f34f-11e8-8373-
005056bb6b85"
        }
    }
},
{
    "uuid": "626bd677-f34f-11e8-8373-005056bb6b85",
    "name": "e0d",
    "node": {
        "name": "examplecluster-node01"
    },
    "_links": {
        "self": {
            "href": "/api/network/ethernet/ports/626bd677-f34f-11e8-8373-
005056bb6b85"
        }
    }
},
],
"mtu": 1500,
"_links": {

```

```

    "self": {
      "href": "/api/network/ethernet/broadcast-domains/6972416c-f34f-
11e8-8373-005056bb6b85"
    }
  }
],
"num_records": 2,
"_links": {
  "self": {
    "href": "/api/network/ethernet/broadcast-domains?fields=*>"
  }
}
}

```

### Retrieving a specific broadcast domain

The following output shows the response returned when a specific broadcast domain is requested. The system returns an error if there is no broadcast domain with the requested UUID.

```

# The API:
/api/network/ethernet/broadcast-domains/{uuid}

# The call:
curl -X GET "https://<mgmt-ip>/api/network/ethernet/broadcast-
domains/4475a2c8-f8a0-11e8-8d33-005056bb986f/?fields=*>" -H "accept:
application/hal+json"

# The response:
{
  "uuid": "4475a2c8-f8a0-11e8-8d33-005056bb986f",
  "name": "Cluster",
  "ipspace": {
    "uuid": "3e518ed5-f8a0-11e8-8d33-005056bb986f",
    "name": "Cluster",
    "_links": {
      "self": {
        "href": "/api/network/ipspaces/3e518ed5-f8a0-11e8-8d33-005056bb986f"
      }
    }
  },
  "ports": [
    {

```

```

"uuid": "3e539a62-f8a0-11e8-8d33-005056bb986f",
"name": "e0a",
"node": {
    "name": "examplecluster-node01"
},
"_links": {
    "self": {
        "href": "/api/network/ethernet/ports/3e539a62-f8a0-11e8-8d33-
005056bb986f"
    }
}
},
{
"uuid": "3e53c94a-f8a0-11e8-8d33-005056bb986f",
"name": "e0b",
"node": {
    "name": "examplecluster-node01"
},
"_links": {
    "self": {
        "href": "/api/network/ethernet/ports/3e53c94a-f8a0-11e8-8d33-
005056bb986f"
    }
}
],
"mtu": 9000,
"_links": {
    "self": {
        "href": "/api/network/ethernet/broadcast-domains/4475a2c8-f8a0-11e8-
8d33-005056bb986f/"
    }
}
}

```

#### **Retrieving all broadcast domains with a specific name**

The following output shows the response returned when broadcast domains with a specific name in any IPspace are requested.

```

# The API:
/api/network/ethernet/broadcast-domains

# The call:
curl -X GET "https://10.224.87.121/api/network/ethernet/broadcast-
domains/?name=bd1" -H "accept: application/hal+json"

# The response:
{
  "records": [
    {
      "uuid": "66b607e5-4bee-11e9-af6a-005056bb13c0",
      "name": "bd1",
      "_links": {
        "self": {
          "href": "/api/network/ethernet/broadcast-domains/66b607e5-4bee-
11e9-af6a-005056bb13c0"
        }
      }
    }
  ],
  "num_records": 1,
  "_links": {
    "self": {
      "href": "/api/network/ethernet/broadcast-domains/?name=bd1"
    }
  }
}

```

#### Retrieving the broadcast domains for an IPspace

The following output shows the response returned when the broadcast domains for a specified IPspace are requested.

```

# The API:
/api/network/ethernet/broadcast-domains

# The call:
curl -X GET "https://10.224.87.121/api/network/ethernet/broadcast-
domains/?ipspace.name=Cluster&fields=*" -H "accept: application/hal+json"

# The response:

```

```
{
  "records": [
    {
      "uuid": "ae69070c-4bed-11e9-af6a-005056bb13c0",
      "name": "Cluster",
      "ipspace": {
        "uuid": "ac466a88-4bed-11e9-af6a-005056bb13c0",
        "name": "Cluster",
        "_links": {
          "self": {
            "href": "/api/network/ipspaces/ac466a88-4bed-11e9-af6a-005056bb13c0"
          }
        }
      },
      "ports": [
        {
          "uuid": "acd67884-4bed-11e9-af6a-005056bb13c0",
          "name": "e0a",
          "node": {
            "name": "examplecluster-node-1"
          },
          "_links": {
            "self": {
              "href": "/api/network/ethernet/ports/acd67884-4bed-11e9-af6a-005056bb13c0"
            }
          }
        },
        {
          "uuid": "ace1a36f-4bed-11e9-af6a-005056bb13c0",
          "name": "e0b",
          "node": {
            "name": "examplecluster-node-1"
          },
          "_links": {
            "self": {
              "href": "/api/network/ethernet/ports/ace1a36f-4bed-11e9-af6a-005056bb13c0"
            }
          }
        }
      ],
      "mtu": 1500,
      "_links": {
        "self": {

```

```
        "href": "/api/network/ethernet/broadcast-domains/ae69070c-4bed-  
11e9-af6a-005056bb13c0"  
    }  
}  
}  
]  
,"num_records": 1,  
"_links": {  
    "self": {  
        "href": "/api/network/ethernet/broadcast-  
domains/?ipspace.name=Cluster&fields=*"  
    }  
}
```

## Creating network Ethernet broadcast domains

You can use the POST API to create broadcast domains.

### Example

#### Creating a new broadcast domain

The following example shows how to create a broadcast domain with a name of 'bd1' and an MTU of 1500.

```

# The API:
/api/network/ethernet/broadcast-domains

# The call:
curl -X POST "https://<mgmt-ip>/api/network/ethernet/broadcast-
domains?return_records=true" -H "accept: application/hal+json" -d '{
"name": "bd1", "mtu": 1500 }'

# The response:
{
  "num_records": 1,
  "records": [
    {
      "name": "bd1",
      "mtu": 1500,
      "_links": {
        "self": {
          "href": "/api/network/ethernet/broadcast-domains/"
        }
      }
    }
  ]
}

```

## Updating network Ethernet broadcast domains

You can use the PATCH API to update the attributes of broadcast domains.

---

## Examples

### Updating the name and MTU of a specific broadcast domain

The following example shows how the PATCH request changes the broadcast domain name to 'bd2' and the broadcast domain MTU to 9000.

```
# The API:  
/api/network/ethernet/broadcast-domains/{uuid}  
  
# The call:  
curl -X PATCH "https://<mgmt-ip>/api/network/ethernet/broadcast-  
domains/6cde03b2-f8a2-11e8-8d33-005056bb986f/" -d '{ "name": "bd2", "mtu":  
9000 }'  
{  
}
```

### Updating the IPspace of a specific broadcast domain

The following example shows how the PATCH request changes the IPspace of a broadcast domain to 'ipspace2'.

```
# The API:  
/api/network/ethernet/broadcast-domains/{uuid}  
  
# The call:  
curl -X PATCH "https://<mgmt-  
ip>/api/network/ethernet/broadcast_domains/c6fe2541-61f4-11e9-a66e-  
005056bbe83e" -d '{ "ipspace" : { "name" : "ipspace2" } }'  
{  
}
```

### Deleting network Ethernet broadcast domains

You can use the DELETE API to delete a broadcast domain from the cluster configuration.

#### Example

##### Deleting a specific broadcast domain

The following DELETE request deletes a broadcast domain.

```
# The API:  
/api/network/ethernet/broadcast-domains/{uuid}  
  
# The call:  
curl -X DELETE "https://<mgmt-ip>/api/network/ethernet/broadcast-  
domains/6cde03b2-f8a2-11e8-8d33-005056bb986f/"
```

## Retrieve broadcast domains for the entire cluster

GET /network/ethernet/broadcast-domains

Retrieves a collection of broadcast domains for the entire cluster.

### Related ONTAP commands

- `network port broadcast-domain show`

### Learn more

- [DOC /network/ethernet/broadcast-domains](#)

### Parameters

Name	Type	In	Required	Description
name	string	query	False	Filter by name
mtu	integer	query	False	Filter by mtu
ports.name	string	query	False	Filter by ports.name
ports.node.name	string	query	False	Filter by ports.node.name
ports.uuid	string	query	False	Filter by ports.uuid
uuid	string	query	False	Filter by uuid
ipspace.uuid	string	query	False	Filter by ipspace.uuid
ipspace.name	string	query	False	Filter by ipspace.name

Name	Type	In	Required	Description
fields	array[string]	query	False	Specify the fields to return.
max_records	integer	query	False	Limit the number of records returned.
return_records	boolean	query	False	The default is true for GET calls. When set to false, only the number of records is returned.
return_timeout	integer	query	False	The number of seconds to allow the call to execute before returning. When iterating over a collection, the default is 15 seconds. ONTAP returns earlier if either max records or the end of the collection is reached.
order_by	array[string]	query	False	Order results by specified fields and optional [asc]

## Response

Status: 200, Ok

Name	Type	Description
_links	<a href="#">_links</a>	
num_records	integer	
records	array[broadcast_domain]	

## Example response

```
{  
    "_links": {  
        "next": {  
            "href": "/api/resourcelink"  
        },  
        "self": {  
            "href": "/api/resourcelink"  
        }  
    },  
    "records": {  
        "_links": {  
            "self": {  
                "href": "/api/resourcelink"  
            }  
        },  
        "ipspace": {  
            "_links": {  
                "self": {  
                    "href": "/api/resourcelink"  
                }  
            },  
            "name": "exchange",  
            "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
        },  
        "mtu": 1500,  
        "name": "bd1",  
        "ports": {  
            "_links": {  
                "self": {  
                    "href": "/api/resourcelink"  
                }  
            },  
            "name": "elb",  
            "node": {  
                "name": "node1"  
            },  
            "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
        },  
        "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
    }  
}
```

## Error

Status: Default, Error

Name	Type	Description
error	error	

### Example error

```
{
  "error": {
    "arguments": {
      "code": "string",
      "message": "string"
    },
    "code": "4",
    "message": "entry doesn't exist",
    "target": "uuid"
  }
}
```

## Definitions

## See Definitions

href

Name	Type	Description
href	string	

\_links

Name	Type	Description
next	<a href="#">href</a>	
self	<a href="#">href</a>	

\_links

Name	Type	Description
self	<a href="#">href</a>	

ipspace

Applies to both SVM and cluster-scoped objects. Either the UUID or name is supplied on input.

Name	Type	Description
_links	<a href="#">_links</a>	
name	string	IPspace name
uuid	string	IPspace UUID

node

Name	Type	Description
name	string	Name of node on which the port is located.

ports

Port UUID along with readable names

Name	Type	Description
_links	<a href="#">_links</a>	
name	string	
node	<a href="#">node</a>	
uuid	string	

## broadcast\_domain

Set of ports that will receive a broadcast Ethernet packet from any of them

Name	Type	Description
_links	<a href="#">_links</a>	
ipspace	<a href="#">ipspace</a>	Applies to both SVM and cluster-scoped objects. Either the UUID or name is supplied on input.
mtu	integer	Maximum transmission unit, largest packet size on this network
name	string	Name of the broadcast domain, scoped to its IPspace
ports	array[ <a href="#">ports</a> ]	Ports that belong to the broadcast domain
uuid	string	Broadcast domain UUID

## error\_arguments

Name	Type	Description
code	string	Argument code
message	string	Message argument

## error

Name	Type	Description
arguments	array[ <a href="#">error_arguments</a> ]	Message arguments
code	string	Error code
message	string	Error message
target	string	The target parameter that caused the error.

## Create a new broadcast domain

POST /network/ethernet/broadcast-domains

Creates a new broadcast domain.

## Required properties

- `name` - Name of the broadcast-domain to create.
- `mtu` - Maximum transmission unit (MTU) of the broadcast domain.

## Recommended optional properties

- `ipspace.name` or `ipspace.uuid` - IPspace the broadcast domain belongs to.

## Default property values

If not specified in POST, the following default property values are assigned:

- `ipspace` - *Default*

## Related ONTAP commands

- `network port broadcast-domain create`

## Learn more

- [DOC /network/ethernet/broadcast-domains](#)

## Parameters

Name	Type	In	Required	Description
return_records	boolean	query	False	The default is false. If set to true, the records are returned.

## Request Body

Name	Type	Description
_links	<a href="#">_links</a>	
ipspace	<a href="#">ipspace</a>	Applies to both SVM and cluster-scoped objects. Either the UUID or name is supplied on input.
mtu	integer	Maximum transmission unit, largest packet size on this network
name	string	Name of the broadcast domain, scoped to its IPspace

Name	Type	Description
ports	array[ports]	Ports that belong to the broadcast domain
uuid	string	Broadcast domain UUID

### Example request

```
{
  "_links": {
    "self": {
      "href": "/api/resourcelink"
    }
  },
  "ipspace": {
    "_links": {
      "self": {
        "href": "/api/resourcelink"
      }
    },
    "name": "exchange",
    "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"
  },
  "mtu": 1500,
  "name": "bd1",
  "ports": {
    "_links": {
      "self": {
        "href": "/api/resourcelink"
      }
    },
    "name": "elb",
    "node": {
      "name": "node1"
    },
    "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"
  },
  "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"
}
```

### Response

Status: 201, Created

## Error

Status: Default

## ONTAP Error Response Codes

Error Code	Description
1377267	The specified IPspace does not exist.
1967082	The specified ipspace.name does not match the IPspace name of ipspace.uuid.
1967102	A POST operation might have left the configuration in an inconsistent state. Check the configuration.
53281982	The specified broadcast domain name is reserved by the system.

Name	Type	Description
error	error	

## Example error

```
{
  "error": {
    "arguments": {
      "code": "string",
      "message": "string"
    },
    "code": "4",
    "message": "entry doesn't exist",
    "target": "uuid"
  }
}
```

## Definitions

## See Definitions

href

Name	Type	Description
href	string	

\_links

Name	Type	Description
self	href	

ipspace

Applies to both SVM and cluster-scoped objects. Either the UUID or name is supplied on input.

Name	Type	Description
_links	_links	
name	string	IPspace name
uuid	string	IPspace UUID

node

Name	Type	Description
name	string	Name of node on which the port is located.

ports

Port UUID along with readable names

Name	Type	Description
_links	_links	
name	string	
node	node	
uuid	string	

broadcast\_domain

Set of ports that will receive a broadcast Ethernet packet from any of them

Name	Type	Description
_links	_links	

Name	Type	Description
ipspace	ipspace	Applies to both SVM and cluster-scoped objects. Either the UUID or name is supplied on input.
mtu	integer	Maximum transmission unit, largest packet size on this network
name	string	Name of the broadcast domain, scoped to its IPspace
ports	array[ports]	Ports that belong to the broadcast domain
uuid	string	Broadcast domain UUID

#### error\_arguments

Name	Type	Description
code	string	Argument code
message	string	Message argument

#### error

Name	Type	Description
arguments	array[error_arguments]	Message arguments
code	string	Error code
message	string	Error message
target	string	The target parameter that caused the error.

## Delete a broadcast domain

`DELETE /network/ethernet/broadcast-domains/{uuid}`

Deletes a broadcast domain.

## Related ONTAP commands

- network port broadcast-domain delete

## Learn more

- [DOC /network/ethernet/broadcast-domains](#)

## Parameters

Name	Type	In	Required	Description
uuid	string	path	True	

## Response

```
Status: 200, Ok
```

## Error

```
Status: Default
```

## ONTAP Error Response Codes

Error Code	Description
1967103	A broadcast domain with ports cannot be deleted.

Name	Type	Description
error	error	

## Example error

```
{
  "error": {
    "arguments": {
      "code": "string",
      "message": "string"
    },
    "code": "4",
    "message": "entry doesn't exist",
    "target": "uuid"
  }
}
```

## Definitions

### See Definitions

error\_arguments

Name	Type	Description
code	string	Argument code
message	string	Message argument

error

Name	Type	Description
arguments	array[error_arguments]	Message arguments
code	string	Error code
message	string	Error message
target	string	The target parameter that caused the error.

## Retrieve broadcast domain details

GET /network/ethernet/broadcast-domains/{uuid}

Retrieves details of a broadcast domain.

### Related ONTAP commands

- network port broadcast-domain show

### Learn more

- [DOC /network/ethernet/broadcast-domains](#)

### Parameters

Name	Type	In	Required	Description
uuid	string	path	True	Broadcast domain UUID
fields	array[string]	query	False	Specify the fields to return.

## Response

Status: 200, Ok

Name	Type	Description
_links	<a href="#">_links</a>	
ipspace	<a href="#">ipspace</a>	Applies to both SVM and cluster-scoped objects. Either the UUID or name is supplied on input.
mtu	integer	Maximum transmission unit, largest packet size on this network
name	string	Name of the broadcast domain, scoped to its IPspace
ports	array[ <a href="#">ports</a> ]	Ports that belong to the broadcast domain
uuid	string	Broadcast domain UUID

## Example response

```
{  
    "_links": {  
        "self": {  
            "href": "/api/resourcelink"  
        }  
    },  
    "ipspace": {  
        "_links": {  
            "self": {  
                "href": "/api/resourcelink"  
            }  
        },  
        "name": "exchange",  
        "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
    },  
    "mtu": 1500,  
    "name": "bd1",  
    "ports": {  
        "_links": {  
            "self": {  
                "href": "/api/resourcelink"  
            }  
        },  
        "name": "elb",  
        "node": {  
            "name": "node1"  
        },  
        "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
    },  
    "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
}
```

## Error

Status: Default, Error

Name	Type	Description
error	error	

## Example error

```
{  
  "error": {  
    "arguments": {  
      "code": "string",  
      "message": "string"  
    },  
    "code": "4",  
    "message": "entry doesn't exist",  
    "target": "uuid"  
  }  
}
```

## Definitions

## See Definitions

href

Name	Type	Description
href	string	

\_links

Name	Type	Description
self	href	

ipspace

Applies to both SVM and cluster-scoped objects. Either the UUID or name is supplied on input.

Name	Type	Description
_links	_links	
name	string	IPspace name
uuid	string	IPspace UUID

node

Name	Type	Description
name	string	Name of node on which the port is located.

ports

Port UUID along with readable names

Name	Type	Description
_links	_links	
name	string	
node	node	
uuid	string	

error\_arguments

Name	Type	Description
code	string	Argument code

Name	Type	Description
message	string	Message argument
error		
Name	Type	Description
arguments	array[error_arguments]	Message arguments
code	string	Error code
message	string	Error message
target	string	The target parameter that caused the error.

## Update broadcast domain properties

PATCH /network/ethernet/broadcast-domains/{uuid}

Updates the properties of a broadcast domain.

### Related ONTAP commands

- network port broadcast-domain modify
- network port broadcast-domain rename

### Learn more

- [DOC /network/ethernet/broadcast-domains](#)

### Parameters

Name	Type	In	Required	Description
uuid	string	path	True	Broadcast domain UUID

### Request Body

Name	Type	Description
_links	_links	
ipspace	ipspace	Applies to both SVM and cluster-scoped objects. Either the UUID or name is supplied on input.

Name	Type	Description
mtu	integer	Maximum transmission unit, largest packet size on this network
name	string	Name of the broadcast domain, scoped to its IPspace
ports	array[ <a href="#">ports</a> ]	Ports that belong to the broadcast domain
uuid	string	Broadcast domain UUID

## Example request

```
{  
    "_links": {  
        "self": {  
            "href": "/api/resourcelink"  
        }  
    },  
    "ipspace": {  
        "_links": {  
            "self": {  
                "href": "/api/resourcelink"  
            }  
        },  
        "name": "exchange",  
        "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
    },  
    "mtu": 1500,  
    "name": "bd1",  
    "ports": {  
        "_links": {  
            "self": {  
                "href": "/api/resourcelink"  
            }  
        },  
        "name": "elb",  
        "node": {  
            "name": "node1"  
        },  
        "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
    },  
    "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
}
```

## Response

```
Status: 200, Ok
```

## Error

```
Status: Default
```

## ONTAP Error Response Codes

Error Code	Description
1377267	The specified IPspace does not exist.
1377269	Failed to lookup the specified IPspace.
1377560	Broadcast domain already exists in specified IPspace.
1377605	Moving the system-generated broadcast domain to another IPspace is not supported.
1967082	The specified ipspace.name does not match the IPspace name of ipspace.uuid.
1967150	The specified ipspace.uuid is not valid.
1967151	The specified ipspace.uuid and ipspace.name do not match.
1967152	Patching IPspace for a broadcast domain requires an effective cluster version of 9.7 or later.

Name	Type	Description
error	error	

### Example error

```
{  
  "error": {  
    "arguments": {  
      "code": "string",  
      "message": "string"  
    },  
    "code": "4",  
    "message": "entry doesn't exist",  
    "target": "uuid"  
  }  
}
```

### Definitions

## See Definitions

href

Name	Type	Description
href	string	

\_links

Name	Type	Description
self	href	

ipspace

Applies to both SVM and cluster-scoped objects. Either the UUID or name is supplied on input.

Name	Type	Description
_links	_links	
name	string	IPspace name
uuid	string	IPspace UUID

node

Name	Type	Description
name	string	Name of node on which the port is located.

ports

Port UUID along with readable names

Name	Type	Description
_links	_links	
name	string	
node	node	
uuid	string	

broadcast\_domain

Set of ports that will receive a broadcast Ethernet packet from any of them

Name	Type	Description
_links	_links	

Name	Type	Description
ipspace	ipspace	Applies to both SVM and cluster-scoped objects. Either the UUID or name is supplied on input.
mtu	integer	Maximum transmission unit, largest packet size on this network
name	string	Name of the broadcast domain, scoped to its IPspace
ports	array[ports]	Ports that belong to the broadcast domain
uuid	string	Broadcast domain UUID

#### error\_arguments

Name	Type	Description
code	string	Argument code
message	string	Message argument

#### error

Name	Type	Description
arguments	array[error_arguments]	Message arguments
code	string	Error code
message	string	Error message
target	string	The target parameter that caused the error.

## Manage network Ethernet ports

### Network Ethernet ports endpoint overview

#### Overview

A port is a physical or virtual Ethernet network device. Physical ports may be combined into Link Aggregation Groups (LAGs or ifgrps), or divided into Virtual LANs (VLANs).

GET (collection), GET (instance), and PATCH APIs are available for all port types. POST and DELETE APIs are available for "lag" (ifgrp) and "vlan" port types.

## Retrieving network port information

The network ports GET API retrieves and displays relevant information pertaining to the ports configured in the cluster. The API retrieves the list of all ports configured in the cluster, or specifically requested ports. The fields returned in the response vary for different ports and configurations.

## Examples

### Retrieving all ports in the cluster

The following output displays the UUID, name, and port type for all ports configured in a 2-node cluster. The port types are physical, vlan, and lag (ifgrp).

```
# The API:  
/api/network/ethernet/ports  
  
# The call:  
curl -X GET "https://<mgmt-  
ip>/api/network/ethernet/ports?fields=uuid,name,type" -H "accept:  
application/hal+json"  
  
# The response:  
{  
  "records": [  
    {  
      "uuid": "2d2c90c0-f70d-11e8-b145-005056bb5b8e",  
      "name": "e0a",  
      "type": "physical",  
      "_links": {  
        "self": {  
          "href": "/api/network/ethernet/ports/2d2c90c0-f70d-11e8-b145-  
005056bb5b8e"  
        }  
      }  
    },  
    {  
      "uuid": "2d3004da-f70d-11e8-b145-005056bb5b8e",  
      "name": "e0b",  
      "type": "physical",  
      "_links": {  
        "self": {  
          "href": "/api/network/ethernet/ports/2d3004da-f70d-11e8-b145-  
005056bb5b8e"  
        }  
      }  
    }  
  ]  
}
```

```

        }
    }
},
{
    "uuid": "2d34a2cb-f70d-11e8-b145-005056bb5b8e",
    "name": "e0c",
    "type": "physical",
    "_links": {
        "self": {
            "href": "/api/network/ethernet/ports/2d34a2cb-f70d-11e8-b145-
005056bb5b8e"
        }
    }
},
{
    "uuid": "2d37189f-f70d-11e8-b145-005056bb5b8e",
    "name": "e0d",
    "type": "physical",
    "_links": {
        "self": {
            "href": "/api/network/ethernet/ports/2d37189f-f70d-11e8-b145-
005056bb5b8e"
        }
    }
},
{
    "uuid": "35de5d8b-f70d-11e8-abdf-005056bb7fc8",
    "name": "e0a",
    "type": "physical",
    "_links": {
        "self": {
            "href": "/api/network/ethernet/ports/35de5d8b-f70d-11e8-abdf-
005056bb7fc8"
        }
    }
},
{
    "uuid": "35de78cc-f70d-11e8-abdf-005056bb7fc8",
    "name": "e0b",
    "type": "physical",
    "_links": {
        "self": {
            "href": "/api/network/ethernet/ports/35de78cc-f70d-11e8-abdf-
005056bb7fc8"
        }
    }
}

```

```

} ,
{
  "uuid": "35dead3c-f70d-11e8-abdf-005056bb7fc8",
  "name": "e0c",
  "type": "physical",
  "_links": {
    "self": {
      "href": "/api/network/ethernet/ports/35dead3c-f70d-11e8-abdf-
005056bb7fc8"
    }
  }
},
{
  "uuid": "35deda90-f70d-11e8-abdf-005056bb7fc8",
  "name": "e0d",
  "type": "physical",
  "_links": {
    "self": {
      "href": "/api/network/ethernet/ports/35deda90-f70d-11e8-abdf-
005056bb7fc8"
    }
  }
},
{
  "uuid": "42e25145-f97d-11e8-ade9-005056bb7fc8",
  "name": "e0c-100",
  "type": "vlan",
  "_links": {
    "self": {
      "href": "/api/network/ethernet/ports/42e25145-f97d-11e8-ade9-
005056bb7fc8"
    }
  }
},
{
  "uuid": "569e0abd-f97d-11e8-ade9-005056bb7fc8",
  "name": "a0a",
  "type": "lag",
  "_links": {
    "self": {
      "href": "/api/network/ethernet/ports/569e0abd-f97d-11e8-ade9-
005056bb7fc8"
    }
  }
}
],

```

```

"num_records": 10,
"_links": {
  "self": {
    "href": "/api/network/ethernet/ports?fields=uuid,name,type"
  }
}
}

```

### Retrieving a specific physical port

The following output displays the response when a specific physical port is requested. The system returns an error when there is no port with the requested UUID. Also, the speed field is set only if the state of the port is up.

```

# The API:
/api/network/ethernet/ports/{uuid}

# The call:
curl -X GET "https://<mgmt-ip>/api/network/ethernet/ports/2d37189f-f70d-
11e8-b145-005056bb5b8e?fields=*" -H "accept: application/hal+json"

# The response:
{
  "uuid": "2d37189f-f70d-11e8-b145-005056bb5b8e",
  "name": "e0d",
  "mac_address": "00:50:56:bb:62:2d",
  "type": "physical",
  "node": {
    "uuid": "faa56898-f70c-11e8-b145-005056bb5b8e",
    "name": "user-cluster-01",
    "_links": {
      "self": {
        "href": "/api/cluster/nodes/faa56898-f70c-11e8-b145-005056bb5b8e"
      }
    }
  },
  "broadcast_domain": {
    "uuid": "36434bec-f70d-11e8-b145-005056bb5b8e",
    "name": "Default",
    "ipspace": {
      "name": "Default"
    },
    "_links": {

```

```

    "self": {
      "href": "/api/network/ethernet/broadcast-domains/36434bec-f70d-11e8-
b145-005056bb5b8e"
    }
  },
  "enabled": true,
  "state": "up",
  "mtu": 1500,
  "speed": "1000",
  "_links": {
    "self": {
      "href": "/api/network/ethernet/ports/2d37189f-f70d-11e8-b145-
005056bb5b8e"
    }
  }
}

```

#### Retrieving a specific VLAN port

The following output displays the response when a specific VLAN port is requested. The system returns an error when there is no port with the requested UUID. Also, the speed field is set only if the state of the port is up.

```

# The API:
/api/network/ethernet/ports/{uuid}

# The call:
curl -X GET "https://<mgmt-ip>/api/network/ethernet/ports/42e25145-f97d-
11e8-ade9-005056bb7fc8?fields=*" -H "accept: application/hal+json"

# The response:
{
  "uuid": "42e25145-f97d-11e8-ade9-005056bb7fc8",
  "name": "e0e-100",
  "mac_address": "00:50:56:bb:52:2f",
  "type": "vlan",
  "node": {
    "uuid": "6042cf47-f70c-11e8-abdf-005056bb7fc8",
    "name": "user-cluster-02",
    "_links": {
      "self": {
        "href": "/api/cluster/nodes/6042cf47-f70c-11e8-abdf-005056bb7fc8"
      }
    }
  }
}

```

```

        }
    }
},
"enabled": true,
"state": "up",
"mtu": 1500,
"speed": "1000",
"vlan": {
    "tag": 100,
    "base_port": {
        "uuid": "35deff03-f70d-11e8-abdf-005056bb7fc8",
        "name": "e0e",
        "node": {
            "name": "user-cluster-02"
        },
        "_links": {
            "self": {
                "href": "/api/network/ethernet/ports/35deff03-f70d-11e8-abdf-
005056bb7fc8"
            }
        }
    }
},
"_links": {
    "self": {
        "href": "/api/network/ethernet/ports/42e25145-f97d-11e8-ade9-
005056bb7fc8"
    }
}
}

```

#### Retrieving a specific LAG port

The following output displays the response when a specific LAG port is requested. The system returns an error when there is no port with the requested UUID. Also, the speed and lag.active\_ports fields are set only if the state of the port is up.

```

# The API:
/api/network/ethernet/ports/{uuid}

# The call:
curl -X GET "https://<mgmt-ip>/api/network/ethernet/ports/569e0abd-f97d-
11e8-ade9-005056bb7fc8?fields=*" -H "accept: application/hal+json"

```

```

# The response:
{
  "uuid": "569e0abd-f97d-11e8-ade9-005056bb7fc8",
  "name": "a0a",
  "mac_address": "02:50:56:bb:7f:c8",
  "type": "lag",
  "node": {
    "uuid": "6042cf47-f70c-11e8-abdf-005056bb7fc8",
    "name": "user-cluster-02",
    "_links": {
      "self": {
        "href": "/api/cluster/nodes/6042cf47-f70c-11e8-abdf-005056bb7fc8"
      }
    }
  },
  "enabled": true,
  "state": "up",
  "mtu": 1500,
  "speed": "1000",
  "lag": {
    "mode": "singlemode",
    "distribution_policy": "mac",
    "member_ports": [
      {
        "uuid": "35df318d-f70d-11e8-abdf-005056bb7fc8",
        "name": "e0f",
        "node": {
          "name": "user-cluster-02"
        },
        "_links": {
          "self": {
            "href": "/api/network/ethernet/ports/35df318d-f70d-11e8-abdf-005056bb7fc8"
          }
        }
      },
      {
        "uuid": "35df5bad-f70d-11e8-abdf-005056bb7fc8",
        "name": "e0g",
        "node": {
          "name": "user-cluster-02"
        },
        "_links": {
          "self": {
            "href": "/api/network/ethernet/ports/35df5bad-f70d-11e8-abdf-005056bb7fc8"
          }
        }
      }
    ]
  }
}

```

```

005056bb7fc8"
    }
}
},
{
  "uuid": "35df9926-f70d-11e8-abdf-005056bb7fc8",
  "name": "e0h",
  "node": {
    "name": "user-cluster-02"
  },
  "_links": {
    "self": {
      "href": "/api/network/ethernet/ports/35df9926-f70d-11e8-abdf-
005056bb7fc8"
    }
  }
}
],
"active_ports": [
  {
    "uuid": "35df318d-f70d-11e8-abdf-005056bb7fc8",
    "name": "e0f",
    "_links": {
      "self": {
        "href": "/api/network/ethernet/ports/35df318d-f70d-11e8-abdf-
005056bb7fc8"
      }
    }
  }
]
},
"_links": {
  "self": {
    "href": "/api/network/ethernet/ports/569e0abd-f97d-11e8-adef-
005056bb7fc8"
  }
}
}

```

#### Retrieving all LAG (ifgrp) ports in the cluster

This command retrieves all LAG ports in the cluster (that is, all ports with type=LAG). The example shows how to filter a GET collection based on type.

```

# The API:
/api/network/ethernet/ports

# The call:
curl -X GET "https://<mgmt-
ip>/api/network/ethernet/ports?type=lag&node.name=user-cluster-
01&fields=name(enabled,speed,mtu)" -H "accept: application/hal+json"

# The response:
{
  "records": [
    {
      "uuid": "0c226db0-4b63-11e9-8113-005056bbe040",
      "name": "a0b",
      "type": "lag",
      "node": {
        "name": "user-cluster-01"
      },
      "enabled": true,
      "mtu": 1500,
      "speed": "1000",
      "_links": {
        "self": {
          "href": "/api/network/ethernet/ports/0c226db0-4b63-11e9-8113-
005056bbe040"
        }
      }
    },
    {
      "uuid": "d3a84153-4b3f-11e9-a00d-005056bbe040",
      "name": "a0a",
      "type": "lag",
      "node": {
        "name": "user-cluster-01"
      },
      "enabled": true,
      "mtu": 1500,
      "speed": "1000",
      "_links": {
        "self": {
          "href": "/api/network/ethernet/ports/d3a84153-4b3f-11e9-a00d-
005056bbe040"
        }
      }
    }
  ]
}

```

```
],
"num_records": 2,
"_links": {
  "self": {
    "href":
    "/api/network/ethernet/ports?fields=name,enabled,speed,mtu&type=lag&node.name=user-cluster-01"
  }
}
}
```

## Creating VLAN and LAG ports

You can use the network ports POST API to create VLAN and LAG ports.

## Examples

### Creating a VLAN port

The following output displays the record returned after the creation of a VLAN port on "e0e" and VLAN tag "100". Also, the VLAN port is added to the "Default" broadcast domain in the "Default" IPspace.

```
# The API:
/api/network/ethernet/ports

# The call:
curl -X POST "https://<mgtm-
ip>/api/network/ethernet/ports?return_records=true" -H "accept:
application/hal+json" -H "Content-Type: application/json" -d "{
\"type\": \"vlan\", \"node\": { \"name\": \"user-cluster-01\" },
\"broadcast_domain\": { \"name\": \"Default\", \"ipspace\": { \"name\":
\"Default\" } }, \"enabled\": true, \"vlan\": { \"tag\": 100,
\"base_port\": { \"name\": \"e0e\", \"node\": { \"name\": \"user-cluster-
01\" } } } }"

# The response:
{
"num_records": 1,
"records": [
{
  "uuid": "88b2f682-fa42-11e8-a6d7-005056bb5b8e",
  "type": "vlan",
```

```

"node": {
    "uuid": "faa56898-f70c-11e8-b145-005056bb5b8e",
    "name": "user-cluster-01",
    "_links": {
        "self": {
            "href": "/api/cluster/nodes/faa56898-f70c-11e8-b145-
005056bb5b8e"
        }
    }
},
"broadcast_domain": {
    "uuid": "36434bec-f70d-11e8-b145-005056bb5b8e",
    "name": "Default",
    "ipspace": {
        "name": "Default"
    },
    "_links": {
        "self": {
            "href": "/api/network/ethernet/broadcast-domains/36434bec-f70d-
11e8-b145-005056bb5b8e"
        }
    }
},
"enabled": true,
"vlan": {
    "tag": 100,
    "base_port": {
        "uuid": "2d39df72-f70d-11e8-b145-005056bb5b8e",
        "name": "e0e",
        "node": {
            "name": "user-cluster-01"
        },
        "_links": {
            "self": {
                "href": "/api/network/ethernet/ports/2d39df72-f70d-11e8-b145-
005056bb5b8e"
            }
        }
    }
},
"_links": {
    "self": {
        "href": "/api/network/ethernet/ports/88b2f682-fa42-11e8-a6d7-
005056bb5b8e"
    }
}
}

```

```
    }
]
}
```

### Creating a LAG (ifgrp) port

The following output displays the record returned after the creation of a LAG port with "e0f", "e0g" and "e0h" as member ports.

```
# The API:
/api/network/ethernet/ports

# The call:
curl -X POST "https://<mgmt-
ip>/api/network/ethernet/ports?return_records=true" -H "accept:
application/json" -H "Content-Type: application/json" -d "{ \"type\":
\"lag\", \"node\": { \"name\": \"user-cluster-01\" }, \"broadcast_domain\": { \"name\": \"Default\", \"ipspace\": { \"name\":
\"Default\" } }, \"enabled\": true, \"lag\": { \"mode\": \"singlemode\", \"distribution_policy\": \"mac\", \"member_ports\": [ { \"name\": \"e0f\", \"node\": { \"name\": \"user-cluster-01\" } }, { \"name\": \"e0g\", \"node\": { \"name\": \"user-cluster-01\" } }, { \"name\": \"e0h\", \"node\": { \"name\": \"user-cluster-01\" } } ] } }" -u admin:netapp1! -k

# The response:
{
  "num_records": 1,
  "records": [
    {
      "uuid": "1807772a-fa4d-11e8-a6d7-005056bb5b8e",
      "type": "lag",
      "node": {
        "uuid": "faa56898-f70c-11e8-b145-005056bb5b8e",
        "name": "user-cluster-01"
      },
      "broadcast_domain": {
        "uuid": "36434bec-f70d-11e8-b145-005056bb5b8e",
        "name": "Default",
        "ipspace": {
          "name": "Default"
        }
      },
      "enabled": true,
```

```

"lag": {
    "mode": "singlemode",
    "distribution_policy": "mac",
    "member_ports": [
        {
            "uuid": "2d3c9adc-f70d-11e8-b145-005056bb5b8e",
            "name": "e0f",
            "node": {
                "name": "user-cluster-01"
            }
        },
        {
            "uuid": "2d40b097-f70d-11e8-b145-005056bb5b8e",
            "name": "e0g",
            "node": {
                "name": "user-cluster-01"
            }
        },
        {
            "uuid": "2d46d01e-f70d-11e8-b145-005056bb5b8e",
            "name": "e0h",
            "node": {
                "name": "user-cluster-01"
            }
        }
    ]
}
]
}

```

## Updating ports

You can use the network ports PATCH API to update the attributes of ports.

---

## Examples

### Updating the broadcast domain of a port

The following PATCH request removes the port from the current broadcast domain and adds it to the specified broadcast domain.

```
# The API:  
/api/network/ethernet/ports/{uuid}  
  
# The call:  
curl -X PATCH "https://<mgmt-ip>/api/network/ethernet/ports/6867efaf-d702-  
11e8-994f-005056bbc994" -H "accept: application/hal+json" -H "Content-  
Type: application/json" -d "{ \"broadcast_domain\": { \"name\":  
\"Default\", \"ipspace\": { \"name\": \"Default\" } } }"
```

### Updating the admin status of a port

The following PATCH request brings the specified port down.

```
# The API:  
/api/network/ethernet/ports/{uuid}  
  
# The call:  
curl -X PATCH "https://<mgmt-ip>/api/network/ethernet/ports/51d3ab39-d86d-  
11e8-aca6-005056bbc994" -H "accept: application/hal+json" -H "Content-  
Type: application/json" -d "{ \"enabled\": \"false\" }"
```

## Deleting ports

You can use the network ports DELETE API to delete VLAN and LAG ports in the cluster. Note that physical ports cannot be deleted. Deleting a port also removes the port from the broadcast domain.

### Example

#### Deleting a VLAN port

The network ports DELETE API is used to delete a VLAN port.

```
# The API:  
/api/network/ethernet/ports/{uuid}  
  
# The call:  
curl -X DELETE "https://<mgmt-ip>/api/network/ethernet/ports/6867efaf-d702-11e8-994f-005056bbc994" -H "accept: application/hal+json" -H  
"Content-Type: application/json"
```

## Retrieve ports

GET /network/ethernet/ports

Retrieves a collection of ports (physical, VLAN and LAG) for an entire cluster.

### Related ONTAP commands

- network port show
- network port ifgrp show
- network port vlan show

### Learn more

- [DOC /network/ethernet/ports](#)

### Parameters

Name	Type	In	Required	Description
mac_address	string	query	False	Filter by mac_address
speed	integer	query	False	Filter by speed
state	string	query	False	Filter by state
mtu	integer	query	False	Filter by mtu
name	string	query	False	Filter by name
node.uuid	string	query	False	Filter by node.uuid
node.name	string	query	False	Filter by node.name

Name	Type	In	Required	Description
vlan.base_port.name	string	query	False	Filter by vlan.base_port.name
vlan.base_port.node.name	string	query	False	Filter by vlan.base_port.node.name
vlan.base_port.uuid	string	query	False	Filter by vlan.base_port.uuid
vlan.tag	integer	query	False	Filter by vlan.tag
enabled	boolean	query	False	Filter by enabled
uuid	string	query	False	Filter by uuid
broadcast_domain.ip_space.name	string	query	False	Filter by broadcast_domain.ip_space.name
broadcast_domain.uid	string	query	False	Filter by broadcast_domain.uid
broadcast_domain.name	string	query	False	Filter by broadcast_domain.name
type	string	query	False	Filter by type
lag.active_ports.name	string	query	False	Filter by lag.active_ports.name
lag.active_ports.node.name	string	query	False	Filter by lag.active_ports.node.name
lag.active_ports.uuid	string	query	False	Filter by lag.active_ports.uuid
lag.distribution_policy	string	query	False	Filter by lag.distribution_policy

Name	Type	In	Required	Description
lag.mode	string	query	False	Filter by lag.mode
lag.member_ports.name	string	query	False	Filter by lag.member_ports.name
lag.member_ports.node.name	string	query	False	Filter by lag.member_ports.node.name
lag.member_ports.uid	string	query	False	Filter by lag.member_ports.uid
fields	array[string]	query	False	Specify the fields to return.
max_records	integer	query	False	Limit the number of records returned.
return_records	boolean	query	False	The default is true for GET calls. When set to false, only the number of records is returned.
return_timeout	integer	query	False	The number of seconds to allow the call to execute before returning. When iterating over a collection, the default is 15 seconds. ONTAP returns earlier if either max records or the end of the collection is reached.
order_by	array[string]	query	False	Order results by specified fields and optional [asc

## Response

Status: 200, Ok

Name	Type	Description
_links	<a href="#">_links</a>	
num_records	integer	
records	array[ <a href="#">port</a> ]	

## Example response

```
{  
    "_links": {  
        "next": {  
            "href": "/api/resourcelink"  
        },  
        "self": {  
            "href": "/api/resourcelink"  
        }  
    },  
    "records": {  
        "_links": {  
            "self": {  
                "href": "/api/resourcelink"  
            }  
        },  
        "broadcast_domain": {  
            "_links": {  
                "self": {  
                    "href": "/api/resourcelink"  
                }  
            },  
            "ipspace": {  
                "name": "ipspace1"  
            },  
            "name": "bd1",  
            "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
        },  
        "lag": {  
            "active_ports": {  
                "_links": {  
                    "self": {  
                        "href": "/api/resourcelink"  
                    }  
                },  
                "name": "elb",  
                "node": {  
                    "name": "node1"  
                },  
                "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
            },  
            "distribution_policy": "port",  
            "member_ports": {  
                "_links": {  
                    "self": {  
                        "href": "/api/resourcelink"  
                    }  
                }  
            }  
        }  
    }  
}
```

```

        "href": "/api/resourcelink"
    }
},
"name": "e1b",
"node": {
    "name": "node1"
},
"uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"
},
"mode": "multimode_lacp"
},
"mac_address": "01:02:03:04:05:06",
"mtu": 1500,
"name": "e1b",
"node": {
    "_links": {
        "self": {
            "href": "/api/resourcelink"
        }
    },
    "name": "node1",
    "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"
},
"speed": 1000,
"state": "up",
"type": "vlan",
"uuid": "1cd8a442-86d1-11e0-ae1c-123478563412",
"vlan": {
    "base_port": {
        "_links": {
            "self": {
                "href": "/api/resourcelink"
            }
        }
    },
    "name": "e1b",
    "node": {
        "name": "node1"
    },
    "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"
},
"tag": 100
}
}
}

```

## Error

Status: Default, Error

Name	Type	Description
error	error	

### Example error

```
{  
  "error": {  
    "arguments": {  
      "code": "string",  
      "message": "string"  
    },  
    "code": "4",  
    "message": "entry doesn't exist",  
    "target": "uuid"  
  }  
}
```

## Definitions

## See Definitions

href

Name	Type	Description
href	string	

\_links

Name	Type	Description
next	href	
self	href	

\_links

Name	Type	Description
self	href	

ipspace

Name	Type	Description
name	string	Name of the broadcast domain's IPspace

broadcast\_domain

Broadcast domain UUID along with a readable name. Either the UUID or both names may be provided on input.

Name	Type	Description
_links	_links	
ipspace	ipspace	
name	string	Name of the broadcast domain, scoped to its IPspace
uuid	string	Broadcast domain UUID

node

Name	Type	Description
name	string	Name of node on which the port is located.

## active\_ports

Port UUID along with readable names. Either the UUID or both names may be supplied on input.

Name	Type	Description
_links	<a href="#">_links</a>	
name	string	
node	<a href="#">node</a>	
uuid	string	

## member\_ports

Port UUID along with readable names. Either the UUID or both names may be supplied on input.

Name	Type	Description
_links	<a href="#">_links</a>	
name	string	
node	<a href="#">node</a>	
uuid	string	

## lag

Name	Type	Description
active_ports	array[ <a href="#">active_ports</a> ]	Active ports of a LAG (ifgrp). (Some member ports may be inactive.)
distribution_policy	string	Policy for mapping flows to ports for outbound packets through a LAG (ifgrp).
member_ports	array[ <a href="#">member_ports</a> ]	
mode	string	Determines how the ports interact with the switch.

## node

Name	Type	Description
_links	<a href="#">_links</a>	
name	string	
uuid	string	

## base\_port

Port UUID along with readable names. Either the UUID or both names may be supplied on input.

Name	Type	Description
_links	<a href="#">_links</a>	
name	string	
node	<a href="#">node</a>	
uuid	string	

vlan

Name	Type	Description
base_port	<a href="#">base_port</a>	Port UUID along with readable names. Either the UUID or both names may be supplied on input.
tag	integer	VLAN ID

port

Name	Type	Description
_links	<a href="#">_links</a>	
broadcast_domain	<a href="#">broadcast_domain</a>	Broadcast domain UUID along with a readable name. Either the UUID or both names may be provided on input.
enabled	boolean	
lag	<a href="#">lag</a>	
mac_address	string	
mtu	integer	MTU of the port in bytes. Set by broadcast domain.
name	string	Portname, such as e0a, e1b-100 (VLAN on ethernet), a0c (LAG/ifgrp), a0d-200 (vlan on LAG/ifgrp)
node	<a href="#">node</a>	
speed	integer	Link speed in Mbps
state	string	Operational state of the port.
type	string	Type of physical or virtual port

Name	Type	Description
uuid	string	Port UUID
vlan	vlan	

error\_arguments

Name	Type	Description
code	string	Argument code
message	string	Message argument

error

Name	Type	Description
arguments	array[error_arguments]	Message arguments
code	string	Error code
message	string	Error message
target	string	The target parameter that caused the error.

## Create a new VLAN or LAG

POST /network/ethernet/ports

Creates a new VLAN (such as node1:e0a-100) or LAG (ifgrp, such as node2:a0a).

### Required properties

- node - Node the port will be created on.
- broadcast\_domain - Broadcast domain the port is associated with.
- type - Defines if a VLAN or LAG will be created:
  - VLAN
    - vlan.base\_port - Physical port or LAG the VLAN will be created on.
    - vlan.tag - Tag used to identify VLAN on the base port.
  - LAG
    - lag.mode - Policy for the LAG that will be created.
    - lag.distribution\_policy - Indicates how the packets are distributed between ports.

- `lag.member_ports` - Set of ports the LAG consists of.

## Related ONTAP commands

- `network port ifgrp create`
- `network port vlan create`

## Learn more

- [DOC /network/ethernet/ports](#)

## Parameters

Name	Type	In	Required	Description
return_records	boolean	query	False	The default is false. If set to true, the records are returned.

## Request Body

Name	Type	Description
<code>_links</code>	<a href="#">_links</a>	
<code>broadcast_domain</code>	<a href="#">broadcast_domain</a>	Broadcast domain UUID along with a readable name. Either the UUID or both names may be provided on input.
<code>enabled</code>	boolean	
<code>lag</code>	<a href="#">lag</a>	
<code>mac_address</code>	string	
<code>mtu</code>	integer	MTU of the port in bytes. Set by broadcast domain.
<code>name</code>	string	Portname, such as e0a, e1b-100 (VLAN on ethernet), a0c (LAG/ifgrp), a0d-200 (vlan on LAG/ifgrp)
<code>node</code>	<a href="#">node</a>	
<code>speed</code>	integer	Link speed in Mbps
<code>state</code>	string	Operational state of the port.

Name	Type	Description
type	string	Type of physical or virtual port
uuid	string	Port UUID
vlan	<a href="#">vlan</a>	

## Example request

```
{  
    "_links": {  
        "self": {  
            "href": "/api/resourcelink"  
        }  
    },  
    "broadcast_domain": {  
        "_links": {  
            "self": {  
                "href": "/api/resourcelink"  
            }  
        },  
        "ipspace": {  
            "name": "ipspace1"  
        },  
        "name": "bd1",  
        "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
    },  
    "lag": {  
        "active_ports": {  
            "_links": {  
                "self": {  
                    "href": "/api/resourcelink"  
                }  
            },  
            "name": "elb",  
            "node": {  
                "name": "node1"  
            },  
            "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
        },  
        "distribution_policy": "port",  
        "member_ports": {  
            "_links": {  
                "self": {  
                    "href": "/api/resourcelink"  
                }  
            },  
            "name": "elb",  
            "node": {  
                "name": "node1"  
            },  
            "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
        },  
    }  
}
```

```

    "mode": "multimode_lacp",
},
"mac_address": "01:02:03:04:05:06",
"mtu": 1500,
"name": "elb",
"node": {
    "_links": {
        "self": {
            "href": "/api/resourcelink"
        }
    },
    "name": "node1",
    "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"
},
"speed": 1000,
"state": "up",
"type": "vlan",
"uuid": "1cd8a442-86d1-11e0-ae1c-123478563412",
"vlan": {
    "base_port": {
        "_links": {
            "self": {
                "href": "/api/resourcelink"
            }
        },
        "name": "elb",
        "node": {
            "name": "node1"
        },
        "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"
    },
    "tag": 100
}
}
}

```

## Response

Status: 201, Created

Name	Type	Description
_links	_links	
num_records	integer	

Name	Type	Description
records	array[ <a href="#">port</a> ]	

## Example response

```
{  
    "_links": {  
        "next": {  
            "href": "/api/resourcelink"  
        },  
        "self": {  
            "href": "/api/resourcelink"  
        }  
    },  
    "records": {  
        "_links": {  
            "self": {  
                "href": "/api/resourcelink"  
            }  
        },  
        "broadcast_domain": {  
            "_links": {  
                "self": {  
                    "href": "/api/resourcelink"  
                }  
            },  
            "ipspace": {  
                "name": "ipspace1"  
            },  
            "name": "bd1",  
            "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
        },  
        "lag": {  
            "active_ports": {  
                "_links": {  
                    "self": {  
                        "href": "/api/resourcelink"  
                    }  
                },  
                "name": "elb",  
                "node": {  
                    "name": "node1"  
                },  
                "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
            },  
            "distribution_policy": "port",  
            "member_ports": {  
                "_links": {  
                    "self": {  
                        "href": "/api/resourcelink"  
                    }  
                }  
            }  
        }  
    }  
}
```

```

        "href": "/api/resourcelink"
    }
},
"name": "e1b",
"node": {
    "name": "node1"
},
"uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"
},
"mode": "multimode_lacp"
},
"mac_address": "01:02:03:04:05:06",
"mtu": 1500,
"name": "e1b",
"node": {
    "_links": {
        "self": {
            "href": "/api/resourcelink"
        }
    },
    "name": "node1",
    "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"
},
"speed": 1000,
"state": "up",
"type": "vlan",
"uuid": "1cd8a442-86d1-11e0-ae1c-123478563412",
"vlan": {
    "base_port": {
        "_links": {
            "self": {
                "href": "/api/resourcelink"
            }
        }
    },
    "name": "e1b",
    "node": {
        "name": "node1"
    },
    "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"
},
"tag": 100
}
}
}

```

## Error

Status: Default

### ONTAP Error Response Codes

Error Code	Description
1376361	Port is already a member of a LAG.
1966189	Port is the home port or current port of an interface.
1967083	The specified type is not valid.
1967084	The specified node UUID is not valid.
1967085	The specified node name is not valid.
1967086	Node name and UUID must match if both are provided.
1967087	The specified broadcast domain UUID is not valid.
1967088	The specified broadcast domain name does not exist in the specified IPspace.
1967089	The specified broadcast domain UUID, name, and IPspace name do not match.
1967090	The specified VLAN base port UUID is not valid.
1967091	The specified VLAN base port name and node name are not valid.
1967092	The specified node does not match the node specified for the VLAN base port.
1967093	The specified VLAN base port UUID, name, and VLAN base port node name do not match.
1967094	The specified LAG member port UUID is not valid.
1967095	The specified LAG member port name and node name combination is not valid.
1967096	The specified node does not match the specified LAG member port node.
1967097	The specified LAG member ports UUID, name, and node name do not match.
1967098	VLAN POST operation has failed because admin status could not be set for the specified port.
1967099	Partial success of the VLAN POST operation. Verify the state of the created VLAN for more information.
1967100	LAG POST operation failed because admin status could not be set.

Error Code	Description
1967101	Partial success of the LAG POST operation. Verify the state of the created LAG for more information.
1967102	POST operation might have left the configuration in an inconsistent state. Check the configuration.
1967148	Failure to remove port from broadcast domain.
1967149	Failure to add port to broadcast domain.
1967175	VLANs cannot be created on ports in the Cluster IPspace.

Name	Type	Description
error	error	

### Example error

```
{
  "error": {
    "arguments": {
      "code": "string",
      "message": "string"
    },
    "code": "4",
    "message": "entry doesn't exist",
    "target": "uuid"
  }
}
```

### Definitions

## See Definitions

href

Name	Type	Description
href	string	

\_links

Name	Type	Description
self	href	

ipspace

Name	Type	Description
name	string	Name of the broadcast domain's IPspace

broadcast\_domain

Broadcast domain UUID along with a readable name. Either the UUID or both names may be provided on input.

Name	Type	Description
_links	_links	
ipspace	ipspace	
name	string	Name of the broadcast domain, scoped to its IPspace
uuid	string	Broadcast domain UUID

node

Name	Type	Description
name	string	Name of node on which the port is located.

active\_ports

Port UUID along with readable names. Either the UUID or both names may be supplied on input.

Name	Type	Description
_links	_links	

Name	Type	Description
name	string	
node	<a href="#">node</a>	
uuid	string	

### member\_ports

Port UUID along with readable names. Either the UUID or both names may be supplied on input.

Name	Type	Description
_links	<a href="#">_links</a>	
name	string	
node	<a href="#">node</a>	
uuid	string	

### lag

Name	Type	Description
active_ports	array[ <a href="#">active_ports</a> ]	Active ports of a LAG (ifgrp). (Some member ports may be inactive.)
distribution_policy	string	Policy for mapping flows to ports for outbound packets through a LAG (ifgrp).
member_ports	array[ <a href="#">member_ports</a> ]	
mode	string	Determines how the ports interact with the switch.

### node

Name	Type	Description
_links	<a href="#">_links</a>	
name	string	
uuid	string	

### base\_port

Port UUID along with readable names. Either the UUID or both names may be supplied on input.

Name	Type	Description
_links	<a href="#">_links</a>	

Name	Type	Description
name	string	
node	<a href="#">node</a>	
uuid	string	

vlan

Name	Type	Description
base_port	<a href="#">base_port</a>	Port UUID along with readable names. Either the UUID or both names may be supplied on input.
tag	integer	VLAN ID

port

Name	Type	Description
_links	<a href="#">_links</a>	
broadcast_domain	<a href="#">broadcast_domain</a>	Broadcast domain UUID along with a readable name. Either the UUID or both names may be provided on input.
enabled	boolean	
lag	<a href="#">lag</a>	
mac_address	string	
mtu	integer	MTU of the port in bytes. Set by broadcast domain.
name	string	Portname, such as e0a, e1b-100 (VLAN on ethernet), a0c (LAG/ifgrp), a0d-200 (vlan on LAG/ifgrp)
node	<a href="#">node</a>	
speed	integer	Link speed in Mbps
state	string	Operational state of the port.
type	string	Type of physical or virtual port
uuid	string	Port UUID

Name	Type	Description
vlan	vlan	

\_links

Name	Type	Description
next	href	
self	href	

error\_arguments

Name	Type	Description
code	string	Argument code
message	string	Message argument

error

Name	Type	Description
arguments	array[error_arguments]	Message arguments
code	string	Error code
message	string	Error message
target	string	The target parameter that caused the error.

## Delete a VLAN or LAG

DELETE /network/ethernet/ports/{uuid}

Deletes a VLAN or LAG.

### Related ONTAP commands

- network port ifgrp delete
- network port vlan delete

### Learn more

- [DOC /network/ethernet/ports](#)

## Parameters

Name	Type	In	Required	Description
uuid	string	path	True	

## Response

```
Status: 200, Ok
```

## Error

```
Status: Default
```

## ONTAP Error Response Codes

Error Code	Description
1376858	Port already has an interface bound.
1966189	Port is the home port or current port of an interface.

Name	Type	Description
error	error	

## Example error

```
{
  "error": {
    "arguments": {
      "code": "string",
      "message": "string"
    },
    "code": "4",
    "message": "entry doesn't exist",
    "target": "uuid"
  }
}
```

## Definitions

## See Definitions

error\_arguments

Name	Type	Description
code	string	Argument code
message	string	Message argument

error

Name	Type	Description
arguments	array[error_arguments]	Message arguments
code	string	Error code
message	string	Error message
target	string	The target parameter that caused the error.

## Retrieve a physical port, VLAN, or LAG details

GET /network/ethernet/ports/{uuid}

Retrieves the details of a physical port, VLAN, or LAG.

### Related ONTAP commands

- network port show
- network port ifgrp show
- network port vlan show

### Learn more

- [DOC /network/ethernet/ports](#)

### Parameters

Name	Type	In	Required	Description
uuid	string	path	True	Port UUID
fields	array[string]	query	False	Specify the fields to return.

## Response

Status: 200, Ok

Name	Type	Description
_links	<a href="#">_links</a>	
broadcast_domain	<a href="#">broadcast_domain</a>	Broadcast domain UUID along with a readable name. Either the UUID or both names may be provided on input.
enabled	boolean	
lag	<a href="#">lag</a>	
mac_address	string	
mtu	integer	MTU of the port in bytes. Set by broadcast domain.
name	string	Portname, such as e0a, e1b-100 (VLAN on ethernet), a0c (LAG/ifgrp), a0d-200 (vlan on LAG/ifgrp)
node	<a href="#">node</a>	
speed	integer	Link speed in Mbps
state	string	Operational state of the port.
type	string	Type of physical or virtual port
uuid	string	Port UUID
vlan	<a href="#">vlan</a>	

## Example response

```
{  
    "_links": {  
        "self": {  
            "href": "/api/resourcelink"  
        }  
    },  
    "broadcast_domain": {  
        "_links": {  
            "self": {  
                "href": "/api/resourcelink"  
            }  
        },  
        "ipspace": {  
            "name": "ipspace1"  
        },  
        "name": "bd1",  
        "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
    },  
    "lag": {  
        "active_ports": {  
            "_links": {  
                "self": {  
                    "href": "/api/resourcelink"  
                }  
            },  
            "name": "elb",  
            "node": {  
                "name": "node1"  
            },  
            "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
        },  
        "distribution_policy": "port",  
        "member_ports": {  
            "_links": {  
                "self": {  
                    "href": "/api/resourcelink"  
                }  
            },  
            "name": "elb",  
            "node": {  
                "name": "node1"  
            },  
            "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
        },  
    }  
}
```

```

    "mode": "multimode_lacp",
},
"mac_address": "01:02:03:04:05:06",
"mtu": 1500,
"name": "elb",
"node": {
    "_links": {
        "self": {
            "href": "/api/resourcelink"
        }
    },
    "name": "node1",
    "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"
},
"speed": 1000,
"state": "up",
"type": "vlan",
"uuid": "1cd8a442-86d1-11e0-ae1c-123478563412",
"vlan": {
    "base_port": {
        "_links": {
            "self": {
                "href": "/api/resourcelink"
            }
        },
        "name": "elb",
        "node": {
            "name": "node1"
        },
        "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"
    },
    "tag": 100
}
}

```

## Error

Status: Default, Error

Name	Type	Description
error	error	

## Example error

```
{  
  "error": {  
    "arguments": {  
      "code": "string",  
      "message": "string"  
    },  
    "code": "4",  
    "message": "entry doesn't exist",  
    "target": "uuid"  
  }  
}
```

## Definitions

## See Definitions

href

Name	Type	Description
href	string	

\_links

Name	Type	Description
self	href	

ipspace

Name	Type	Description
name	string	Name of the broadcast domain's IPspace

broadcast\_domain

Broadcast domain UUID along with a readable name. Either the UUID or both names may be provided on input.

Name	Type	Description
_links	_links	
ipspace	ipspace	
name	string	Name of the broadcast domain, scoped to its IPspace
uuid	string	Broadcast domain UUID

node

Name	Type	Description
name	string	Name of node on which the port is located.

active\_ports

Port UUID along with readable names. Either the UUID or both names may be supplied on input.

Name	Type	Description
_links	_links	

Name	Type	Description
name	string	
node	<a href="#">node</a>	
uuid	string	

### member\_ports

Port UUID along with readable names. Either the UUID or both names may be supplied on input.

Name	Type	Description
_links	<a href="#">_links</a>	
name	string	
node	<a href="#">node</a>	
uuid	string	

### lag

Name	Type	Description
active_ports	array[ <a href="#">active_ports</a> ]	Active ports of a LAG (ifgrp). (Some member ports may be inactive.)
distribution_policy	string	Policy for mapping flows to ports for outbound packets through a LAG (ifgrp).
member_ports	array[ <a href="#">member_ports</a> ]	
mode	string	Determines how the ports interact with the switch.

### node

Name	Type	Description
_links	<a href="#">_links</a>	
name	string	
uuid	string	

### base\_port

Port UUID along with readable names. Either the UUID or both names may be supplied on input.

Name	Type	Description
_links	<a href="#">_links</a>	

Name	Type	Description
name	string	
node	<a href="#">node</a>	
uuid	string	

vlan

Name	Type	Description
base_port	<a href="#">base_port</a>	Port UUID along with readable names. Either the UUID or both names may be supplied on input.
tag	integer	VLAN ID

error\_arguments

Name	Type	Description
code	string	Argument code
message	string	Message argument

error

Name	Type	Description
arguments	<a href="#">array[error_arguments]</a>	Message arguments
code	string	Error code
message	string	Error message
target	string	The target parameter that caused the error.

## Update a port

PATCH /network/ethernet/ports/{uuid}

Updates a port.

### Related ONTAP commands

- `network port broadcast-domain add-ports`

- network port broadcast-domain remove-ports
- network port ifgrp modify
- network port modify
- network port vlan modify

## Learn more

- [DOC /network/ethernet/ports](#)

## Parameters

Name	Type	In	Required	Description
uuid	string	path	True	Port UUID

## Request Body

Name	Type	Description
_links	<a href="#">_links</a>	
broadcast_domain	<a href="#">broadcast_domain</a>	Broadcast domain UUID along with a readable name. Either the UUID or both names may be provided on input.
enabled	boolean	
lag	<a href="#">lag</a>	
mac_address	string	
mtu	integer	MTU of the port in bytes. Set by broadcast domain.
name	string	Portname, such as e0a, e1b-100 (VLAN on ethernet), a0c (LAG/ifgrp), a0d-200 (vlan on LAG/ifgrp)
node	<a href="#">node</a>	
speed	integer	Link speed in Mbps
state	string	Operational state of the port.
type	string	Type of physical or virtual port
uuid	string	Port UUID

Name	Type	Description
vlan	<a href="#">vlan</a>	

## Example request

```
{  
    "_links": {  
        "self": {  
            "href": "/api/resourcelink"  
        }  
    },  
    "broadcast_domain": {  
        "_links": {  
            "self": {  
                "href": "/api/resourcelink"  
            }  
        },  
        "ipspace": {  
            "name": "ipspace1"  
        },  
        "name": "bd1",  
        "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
    },  
    "lag": {  
        "active_ports": {  
            "_links": {  
                "self": {  
                    "href": "/api/resourcelink"  
                }  
            },  
            "name": "elb",  
            "node": {  
                "name": "node1"  
            },  
            "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
        },  
        "distribution_policy": "port",  
        "member_ports": {  
            "_links": {  
                "self": {  
                    "href": "/api/resourcelink"  
                }  
            },  
            "name": "elb",  
            "node": {  
                "name": "node1"  
            },  
            "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
        },  
    }  
}
```

```

    "mode": "multimode_lacp",
},
"mac_address": "01:02:03:04:05:06",
"mtu": 1500,
"name": "elb",
"node": {
    "_links": {
        "self": {
            "href": "/api/resourcelink"
        }
    },
    "name": "node1",
    "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"
},
"speed": 1000,
"state": "up",
"type": "vlan",
"uuid": "1cd8a442-86d1-11e0-ae1c-123478563412",
"vlan": {
    "base_port": {
        "_links": {
            "self": {
                "href": "/api/resourcelink"
            }
        },
        "name": "elb",
        "node": {
            "name": "node1"
        },
        "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"
    },
    "tag": 100
}
}

```

## Response

Status: 200, Ok

## Error

Status: Default

## ONTAP Error Response Codes

Error Code	Description
1376361	Port is already a member of a LAG.
1377562	Port cannot be used because it is currently the home port or current port of an interface.
1377563	Port is already a member of a LAG.
1967087	The specified broadcast domain UUID is not valid.
1967088	The specified broadcast domain name does not exist in the specified IPspace.
1967089	The specified broadcast domain UUID, name and IPspace name do not match.
1967094	The specified LAG member port UUID is not valid.
1967095	The specified LAG member port name and node name combination is not valid.
1967096	The specified node does not match the specified LAG member port node.
1967097	The specified LAG member ports UUID, name, and node name do not match.
1967148	Failure to remove port from broadcast domain.
1967149	Failure to add port to broadcast domain.

Name	Type	Description
error	error	

### Example error

```
{
  "error": {
    "arguments": {
      "code": "string",
      "message": "string"
    },
    "code": "4",
    "message": "entry doesn't exist",
    "target": "uuid"
  }
}
```

## **Definitions**

## See Definitions

href

Name	Type	Description
href	string	

\_links

Name	Type	Description
self	href	

ipspace

Name	Type	Description
name	string	Name of the broadcast domain's IPspace

broadcast\_domain

Broadcast domain UUID along with a readable name. Either the UUID or both names may be provided on input.

Name	Type	Description
_links	_links	
ipspace	ipspace	
name	string	Name of the broadcast domain, scoped to its IPspace
uuid	string	Broadcast domain UUID

node

Name	Type	Description
name	string	Name of node on which the port is located.

active\_ports

Port UUID along with readable names. Either the UUID or both names may be supplied on input.

Name	Type	Description
_links	_links	

Name	Type	Description
name	string	
node	<a href="#">node</a>	
uuid	string	

### member\_ports

Port UUID along with readable names. Either the UUID or both names may be supplied on input.

Name	Type	Description
_links	<a href="#">_links</a>	
name	string	
node	<a href="#">node</a>	
uuid	string	

### lag

Name	Type	Description
active_ports	array[ <a href="#">active_ports</a> ]	Active ports of a LAG (ifgrp). (Some member ports may be inactive.)
distribution_policy	string	Policy for mapping flows to ports for outbound packets through a LAG (ifgrp).
member_ports	array[ <a href="#">member_ports</a> ]	
mode	string	Determines how the ports interact with the switch.

### node

Name	Type	Description
_links	<a href="#">_links</a>	
name	string	
uuid	string	

### base\_port

Port UUID along with readable names. Either the UUID or both names may be supplied on input.

Name	Type	Description
_links	<a href="#">_links</a>	

Name	Type	Description
name	string	
node	<a href="#">node</a>	
uuid	string	

vlan

Name	Type	Description
base_port	<a href="#">base_port</a>	Port UUID along with readable names. Either the UUID or both names may be supplied on input.
tag	integer	VLAN ID

port

Name	Type	Description
_links	<a href="#">_links</a>	
broadcast_domain	<a href="#">broadcast_domain</a>	Broadcast domain UUID along with a readable name. Either the UUID or both names may be provided on input.
enabled	boolean	
lag	<a href="#">lag</a>	
mac_address	string	
mtu	integer	MTU of the port in bytes. Set by broadcast domain.
name	string	Portname, such as e0a, e1b-100 (VLAN on ethernet), a0c (LAG/ifgrp), a0d-200 (vlan on LAG/ifgrp)
node	<a href="#">node</a>	
speed	integer	Link speed in Mbps
state	string	Operational state of the port.
type	string	Type of physical or virtual port
uuid	string	Port UUID

Name	Type	Description
vlan	vlan	

error\_arguments

Name	Type	Description
code	string	Argument code
message	string	Message argument

error

Name	Type	Description
arguments	array[error_arguments]	Message arguments
code	string	Error code
message	string	Error message
target	string	The target parameter that caused the error.

## Manage FC network interfaces

### Network FC interfaces endpoint overview

#### Overview

Fibre Channel (FC) interfaces are the logical endpoints for FC network connections to an SVM. An FC interface provides FC access to storage within the interface SVM using either Fibre Channel Protocol or NVMe over FC (NVMe/FC).

The Fibre Channel interface REST API allows you to create, delete, update, and discover FC interfaces, and obtain status information for FC interfaces.

An FC interface is created on an FC port which is located on a cluster node. The FC port must be specified to identify the location of the interface for a POST or PATCH request that relocates an interface. You can identify the port by supplying either the node and port names or the port UUID.

#### Examples

##### Creating an FC interface using the port node and name to identify the location

This example uses the `return_records` query parameter to retrieve the newly created FC interface in the POST response.

```

# The API:
POST /api/network/fc/interfaces

# The call:
curl -X POST 'https://<mgmt-
ip>/api/network/fc/interfaces?return_records=true' -H 'accept:
application/hal+json' -d '{ "svm": { "name": "svml" }, "name": "lif1",
"location": { "port": { "name": "0a", "node": { "name": "node1" } } },
"data_protocol": "fcp" }'

# The response:
{
  "num_records": 1,
  "records": [
    {
      "svm": {
        "uuid": "cf300f5c-db83-11e8-bd46-005056bba0e0",
        "name": "svml",
        "_links": {
          "self": {
            "href": "/api/svm/svms/cf300f5c-db83-11e8-bd46-005056bba0e0"
          }
        }
      },
      "uuid": "f6045b92-dec7-11e8-a733-005056bba0e0",
      "name": "lif1",
      "location": {
        "node": {
          "uuid": "bafe9b9f-db81-11e8-bd46-005056bba0e0",
          "name": "node1",
          "_links": {
            "self": {
              "href": "/api/cluster/nodes/bafe9b9f-db81-11e8-bd46-
005056bba0e0"
            }
          }
        }
      },
      "port": {
        "uuid": "300c1ae3-db82-11e8-bd46-005056bba0e0",
        "name": "0a",
        "node": {
          "name": "node1"
        },
        "_links": {
          "self": {
            "href": "/api/network/fc/ports/300c1ae3-db82-11e8-bd46-

```

```

        "005056bba0e0"
    }
}
},
{
"enabled": true,
"state": "down",
"data_protocol": "fcp",
"wwpn": "20:04:00:50:56:bb:a0:e0",
"wwnn": "20:00:00:50:56:bb:a0:e0",
"port_address": "9da2cb1",
"_links": {
    "self": {
        "href": "/api/network/fc/interfaces/f6045b92-dec7-11e8-a733-
005056bba0e0"
    }
}
}
]
}

```

#### **Creating an FC interface using the port UUID to identify the location**

This example uses the `return_records` query parameter to retrieve the newly created FC interface in the POST response.

```

# The API:
POST /api/network/fc/interfaces

# The call:
curl -X POST 'https://<mgmt-
ip>/api/network/fc/interfaces?return_records=true' -H 'accept:
application/hal+json' -d '{ "svm": { "name": "svm3" }, "name": "lif2",
"location": { "port": { "uuid": "24bb636a-db83-11e8-9a49-005056bb1ec6" } },
"data_protocol": "fc_nvme" }'

# The response:
{
"num_records": 1,
"records": [
{
    "svm": {
        "uuid": "a5060466-dbab-11e8-bd46-005056bba0e0",
        "name": "svm3",

```

```

    "_links": {
        "self": {
            "href": "/api/svm/svms/a5060466-dbab-11e8-bd46-005056bba0e0"
        }
    },
    "uuid": "cdeb5591-dec9-11e8-a733-005056bba0e0",
    "name": "lif2",
    "location": {
        "node": {
            "uuid": "e85aa147-db83-11e8-9a48-005056bb1ec6",
            "name": "node3",
            "_links": {
                "self": {
                    "href": "/api/cluster/nodes/e85aa147-db83-11e8-9a48-
005056bb1ec6"
                }
            }
        },
        "port": {
            "uuid": "24bb636a-db83-11e8-9a49-005056bb1ec6",
            "name": "1b",
            "node": {
                "name": "node3"
            },
            "_links": {
                "self": {
                    "href": "/api/network/fc/ports/24bb636a-db83-11e8-9a49-
005056bb1ec6"
                }
            }
        }
    },
    "enabled": true,
    "state": "down",
    "data_protocol": "fc_nvme",
    "wwpn": "20:05:00:50:56:bb:a0:e0",
    "wwnn": "20:02:00:50:56:bb:a0:e0",
    "port_address": "612e202b",
    "_links": {
        "self": {
            "href": "/api/network/fc/interfaces/cdeb5591-dec9-11e8-a733-
005056bba0e0"
        }
    }
}

```

]  
}

## **Retrieving all properties for all FC interfaces**

This example uses the `fields` query parameter to retrieve all properties.

```

        "name": "node3"
    },
    "_links": {
        "self": {
            "href": "/api/network/fc/ports/24bb636a-db83-11e8-9a49-
005056bb1ec6"
        }
    }
},
"enabled": true,
"state": "down",
"data_protocol": "fc_nvme",
"wwpn": "20:05:00:50:56:bb:a0:e0",
"wwnn": "20:02:00:50:56:bb:a0:e0",
"port_address": "612e202b",
"_links": {
    "self": {
        "href": "/api/network/fc/interfaces/cdeb5591-dec9-11e8-a733-
005056bba0e0"
    }
}
},
{
    "svm": {
        "uuid": "cf300f5c-db83-11e8-bd46-005056bba0e0",
        "name": "svm1",
        "_links": {
            "self": {
                "href": "/api/svm/svms/cf300f5c-db83-11e8-bd46-005056bba0e0"
            }
        }
    },
    "uuid": "f6045b92-dec7-11e8-a733-005056bba0e0",
    "name": "lif1",
    "location": {
        "node": {
            "uuid": "bafe9b9f-db81-11e8-bd46-005056bba0e0",
            "name": "node1",
            "_links": {
                "self": {
                    "href": "/api/cluster/nodes/bafe9b9f-db81-11e8-bd46-
005056bba0e0"
                }
            }
        }
    }
},

```

```

"port": {
    "uuid": "300c1ae3-db82-11e8-bd46-005056bba0e0",
    "name": "0a",
    "node": {
        "name": "node1"
    },
    "_links": {
        "self": {
            "href": "/api/network/fc/ports/300c1ae3-db82-11e8-bd46-005056bba0e0"
        }
    }
},
"enabled": true,
"state": "down",
"data_protocol": "fcp",
"wwpn": "20:04:00:50:56:bb:a0:e0",
"wwnn": "20:00:00:50:56:bb:a0:e0",
"port_address": "9da2cb1",
"_links": {
    "self": {
        "href": "/api/network/fc/interfaces/f6045b92-dec7-11e8-a733-005056bba0e0"
    }
}
},
"num_records": 2,
"_links": {
    "self": {
        "href": "/api/network/fc/interfaces?fields=*"
    }
}
}

```

#### Retrieving a list of selected FC interfaces

This example uses property query parameters to retrieve FC interfaces configured for the FC Protocol that are set to *up*.

```

# The API:
GET /api/network/fc/interfaces

# The call:
curl -X GET 'https://<mgmt-
ip>/api/network/fc/interfaces?data_protocol=fcp&state=up' -H 'accept:
application/hal+json'

# The response:
{
  "records": [
    {
      "svm": {
        "uuid": "cf300f5c-db83-11e8-bd46-005056bba0e0",
        "name": "svm1",
        "_links": {
          "self": {
            "href": "/api/svm/svms/cf300f5c-db83-11e8-bd46-005056bba0e0"
          }
        }
      },
      "uuid": "f6045b92-dec7-11e8-a733-005056bba0e0",
      "name": "lif1",
      "state": "up",
      "data_protocol": "fcp",
      "_links": {
        "self": {
          "href": "/api/network/fc/interfaces/f6045b92-dec7-11e8-a733-
005056bba0e0"
        }
      }
    }
  ],
  "num_records": 1,
  "_links": {
    "self": {
      "href": "/api/network/fc/interfaces?data_protocol=fcp&state=up"
    }
  }
}

```

## **Retrieving a specific FC interface**

```
# The API:  
GET /api/network/fc/interfaces/{uuid}  
  
# The call:  
curl -X GET 'https://<mgmt-ip>/api/network/fc/interfaces/cdeb5591-dec9-  
11e8-a733-005056bba0e0' -H 'accept: application/hal+json'  
  
# The response:  
{  
  "svm": {  
    "uuid": "a5060466-dbab-11e8-bd46-005056bba0e0",  
    "name": "svm3",  
    "_links": {  
      "self": {  
        "href": "/api/svm/svms/a5060466-dbab-11e8-bd46-005056bba0e0"  
      }  
    }  
  },  
  "uuid": "cdeb5591-dec9-11e8-a733-005056bba0e0",  
  "name": "lif2",  
  "location": {  
    "node": {  
      "uuid": "e85aa147-db83-11e8-9a48-005056bb1ec6",  
      "name": "node3",  
      "_links": {  
        "self": {  
          "href": "/api/cluster/nodes/e85aa147-db83-11e8-9a48-005056bb1ec6"  
        }  
      }  
    }  
  },  
  "port": {  
    "uuid": "24bb636a-db83-11e8-9a49-005056bb1ec6",  
    "name": "1b",  
    "node": {  
      "name": "node3"  
    },  
    "_links": {  
      "self": {  
        "href": "/api/network/fc/ports/24bb636a-db83-11e8-9a49-  
005056bb1ec6"  
      }  
    }  
  }  
},
```

```
"enabled": true,
"state": "down",
"data_protocol": "fc_nvme",
"wwpn": "20:05:00:50:56:bb:a0:e0",
"wwnn": "20:02:00:50:56:bb:a0:e0",
"port_address": "612e202b",
"_links": {
  "self": {
    "href": "/api/network/fc/interfaces/cdeb5591-dec9-11e8-a733-
005056bba0e0"
  }
}
```

## Disabling an FC interface

When updating certain properties or deleting an FC interface, the interface must first be disabled using the following:

```
# The API:
PATCH /api/network/fc/interfaces/{uuid}

# The call:
curl -X PATCH 'https://<mgmt-ip>/api/network/fc/interfaces/f6045b92-dec7-
11e8-a733-005056bba0e0' -H 'accept: application/hal+json' -d '{ "enabled": 
false }'
```

## Moving an FC interface to a new node and port

To move an FC interface to another node or port, the destination FC port must be specified in a PATCH request. Either the port UUID or node and port names can be used to identify the port.

Note that only FC interfaces configured for the FC Protocol can be moved. FC interfaces configured for NVMe/FC cannot be moved. The interface must also be set to the disabled state before being moved.

```

# The API:
PATCH /api/network/fc/interfaces/{uuid}

# The call:
curl -X PATCH 'https://<mgmt-ip>/api/network/fc/interfaces/f6045b92-dec7-
11e8-a733-005056bba0e0' -H 'accept: application/hal+json' -d '{
"location": { "port": { "uuid": "a1dc7aa5-db83-11e8-9ef7-005056bbbbcc" } }
}'

```

## Deleting an FC interface

The FC interface must be disabled before being deleted.

```

# The API:
DELETE /api/network/fc/interfaces/{uuid}

# The call:
curl -X DELETE 'https://<mgmt-ip>/api/network/fc/interfaces/f6045b92-dec7-
11e8-a733-005056bba0e0' -H 'accept: application/hal+json'

```

## Retrieve FC interfaces

GET /network/fc/interfaces

Retrieves FC interfaces.

### Related ONTAP commands

- network interface show
- vserver fcp interface show

### Learn more

- [DOC /network/fc/interfaces](#)

### Parameters

Name	Type	In	Required	Description
location.port.name	string	query	False	Filter by location.port.name

Name	Type	In	Required	Description
location.port.node.name	string	query	False	Filter by location.port.node.name
location.port.uuid	string	query	False	Filter by location.port.uuid
location.node.uuid	string	query	False	Filter by location.node.uuid
location.node.name	string	query	False	Filter by location.node.name
enabled	boolean	query	False	Filter by enabled
uuid	string	query	False	Filter by uuid
wwnn	string	query	False	Filter by wwnn
port_address	string	query	False	Filter by port_address
svm.uuid	string	query	False	Filter by svm.uuid
svm.name	string	query	False	Filter by svm.name
wwpn	string	query	False	Filter by wwpn
state	string	query	False	Filter by state
comment	string	query	False	Filter by comment
data_protocol	string	query	False	Filter by data_protocol
name	string	query	False	Filter by name
fields	array[string]	query	False	Specify the fields to return.
max_records	integer	query	False	Limit the number of records returned.

Name	Type	In	Required	Description
return_records	boolean	query	False	The default is true for GET calls. When set to false, only the number of records is returned.
return_timeout	integer	query	False	The number of seconds to allow the call to execute before returning. When iterating over a collection, the default is 15 seconds. ONTAP returns earlier if either max records or the end of the collection is reached.
order_by	array[string]	query	False	Order results by specified fields and optional [asc

## Response

```
Status: 200, Ok
```

Name	Type	Description
_links	<a href="#">_links</a>	
num_records	integer	Number of records.
records	array[ <a href="#">fc_interface</a> ]	

## Example response

```
{  
    "_links": {  
        "next": {  
            "href": "/api/resourcelink"  
        },  
        "self": {  
            "href": "/api/resourcelink"  
        }  
    },  
    "records": {  
        "_links": {  
            "self": {  
                "href": "/api/resourcelink"  
            }  
        },  
        "comment": "string",  
        "data_protocol": "fcp",  
        "location": {  
            "node": {  
                "_links": {  
                    "self": {  
                        "href": "/api/resourcelink"  
                    }  
                },  
                "name": "node1",  
                "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
            },  
            "port": {  
                "_links": {  
                    "self": {  
                        "href": "/api/resourcelink"  
                    }  
                },  
                "name": "0a",  
                "node": {  
                    "name": "node1"  
                },  
                "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
            }  
        },  
        "name": "lif1",  
        "port_address": "5060F",  
        "state": "up",  
        "svm": {  
    }
```

```

    "_links": {
        "self": {
            "href": "/api/resourcelink"
        }
    },
    "name": "svm1",
    "uuid": "02c9e252-41be-11e9-81d5-00a0986138f7"
},
"uuid": "1cd8a442-86d1-11e0-ae1c-123478563412",
"wwnn": "20:00:00:50:56:b4:13:01",
"wwpn": "20:00:00:50:56:b4:13:a8"
}
}

```

## Error

Status: Default, Error

Name	Type	Description
error	error	

## Example error

```
{
    "error": {
        "arguments": {
            "code": "string",
            "message": "string"
        },
        "code": "4",
        "message": "entry doesn't exist",
        "target": "uuid"
    }
}
```

## Definitions

## See Definitions

href

Name	Type	Description
href	string	

\_links

Name	Type	Description
next	href	
self	href	

\_links

Name	Type	Description
self	href	

node

Name	Type	Description
_links	_links	
name	string	
uuid	string	

node

The node on which the FC port is located.

Name	Type	Description
name	string	The name of the node on which the FC port is located.

fc\_port\_reference

An FC port is the physical port of an FC adapter on a cluster node that can be connected to an FC network.

Name	Type	Description
_links	_links	
name	string	The name of the FC port.
node	node	The node on which the FC port is located.

Name	Type	Description
uuid	string	The unique identifier of the FC port.

## location

The location of the FC interface is defined by the location of its port. An FC port is identified by its UUID, or a combination of its node name and port name. Either the UUID or the node name and port name are required for POST. To move an interface, supply either the UUID or the node name and port name in a PATCH.

Name	Type	Description
node	node	
port	fc_port_reference	An FC port is the physical port of an FC adapter on a cluster node that can be connected to an FC network.

## svm

Name	Type	Description
_links	_links	
name	string	The name of the SVM.
uuid	string	The unique identifier of the SVM.

## fc\_interface

A Fibre Channel (FC) interface is the logical endpoint for FC network connections to an SVM. An FC interface provides FC access to storage within the interface SVM using either Fibre Channel Protocol or NVMe over Fibre Channel (NVMe/FC).

An FC interface is created on an FC port which is located on a cluster node. The FC port must be specified to identify the location of the interface for a POST or PATCH operation that relocates an interface. You can identify the port by supplying either the node and port names or the port UUID.

Name	Type	Description
_links	_links	
comment	string	A user configurable comment. Optional in POST; valid in PATCH. To clear a prior comment, set the property to an empty string in PATCH.

Name	Type	Description
data_protocol	string	The data protocol for which the FC interface is configured. Required in POST.
enabled	boolean	The administrative state of the FC interface. The FC interface can be disabled to block all FC communication with the SVM through this interface. Optional in POST and PATCH; defaults to <code>true</code> (enabled) in POST.
location	location	The location of the FC interface is defined by the location of its port. An FC port is identified by its UUID, or a combination of its node name and port name. Either the UUID or the node name and port name are required for POST. To move an interface, supply either the UUID or the node name and port name in a PATCH.
name	string	The name of the FC interface. Required in POST; optional in PATCH.
port_address	string	<p>The port address of the FC interface. Each FC port in an FC switched fabric has its own unique FC port address for routing purposes. The FC port address is assigned by a switch in the fabric when that port logs in to the fabric. This property refers to the address given by a switch to the FC interface when the SVM performs a port login (PLOGI).</p> <p>This is useful for obtaining statistics and diagnostic information from FC switches.</p> <p>This is a hexadecimal encoded numeric value.</p>

Name	Type	Description
state	string	<p>The current operational state of the FC interface. The state is set to <i>down</i> if the interface is not enabled.</p> <p>If the node hosting the port is down or unavailable, no state value is returned.</p>
svm	<a href="#">svm</a>	
uuid	string	The unique identifier of the FC interface. Required in the URL.
wwnn	string	<p>The world wide node name (WWNN) of the FC interface SVM. The WWNN is generated by ONTAP when Fibre Channel Protocol or the NVMe service is created for the FC interface SVM.</p> <ul style="list-style-type: none"> <li>example: 20:00:00:50:56:b4:13:01</li> <li>readOnly: 1</li> </ul>
wwpn	string	<p>The world wide port name (WWPN) of the FC interface. The WWPN is generated by ONTAP when the FC interface is created.</p> <ul style="list-style-type: none"> <li>example: 20:00:00:50:56:b4:13:a8</li> <li>readOnly: 1</li> </ul>

#### error\_arguments

Name	Type	Description
code	string	Argument code
message	string	Message argument

#### error

Name	Type	Description
arguments	array[error_arguments]	Message arguments

Name	Type	Description
code	string	Error code
message	string	Error message
target	string	The target parameter that caused the error.

## Create an FC interface

POST /network/fc/interfaces

Creates an FC interface.

### Required properties

- `svm.uuid` or `svm.name` - Existing SVM in which to create the FC interface.
- `name` - Name of the FC interface.
- `location.port.uuid` or both `location.port.name` and `location.port.node.name` - FC port on which to create the FC interface.
- `data_protocol` - Data protocol for the FC interface.

### Default property values

If not specified in POST, the following default property values are assigned.

- `enabled` - `true`

### Related ONTAP commands

- `network interface create`

### Learn more

- [DOC /network/fc/interfaces](#)

### Parameters

Name	Type	In	Required	Description
<code>return_records</code>	boolean	query	False	The default is false. If set to true, the records are returned.

## Request Body

Name	Type	Description
_links	<a href="#">_links</a>	
comment	string	A user configurable comment. Optional in POST; valid in PATCH. To clear a prior comment, set the property to an empty string in PATCH.
data_protocol	string	The data protocol for which the FC interface is configured. Required in POST.
enabled	boolean	The administrative state of the FC interface. The FC interface can be disabled to block all FC communication with the SVM through this interface. Optional in POST and PATCH; defaults to <i>true</i> (enabled) in POST.
location	<a href="#">location</a>	The location of the FC interface is defined by the location of its port. An FC port is identified by its UUID, or a combination of its node name and port name. Either the UUID or the node name and port name are required for POST. To move an interface, supply either the UUID or the node name and port name in a PATCH.
name	string	The name of the FC interface. Required in POST; optional in PATCH.

Name	Type	Description
port_address	string	<p>The port address of the FC interface. Each FC port in an FC switched fabric has its own unique FC port address for routing purposes. The FC port address is assigned by a switch in the fabric when that port logs in to the fabric. This property refers to the address given by a switch to the FC interface when the SVM performs a port login (PLOGI).</p> <p>This is useful for obtaining statistics and diagnostic information from FC switches.</p> <p>This is a hexadecimal encoded numeric value.</p>
state	string	<p>The current operational state of the FC interface. The state is set to <i>down</i> if the interface is not enabled.</p> <p>If the node hosting the port is down or unavailable, no state value is returned.</p>
svm	<a href="#">svm</a>	
uuid	string	The unique identifier of the FC interface. Required in the URL.
wwnn	string	<p>The world wide node name (WWNN) of the FC interface SVM. The WWNN is generated by ONTAP when Fibre Channel Protocol or the NVMe service is created for the FC interface SVM.</p> <ul style="list-style-type: none"> <li>• example: 20:00:00:50:56:b4:13:01</li> <li>• readOnly: 1</li> </ul>

Name	Type	Description
wwpn	string	<p>The world wide port name (WWPN) of the FC interface. The WWPN is generated by ONTAP when the FC interface is created.</p> <ul style="list-style-type: none"> <li>• example: 20:00:00:50:56:b4:13:a8</li> <li>• readOnly: 1</li> </ul>

## Example request

```
{  
    "_links": {  
        "self": {  
            "href": "/api/resourcelink"  
        }  
    },  
    "comment": "string",  
    "data_protocol": "fcp",  
    "location": {  
        "node": {  
            "_links": {  
                "self": {  
                    "href": "/api/resourcelink"  
                }  
            },  
            "name": "node1",  
            "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
        },  
        "port": {  
            "_links": {  
                "self": {  
                    "href": "/api/resourcelink"  
                }  
            },  
            "name": "0a",  
            "node": {  
                "name": "node1"  
            },  
            "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
        },  
        "name": "lif1",  
        "port_address": "5060F",  
        "state": "up",  
        "svm": {  
            "_links": {  
                "self": {  
                    "href": "/api/resourcelink"  
                }  
            },  
            "name": "svml1",  
            "uuid": "02c9e252-41be-11e9-81d5-00a0986138f7"  
        },  
        "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412",  
    }  
}
```

```
"wwnn": "20:00:00:50:56:b4:13:01",
"wwpn": "20:00:00:50:56:b4:13:a8"
}
```

## Response

Status: 201, Created

Name	Type	Description
_links	<a href="#">_links</a>	
num_records	integer	Number of records.
records	array[ <a href="#">fc_interface</a> ]	

## Example response

```
{  
    "_links": {  
        "next": {  
            "href": "/api/resourcelink"  
        },  
        "self": {  
            "href": "/api/resourcelink"  
        }  
    },  
    "records": {  
        "_links": {  
            "self": {  
                "href": "/api/resourcelink"  
            }  
        },  
        "comment": "string",  
        "data_protocol": "fcp",  
        "location": {  
            "node": {  
                "_links": {  
                    "self": {  
                        "href": "/api/resourcelink"  
                    }  
                },  
                "name": "node1",  
                "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
            },  
            "port": {  
                "_links": {  
                    "self": {  
                        "href": "/api/resourcelink"  
                    }  
                },  
                "name": "0a",  
                "node": {  
                    "name": "node1"  
                },  
                "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
            }  
        },  
        "name": "lif1",  
        "port_address": "5060F",  
        "state": "up",  
        "svm": {  
    }
```

```

    "_links": {
        "self": {
            "href": "/api/resourcelink"
        }
    },
    "name": "svm1",
    "uuid": "02c9e252-41be-11e9-81d5-00a0986138f7"
},
"uuid": "1cd8a442-86d1-11e0-ae1c-123478563412",
"wwnn": "20:00:00:50:56:b4:13:01",
"wwpn": "20:00:00:50:56:b4:13:a8"
}
}

```

## Error

Status: Default

### ONTAP Error Response Codes

Error Code	Description
1966140	An interface with the same name already exists.
1966217	The specified port is not valid on the node provided.
2621462	The supplied SVM does not exist.
2621706	The specified <code>svm.uuid</code> and <code>svm.name</code> do not refer to the same SVM.
2621707	No SVM was specified. Either <code>svm.name</code> or <code>svm.uuid</code> must be supplied.
5373966	A Fibre Channel interface with the <code>fcp</code> protocol cannot be created in an SVM that is configured for NVMe.
5374102	The specified Fibre Channel interface cannot be created because the Fibre Channel adapter is down. Bring the adapter up and try again.
5374871	The Fibre Channel port identified by the specified UUID does not refer to the same port as that identified by the specified node name and/or port name.
5374872	If either <code>location.port.node.name</code> or <code>location.port.name</code> is supplied, both properties must be supplied.

Error Code	Description
5374873	The Fibre Channel port must be specified using either location.port.uuid or location.port.node.name and location.port.name.
72089652	An NVMe service must be created before creating a Fibre Channel interface using the NVMe over FC data protocol.
72089672	The specified Fibre Channel port does not support the NVMe over FC data protocol.
72089900	A Fibre Channel interface with the <i>fc_nvme</i> protocol cannot be created in an SVM that is configured for a SAN protocol.

Name	Type	Description
error	error	

### Example error

```
{
  "error": {
    "arguments": {
      "code": "string",
      "message": "string"
    },
    "code": "4",
    "message": "entry doesn't exist",
    "target": "uuid"
  }
}
```

### Definitions

## See Definitions

href

Name	Type	Description
href	string	

\_links

Name	Type	Description
self	href	

node

Name	Type	Description
_links	_links	
name	string	
uuid	string	

node

The node on which the FC port is located.

Name	Type	Description
name	string	The name of the node on which the FC port is located.

fc\_port\_reference

An FC port is the physical port of an FC adapter on a cluster node that can be connected to an FC network.

Name	Type	Description
_links	_links	
name	string	The name of the FC port.
node	node	The node on which the FC port is located.
uuid	string	The unique identifier of the FC port.

location

The location of the FC interface is defined by the location of its port. An FC port is identified by its UUID,

or a combination of its node name and port name. Either the UUID or the node name and port name are required for POST. To move an interface, supply either the UUID or the node name and port name in a PATCH.

Name	Type	Description
node	<a href="#">node</a>	
port	<a href="#">fc_port_reference</a>	An FC port is the physical port of an FC adapter on a cluster node that can be connected to an FC network.

## svm

Name	Type	Description
_links	<a href="#">_links</a>	
name	string	The name of the SVM.
uuid	string	The unique identifier of the SVM.

## fc\_interface

A Fibre Channel (FC) interface is the logical endpoint for FC network connections to an SVM. An FC interface provides FC access to storage within the interface SVM using either Fibre Channel Protocol or NVMe over Fibre Channel (NVMe/FC).

An FC interface is created on an FC port which is located on a cluster node. The FC port must be specified to identify the location of the interface for a POST or PATCH operation that relocates an interface. You can identify the port by supplying either the node and port names or the port UUID.

Name	Type	Description
_links	<a href="#">_links</a>	
comment	string	A user configurable comment. Optional in POST; valid in PATCH. To clear a prior comment, set the property to an empty string in PATCH.
data_protocol	string	The data protocol for which the FC interface is configured. Required in POST.

Name	Type	Description
enabled	boolean	The administrative state of the FC interface. The FC interface can be disabled to block all FC communication with the SVM through this interface. Optional in POST and PATCH; defaults to <i>true</i> (enabled) in POST.
location	location	The location of the FC interface is defined by the location of its port. An FC port is identified by its UUID, or a combination of its node name and port name. Either the UUID or the node name and port name are required for POST. To move an interface, supply either the UUID or the node name and port name in a PATCH.
name	string	The name of the FC interface. Required in POST; optional in PATCH.
port_address	string	<p>The port address of the FC interface. Each FC port in an FC switched fabric has its own unique FC port address for routing purposes. The FC port address is assigned by a switch in the fabric when that port logs in to the fabric. This property refers to the address given by a switch to the FC interface when the SVM performs a port login (PLOGI).</p> <p>This is useful for obtaining statistics and diagnostic information from FC switches.</p> <p>This is a hexadecimal encoded numeric value.</p>
state	string	<p>The current operational state of the FC interface. The state is set to <i>down</i> if the interface is not enabled.</p> <p>If the node hosting the port is down or unavailable, no state value is returned.</p>

Name	Type	Description
svm	svm	
uuid	string	The unique identifier of the FC interface. Required in the URL.
wwnn	string	<p>The world wide node name (WWNN) of the FC interface SVM. The WWNN is generated by ONTAP when Fibre Channel Protocol or the NVMe service is created for the FC interface SVM.</p> <ul style="list-style-type: none"> <li>• example: 20:00:00:50:56:b4:13:01</li> <li>• readOnly: 1</li> </ul>
wwpn	string	<p>The world wide port name (WWPN) of the FC interface. The WWPN is generated by ONTAP when the FC interface is created.</p> <ul style="list-style-type: none"> <li>• example: 20:00:00:50:56:b4:13:a8</li> <li>• readOnly: 1</li> </ul>

## \_links

Name	Type	Description
next	<a href="#">href</a>	
self	<a href="#">href</a>	

## error\_arguments

Name	Type	Description
code	string	Argument code
message	string	Message argument

## error

Name	Type	Description
arguments	array[error_arguments]	Message arguments
code	string	Error code

Name	Type	Description
message	string	Error message
target	string	The target parameter that caused the error.

## Delete an FC interface

DELETE /network/fc/interfaces/{uuid}

Deletes an FC interface.

### Related ONTAP commands

- `network interface delete`

### Learn more

- [DOC /network/fc/interfaces](#)

### Parameters

Name	Type	In	Required	Description
uuid	string	path	True	

### Response

Status: 200, Ok

### Error

Status: Default

### ONTAP Error Response Codes

Error Code	Description
53280992	The FC interface could not be deleted because it is enabled.

Name	Type	Description
error	error	

## Example error

```
{  
  "error": {  
    "arguments": {  
      "code": "string",  
      "message": "string"  
    },  
    "code": "4",  
    "message": "entry doesn't exist",  
    "target": "uuid"  
  }  
}
```

## Definitions

### See Definitions

#### error\_arguments

Name	Type	Description
code	string	Argument code
message	string	Message argument

#### error

Name	Type	Description
arguments	array[error_arguments]	Message arguments
code	string	Error code
message	string	Error message
target	string	The target parameter that caused the error.

## Retrieve an FC interface

GET /network/fc/interfaces/{uuid}

Retrieves an FC interface.

## Related ONTAP commands

- network interface show
- vserver fc interface show

## Learn more

- [DOC /network/fc/interfaces](#)

## Parameters

Name	Type	In	Required	Description
uuid	string	path	True	The unique identifier for the FC interface.
fields	array[string]	query	False	Specify the fields to return.

## Response

```
Status: 200, Ok
```

Name	Type	Description
_links	<a href="#">_links</a>	
comment	string	A user configurable comment. Optional in POST; valid in PATCH. To clear a prior comment, set the property to an empty string in PATCH.
data_protocol	string	The data protocol for which the FC interface is configured. Required in POST.
enabled	boolean	The administrative state of the FC interface. The FC interface can be disabled to block all FC communication with the SVM through this interface. Optional in POST and PATCH; defaults to <i>true</i> (enabled) in POST.

Name	Type	Description
location	location	The location of the FC interface is defined by the location of its port. An FC port is identified by its UUID, or a combination of its node name and port name. Either the UUID or the node name and port name are required for POST. To move an interface, supply either the UUID or the node name and port name in a PATCH.
name	string	The name of the FC interface. Required in POST; optional in PATCH.
port_address	string	<p>The port address of the FC interface. Each FC port in an FC switched fabric has its own unique FC port address for routing purposes. The FC port address is assigned by a switch in the fabric when that port logs in to the fabric. This property refers to the address given by a switch to the FC interface when the SVM performs a port login (PLOGI).</p> <p>This is useful for obtaining statistics and diagnostic information from FC switches.</p> <p>This is a hexadecimal encoded numeric value.</p>
state	string	<p>The current operational state of the FC interface. The state is set to <i>down</i> if the interface is not enabled.</p> <p>If the node hosting the port is down or unavailable, no state value is returned.</p>
svm	svm	
uuid	string	The unique identifier of the FC interface. Required in the URL.

Name	Type	Description
wwnn	string	<p>The world wide node name (WWNN) of the FC interface SVM. The WWNN is generated by ONTAP when Fibre Channel Protocol or the NVMe service is created for the FC interface SVM.</p> <ul style="list-style-type: none"> <li>• example: 20:00:00:50:56:b4:13:01</li> <li>• readOnly: 1</li> </ul>
wwpn	string	<p>The world wide port name (WWPN) of the FC interface. The WWPN is generated by ONTAP when the FC interface is created.</p> <ul style="list-style-type: none"> <li>• example: 20:00:00:50:56:b4:13:a8</li> <li>• readOnly: 1</li> </ul>

## Example response

```
{  
    "_links": {  
        "self": {  
            "href": "/api/resourcelink"  
        }  
    },  
    "comment": "string",  
    "data_protocol": "fcp",  
    "location": {  
        "node": {  
            "_links": {  
                "self": {  
                    "href": "/api/resourcelink"  
                }  
            },  
            "name": "node1",  
            "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
        },  
        "port": {  
            "_links": {  
                "self": {  
                    "href": "/api/resourcelink"  
                }  
            },  
            "name": "0a",  
            "node": {  
                "name": "node1"  
            },  
            "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
        },  
        "name": "lif1",  
        "port_address": "5060F",  
        "state": "up",  
        "svm": {  
            "_links": {  
                "self": {  
                    "href": "/api/resourcelink"  
                }  
            },  
            "name": "svml1",  
            "uuid": "02c9e252-41be-11e9-81d5-00a0986138f7"  
        },  
        "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412",  
    }  
}
```

```
"wwnn": "20:00:00:50:56:b4:13:01",
"wwpn": "20:00:00:50:56:b4:13:a8"
}
```

## Error

Status: Default, Error

Name	Type	Description
error	error	

## Example error

```
{
  "error": {
    "arguments": {
      "code": "string",
      "message": "string"
    },
    "code": "4",
    "message": "entry doesn't exist",
    "target": "uuid"
  }
}
```

## Definitions

## See Definitions

href

Name	Type	Description
href	string	

\_links

Name	Type	Description
self	href	

node

Name	Type	Description
_links	_links	
name	string	
uuid	string	

node

The node on which the FC port is located.

Name	Type	Description
name	string	The name of the node on which the FC port is located.

fc\_port\_reference

An FC port is the physical port of an FC adapter on a cluster node that can be connected to an FC network.

Name	Type	Description
_links	_links	
name	string	The name of the FC port.
node	node	The node on which the FC port is located.
uuid	string	The unique identifier of the FC port.

location

The location of the FC interface is defined by the location of its port. An FC port is identified by its UUID,

or a combination of its node name and port name. Either the UUID or the node name and port name are required for POST. To move an interface, supply either the UUID or the node name and port name in a PATCH.

Name	Type	Description
node	<a href="#">node</a>	
port	<a href="#">fc_port_reference</a>	An FC port is the physical port of an FC adapter on a cluster node that can be connected to an FC network.

svm

Name	Type	Description
_links	<a href="#">_links</a>	
name	string	The name of the SVM.
uuid	string	The unique identifier of the SVM.

error\_arguments

Name	Type	Description
code	string	Argument code
message	string	Message argument

error

Name	Type	Description
arguments	array[ <a href="#">error_arguments</a> ]	Message arguments
code	string	Error code
message	string	Error message
target	string	The target parameter that caused the error.

## Update an FC interface

PATCH /network/fc/interfaces/{uuid}

Updates an FC interface.

## Related ONTAP commands

- `network interface modify`

## Learn more

- [DOC /network/fc/interfaces](#)

## Parameters

Name	Type	In	Required	Description
uuid	string	path	True	The unique identifier for the FC interface.

## Request Body

Name	Type	Description
_links	<a href="#">_links</a>	
comment	string	A user configurable comment. Optional in POST; valid in PATCH. To clear a prior comment, set the property to an empty string in PATCH.
data_protocol	string	The data protocol for which the FC interface is configured. Required in POST.
enabled	boolean	The administrative state of the FC interface. The FC interface can be disabled to block all FC communication with the SVM through this interface. Optional in POST and PATCH; defaults to <i>true</i> (enabled) in POST.
location	<a href="#">location</a>	The location of the FC interface is defined by the location of its port. An FC port is identified by its UUID, or a combination of its node name and port name. Either the UUID or the node name and port name are required for POST. To move an interface, supply either the UUID or the node name and port name in a PATCH.

Name	Type	Description
name	string	The name of the FC interface. Required in POST; optional in PATCH.
port_address	string	<p>The port address of the FC interface. Each FC port in an FC switched fabric has its own unique FC port address for routing purposes. The FC port address is assigned by a switch in the fabric when that port logs in to the fabric. This property refers to the address given by a switch to the FC interface when the SVM performs a port login (PLOGI).</p> <p>This is useful for obtaining statistics and diagnostic information from FC switches.</p> <p>This is a hexadecimal encoded numeric value.</p>
state	string	<p>The current operational state of the FC interface. The state is set to <i>down</i> if the interface is not enabled.</p> <p>If the node hosting the port is down or unavailable, no state value is returned.</p>
svm	svm	
uuid	string	The unique identifier of the FC interface. Required in the URL.
wwnn	string	<p>The world wide node name (WWNN) of the FC interface SVM. The WWNN is generated by ONTAP when Fibre Channel Protocol or the NVMe service is created for the FC interface SVM.</p> <ul style="list-style-type: none"> <li>• example: 20:00:00:50:56:b4:13:01</li> <li>• readOnly: 1</li> </ul>

Name	Type	Description
wwpn	string	<p>The world wide port name (WWPN) of the FC interface. The WWPN is generated by ONTAP when the FC interface is created.</p> <ul style="list-style-type: none"> <li>• example: 20:00:00:50:56:b4:13:a8</li> <li>• readOnly: 1</li> </ul>

## Example request

```
{  
    "_links": {  
        "self": {  
            "href": "/api/resourcelink"  
        }  
    },  
    "comment": "string",  
    "data_protocol": "fcp",  
    "location": {  
        "node": {  
            "_links": {  
                "self": {  
                    "href": "/api/resourcelink"  
                }  
            },  
            "name": "node1",  
            "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
        },  
        "port": {  
            "_links": {  
                "self": {  
                    "href": "/api/resourcelink"  
                }  
            },  
            "name": "0a",  
            "node": {  
                "name": "node1"  
            },  
            "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
        },  
        "name": "lif1",  
        "port_address": "5060F",  
        "state": "up",  
        "svm": {  
            "_links": {  
                "self": {  
                    "href": "/api/resourcelink"  
                }  
            },  
            "name": "svml1",  
            "uuid": "02c9e252-41be-11e9-81d5-00a0986138f7"  
        },  
        "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412",  
    }  
}
```

```

    "wwnn": "20:00:00:50:56:b4:13:01",
    "wwpn": "20:00:00:50:56:b4:13:a8"
}

```

## Response

Status: 200, Ok

## Error

Status: Default

### ONTAP Error Response Codes

Error Code	Description
1966140	An interface with the same name already exists.
1966217	The specified port is not valid on the node provided.
1966238	The node or port of an active SAN data interface cannot be changed.
1966702	The destination node is not healthy.
5374579	The SAN Kernel Agent on the node is unavailable.
5374870	A partial failure occurred; renaming the interface failed. Correct the error and resubmit the request.
5374871	The Fibre Channel port identified by the specified UUID does not refer to the same port as that identified by the specified node name and/or port name.
5374872	If either location.port.node.name or location.port.name is supplied, both properties must be supplied.
72089674	You cannot move a Fibre Channel interface configured for the NVMe over FC data protocol.

Name	Type	Description
error	error	

## Example error

```
{  
  "error": {  
    "arguments": {  
      "code": "string",  
      "message": "string"  
    },  
    "code": "4",  
    "message": "entry doesn't exist",  
    "target": "uuid"  
  }  
}
```

## Definitions

## See Definitions

href

Name	Type	Description
href	string	

\_links

Name	Type	Description
self	href	

node

Name	Type	Description
_links	_links	
name	string	
uuid	string	

node

The node on which the FC port is located.

Name	Type	Description
name	string	The name of the node on which the FC port is located.

fc\_port\_reference

An FC port is the physical port of an FC adapter on a cluster node that can be connected to an FC network.

Name	Type	Description
_links	_links	
name	string	The name of the FC port.
node	node	The node on which the FC port is located.
uuid	string	The unique identifier of the FC port.

location

The location of the FC interface is defined by the location of its port. An FC port is identified by its UUID,

or a combination of its node name and port name. Either the UUID or the node name and port name are required for POST. To move an interface, supply either the UUID or the node name and port name in a PATCH.

Name	Type	Description
node	<a href="#">node</a>	
port	<a href="#">fc_port_reference</a>	An FC port is the physical port of an FC adapter on a cluster node that can be connected to an FC network.

## svm

Name	Type	Description
_links	<a href="#">_links</a>	
name	string	The name of the SVM.
uuid	string	The unique identifier of the SVM.

## fc\_interface

A Fibre Channel (FC) interface is the logical endpoint for FC network connections to an SVM. An FC interface provides FC access to storage within the interface SVM using either Fibre Channel Protocol or NVMe over Fibre Channel (NVMe/FC).

An FC interface is created on an FC port which is located on a cluster node. The FC port must be specified to identify the location of the interface for a POST or PATCH operation that relocates an interface. You can identify the port by supplying either the node and port names or the port UUID.

Name	Type	Description
_links	<a href="#">_links</a>	
comment	string	A user configurable comment. Optional in POST; valid in PATCH. To clear a prior comment, set the property to an empty string in PATCH.
data_protocol	string	The data protocol for which the FC interface is configured. Required in POST.

Name	Type	Description
enabled	boolean	The administrative state of the FC interface. The FC interface can be disabled to block all FC communication with the SVM through this interface. Optional in POST and PATCH; defaults to <i>true</i> (enabled) in POST.
location	location	The location of the FC interface is defined by the location of its port. An FC port is identified by its UUID, or a combination of its node name and port name. Either the UUID or the node name and port name are required for POST. To move an interface, supply either the UUID or the node name and port name in a PATCH.
name	string	The name of the FC interface. Required in POST; optional in PATCH.
port_address	string	<p>The port address of the FC interface. Each FC port in an FC switched fabric has its own unique FC port address for routing purposes. The FC port address is assigned by a switch in the fabric when that port logs in to the fabric. This property refers to the address given by a switch to the FC interface when the SVM performs a port login (PLOGI).</p> <p>This is useful for obtaining statistics and diagnostic information from FC switches.</p> <p>This is a hexadecimal encoded numeric value.</p>
state	string	<p>The current operational state of the FC interface. The state is set to <i>down</i> if the interface is not enabled.</p> <p>If the node hosting the port is down or unavailable, no state value is returned.</p>

Name	Type	Description
svm	svm	
uuid	string	The unique identifier of the FC interface. Required in the URL.
wwnn	string	<p>The world wide node name (WWNN) of the FC interface SVM. The WWNN is generated by ONTAP when Fibre Channel Protocol or the NVMe service is created for the FC interface SVM.</p> <ul style="list-style-type: none"> <li>• example: 20:00:00:50:56:b4:13:01</li> <li>• readOnly: 1</li> </ul>
wwpn	string	<p>The world wide port name (WWPN) of the FC interface. The WWPN is generated by ONTAP when the FC interface is created.</p> <ul style="list-style-type: none"> <li>• example: 20:00:00:50:56:b4:13:a8</li> <li>• readOnly: 1</li> </ul>

#### error\_arguments

Name	Type	Description
code	string	Argument code
message	string	Message argument

#### error

Name	Type	Description
arguments	array[error_arguments]	Message arguments
code	string	Error code
message	string	Error message
target	string	The target parameter that caused the error.

# Retrieve FC port information

## Network FC ports endpoint overview

### Overview

Fibre Channel (FC) ports are the physical ports of FC adapters on ONTAP cluster nodes that can be connected to FC networks to provide FC network connectivity. An FC port defines the location of an FC interface within the ONTAP cluster.

The Fibre Channel port REST API allows you to discover FC ports, obtain status information for FC ports, and configure FC port properties. POST and DELETE requests are not supported. You must physically add and remove FC adapters to ONTAP nodes to create and remove ports from the ONTAP cluster.

### Examples

#### Retrieving all FC ports

```
# The API:  
GET /api/network/fc/ports  
  
# The call:  
curl -X GET "https://<mgmt-ip>/api/network/fc/ports" -H "accept:  
application/hal+json"  
  
# The response:  
{  
  "records": [  
    {  
      "node": {  
        "name": "node1",  
        "uuid": "3c768e01-1abc-4b3b-b7c0-629ceb62a497",  
        "_links": {  
          "self": {  
            "href": "/api/cluster/nodes/3c768e01-1abc-4b3b-b7c0-  
629ceb62a497"  
          }  
        }  
      },  
      "uuid": "931b20f8-b047-11e8-9af3-005056bb838e",  
      "name": "0a",  
      "_links": {  
        "self": {  
          "href": "/api/network/fc/ports/931b20f8-b047-11e8-9af3-  
005056bb838e"  
        }  
      }  
    },  
  ]
```

```
{
  "node": {
    "name": "node1",
    "uuid": "3c768e01-1abc-4b3b-b7c0-629ceb62a497",
    "_links": {
      "self": {
        "href": "/api/cluster/nodes/3c768e01-1abc-4b3b-b7c0-629ceb62a497"
      }
    }
  },
  "uuid": "931b23f7-b047-11e8-9af3-005056bb838e",
  "name": "0b",
  "_links": {
    "self": {
      "href": "/api/network/fc/ports/931b23f7-b047-11e8-9af3-005056bb838e"
    }
  }
},
{
  "node": {
    "name": "node1",
    "uuid": "3c768e01-1abc-4b3b-b7c0-629ceb62a497",
    "_links": {
      "self": {
        "href": "/api/cluster/nodes/3c768e01-1abc-4b3b-b7c0-629ceb62a497"
      }
    }
  },
  "uuid": "931b25ba-b047-11e8-9af3-005056bb838e",
  "name": "0c",
  "_links": {
    "self": {
      "href": "/api/network/fc/ports/931b25ba-b047-11e8-9af3-005056bb838e"
    }
  }
},
{
  "node": {
    "name": "node1",
    "uuid": "3c768e01-1abc-4b3b-b7c0-629ceb62a497",
    "_links": {
      "self": {

```

```
        "href": "/api/cluster/nodes/3c768e01-1abc-4b3b-b7c0-  
629ceb62a497"  
    }  
}  
,  
"uuid": "931b2748-b047-11e8-9af3-005056bb838e",  
"name": "0d",  
"_links": {  
    "self": {  
        "href": "/api/network/fc/ports/931b2748-b047-11e8-9af3-  
005056bb838e"  
    }  
}  
,  
{  
    "node": {  
        "name": "node1",  
        "uuid": "3c768e01-1abc-4b3b-b7c0-629ceb62a497",  
        "_links": {  
            "self": {  
                "href": "/api/cluster/nodes/3c768e01-1abc-4b3b-b7c0-  
629ceb62a497"  
            }  
        }  
},  
"uuid": "931b28c2-b047-11e8-9af3-005056bb838e",  
"name": "0e",  
"_links": {  
    "self": {  
        "href": "/api/network/fc/ports/931b28c2-b047-11e8-9af3-  
005056bb838e"  
    }  
}  
,  
{  
    "node": {  
        "name": "node1",  
        "uuid": "3c768e01-1abc-4b3b-b7c0-629ceb62a497",  
        "_links": {  
            "self": {  
                "href": "/api/cluster/nodes/3c768e01-1abc-4b3b-b7c0-  
629ceb62a497"  
            }  
        }  
},  
"uuid": "931b2a7b-b047-11e8-9af3-005056bb838e",
```

```

    "name": "0f",
    "_links": {
        "self": {
            "href": "/api/network/fc/ports/931b2a7b-b047-11e8-9af3-
005056bb838e"
        }
    }
},
{
    "node": {
        "name": "node1",
        "uuid": "3c768e01-1abc-4b3b-b7c0-629ceb62a497",
        "_links": {
            "self": {
                "href": "/api/cluster/nodes/3c768e01-1abc-4b3b-b7c0-
629ceb62a497"
            }
        }
    },
    "uuid": "931b2e2b-b047-11e8-9af3-005056bb838e",
    "name": "1b",
    "_links": {
        "self": {
            "href": "/api/network/fc/ports/931b2e2b-b047-11e8-9af3-
005056bb838e"
        }
    }
}
],
"num_records": 8,
"_links": {
    "self": {
        "href": "/api/network/fc/ports"
    }
}
}

```

#### **Retrieving all FC ports with state *online***

The state query parameter is used to perform the query.

```
# The API:
GET /api/network/fc/ports
```

```

# The call:
curl -X GET "https://<mgmt-ip>/api/network/fc/ports?state=online" -H
"accept: application/hal+json"

# The response:
{
  "records": [
    {
      "node": {
        "name": "node1",
        "uuid": "3c768e01-1abc-4b3b-b7c0-629ceb62a497",
        "_links": {
          "self": {
            "href": "/api/cluster/nodes/3c768e01-1abc-4b3b-b7c0-
629ceb62a497"
          }
        }
      }
    },
    {
      "node": {
        "name": "0a",
        "state": "online",
        "_links": {
          "self": {
            "href": "/api/network/fc/ports/931b20f8-b047-11e8-9af3-
005056bb838e"
          }
        }
      }
    },
    {
      "node": {
        "name": "node1",
        "uuid": "3c768e01-1abc-4b3b-b7c0-629ceb62a497",
        "_links": {
          "self": {
            "href": "/api/cluster/nodes/3c768e01-1abc-4b3b-b7c0-
629ceb62a497"
          }
        }
      }
    },
    {
      "node": {
        "name": "0b",
        "state": "online",
        "_links": {
          "self": {
            "href": "/api/network/fc/ports/931b23f7-b047-11e8-9af3-
005056bb838e"
          }
        }
      }
    }
  ]
}

```

```

        }
    }
},
{
  "node": {
    "name": "node1",
    "uuid": "3c768e01-1abc-4b3b-b7c0-629ceb62a497",
    "_links": {
      "self": {
        "href": "/api/cluster/nodes/3c768e01-1abc-4b3b-b7c0-629ceb62a497"
      }
    }
  }
  "uuid": "931b25ba-b047-11e8-9af3-005056bb838e",
  "name": "0c",
  "state": "online",
  "_links": {
    "self": {
      "href": "/api/network/fc/ports/931b25ba-b047-11e8-9af3-005056bb838e"
    }
  }
}
],
"num_records": 3,
"_links": {
  "self": {
    "href": "/api/network/fc/ports?state=online"
  }
}
}

```

## Retrieving an FC port

```

# The API:
GET /api/network/fc/ports/{uuid}

# The call:
curl -X GET "https://<mgmt-ip>/api/network/fc/ports/931b20f8-b047-11e8-9af3-005056bb838e" -H "accept: application/hal+json"

# The response:
{

```

```

"node": {
    "name": "node1",
    "uuid": "5a534a72-b047-11e8-9af3-005056bb838e",
    "_links": {
        "self": {
            "href": "/api/cluster/nodes/5a534a72-b047-11e8-9af3-005056bb838e"
        }
    }
},
"uuid": "931b20f8-b047-11e8-9af3-005056bb838e",
"name": "0a",
"description": "Fibre Channel Target Adapter 0a (ACME Fibre Channel Adapter, rev. 1.0.0, 8G)",
"enabled": true,
"fabric": {
    "connected": true,
    "connected_speed": 8,
    "name": "55:0e:b1:a0:20:40:80:00",
    "port_address": "52100",
    "switch_port": "ssan-g620-03:1"
},
"physical_protocol": "fibre_channel",
"speed": {
    "maximum": "8",
    "configured": "auto"
},
"state": "online",
"supported_protocols": [
    "fcp"
],
"transceiver": {
    "form_factor": "SFP",
    "manufacturer": "ACME",
    "capabilities": [
        4,
        8
    ],
    "part_number": "1000"
},
"wwnn": "50:0a:09:80:bb:83:8e:00",
"wwpn": "50:0a:09:82:bb:83:8e:00",
"_links": {
    "self": {
        "href": "/api/network/fc/ports/931b20f8-b047-11e8-9af3-005056bb838e"
    }
}
}

```

```
}
```

## Disabling an FC port

If an active FC interface exists on an FC port, the port cannot be disabled.

```
# The API:  
PATCH /api/network/fc/ports/{uuid}  
  
# The call:  
curl -X PATCH "http://<mgmt-ip>/api/network/fc/ports/931b20f8-b047-11e8-  
9af3-005056bb838e" -H "accept: application/hal+json" -d '{ "enabled":  
false }'
```

## Retrieve FC ports

GET /network/fc/ports

Retrieves FC ports.

### Expensive properties

There is an added cost to retrieving values for these properties. They are not included by default in GET results and must be explicitly requested using the `fields` query parameter. See [DOC Requesting specific fields](#) to learn more.

- `fabric.name`

### Related ONTAP commands

- `network fcp adapter show`

### Learn more

- [DOC /network/fc/ports](#)

### Parameters

Name	Type	In	Required	Description
<code>speed.maximum</code>	string	query	False	Filter by <code>speed.maximum</code>
<code>speed.configured</code>	string	query	False	Filter by <code>speed.configured</code>

Name	Type	In	Required	Description
state	string	query	False	Filter by state
transceiver.manufacturer	string	query	False	Filter by transceiver.manufacturer
transceiver.capabilities	integer	query	False	Filter by transceiver.capabilities
transceiver.form-factor	string	query	False	Filter by transceiver.form-factor
transceiver.part_number	string	query	False	Filter by transceiver.part_number
name	string	query	False	Filter by name
node.uuid	string	query	False	Filter by node.uuid
node.name	string	query	False	Filter by node.name
enabled	boolean	query	False	Filter by enabled
physical_protocol	string	query	False	Filter by physical_protocol
uuid	string	query	False	Filter by uuid
fabric.port_address	string	query	False	Filter by fabric.port_address
fabric.connected_speed	integer	query	False	Filter by fabric.connected_speed
fabric.name	string	query	False	Filter by fabric.name
fabric.switch_port	string	query	False	Filter by fabric.switch_port
fabric.connected	boolean	query	False	Filter by fabric.connected

Name	Type	In	Required	Description
wwnn	string	query	False	Filter by wwnn
wwpn	string	query	False	Filter by wwpn
description	string	query	False	Filter by description
supported_protocols	string	query	False	Filter by supported_protocols
fields	array[string]	query	False	Specify the fields to return.
max_records	integer	query	False	Limit the number of records returned.
return_records	boolean	query	False	The default is true for GET calls. When set to false, only the number of records is returned.
return_timeout	integer	query	False	The number of seconds to allow the call to execute before returning. When iterating over a collection, the default is 15 seconds. ONTAP returns earlier if either max records or the end of the collection is reached.
order_by	array[string]	query	False	Order results by specified fields and optional [asc

## Response

Status: 200, Ok

Name	Type	Description
_links	<a href="#">_links</a>	

Name	Type	Description
num_records	integer	Number of records.
records	array[fc_port]	

## Example response

```
{  
    "_links": {  
        "next": {  
            "href": "/api/resourcelink"  
        },  
        "self": {  
            "href": "/api/resourcelink"  
        }  
    },  
    "records": {  
        "_links": {  
            "self": {  
                "href": "/api/resourcelink"  
            }  
        },  
        "description": "Fibre Channel Target Adapter 0a (ACME Fibre Channel  
Adapter, rev. 1.0.0, 8G)",  
        "fabric": {  
            "connected_speed": 16,  
            "name": "string",  
            "port_address": "52100A",  
            "switch_port": "ssan-g620-03:33"  
        },  
        "name": "0a",  
        "node": {  
            "_links": {  
                "self": {  
                    "href": "/api/resourcelink"  
                }  
            },  
            "name": "node1",  
            "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
        },  
        "physical_protocol": "fibre_channel",  
        "speed": {  
            "configured": "auto",  
            "maximum": 32  
        },  
        "state": "online",  
        "supported_protocols": {  
        },  
        "transceiver": {  
            "capabilities": {  
            },  
            "model": "HPE 8Gb Fibre Channel SFP+ Transceiver",  
            "serial": "J9100A",  
            "type": "Fibre Channel Transceiver"  
        }  
    }  
}
```

```

        "form-factor": "sfp",
        "manufacturer": "Acme, Inc.",
        "part_number": "string"
    },
    "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412",
    "wwnn": "20:00:00:50:56:b4:13:a8",
    "wwpn": "20:00:00:50:56:b4:13:a8"
}
}

```

## Error

Status: Default, Error

Name	Type	Description
error	error	

## Example error

```
{
  "error": {
    "arguments": {
      "code": "string",
      "message": "string"
    },
    "code": "4",
    "message": "entry doesn't exist",
    "target": "uuid"
  }
}
```

## Definitions

## See Definitions

href

Name	Type	Description
href	string	

\_links

Name	Type	Description
next	<a href="#">href</a>	
self	<a href="#">href</a>	

\_links

Name	Type	Description
self	<a href="#">href</a>	

fabric

Properties of the fabric to which the FC port is attached.

Name	Type	Description
connected	boolean	Reports if the physical port has established a connection with the FC fabric.
connected_speed	integer	The negotiated data rate between the target FC port and the fabric in gigabits per second.
name	string	<p>The name of the fabric to which the port is connected. This is only available when the FC port is connected to a fabric.</p> <p>There is an added cost to retrieving this property's value. It is not populated for either a collection GET or an instance GET unless it is explicitly requested using the <code>fields</code> query parameter. See <a href="#">DOC Requesting specific fields</a> to learn more.</p>

Name	Type	Description
port_address	string	<p>The FC port address of the host bus adapter (HBA) physical port.</p> <p>Each FC port in an FC switched fabric has its own unique FC port address for routing purposes. The FC port address is assigned by a switch in the fabric when that port logs in to the fabric. This property refers to the FC port address given to the physical host bus adapter (HBA) port when the port performs a fabric login (FLOGI).</p> <p>This is useful for obtaining statistics and diagnostic information from FC switches.</p> <p>This is a six-digit hexadecimal encoded numeric value.</p>
switch_port	string	The switch port to which the FC port is connected.

## node

Name	Type	Description
_links	<a href="#">_links</a>	
name	string	
uuid	string	

## speed

The physical device speed related properties of the FC port.

Name	Type	Description
configured	string	The configured speed of the FC port in gigabits per second.
maximum	string	The maximum speed supported by the FC port in gigabits per second.

## transceiver

Properties of the transceiver connected to the FC port.

Name	Type	Description
capabilities	array[integer]	The speeds of which the transceiver is capable in gigabits per second.
form-factor	string	The form factor of the transceiver. Possible values are: <ul style="list-style-type: none"> <li><i>sfp</i> - Small Form Factor - Pluggable</li> <li><i>sff</i> - Small Form Factor</li> <li><i>unk</i> - Unknown</li> </ul>
manufacturer	string	The manufacturer of the transceiver.
part_number	string	The part number of the transceiver.

### fc\_port

A Fibre Channel (FC) port is the physical port of an FC adapter on an ONTAP cluster node that can be connected to an FC network to provide FC network connectivity. An FC port defines the location of an FC interface within the ONTAP cluster.

Name	Type	Description
_links	<a href="#">_links</a>	
description	string	A description of the FC port.
enabled	boolean	The administrative state of the FC port. If this property is set to <i>false</i> , all FC connectivity to FC interfaces are blocked. Optional in PATCH.
fabric	<a href="#">fabric</a>	Properties of the fabric to which the FC port is attached.
name	string	The FC port name.
node	<a href="#">node</a>	
physical_protocol	string	The physical network protocol of the FC port.

Name	Type	Description
speed	speed	The physical device speed related properties of the FC port.
state	string	<p>The operational state of the FC port.</p> <ul style="list-style-type: none"> <li>• startup - The port is booting up.</li> <li>• link_not_connected - The port has finished initialization, but a link with the fabric is not established.</li> <li>• online - The port is initialized and a link with the fabric has been established.</li> <li>• link_disconnected - The link was present at one point on this port but is currently not established.</li> <li>• offlined_by_user - The port is administratively disabled.</li> <li>• offlined_by_system - The port is set to offline by the system. This happens when the port encounters too many errors.</li> <li>• node_offline - The state information for the port cannot be retrieved. The node is offline or inaccessible.</li> </ul>
supported_protocols	array[string]	The network protocols supported by the FC port.
transceiver	transceiver	Properties of the transceiver connected to the FC port.
uuid	string	The unique identifier of the FC port.
wwnn	string	The base world wide node name (WWNN) for the FC port.
wwpn	string	The base world wide port name (WWPN) for the FC port.

error\_arguments

Name	Type	Description
code	string	Argument code
message	string	Message argument

error

Name	Type	Description
arguments	array[error_arguments]	Message arguments
code	string	Error code
message	string	Error message
target	string	The target parameter that caused the error.

## Retrieve an FC port

GET /network/fc/ports/{uuid}

Retrieves an FC port.

### Expensive properties

There is an added cost to retrieving values for these properties. They are not included by default in GET results and must be explicitly requested using the `fields` query parameter. See [DOC Requesting specific fields](#) to learn more.

- `fabric.name`

### Related ONTAP commands

- `network fcp adapter show`

### Learn more

- [DOC /network/fc/ports](#)

### Parameters

Name	Type	In	Required	Description
uuid	string	path	True	The unique identifier for the FC port.

Name	Type	In	Required	Description
fields	array[string]	query	False	Specify the fields to return.

## Response

Status: 200, Ok

Name	Type	Description
_links	<a href="#">_links</a>	
description	string	A description of the FC port.
enabled	boolean	The administrative state of the FC port. If this property is set to <i>false</i> , all FC connectivity to FC interfaces are blocked. Optional in PATCH.
fabric	<a href="#">fabric</a>	Properties of the fabric to which the FC port is attached.
name	string	The FC port name.
node	<a href="#">node</a>	
physical_protocol	string	The physical network protocol of the FC port.
speed	<a href="#">speed</a>	The physical device speed related properties of the FC port.

Name	Type	Description
state	string	<p>The operational state of the FC port.</p> <ul style="list-style-type: none"> <li>• startup - The port is booting up.</li> <li>• link_not_connected - The port has finished initialization, but a link with the fabric is not established.</li> <li>• online - The port is initialized and a link with the fabric has been established.</li> <li>• link_disconnected - The link was present at one point on this port but is currently not established.</li> <li>• offlined_by_user - The port is administratively disabled.</li> <li>• offlined_by_system - The port is set to offline by the system. This happens when the port encounters too many errors.</li> <li>• node_offline - The state information for the port cannot be retrieved. The node is offline or inaccessible.</li> </ul>
supported_protocols	array[string]	The network protocols supported by the FC port.
transceiver	<a href="#">transceiver</a>	Properties of the transceiver connected to the FC port.
uuid	string	The unique identifier of the FC port.
wwnn	string	The base world wide node name (WWNN) for the FC port.
wwpn	string	The base world wide port name (WWPN) for the FC port.

## Example response

```
{  
    "_links": {  
        "self": {  
            "href": "/api/resourcelink"  
        }  
    },  
    "description": "Fibre Channel Target Adapter 0a (ACME Fibre Channel  
Adapter, rev. 1.0.0, 8G)",  
    "fabric": {  
        "connected_speed": 16,  
        "name": "string",  
        "port_address": "52100A",  
        "switch_port": "ssan-g620-03:33"  
    },  
    "name": "0a",  
    "node": {  
        "_links": {  
            "self": {  
                "href": "/api/resourcelink"  
            }  
        },  
        "name": "node1",  
        "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
    },  
    "physical_protocol": "fibre_channel",  
    "speed": {  
        "configured": "auto",  
        "maximum": 32  
    },  
    "state": "online",  
    "supported_protocols": {  
    },  
    "transceiver": {  
        "capabilities": {  
        },  
        "form-factor": "sfp",  
        "manufacturer": "Acme, Inc.",  
        "part_number": "string"  
    },  
    "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412",  
    "wwnn": "20:00:00:50:56:b4:13:a8",  
    "wwpn": "20:00:00:50:56:b4:13:a8"  
}
```

## Error

Status: Default, Error

Name	Type	Description
error	error	

### Example error

```
{  
  "error": {  
    "arguments": {  
      "code": "string",  
      "message": "string"  
    },  
    "code": "4",  
    "message": "entry doesn't exist",  
    "target": "uuid"  
  }  
}
```

## Definitions

## See Definitions

href

Name	Type	Description
href	string	

\_links

Name	Type	Description
self	href	

fabric

Properties of the fabric to which the FC port is attached.

Name	Type	Description
connected	boolean	Reports if the physical port has established a connection with the FC fabric.
connected_speed	integer	The negotiated data rate between the target FC port and the fabric in gigabits per second.
name	string	<p>The name of the fabric to which the port is connected. This is only available when the FC port is connected to a fabric.</p> <p>There is an added cost to retrieving this property's value. It is not populated for either a collection GET or an instance GET unless it is explicitly requested using the <code>fields</code> query parameter. See <a href="#">DOC Requesting specific fields</a> to learn more.</p>

Name	Type	Description
port_address	string	<p>The FC port address of the host bus adapter (HBA) physical port.</p> <p>Each FC port in an FC switched fabric has its own unique FC port address for routing purposes. The FC port address is assigned by a switch in the fabric when that port logs in to the fabric. This property refers to the FC port address given to the physical host bus adapter (HBA) port when the port performs a fabric login (FLOGI).</p> <p>This is useful for obtaining statistics and diagnostic information from FC switches.</p> <p>This is a six-digit hexadecimal encoded numeric value.</p>
switch_port	string	The switch port to which the FC port is connected.

## node

Name	Type	Description
_links	<a href="#">_links</a>	
name	string	
uuid	string	

## speed

The physical device speed related properties of the FC port.

Name	Type	Description
configured	string	The configured speed of the FC port in gigabits per second.
maximum	string	The maximum speed supported by the FC port in gigabits per second.

## transceiver

Properties of the transceiver connected to the FC port.

Name	Type	Description
capabilities	array[integer]	The speeds of which the transceiver is capable in gigabits per second.
form-factor	string	The form factor of the transceiver. Possible values are: <ul style="list-style-type: none"><li>• <i>sfp</i> - Small Form Factor - Pluggable</li><li>• <i>sff</i> - Small Form Factor</li><li>• <i>unk</i> - Unknown</li></ul>
manufacturer	string	The manufacturer of the transceiver.
part_number	string	The part number of the transceiver.

#### error\_arguments

Name	Type	Description
code	string	Argument code
message	string	Message argument

#### error

Name	Type	Description
arguments	array[error_arguments]	Message arguments
code	string	Error code
message	string	Error message
target	string	The target parameter that caused the error.

## Update an FC port

PATCH /network/fc/ports/{uuid}

Updates an FC port.

## Related ONTAP commands

- `network fcp adapter modify`

## Learn more

- [DOC /network/fc/ports](#)

## Parameters

Name	Type	In	Required	Description
uuid	string	path	True	The unique identifier for the FC port.

## Request Body

Name	Type	Description
_links	<a href="#">_links</a>	
description	string	A description of the FC port.
enabled	boolean	The administrative state of the FC port. If this property is set to <code>false</code> , all FC connectivity to FC interfaces are blocked. Optional in PATCH.
fabric	<a href="#">fabric</a>	Properties of the fabric to which the FC port is attached.
name	string	The FC port name.
node	<a href="#">node</a>	
physical_protocol	string	The physical network protocol of the FC port.
speed	<a href="#">speed</a>	The physical device speed related properties of the FC port.

Name	Type	Description
state	string	<p>The operational state of the FC port.</p> <ul style="list-style-type: none"> <li>• startup - The port is booting up.</li> <li>• link_not_connected - The port has finished initialization, but a link with the fabric is not established.</li> <li>• online - The port is initialized and a link with the fabric has been established.</li> <li>• link_disconnected - The link was present at one point on this port but is currently not established.</li> <li>• offlined_by_user - The port is administratively disabled.</li> <li>• offlined_by_system - The port is set to offline by the system. This happens when the port encounters too many errors.</li> <li>• node_offline - The state information for the port cannot be retrieved. The node is offline or inaccessible.</li> </ul>
supported_protocols	array[string]	The network protocols supported by the FC port.
transceiver	<a href="#">transceiver</a>	Properties of the transceiver connected to the FC port.
uuid	string	The unique identifier of the FC port.
wwnn	string	The base world wide node name (WWNN) for the FC port.
wwpn	string	The base world wide port name (WWPN) for the FC port.

## Example request

```
{  
    "_links": {  
        "self": {  
            "href": "/api/resourcelink"  
        }  
    },  
    "description": "Fibre Channel Target Adapter 0a (ACME Fibre Channel  
Adapter, rev. 1.0.0, 8G)",  
    "fabric": {  
        "connected_speed": 16,  
        "name": "string",  
        "port_address": "52100A",  
        "switch_port": "ssan-g620-03:33"  
    },  
    "name": "0a",  
    "node": {  
        "_links": {  
            "self": {  
                "href": "/api/resourcelink"  
            }  
        },  
        "name": "node1",  
        "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
    },  
    "physical_protocol": "fibre_channel",  
    "speed": {  
        "configured": "auto",  
        "maximum": 32  
    },  
    "state": "online",  
    "supported_protocols": {  
    },  
    "transceiver": {  
        "capabilities": {  
        },  
        "form-factor": "sfp",  
        "manufacturer": "Acme, Inc.",  
        "part_number": "string"  
    },  
    "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412",  
    "wwnn": "20:00:00:50:56:b4:13:a8",  
    "wwpn": "20:00:00:50:56:b4:13:a8"  
}
```

## Response

Status: 200, Ok

## Error

Status: Default

### ONTAP Error Response Codes

Error Code	Description
5374085	The node where the Fibre Channel port is located is offline.
5374087	The Fibre Channel port has active Fibre Channel interfaces and cannot be disabled.

Name	Type	Description
error	error	

### Example error

```
{
  "error": {
    "arguments": {
      "code": "string",
      "message": "string"
    },
    "code": "4",
    "message": "entry doesn't exist",
    "target": "uuid"
  }
}
```

## Definitions

## See Definitions

href

Name	Type	Description
href	string	

\_links

Name	Type	Description
self	href	

fabric

Properties of the fabric to which the FC port is attached.

Name	Type	Description
connected	boolean	Reports if the physical port has established a connection with the FC fabric.
connected_speed	integer	The negotiated data rate between the target FC port and the fabric in gigabits per second.
name	string	<p>The name of the fabric to which the port is connected. This is only available when the FC port is connected to a fabric.</p> <p>There is an added cost to retrieving this property's value. It is not populated for either a collection GET or an instance GET unless it is explicitly requested using the <code>fields</code> query parameter. See <a href="#">DOC Requesting specific fields</a> to learn more.</p>

Name	Type	Description
port_address	string	<p>The FC port address of the host bus adapter (HBA) physical port.</p> <p>Each FC port in an FC switched fabric has its own unique FC port address for routing purposes. The FC port address is assigned by a switch in the fabric when that port logs in to the fabric. This property refers to the FC port address given to the physical host bus adapter (HBA) port when the port performs a fabric login (FLOGI).</p> <p>This is useful for obtaining statistics and diagnostic information from FC switches.</p> <p>This is a six-digit hexadecimal encoded numeric value.</p>
switch_port	string	The switch port to which the FC port is connected.

## node

Name	Type	Description
_links	<a href="#">_links</a>	
name	string	
uuid	string	

## speed

The physical device speed related properties of the FC port.

Name	Type	Description
configured	string	The configured speed of the FC port in gigabits per second.
maximum	string	The maximum speed supported by the FC port in gigabits per second.

## transceiver

Properties of the transceiver connected to the FC port.

Name	Type	Description
capabilities	array[integer]	The speeds of which the transceiver is capable in gigabits per second.
form-factor	string	The form factor of the transceiver. Possible values are: <ul style="list-style-type: none"> <li><i>sfp</i> - Small Form Factor - Pluggable</li> <li><i>sff</i> - Small Form Factor</li> <li><i>unk</i> - Unknown</li> </ul>
manufacturer	string	The manufacturer of the transceiver.
part_number	string	The part number of the transceiver.

### fc\_port

A Fibre Channel (FC) port is the physical port of an FC adapter on an ONTAP cluster node that can be connected to an FC network to provide FC network connectivity. An FC port defines the location of an FC interface within the ONTAP cluster.

Name	Type	Description
_links	<a href="#">_links</a>	
description	string	A description of the FC port.
enabled	boolean	The administrative state of the FC port. If this property is set to <i>false</i> , all FC connectivity to FC interfaces are blocked. Optional in PATCH.
fabric	<a href="#">fabric</a>	Properties of the fabric to which the FC port is attached.
name	string	The FC port name.
node	<a href="#">node</a>	
physical_protocol	string	The physical network protocol of the FC port.

Name	Type	Description
speed	speed	The physical device speed related properties of the FC port.
state	string	<p>The operational state of the FC port.</p> <ul style="list-style-type: none"> <li>• startup - The port is booting up.</li> <li>• link_not_connected - The port has finished initialization, but a link with the fabric is not established.</li> <li>• online - The port is initialized and a link with the fabric has been established.</li> <li>• link_disconnected - The link was present at one point on this port but is currently not established.</li> <li>• offlined_by_user - The port is administratively disabled.</li> <li>• offlined_by_system - The port is set to offline by the system. This happens when the port encounters too many errors.</li> <li>• node_offline - The state information for the port cannot be retrieved. The node is offline or inaccessible.</li> </ul>
supported_protocols	array[string]	The network protocols supported by the FC port.
transceiver	transceiver	Properties of the transceiver connected to the FC port.
uuid	string	The unique identifier of the FC port.
wwnn	string	The base world wide node name (WWNN) for the FC port.
wwpn	string	The base world wide port name (WWPN) for the FC port.

error\_arguments

Name	Type	Description
code	string	Argument code
message	string	Message argument

error

Name	Type	Description
arguments	array[error_arguments]	Message arguments
code	string	Error code
message	string	Error message
target	string	The target parameter that caused the error.

## Manage HTTP proxy configuration

### Network http-proxy endpoint overview

#### Overview

Configuration of an HTTP proxy for an SVM or a Cluster IPspace.

#### Retrieve HTTP proxy information

The HTTP proxy GET operation retrieves all configurations for an SVM or a Cluster IPspace via '/api/cluster'.

#### Examples

##### Retrieving all fields for all HTTP proxy configurations

```

# The API:
/api/network/http-proxy

# The call:
curl -X GET "https://<mgmt-ip>/api/network/http-
proxy?fields=*&return_records=true&return_timeout=15" -H "accept:
application/json"

# The response:
{
  "records": [
    {
      "uuid": "4133a1fc-7228-11e9-b40c-005056bb4f0c",
      "svm": {
        "name": "vs1",
        "uuid": "4133a1fc-7228-11e9-b40c-005056bb4f0c"
      },
      "server": "server1.example.com",
      "port": 3128
    },
    {
      "uuid": "96219ce3-7214-11e9-828c-005056bb4f0c",
      "svm": {
        "name": "cluster-1",
        "uuid": "96219ce3-7214-11e9-828c-005056bb4f0c"
      },
      "ipspace": {
        "uuid": "7433520f-7214-11e9-828c-005056bb4f0c",
        "name": "Default"
      },
      "server": "1.1.1.",
      "port": 3128
    }
  ],
  "num_records": 2
}

```

#### Retrieving the HTTP proxy configuration for a specific SVM

```

# The API:
/api/network/http-proxy/{uuid}

# The call:
curl -X GET "https://<mgmt-ip>/api/network/http-proxy/96219ce3-7214-11e9-
828c-005056bb4f0c" -H "accept: application/json"

# The response
{
  "uuid": "96219ce3-7214-11e9-828c-005056bb4f0c",
  "svm": {
    "name": "cluster-1",
    "uuid": "96219ce3-7214-11e9-828c-005056bb4f0c"
  },
  "ipspace": {
    "uuid": "7433520f-7214-11e9-828c-005056bb4f0c",
    "name": "Default"
  },
  "server": "1.1.1.1",
  "port": 3128
}

```

## Creating an HTTP proxy configuration

You can use the HTTP proxy POST operation to create an HTTP proxy configuration for the specified SVM.

### Examples

#### Creating an HTTP proxy configuration for a particular SVM

```

# The API:
/api/network/http-proxy

# The call:
curl -X POST "https://<mgmt-ip>/api/network/http-proxy" -H "accept:
application/json" -H "Content-Type: application/json" -d "{      \"port\":
3128,  \"server\": \"1.1.1.1\",  \"svm\": {      \"name\": \"cluster-1\" } }"

```

#### Creating an HTTP proxy configuration for a particular IPspace

```

# The API:
/api/network/http-proxy

# The call:
curl -X POST "https://<mgmt-ip>/api/network/http-proxy" -H "accept: application/json" -H "Content-Type: application/json" -d "{ \"ipspace\": { \"name\": \"Default\" }, \"port\": 3128, \"server\": \"1.1.1.1\" }}"

```

## Update an HTTP proxy configuration for a specified SVM

You can use the HTTP proxy PATCH operation to update the HTTP proxy configuration for the specified SVM.

### Example

The following example shows how a PATCH operation is used to update an HTTP proxy configuration for a specific SVM:

```

# The API:
/api/network/http-proxy/{uuid}

# The call:
curl -X PATCH "https://<mgmt-ip>/api/network/http-proxy/96219ce3-7214-11e9-828c-005056bb4f0c" -H "accept: application/json" -H "Content-Type: application/json" -d "{ \"port\": 3128, \"server\": \"server2.example.com\"}"

```

## Delete an HTTP proxy configuration for a specified SVM

You can use the HTTP proxy DELETE operation to delete the HTTP proxy configuration for the specified SVM.

### Example

The following example shows how a DELETE operation is used to delete an HTTP proxy configuration for a specific SVM:

```

# The API:
/api/network/http-proxy/{uuid}

# The call:
curl -X DELETE "https://<mgmt-ip>/api/network/http-proxy/96219ce3-7214-11e9-828c-005056bb4f0c" -H "accept: application/json"

```

## Retrieve HTTP proxy configurations for all SVMs and cluster IPspaces

GET /network/http-proxy

Retrieves the HTTP proxy configurations of all the SVMs and Cluster IPspaces.

## Related ONTAP commands

- `vserver http-proxy show`

## Learn more

- [DOC /network/http-proxy](#)

## Parameters

Name	Type	In	Required	Description
scope	string	query	False	Filter by scope
uuid	string	query	False	Filter by uuid
port	integer	query	False	Filter by port
server	string	query	False	Filter by server
ipspace.uuid	string	query	False	Filter by ipspace.uuid
ipspace.name	string	query	False	Filter by ipspace.name
svm.uuid	string	query	False	Filter by svm.uuid
svm.name	string	query	False	Filter by svm.name
fields	array[string]	query	False	Specify the fields to return.
max_records	integer	query	False	Limit the number of records returned.
return_records	boolean	query	False	The default is true for GET calls. When set to false, only the number of records is returned.

Name	Type	In	Required	Description
return_timeout	integer	query	False	The number of seconds to allow the call to execute before returning. When iterating over a collection, the default is 15 seconds. ONTAP returns earlier if either max records or the end of the collection is reached.
order_by	array[string]	query	False	Order results by specified fields and optional [asc

## Response

Status: 200, Ok

Name	Type	Description
_links	<a href="#">_links</a>	
num_records	integer	
records	array[ <a href="#">network_http_proxy</a> ]	

## Example response

```
{  
  "_links": {  
    "next": {  
      "href": "/api/resourcelink"  
    },  
    "self": {  
      "href": "/api/resourcelink"  
    }  
  },  
  "records": {  
    "_links": {  
      "self": {  
        "href": "/api/resourcelink"  
      }  
    },  
    "ipspace": {  
      "_links": {  
        "self": {  
          "href": "/api/resourcelink"  
        }  
      },  
      "name": "exchange",  
      "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
    },  
    "port": 3128,  
    "scope": "svm",  
    "svm": {  
      "_links": {  
        "self": {  
          "href": "/api/resourcelink"  
        }  
      },  
      "name": "svml1",  
      "uuid": "02c9e252-41be-11e9-81d5-00a0986138f7"  
    },  
    "uuid": "string"  
  }  
}
```

## Error

Status: Default, Error

Name	Type	Description
error	error	

### Example error

```
{  
  "error": {  
    "arguments": {  
      "code": "string",  
      "message": "string"  
    },  
    "code": "4",  
    "message": "entry doesn't exist",  
    "target": "uuid"  
  }  
}
```

### Definitions

## See Definitions

href

Name	Type	Description
href	string	

\_links

Name	Type	Description
next	href	
self	href	

\_links

Name	Type	Description
self	href	

ipspace

Applies to both SVM and cluster-scoped objects. Either the UUID or name is supplied on input.

Name	Type	Description
_links	_links	
name	string	IPspace name
uuid	string	IPspace UUID

svm

Name	Type	Description
_links	_links	
name	string	The name of the SVM.
uuid	string	The unique identifier of the SVM.

network\_http\_proxy

Name	Type	Description
_links	_links	

Name	Type	Description
ipspace	ipspace	Applies to both SVM and cluster-scoped objects. Either the UUID or name is supplied on input.
port	integer	The port number on which the HTTP proxy service is configured on the proxy server.
scope	string	Set to "svm" for proxy owned by an SVM. Otherwise, set to "cluster".
server	string	The fully qualified domain name (FQDN) or IP address of the proxy server.
svm	svm	
uuid	string	The UUID that uniquely identifies the HTTP proxy.

#### error\_arguments

Name	Type	Description
code	string	Argument code
message	string	Message argument

#### error

Name	Type	Description
arguments	array[error_arguments]	Message arguments
code	string	Error code
message	string	Error message
target	string	The target parameter that caused the error.

## Create an http proxy configuration for an SVM or cluster IPspace

POST /network/http-proxy

Creates an HTTP proxy configuration for an SVM or a Cluster IPspace. Important notes:

- IPv6 must be enabled if IPv6 family addresses are specified in the "server" field.
- The server and the port combination specified using the "server" and "port" fields is validated during this operation. The validation will fail in the following scenarios:
  - The HTTP proxy service is not configured on the server.
  - The HTTP proxy service is not running on the specified port.
  - The server is unreachable.

## Required properties

- SVM-scoped HTTP proxy
  - `svm.uuid` or `svm.name` - Existing SVM in which to create the HTTP proxy.
- Cluster-scoped HTTP proxy
  - `ipspace.uuid` or `ipspace.name` - Existing Cluster IPspace in which to create the HTTP proxy.
- `server` - HTTP proxy server FQDN or IP address.
- `port` - HTTP proxy server port.

## Related ONTAP commands

- `vserver http-proxy create`

## Learn more

- [DOC /network/http-proxy](#)

## Parameters

Name	Type	In	Required	Description
<code>return_records</code>	boolean	query	False	The default is false. If set to true, the records are returned.

## Request Body

Name	Type	Description
<code>_links</code>	<a href="#">_links</a>	
<code>ipspace</code>	<a href="#">ipspace</a>	Applies to both SVM and cluster-scoped objects. Either the UUID or name is supplied on input.
<code>port</code>	integer	The port number on which the HTTP proxy service is configured on the proxy server.

Name	Type	Description
scope	string	Set to "svm" for proxy owned by an SVM. Otherwise, set to "cluster".
server	string	The fully qualified domain name (FQDN) or IP address of the proxy server.
svm	svm	
uuid	string	The UUID that uniquely identifies the HTTP proxy.

### Example request

```
{
  "_links": {
    "self": {
      "href": "/api/resourcelink"
    }
  },
  "ipspace": {
    "_links": {
      "self": {
        "href": "/api/resourcelink"
      }
    },
    "name": "exchange",
    "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"
  },
  "port": 3128,
  "scope": "svm",
  "svm": {
    "_links": {
      "self": {
        "href": "/api/resourcelink"
      }
    },
    "name": "svml",
    "uuid": "02c9e252-41be-11e9-81d5-00a0986138f7"
  },
  "uuid": "string"
}
```

## Response

Status: 201, Created

Name	Type	Description
_links	<a href="#">_links</a>	
num_records	integer	
records	array[ <a href="#">network_http_proxy</a> ]	

## Example response

```
{  
    "_links": {  
        "next": {  
            "href": "/api/resourcelink"  
        },  
        "self": {  
            "href": "/api/resourcelink"  
        }  
    },  
    "records": {  
        "_links": {  
            "self": {  
                "href": "/api/resourcelink"  
            }  
        },  
        "ipspace": {  
            "_links": {  
                "self": {  
                    "href": "/api/resourcelink"  
                }  
            },  
            "name": "exchange",  
            "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
        },  
        "port": 3128,  
        "scope": "svm",  
        "svm": {  
            "_links": {  
                "self": {  
                    "href": "/api/resourcelink"  
                }  
            },  
            "name": "svml",  
            "uuid": "02c9e252-41be-11e9-81d5-00a0986138f7"  
        },  
        "uuid": "string"  
    }  
}
```

## Error

Status: Default

## ONTAP Error Response Codes

Error Code	Description
26214473	HTTP proxy configuration is not valid.
26214476	The "IPspace" parameter should not be specified in the SVM context.
26214477	The specified IPspace does not exist.
23724130	Cannot use an IPv6 name server address because there are no IPv6 interfaces.

Name	Type	Description
error	error	

### Example error

```
{
  "error": {
    "arguments": {
      "code": "string",
      "message": "string"
    },
    "code": "4",
    "message": "entry doesn't exist",
    "target": "uuid"
  }
}
```

### Definitions

## See Definitions

href

Name	Type	Description
href	string	

\_links

Name	Type	Description
self	href	

ipspace

Applies to both SVM and cluster-scoped objects. Either the UUID or name is supplied on input.

Name	Type	Description
_links	_links	
name	string	IPspace name
uuid	string	IPspace UUID

svm

Name	Type	Description
_links	_links	
name	string	The name of the SVM.
uuid	string	The unique identifier of the SVM.

network\_http\_proxy

Name	Type	Description
_links	_links	
ipspace	ipspace	Applies to both SVM and cluster-scoped objects. Either the UUID or name is supplied on input.
port	integer	The port number on which the HTTP proxy service is configured on the proxy server.

Name	Type	Description
scope	string	Set to "svm" for proxy owned by an SVM. Otherwise, set to "cluster".
server	string	The fully qualified domain name (FQDN) or IP address of the proxy server.
svm	svm	
uuid	string	The UUID that uniquely identifies the HTTP proxy.

### \_links

Name	Type	Description
next	href	
self	href	

### error\_arguments

Name	Type	Description
code	string	Argument code
message	string	Message argument

### error

Name	Type	Description
arguments	array[error_arguments]	Message arguments
code	string	Error code
message	string	Error message
target	string	The target parameter that caused the error.

## Delete http proxy configuration for an SVM or cluster IPspace

DELETE /network/http-proxy/{uuid}

Deletes the HTTP proxy configuration of the specified SVM or Cluster IPspace.

## Related ONTAP commands

- vserver http-proxy delete

## Learn more

- [DOC /network/http-proxy](#)

## Parameters

Name	Type	In	Required	Description
uuid	string	path	True	

## Response

```
Status: 200, Ok
```

## Error

```
Status: Default, Error
```

Name	Type	Description
error	error	

## Example error

```
{
  "error": {
    "arguments": {
      "code": "string",
      "message": "string"
    },
    "code": "4",
    "message": "entry doesn't exist",
    "target": "uuid"
  }
}
```

## Definitions

## See Definitions

error\_arguments

Name	Type	Description
code	string	Argument code
message	string	Message argument

error

Name	Type	Description
arguments	array[error_arguments]	Message arguments
code	string	Error code
message	string	Error message
target	string	The target parameter that caused the error.

## Display http proxy server, port, and IPspace information for an SVM or cluster IPspace

GET /network/http-proxy/{uuid}

Displays the HTTP proxy server, port, and IPspace of the specified SVM or Cluster IPspace.

### Related ONTAP commands

- vserver http-proxy show

### Learn more

- [DOC /network/http-proxy](#)

### Parameters

Name	Type	In	Required	Description
uuid	string	path	True	HTTP proxy UUID
fields	array[string]	query	False	Specify the fields to return.

## Response

Status: 200, Ok

Name	Type	Description
_links	<a href="#">_links</a>	
ipspace	<a href="#">ipspace</a>	Applies to both SVM and cluster-scoped objects. Either the UUID or name is supplied on input.
port	integer	The port number on which the HTTP proxy service is configured on the proxy server.
scope	string	Set to "svm" for proxy owned by an SVM. Otherwise, set to "cluster".
server	string	The fully qualified domain name (FQDN) or IP address of the proxy server.
svm	<a href="#">svm</a>	
uuid	string	The UUID that uniquely identifies the HTTP proxy.

## Example response

```
{  
    "_links": {  
        "self": {  
            "href": "/api/resourcelink"  
        }  
    },  
    "ipspace": {  
        "_links": {  
            "self": {  
                "href": "/api/resourcelink"  
            }  
        },  
        "name": "exchange",  
        "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
    },  
    "port": 3128,  
    "scope": "svm",  
    "svm": {  
        "_links": {  
            "self": {  
                "href": "/api/resourcelink"  
            }  
        },  
        "name": "svml1",  
        "uuid": "02c9e252-41be-11e9-81d5-00a0986138f7"  
    },  
    "uuid": "string"  
}
```

## Error

Status: Default, Error

Name	Type	Description
error	error	

## Example error

```
{  
  "error": {  
    "arguments": {  
      "code": "string",  
      "message": "string"  
    },  
    "code": "4",  
    "message": "entry doesn't exist",  
    "target": "uuid"  
  }  
}
```

## Definitions

## See Definitions

href

Name	Type	Description
href	string	

\_links

Name	Type	Description
self	href	

ipspace

Applies to both SVM and cluster-scoped objects. Either the UUID or name is supplied on input.

Name	Type	Description
_links	_links	
name	string	IPspace name
uuid	string	IPspace UUID

svm

Name	Type	Description
_links	_links	
name	string	The name of the SVM.
uuid	string	The unique identifier of the SVM.

error\_arguments

Name	Type	Description
code	string	Argument code
message	string	Message argument

error

Name	Type	Description
arguments	array[error_arguments]	Message arguments

Name	Type	Description
code	string	Error code
message	string	Error message
target	string	The target parameter that caused the error.

## Update proxy server, port, username, and password parameters

PATCH /network/http-proxy/{uuid}

Updates the proxy server, port, username, and password parameters. Important notes:

- IPv6 must be enabled if IPv6 family addresses are specified in the "server" field.
- The server and the port combination specified using the "server" and "port" fields is validated during this operation. The validation will fail in the following scenarios:
  - The HTTP proxy service is not configured on the server.
  - The HTTP proxy service is not running on the specified port.
  - The server is unreachable.

### Related ONTAP commands

- vserver http-proxy modify

### Learn more

- [DOC /network/http-proxy](#)

### Parameters

Name	Type	In	Required	Description
uuid	string	path	True	HTTP proxy UUID

### Request Body

Name	Type	Description
_links	<a href="#">_links</a>	
ipspace	<a href="#">ipspace</a>	Applies to both SVM and cluster-scoped objects. Either the UUID or name is supplied on input.

Name	Type	Description
port	integer	The port number on which the HTTP proxy service is configured on the proxy server.
scope	string	Set to "svm" for proxy owned by an SVM. Otherwise, set to "cluster".
server	string	The fully qualified domain name (FQDN) or IP address of the proxy server.
svm	<a href="#">svm</a>	
uuid	string	The UUID that uniquely identifies the HTTP proxy.

## Example request

```
{  
    "_links": {  
        "self": {  
            "href": "/api/resourcelink"  
        }  
    },  
    "ipspace": {  
        "_links": {  
            "self": {  
                "href": "/api/resourcelink"  
            }  
        },  
        "name": "exchange",  
        "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
    },  
    "port": 3128,  
    "scope": "svm",  
    "svm": {  
        "_links": {  
            "self": {  
                "href": "/api/resourcelink"  
            }  
        },  
        "name": "svml1",  
        "uuid": "02c9e252-41be-11e9-81d5-00a0986138f7"  
    },  
    "uuid": "string"  
}
```

## Response

```
Status: 200, Ok
```

## Error

```
Status: Default
```

## ONTAP Error Response Codes

Error Code	Description
26214473	The HTTP proxy configuration is not valid.
23724130	Cannot use an IPv6 name server address because there are no IPv6 interfaces.

Name	Type	Description
error	error	

## Example error

```
{
  "error": {
    "arguments": {
      "code": "string",
      "message": "string"
    },
    "code": "4",
    "message": "entry doesn't exist",
    "target": "uuid"
  }
}
```

## Definitions

## See Definitions

href

Name	Type	Description
href	string	

\_links

Name	Type	Description
self	href	

ipspace

Applies to both SVM and cluster-scoped objects. Either the UUID or name is supplied on input.

Name	Type	Description
_links	_links	
name	string	IPspace name
uuid	string	IPspace UUID

svm

Name	Type	Description
_links	_links	
name	string	The name of the SVM.
uuid	string	The unique identifier of the SVM.

network\_http\_proxy

Name	Type	Description
_links	_links	
ipspace	ipspace	Applies to both SVM and cluster-scoped objects. Either the UUID or name is supplied on input.
port	integer	The port number on which the HTTP proxy service is configured on the proxy server.

Name	Type	Description
scope	string	Set to "svm" for proxy owned by an SVM. Otherwise, set to "cluster".
server	string	The fully qualified domain name (FQDN) or IP address of the proxy server.
svm	svm	
uuid	string	The UUID that uniquely identifies the HTTP proxy.

#### error\_arguments

Name	Type	Description
code	string	Argument code
message	string	Message argument

#### error

Name	Type	Description
arguments	array[error_arguments]	Message arguments
code	string	Error code
message	string	Error message
target	string	The target parameter that caused the error.

## Manage BGP peer groups

### Network IP BGP peer-groups endpoint overview

#### Overview

The following operations are supported:

- Creation: POST network/ip/bgp/peer-groups
- Collection Get: GET network/ip/bgp/peer-groups
- Instance Get: GET network/ip/bgp/peer-groups/{uuid}

- Instance Patch: PATCH network/ip/bgp/peer-groups/{uuid}
- Instance Delete: DELETE network/ip/bgp/peer-groups/{uuid}

## **Retrieving network BGP sessions information**

The IP BGP peer-groups GET API retrieves and displays relevant information pertaining to the BGP peer-groups configured in the cluster. The response can contain a list of multiple BGP peer-groups or a specific peer-group. Each BGP peer-group represents a BGP session configured between a local interface and a peer router.

## **Examples**

### **Retrieving all BGP peer-groups in the cluster**

The following example shows the list of all BGP peer-groups configured in a cluster.

```

# The API:
/api/network/ip/bgp/peer-groups

# The call:
curl -X GET "https://<mgmt-ip>/api/network/ip/bgp/peer-groups" -H "accept: application/hal+json"

# The response:
{
  "records": [
    {
      "uuid": "5f22ae9d-87b2-11e9-a3a6-005056bb81a4",
      "name": "pg1",
      "_links": {
        "self": {
          "href": "/api/network/ip/bgp/peer-groups/5f22ae9d-87b2-11e9-a3a6-005056bb81a4"
        }
      }
    },
    {
      "uuid": "5fd08be3-87b2-11e9-952f-005056bb2170",
      "name": "pg2",
      "_links": {
        "self": {
          "href": "/api/network/ip/bgp/peer-groups/5fd08be3-87b2-11e9-952f-005056bb2170"
        }
      }
    }
  ],
  "num_records": 2,
  "_links": {
    "self": {
      "href": "/api/network/ip/bgp/peer-groups"
    }
  }
}

```

### Retrieving a specific BGP peer-group

The following example shows the response when a specific BGP peer-group is requested. The system returns an error when there is no peer-group with the requested UUID.

```

# The API:
/api/network/ip/bgp/peer-groups/{uuid}

# The call:
curl -X GET "https://<mgmt-ip>/api/network/ip/bgp/peer-groups/5fd08be3-
87b2-11e9-952f-005056bb2170" -H "accept: application/hal+json"

# The response:
{
  "uuid": "5fd08be3-87b2-11e9-952f-005056bb2170",
  "name": "pg2",
  "ipspace": {
    "uuid": "84fd3375-879a-11e9-a3a6-005056bb81a4",
    "name": "Default",
    "_links": {
      "self": {
        "href": "/api/network/ipspaces/84fd3375-879a-11e9-a3a6-005056bb81a4"
      }
    }
  },
  "local": {
    "interface": {
      "uuid": "5e76a305-87b2-11e9-952f-005056bb2170",
      "name": "bgp2",
      "ip": {
        "address": "10.10.10.2"
      }
    },
    "port": {
      "uuid": "f8ff73de-879a-11e9-952f-005056bb2170",
      "name": "e0h",
      "node": {
        "name": "node1"
      }
    }
  },
  "peer": {
    "address": "10.10.10.1",
    "asn": 65501
  },
  "state": "up",
  "_links": {
    "self": {
      "href": "/api/network/ip/bgp/peer-groups/5fd08be3-87b2-11e9-952f-
005056bb2170"
    }
  }
}

```

```
    }
}
}
```

### Retrieving specific fields and limiting the output using filters

The following example shows the response when a filter is applied (`location.port.node.name=node1`) and only certain fields are requested. Filtered fields are in the output in addition to the default fields and requested fields.

```
# The API:  
/api/network/ip/bgp/peer-groups  
  
# The call:  
curl -X GET "https://<mgmt-ip>/api/network/ip/bgp/peer-  
groups?local.port.node.name=node1&fields=local.interface.ip,peer" -H  
"accept: application/hal+json"  
  
# The response:  
{  
  "records": [  
    {  
      "uuid": "5f22ae9d-87b2-11e9-a3a6-005056bb81a4",  
      "name": "pg1",  
      "local": {  
        "interface": {  
          "ip": {  
            "address": "10.10.10.1"  
          }  
        },  
        "port": {  
          "node": {  
            "name": "node1"  
          }  
        }  
      },  
      "peer": {  
        "address": "10.10.10.2",  
        "asn": 65501  
      },  
      "_links": {  
        "self": {  
          "href": "/api/network/ip/bgp/peer-groups/5f22ae9d-87b2-11e9-a3a6-
```

```
005056bb81a4"
    }
}
]
,
"num_records": 1,
"_links": {
  "self": {
    "href": "/api/network/ip/bgp/peer-
groups?local.port.node.name=node1&fields=local.interface.ip,peer"
  }
}
}
```

## Creating a BGP peer-group

The BGP peer-group POST API is used to create a peer-group as shown in the following examples.

## Examples

### Creating a BGP peer-group with an existing interface

The following example shows how to create a BGP peer-group between an existing interface "bgp1" and peer router with the address "10.10.10.10". The local interface "bgp1" needs to support the management-bgp service, otherwise the system returns an error.

```

# The API:
/api/network/ip/bgp/peer-groups

# The call:
curl -X POST "https://<mgmt-ip>/api/network/bgp/peer-
groups?return_records=true" -d'{"name": "newPg", "ipspace.name":"Default",
"local.interface.name": "bgp1", "peer.address":"10.10.10.10"}'

# The response:
{
  "num_records": 1,
  "records": [
    {
      "uuid": "e3faacc6-87cb-11e9-a3a6-005056bb81a4",
      "name": "newPg",
      "ipspace": {
        "name": "Default"
      },
      "local": {
        "interface": {
          "name": "bgp1"
        }
      },
      "peer": {
        "address": "10.10.10.10"
      },
      "_links": {
        "self": {
          "href": "/api/network/ip/bgp/peer-groups/e3faacc6-87cb-11e9-a3a6-
005056bb81a4"
        }
      }
    }
  ]
}

```

#### **Creating a BGP peer-group and provisioning a new local interface**

The following example shows how to create a BGP peer-group with any local interface. If the local interface doesn't exist, the system will create it first before creating the peer-group.

```

# The API:
/api/network/ip/bgp/peer-groups

# The call:
curl -X POST "https://<mgmt-ip>/api/network/bgp/peer-
groups?return_records=true" -d'{"name": "newPg1", "ipspace.name":"Default",
"local": {"interface": {"name": "newlif"}, "ip": {"address": "9.9.9.9",
"netmask": "24"}, "port": {"name": "e0f", "node": {"name": "node1"}}, "peer.address": "10.10.10.10"}'

# The response:
{
  "num_records": 1,
  "records": [
    {
      "uuid": "c292f069-8872-11e9-a3a6-005056bb81a4",
      "name": "newPg1",
      "ipspace": {
        "name": "Default"
      },
      "local": {
        "interface": {
          "name": "newlif"
        },
        "port": {
          "name": "e0f",
          "node": {
            "name": "node1"
          }
        }
      },
      "peer": {
        "address": "10.10.10.10"
      },
      "_links": {
        "self": {
          "href": "/api/network/ip/bgp/peer-groups/c292f069-8872-11e9-a3a6-
005056bb81a4"
        }
      }
    }
  ]
}

```

## Updating BGP peer-groups

The BGP peer-groups PATCH API is used to update attributes of a peer-group.

## Examples

### Updating the peer router address

The following example shows how the PATCH request changes the peer router IP address.

```
# The API:  
/api/network/ip/bgp/peer-groups/{uuid}  
  
# The call:  
curl -X PATCH "https://<mgmt-ip>/api/network/bgp/peer-groups/80d271c9-  
1f43-11e9-803e-005056a7646a" -H "accept: application/hal+json" -d  
'{"peer.address": "10.10.10.20"}'  
{  
}
```

### Updating the peer-group to a new name

The following example shows how the PATCH request renames the peer-group.

```
# The API:  
/api/network/ip/bgp/peer-groups/{uuid}  
  
# The call:  
curl -X PATCH "https://<mgmt-ip>/api/network/bgp/peer-groups/80d271c9-  
1f43-11e9-803e-005056a7646a" -H "accept: application/hal+json" -d  
'{"name": "NewName"}'  
{  
}
```

## Deleting BGP peer-groups

The BGP peer-groups DELETE API is used to delete an BGP peer-group.

## Example

### Deleting a BGP peer-group

The following DELETE request deletes a BGP peer-group.

```
# The API:  
/api/network/ip/bgp/peer-group/{uuid}  
  
# The call:  
curl -X DELETE "https://<mgmt-ip>/api/network/ip/bgp/peer-groups/80d271c9-  
1f43-11e9-803e-005056a7646a"  
{  
}
```

## Retrieve all BGP peer group details for VIP

GET /network/ip/bgp/peer-groups

Retrieves the details of all BGP peer groups for VIP.

### Related ONTAP Commands

- `network bgp peer-group show`

### Learn more

- [DOC /network/ip/bgp/peer-groups](#)

### Parameters

Name	Type	In	Required	Description
name	string	query	False	Filter by name
peer.asn	integer	query	False	Filter by peer.asn
peer.address	string	query	False	Filter by peer.address
state	string	query	False	Filter by state
ipspace.uuid	string	query	False	Filter by ipspace.uuid

Name	Type	In	Required	Description
ipspace.name	string	query	False	Filter by ipspace.name
local.interface.name	string	query	False	Filter by local.interface.name
local.interface.ip.address	string	query	False	Filter by local.interface.ip.address
local.interface.uuid	string	query	False	Filter by local.interface.uuid
local.port.name	string	query	False	Filter by local.port.name
local.port.node.name	string	query	False	Filter by local.port.node.name
local.port.uuid	string	query	False	Filter by local.port.uuid
uuid	string	query	False	Filter by uuid
fields	array[string]	query	False	Specify the fields to return.
max_records	integer	query	False	Limit the number of records returned.
return_records	boolean	query	False	The default is true for GET calls. When set to false, only the number of records is returned.

Name	Type	In	Required	Description
return_timeout	integer	query	False	The number of seconds to allow the call to execute before returning. When iterating over a collection, the default is 15 seconds. ONTAP returns earlier if either max records or the end of the collection is reached.
order_by	array[string]	query	False	Order results by specified fields and optional [asc

## Response

Status: 200, Ok

Name	Type	Description
_links	<a href="#">_links</a>	
num_records	integer	
records	array[ <a href="#">bgp_peer_group</a> ]	

## Example response

```
{  
    "_links": {  
        "next": {  
            "href": "/api/resourcelink"  
        },  
        "self": {  
            "href": "/api/resourcelink"  
        }  
    },  
    "num_records": 1,  
    "records": {  
        "ipspace": {  
            "_links": {  
                "self": {  
                    "href": "/api/resourcelink"  
                }  
            },  
            "name": "exchange",  
            "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
        },  
        "local": {  
            "interface": {  
                "_links": {  
                    "self": {  
                        "href": "/api/resourcelink"  
                    }  
                },  
                "ip": {  
                    "address": "10.10.10.7"  
                },  
                "name": "lif1",  
                "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
            },  
            "ip": {  
                "address": "10.10.10.7",  
                "netmask": "24"  
            },  
            "port": {  
                "_links": {  
                    "self": {  
                        "href": "/api/resourcelink"  
                    }  
                },  
                "name": "elb",  
                "port": 80  
            }  
        }  
    }  
}
```

```

    "node": {
        "name": "node1"
    },
    "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"
}
},
"name": "bgpv4peer",
"peer": {
    "address": "10.10.10.7"
},
"state": "up",
"uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"
}
}

```

## Error

Status: Default, Error

Name	Type	Description
error	error	

## Example error

```

{
    "error": {
        "arguments": {
            "code": "string",
            "message": "string"
        },
        "code": "4",
        "message": "entry doesn't exist",
        "target": "uuid"
    }
}

```

## Definitions

## See Definitions

href

Name	Type	Description
href	string	

\_links

Name	Type	Description
next	href	
self	href	

\_links

Name	Type	Description
self	href	

ipspace

Either the UUID or name is supplied on input.

Name	Type	Description
_links	_links	
name	string	IPspace name
uuid	string	IPspace UUID

ip

IP information

Name	Type	Description
address	string	IPv4 or IPv6 address

interface

Name	Type	Description
_links	_links	
ip	ip	IP information
name	string	The name of the interface.

Name	Type	Description
uuid	string	The UUID that uniquely identifies the interface.

## ip

IP information to create a new interface.

Name	Type	Description
address	string	IPv4 or IPv6 address
netmask	string	Input as netmask length (16) or IPv4 mask (255.255.0.0). For IPv6, you must set the netmask length. The default value is 64. Output is always netmask length.

## node

Name	Type	Description
name	string	Name of node on which the port is located.

## port

Name	Type	Description
_links	<a href="#">_links</a>	
name	string	
node	<a href="#">node</a>	
uuid	string	

## local

Information describing the local interface that is being used to peer with a router using BGP. On a POST operation, an existing BGP interface is used by specifying the interface, or create a new one by specifying the port and IP address.

Name	Type	Description
interface	<a href="#">interface</a>	
ip	<a href="#">ip</a>	IP information to create a new interface.
port	<a href="#">port</a>	

## peer

Information describing the router to peer with

Name	Type	Description
address	string	Peer router address
asn	integer	Autonomous system number of peer

## bgp\_peer\_group

A BGP peer group between a local network interface and a router, for the purpose of announcing VIP interface locations for SVMs in this IPspace.

Name	Type	Description
ipspace	ipspace	Either the UUID or name is supplied on input.
local	local	Information describing the local interface that is being used to peer with a router using BGP. On a POST operation, an existing BGP interface is used by specifying the interface, or create a new one by specifying the port and IP address.
name	string	Name of the peer group
peer	peer	Information describing the router to peer with
state	string	State of the peer group
uuid	string	UUID of the peer group

## error\_arguments

Name	Type	Description
code	string	Argument code
message	string	Message argument

## error

Name	Type	Description
arguments	array[error_arguments]	Message arguments
code	string	Error code
message	string	Error message
target	string	The target parameter that caused the error.

## Create a new BGP peer group for VIP

POST /network/ip/bgp/peer-groups

Creates a new BGP peer group for VIP. Multipath-routing is turned on cluster-wide automatically if the peer group being created results in multiple paths being available for an existing or future VIP interface.

### Required properties

- name - Name of the peer-group to create.
- ipspace.name or ipspace.uuid
  - Required with local.interface.name to identify a local interface
  - Optional when local.interface.uuid is specified
- local.interface.uuid or local.interface.name
  - Required when specifying an existing local interface.
- local.interface.name, local.ip and local.port
  - Required to create a new local interface.
- peer.address - IP address of the peer router

### Related ONTAP commands

- `network bgp peer-group create`

### Learn more

- [DOC /network/ip/bgp/peer-groups](#)

### Parameters

Name	Type	In	Required	Description
return_records	boolean	query	False	The default is false. If set to true, the records are returned.

## Request Body

Name	Type	Description
ipspace	<a href="#">ipspace</a>	Either the UUID or name is supplied on input.
local	<a href="#">local</a>	Information describing the local interface that is being used to peer with a router using BGP. On a POST operation, an existing BGP interface is used by specifying the interface, or create a new one by specifying the port and IP address.
name	string	Name of the peer group
peer	<a href="#">peer</a>	Information describing the router to peer with
state	string	State of the peer group
uuid	string	UUID of the peer group

## Example request

```
{  
    "ipspace": {  
        "_links": {  
            "self": {  
                "href": "/api/resourcelink"  
            }  
        },  
        "name": "exchange",  
        "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
    },  
    "local": {  
        "interface": {  
            "_links": {  
                "self": {  
                    "href": "/api/resourcelink"  
                }  
            },  
            "ip": {  
                "address": "10.10.10.7"  
            },  
            "name": "lif1",  
            "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
        },  
        "ip": {  
            "address": "10.10.10.7",  
            "netmask": "24"  
        },  
        "port": {  
            "_links": {  
                "self": {  
                    "href": "/api/resourcelink"  
                }  
            },  
            "name": "elb",  
            "node": {  
                "name": "node1"  
            },  
            "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
        },  
        "name": "bgpv4peer",  
        "peer": {  
            "address": "10.10.10.7"  
        },  
    },  
}
```

```

    "state": "up",
    "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"
}

```

## Response

Status: 201, Created

## Error

Status: Default

### ONTAP Error Response Codes

Error Code	Description
1376963	Duplicate IP address is specified.
1966133	Netmask and address pair result in a network address.
1966267	IPv6 addresses must have a prefix length of 64.
1966269	IPv4 addresses must have a netmask length between 1 and 32.
1967082	IPspace name and UUID must match if both are given.
1967155	The specified local.port.name does not match the location.port.name for the specified local.interface.
1967156	The specified local.port.node.name does not match the location.port.node.name for the specified local.interface.
1967157	The specified local.port.uuid does not match the location.port.uuid for the specified local.interface.
1967158	The specified local.interface.name does not exist in the associated IPspace. local.ip.address and local.ip.netmask are required to create a new LIF.
1967159	local.interface does not support management-bgp service.
1967160	The specified local.interface.name does not match the specified interface name of local.interface.uuid.
1967161	The specified local.interface.uuid does not exist in the specified IPspace.

Error Code	Description
1967162	Either local.interface or local.ip and local.port are required to specify a local LIF.
1967163	The specified local.port.name does not match the specified port name of local.port.uuid.
1967164	The specified local.port.node.name does not match the specified node name of local.port.uuid.
1967165	The specified local.port does not exist.
1967166	ipspace.uuid or ipspace.name must be provided with local.interface.name together to identify a LIF.
1967167	Internal error. Failed to update BGP configuration for node. Retry the command, if necessary.
1967168	Internal error. Failed to create a VIP port for IPspace on node. Retry the command, if necessary.
1967169	Internal error. BGP configuration changed during the operation. Retry the command, if necessary.
1967170	Internal error. VIP port configuration changed during the operation. Retry the command, if necessary.
1967171	Internal error. Fail to access or update BGP peer group. Retry the command, if necessary.
1967172	Peer group could not be updated because IPspace does not exist. Retry the command, if necessary.
1967173	The specified local.ip.address does not match the address for the specified local.interface.
1967174	The specified local.ip.netmask does not match the netmask for the specified local.interface.
1967176	The specified local.interface.name does not exist in the associated IPspace. local.port.name, local.port.node.name, or local.port.uuid is required to create a new LIF.
1967177	Internal error. Failed to access the local interface. Retry the command, if necessary.
1967178	The IPv6 address specified with local.ip.address is not supported because it is link-local, multicast, v4-compatible, v4-mapped, loopback or "::".
1967179	The IPv4 address specified with local.ip.address is not supported because it is multicast, loopback or 0.0.0.0.
53281985	Internal error. Failed to update BGP peer group because BGP LIF moved during the operation. Wait a few minutes and try the command again.

Error Code	Description
53282006	BGP peer group could not be updated to use a peer address because the value provided is not a valid peer address. If necessary, try the command again with a routable host address.
53282007	BGP peer group could not be updated to use a peer address because the address represents a different address family to the address of the associated BGP LIF. If necessary, try the command again with a matching address family.
53282018	Failed to create BGP peer group because an existing peer group has already established a BGP session between LIF and peer address. If necessary, try the command again with a different BGP LIF or a different peer address.

Name	Type	Description
error	error	

### Example error

```
{
  "error": {
    "arguments": {
      "code": "string",
      "message": "string"
    },
    "code": "4",
    "message": "entry doesn't exist",
    "target": "uuid"
  }
}
```

### Definitions

## See Definitions

href

Name	Type	Description
href	string	

\_links

Name	Type	Description
self	href	

ipspace

Either the UUID or name is supplied on input.

Name	Type	Description
_links	_links	
name	string	IPspace name
uuid	string	IPspace UUID

ip

IP information

Name	Type	Description
address	string	IPv4 or IPv6 address

interface

Name	Type	Description
_links	_links	
ip	ip	IP information
name	string	The name of the interface.
uuid	string	The UUID that uniquely identifies the interface.

ip

IP information to create a new interface.

Name	Type	Description
address	string	IPv4 or IPv6 address
netmask	string	Input as netmask length (16) or IPv4 mask (255.255.0.0). For IPv6, you must set the netmask length. The default value is 64. Output is always netmask length.

node

Name	Type	Description
name	string	Name of node on which the port is located.

port

Name	Type	Description
_links	<a href="#">_links</a>	
name	string	
node	<a href="#">node</a>	
uuid	string	

local

Information describing the local interface that is being used to peer with a router using BGP. On a POST operation, an existing BGP interface is used by specifying the interface, or create a new one by specifying the port and IP address.

Name	Type	Description
interface	<a href="#">interface</a>	
ip	<a href="#">ip</a>	IP information to create a new interface.
port	<a href="#">port</a>	

peer

Information describing the router to peer with

Name	Type	Description
address	string	Peer router address

Name	Type	Description
asn	integer	Autonomous system number of peer

## bgp\_peer\_group

A BGP peer group between a local network interface and a router, for the purpose of announcing VIP interface locations for SVMs in this IPspace.

Name	Type	Description
ipspace	<a href="#">ipspace</a>	Either the UUID or name is supplied on input.
local	<a href="#">local</a>	Information describing the local interface that is being used to peer with a router using BGP. On a POST operation, an existing BGP interface is used by specifying the interface, or create a new one by specifying the port and IP address.
name	string	Name of the peer group
peer	<a href="#">peer</a>	Information describing the router to peer with
state	string	State of the peer group
uuid	string	UUID of the peer group

## error\_arguments

Name	Type	Description
code	string	Argument code
message	string	Message argument

## error

Name	Type	Description
arguments	<a href="#">array[error_arguments]</a>	Message arguments
code	string	Error code

Name	Type	Description
message	string	Error message
target	string	The target parameter that caused the error.

## Delete a BGP peer group for VIP

DELETE /network/ip/bgp/peer-groups/{uuid}

Deletes a BGP peer group for VIP.

### Related ONTAP commands

- `network bgp peer-group delete`

### Learn more

- [DOC /network/ip/bgp/peer-groups](#)

### Parameters

Name	Type	In	Required	Description
uuid	string	path	True	

### Response

Status: 200, Ok

### Error

Status: Default

### ONTAP Error Response Codes

Error Code	Description
53282019	Internal error. Failed to remove BGP peer group on node. Wait a few minutes and try the command again.

Name	Type	Description
error	error	

## Example error

```
{  
  "error": {  
    "arguments": {  
      "code": "string",  
      "message": "string"  
    },  
    "code": "4",  
    "message": "entry doesn't exist",  
    "target": "uuid"  
  }  
}
```

## Definitions

### See Definitions

#### error\_arguments

Name	Type	Description
code	string	Argument code
message	string	Message argument

#### error

Name	Type	Description
arguments	array[error_arguments]	Message arguments
code	string	Error code
message	string	Error message
target	string	The target parameter that caused the error.

## Retrieve details of a BGP peer group for VIP

GET /network/ip/bgp/peer-groups/{uuid}

Retrieves details of a BGP peer group for VIP.

## Related ONTAP commands

- `network bgp peer-group show`

## Learn more

- [DOC /network/ip/bgp/peer-groups](#)

## Parameters

Name	Type	In	Required	Description
uuid	string	path	True	UUID of the peer group
fields	array[string]	query	False	Specify the fields to return.

## Response

Status: 200, Ok

Name	Type	Description
ipspace	<a href="#">ipspace</a>	Either the UUID or name is supplied on input.
local	<a href="#">local</a>	Information describing the local interface that is being used to peer with a router using BGP. On a POST operation, an existing BGP interface is used by specifying the interface, or create a new one by specifying the port and IP address.
name	string	Name of the peer group
peer	<a href="#">peer</a>	Information describing the router to peer with
state	string	State of the peer group
uuid	string	UUID of the peer group

## Example response

```
{  
    "ipspace": {  
        "_links": {  
            "self": {  
                "href": "/api/resourcelink"  
            }  
        },  
        "name": "exchange",  
        "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
    },  
    "local": {  
        "interface": {  
            "_links": {  
                "self": {  
                    "href": "/api/resourcelink"  
                }  
            },  
            "ip": {  
                "address": "10.10.10.7"  
            },  
            "name": "lif1",  
            "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
        },  
        "ip": {  
            "address": "10.10.10.7",  
            "netmask": "24"  
        },  
        "port": {  
            "_links": {  
                "self": {  
                    "href": "/api/resourcelink"  
                }  
            },  
            "name": "elb",  
            "node": {  
                "name": "node1"  
            },  
            "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
        },  
        "name": "bgpv4peer",  
        "peer": {  
            "address": "10.10.10.7"  
        },  
    }  
}
```

```
"state": "up",
"uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"
}
```

## Error

Status: Default, Error

Name	Type	Description
error	error	

## Example error

```
{
  "error": {
    "arguments": {
      "code": "string",
      "message": "string"
    },
    "code": "4",
    "message": "entry doesn't exist",
    "target": "uuid"
  }
}
```

## Definitions

## See Definitions

href

Name	Type	Description
href	string	

\_links

Name	Type	Description
self	href	

ipspace

Either the UUID or name is supplied on input.

Name	Type	Description
_links	_links	
name	string	IPspace name
uuid	string	IPspace UUID

ip

IP information

Name	Type	Description
address	string	IPv4 or IPv6 address

interface

Name	Type	Description
_links	_links	
ip	ip	IP information
name	string	The name of the interface.
uuid	string	The UUID that uniquely identifies the interface.

ip

IP information to create a new interface.

Name	Type	Description
address	string	IPv4 or IPv6 address
netmask	string	Input as netmask length (16) or IPv4 mask (255.255.0.0). For IPv6, you must set the netmask length. The default value is 64. Output is always netmask length.

node

Name	Type	Description
name	string	Name of node on which the port is located.

port

Name	Type	Description
_links	<a href="#">_links</a>	
name	string	
node	<a href="#">node</a>	
uuid	string	

local

Information describing the local interface that is being used to peer with a router using BGP. On a POST operation, an existing BGP interface is used by specifying the interface, or create a new one by specifying the port and IP address.

Name	Type	Description
interface	<a href="#">interface</a>	
ip	<a href="#">ip</a>	IP information to create a new interface.
port	<a href="#">port</a>	

peer

Information describing the router to peer with

Name	Type	Description
address	string	Peer router address

Name	Type	Description
asn	integer	Autonomous system number of peer

#### error\_arguments

Name	Type	Description
code	string	Argument code
message	string	Message argument

#### error

Name	Type	Description
arguments	array[error_arguments]	Message arguments
code	string	Error code
message	string	Error message
target	string	The target parameter that caused the error.

## Update a BGP peer group for VIP

PATCH /network/ip/bgp/peer-groups/{uuid}

Updates a BGP peer group for VIP.

### Related ONTAP commands

- `network bgp peer-group modify`
- `network bgp peer-group rename`

### Learn more

- [DOC /network/ip/bgp/peer-groups](#)

### Parameters

Name	Type	In	Required	Description
uuid	string	path	True	UUID of the peer group

## Request Body

Name	Type	Description
ipspace	<a href="#">ipspace</a>	Either the UUID or name is supplied on input.
local	<a href="#">local</a>	Information describing the local interface that is being used to peer with a router using BGP. On a POST operation, an existing BGP interface is used by specifying the interface, or create a new one by specifying the port and IP address.
name	string	Name of the peer group
peer	<a href="#">peer</a>	Information describing the router to peer with
state	string	State of the peer group
uuid	string	UUID of the peer group

## Example request

```
{  
    "ipspace": {  
        "_links": {  
            "self": {  
                "href": "/api/resourcelink"  
            }  
        },  
        "name": "exchange",  
        "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
    },  
    "local": {  
        "interface": {  
            "_links": {  
                "self": {  
                    "href": "/api/resourcelink"  
                }  
            },  
            "ip": {  
                "address": "10.10.10.7"  
            },  
            "name": "lif1",  
            "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
        },  
        "ip": {  
            "address": "10.10.10.7",  
            "netmask": "24"  
        },  
        "port": {  
            "_links": {  
                "self": {  
                    "href": "/api/resourcelink"  
                }  
            },  
            "name": "elb",  
            "node": {  
                "name": "node1"  
            },  
            "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
        },  
        "name": "bgpv4peer",  
        "peer": {  
            "address": "10.10.10.7"  
        },  
    },  
}
```

```
"state": "up",
"uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"
}
```

## Response

Status: 200, Ok

## Error

Status: Default

### ONTAP Error Response Codes

Error Code	Description
1967171	Internal error. Fail to access or update BGP peer group. Retry the command, if necessary.
53281998	Failed to rename the BGP peer group because that name is already assigned to a different peer group in the IPspace.
53282006	BGP peer group could not be updated to use a peer address because the value provided is not a valid peer address. If necessary, try the command again with a routable host address.
53282007	BGP peer group could not be updated to use a peer address because the address represents a different address family to the address of the associated BGP LIF. If necessary, try the command again with a matching address family.
53282018	Failed to create BGP peer group because an existing peer group has already established a BGP session between LIF and peer address. If necessary, try the command again with a different BGP LIF or a different peer address.

Name	Type	Description
error	error	

## Example error

```
{  
  "error": {  
    "arguments": {  
      "code": "string",  
      "message": "string"  
    },  
    "code": "4",  
    "message": "entry doesn't exist",  
    "target": "uuid"  
  }  
}
```

## Definitions

## See Definitions

href

Name	Type	Description
href	string	

\_links

Name	Type	Description
self	href	

ipspace

Either the UUID or name is supplied on input.

Name	Type	Description
_links	_links	
name	string	IPspace name
uuid	string	IPspace UUID

ip

IP information

Name	Type	Description
address	string	IPv4 or IPv6 address

interface

Name	Type	Description
_links	_links	
ip	ip	IP information
name	string	The name of the interface.
uuid	string	The UUID that uniquely identifies the interface.

ip

IP information to create a new interface.

Name	Type	Description
address	string	IPv4 or IPv6 address
netmask	string	Input as netmask length (16) or IPv4 mask (255.255.0.0). For IPv6, you must set the netmask length. The default value is 64. Output is always netmask length.

node

Name	Type	Description
name	string	Name of node on which the port is located.

port

Name	Type	Description
_links	<a href="#">_links</a>	
name	string	
node	<a href="#">node</a>	
uuid	string	

local

Information describing the local interface that is being used to peer with a router using BGP. On a POST operation, an existing BGP interface is used by specifying the interface, or create a new one by specifying the port and IP address.

Name	Type	Description
interface	<a href="#">interface</a>	
ip	<a href="#">ip</a>	IP information to create a new interface.
port	<a href="#">port</a>	

peer

Information describing the router to peer with

Name	Type	Description
address	string	Peer router address

Name	Type	Description
asn	integer	Autonomous system number of peer

### bgp\_peer\_group

A BGP peer group between a local network interface and a router, for the purpose of announcing VIP interface locations for SVMs in this IPspace.

Name	Type	Description
ipspace	<a href="#">ipspace</a>	Either the UUID or name is supplied on input.
local	<a href="#">local</a>	Information describing the local interface that is being used to peer with a router using BGP. On a POST operation, an existing BGP interface is used by specifying the interface, or create a new one by specifying the port and IP address.
name	string	Name of the peer group
peer	<a href="#">peer</a>	Information describing the router to peer with
state	string	State of the peer group
uuid	string	UUID of the peer group

### error\_arguments

Name	Type	Description
code	string	Argument code
message	string	Message argument

### error

Name	Type	Description
arguments	<a href="#">array[error_arguments]</a>	Message arguments
code	string	Error code

Name	Type	Description
message	string	Error message
target	string	The target parameter that caused the error.

# Manage network IP interfaces

## Network IP interfaces endpoint overview

## Overview

The following operations are supported:

- Creation: POST network/ip/interfaces
  - Collection Get: GET network/ip/interfaces
  - Instance Get: GET network/ip/interfaces/{uuid}
  - Instance Patch: PATCH network/ip/interfaces/{uuid}
  - Instance Delete: DELETE network/ip/interfaces/{uuid}

## Retrieving network interface information

The IP interfaces GET API retrieves and displays relevant information pertaining to the interfaces configured in the cluster. The response can contain a list of multiple interfaces or a specific interface. The fields returned in the response vary for different interfaces and configurations.

## Examples

## Retrieving all interfaces in the cluster

The following example shows the list of all interfaces configured in a cluster.

```
"name": "user-cluster-01_mgmt1",
"_links": {
  "self": {
    "href": "/api/network/ip/interfaces/14531286-59fc-11e8-ba55-005056b4340f"
  }
},
{
  "uuid": "145318ba-59fc-11e8-ba55-005056b4340f",
  "name": "user-cluster-01_clus2",
  "_links": {
    "self": {
      "href": "/api/network/ip/interfaces/145318ba-59fc-11e8-ba55-005056b4340f"
    }
  }
},
{
  "uuid": "14531e45-59fc-11e8-ba55-005056b4340f",
  "name": "user-cluster-01_clus1",
  "_links": {
    "self": {
      "href": "/api/network/ip/interfaces/14531e45-59fc-11e8-ba55-005056b4340f"
    }
  }
},
{
  "uuid": "245979de-59fc-11e8-ba55-005056b4340f",
  "name": "cluster_mgmt",
  "_links": {
    "self": {
      "href": "/api/network/ip/interfaces/245979de-59fc-11e8-ba55-005056b4340f"
    }
  }
},
{
  "uuid": "c670707c-5a11-11e8-8fcb-005056b4340f",
  "name": "lif1",
  "_links": {
    "self": {
      "href": "/api/network/ip/interfaces/c670707c-5a11-11e8-8fcb-005056b4340f"
    }
  }
}
```

```

        }
    }
],
"num_records": 5,
"_links": {
    "self": {
        "href": "/api/network/ip/interfaces"
    }
}
}
}

```

### Retrieving a specific Cluster-scoped interface

The following example shows the response when a specific Cluster-scoped interface is requested. The system returns an error when there is no interface with the requested UUID. SVM information is not returned for Cluster-scoped interfaces.

```

# The API:
/api/network/ip/interfaces/{uuid}

# The call:
curl -X GET "https://<mgmt-ip>/api/network/ip/interfaces/245979de-59fc-
11e8-ba55-005056b4340f" -H "accept: application/hal+json"

# The response:
{
  "uuid": "245979de-59fc-11e8-ba55-005056b4340f",
  "name": "cluster_mgmt",
  "ip": {
    "address": "10.63.41.6",
    "netmask": "18",
    "family": "ipv4",
  },
  "enabled": true,
  "state": "up",
  "scope": "cluster",
  "ipspace": {
    "uuid": "114ecfb5-59fc-11e8-ba55-005056b4340f",
    "name": "Default",
    "_links": {
      "self": {
        "href": "/api/network/ipspaces/114ecfb5-59fc-11e8-ba55-
005056b4340f"
      }
    }
  }
}
}

```

```

        }
    }
},
"services": [
    "management_core",
    "management_autosupport",
    "management_access"
],
"location": {
    "is_home": true,
    "auto_revert": false,
    "failover": "broadcast_domain_only",
    "node": {
        "uuid": "c1db2904-1396-11e9-bb7d-005056acfcb",
        "name": "user-cluster-01-a",
        "_links": {
            "self": {
                "href": "/api/cluster/nodes/c1db2904-1396-11e9-bb7d-005056acfcb"
            }
        }
    },
    "port": {
        "uuid": "c84d5337-1397-11e9-87c2-005056acfcb",
        "name": "e0d",
        "node": {
            "name": "user-cluster-01-a"
        },
        "_links": {
            "self": {
                "href": "/api/network/ethernet/ports/c84d5337-1397-11e9-87c2-005056acfcb"
            }
        }
    },
    "home_node": {
        "uuid": "c1db2904-1396-11e9-bb7d-005056acfcb",
        "name": "user-cluster-01-a",
        "_links": {
            "self": {
                "href": "/api/cluster/nodes/c1db2904-1396-11e9-bb7d-005056acfcb"
            }
        }
    },
    "home_port": {
        "uuid": "c84d5337-1397-11e9-87c2-005056acfcb",
        "name": "e0d",
    }
}

```

```

"node": {
    "name": "user-cluster-01-a"
},
"_links": {
    "self": {
        "href": "/api/network/ethernet/ports/c84d5337-1397-11e9-87c2-
005056acfcb"
    }
}
},
"service_policy": {
    "uuid": "9e0f4151-141b-11e9-851e-005056ac1ce0",
    "name": "default-management"
},
"vip": false,
"_links": {
    "self": {
        "href": "/api/network/ip/interfaces/245979de-59fc-11e8-ba55-
005056b4340f"
    }
}
}

```

#### Retrieving a specific SVM-scoped interface using a filter

The following example shows the response when a specific SVM-scoped interface is requested. The SVM object is only included for SVM-scoped interfaces.

```

# The API:
/api/network/ip/interfaces

# The call:
curl -X GET "https://<mgmt-
ip>/api/network/ip/interfaces?name=lif1&fields=*" -H "accept:
application/hal+json"

# The response:
{
"records": [
{
    "uuid": "c670707c-5a11-11e8-8fcb-005056b4340f",
    "name": "lif1",

```

```

"ip": {
    "address": "10.10.10.11",
    "netmask": "24",
    "family": "ipv4",
},
"enabled": true,
"state": "up",
"scope": "svm",
"ipspace": {
    "uuid": "114ecfb5-59fc-11e8-ba55-005056b4340f",
    "name": "Default",
    "_links": {
        "self": {
            "href": "/api/network/ipspaces/114ecfb5-59fc-11e8-ba55-005056b4340f"
        }
    }
},
"svm": {
    "uuid": "c2134665-5a11-11e8-8fcb-005056b4340f",
    "name": "user_vs0",
    "_links": {
        "self": {
            "href": "/api/svm/svms/c2134665-5a11-11e8-8fcb-005056b4340f"
        }
    }
},
"services": [
    "data_core",
    "data_nfs",
    "data_cifs",
    "data_flexcache"
],
"location": {
    "is_home": true,
    "auto_revert": false,
    "failover": "broadcast_domain_only",
    "node": {
        "uuid": "c1db2904-1396-11e9-bb7d-005056acfccb",
        "name": "user-cluster-01-a",
        "_links": {
            "self": {
                "href": "/api/cluster/nodes/c1db2904-1396-11e9-bb7d-005056acfccb"
            }
        }
    }
}

```

```

        },
        "port": {
            "uuid": "c84d5337-1397-11e9-87c2-005056acfcb",
            "name": "e0d",
            "node": {
                "name": "user-cluster-01-a"
            },
            "_links": {
                "self": {
                    "href": "/api/network/ethernet/ports/c84d5337-1397-11e9-87c2-
005056acfcb"
                }
            }
        },
        "home_node": {
            "uuid": "c1db2904-1396-11e9-bb7d-005056acfcb",
            "name": "user-cluster-01-a",
            "_links": {
                "self": {
                    "href": "/api/cluster/nodes/c1db2904-1396-11e9-bb7d-
005056acfcb"
                }
            }
        },
        "home_port": {
            "uuid": "c84d5337-1397-11e9-87c2-005056acfcb",
            "name": "e0d",
            "node": {
                "name": "user-cluster-01-a"
            },
            "_links": {
                "self": {
                    "href": "/api/network/ethernet/ports/c84d5337-1397-11e9-87c2-
005056acfcb"
                }
            }
        },
        "service_policy": {
            "uuid": "9e53525f-141b-11e9-851e-005056ac1ce0",
            "name": "default-data-files"
        },
        "vip": false,
        "_links": {
            "self": {
                "href": "/api/network/ip/interfaces/c670707c-5a11-11e8-8fcb-

```

```

005056b4340f"
    }
}
]
,
"num_records": 1,
"_links": {
  "self": {
    "href": "/api/network/ip/interfaces?name=lif1&fields=*&limit=1"
  }
}
}

```

#### Retrieving specific fields and limiting the output using filters

The following example shows the response when a filter is applied (location.home\_port.name=e0a) and only certain fields are requested. Filtered fields are in the output in addition to the default fields and requested fields.

```

# The API:
/api/network/ip/interfaces

# The call:
curl -X GET "https://<mgmt-
ip>/api/network/ip/interfaces?location.home_port.name=e0a&fields=location.
home_node.name,service_policy.name,ip.address(enabled" -H "accept:
application/hal+json"

# The response:
{
"records": [
{
  "uuid": "1d1c9dc8-4f17-11e9-9553-005056ac918a",
  "name": "user-cluster-01-a_clus1",
  "ip": {
    "address": "192.168.170.24"
  },
  "enabled": true,
  "location": {
    "home_node": {
      "name": "user-cluster-01-a"
    },
    "home_port": {
      "name": "e0a"
    }
  }
}
]
```

```

        "name": "e0a"
    }
},
"service_policy": {
    "name": "default-cluster"
},
"_links": {
    "self": {
        "href": "/api/network/ip/interfaces/1d1c9dc8-4f17-11e9-9553-
005056ac918a"
    }
}
},
{
    "uuid": "d07782c1-4f16-11e9-86e7-005056ace7ee",
    "name": "user-cluster-01-b_clus1",
    "ip": {
        "address": "192.168.170.22"
    },
    "enabled": true,
    "location": {
        "home_node": {
            "name": "user-cluster-01-b"
        },
        "home_port": {
            "name": "e0a"
        }
    },
    "service_policy": {
        "name": "default-cluster"
    },
    "_links": {
        "self": {
            "href": "/api/network/ip/interfaces/d07782c1-4f16-11e9-86e7-
005056ace7ee"
        }
    }
}
],
"num_records": 2,
"_links": {
    "self": {
        "href": "
/api/network/ip/interfaces?location.home_port.name=e0a&fields=location.ho
me_node.name,service_policy.name,ip.address,enabled"
    }
}

```

```
}
```

```
}
```

## Creating IP interfaces

You can use the IP interfaces POST API to create IP interfaces as shown in the following examples.

## Examples

### Creating a Cluster-scoped IP interface using names

The following example shows the record returned after the creation of an IP interface on "e0d".

```
# The API:  
/api/network/ip/interfaces  
  
# The call:  
curl -X POST "https://<mgmt-  
ip>/api/network/ip/interfaces?return_records=true" -H "accept:  
application/hal+json" -d '{ "name": "cluster_mgmt", "ip": { "address":  
"10.63.41.6", "netmask": "18" }, "enabled": true, "scope": "cluster",  
"ipspace": { "name": "Default" }, "location": { "auto_revert": false,  
"failover": "broadcast_domain_only", "home_port": { "name": "e0d", "node":  
{ "name": "user-cluster-01-a" } } }, "service_policy": { "name": "default-  
management" } }'  
  
# The response:  
{  
  "num_records": 1,  
  "records": [  
    {  
      "uuid": "245979de-59fc-11e8-ba55-005056b4340f",  
      "name": "cluster_mgmt",  
      "ip": {  
        "address": "10.63.41.6",  
        "netmask": "18"  
      },  
      "enabled": true,  
      "scope": "cluster",  
      "ipspace": {  
        "name": "Default"  
      },  
    }  
  ]  
}
```

```

"location": {
    "auto_revert": false,
    "failover": "broadcast_domain_only",
    "home_port": {
        "name": "e0d",
        "node": {
            "name": "user-cluster-01-a"
        }
    },
},
"service_policy": {
    "name": "default-management"
},
"_links": {
    "self": {
        "href": "/api/network/ip/interfaces/245979de-59fc-11e8-ba55-
005056b4340f"
    }
}
}
]
}

```

### Creating a SVM-scoped IP interface using a mix of parameter types

The following example shows the record returned after the creation of a IP interface by specifying a broadcast domain as the location.

```

# The API:
/api/network/ip/interfaces

# The call:
curl -X POST "https://<mgmt-
ip>/api/network/ip/interfaces?return_records=true" -H "accept:
application/hal+json" -d '{ "name": "Data1", "ip": { "address":
"10.234.101.116", "netmask": "255.255.240.0" }, "enabled": true, "scope":
"svm", "svm": { "uuid": "137f3618-1e89-11e9-803e-005056a7646a" },
"location": { "auto_revert": true, "broadcast_domain": { "name": "Default" } },
"service_policy": { "name": "default-data-files" } }'

# The response:
{
"num_records": 1,

```

```

"records": [
  {
    "uuid": "80d271c9-1f43-11e9-803e-005056a7646a",
    "name": "Data1",
    "ip": {
      "address": "10.234.101.116",
      "netmask": "20"
    },
    "enabled": true,
    "scope": "svm",
    "svm": {
      "uuid": "137f3618-1e89-11e9-803e-005056a7646a",
      "name": "vs0",
      "_links": {
        "self": {
          "href": "/api/svm/svms/137f3618-1e89-11e9-803e-005056a7646a"
        }
      }
    },
    "location": {
      "auto_revert": true
    },
    "service_policy": {
      "name": "default-data-files"
    },
    "_links": {
      "self": {
        "href": "/api/network/ip/interfaces/80d271c9-1f43-11e9-803e-005056a7646a"
      }
    }
  }
]
}

```

#### **Creating a Cluster-scoped IP interface without specifying the scope parameter**

The following example shows the record returned after creating an IP interface on "e0d" without specifying the scope parameter. The scope is "cluster" if an "svm" is not specified.

```

# The API:
/api/network/ip/interfaces

```

```

# The call:
curl -X POST "https://<mgmt-
ip>/api/network/ip/interfaces?return_records=true" -H "accept:
application/hal+json" -d '{ "name": "cluster_mgmt", "ip": { "address":
"10.63.41.6", "netmask": "18" }, "enabled": true, "ipspace": { "name":
"Default" }, "location": { "auto_revert": false, "home_port": { "name":
"e0d", "node": { "name": "user-cluster-01-a" } } }, "service_policy": {
"name": "default-management" } }'

# The response:
{
  "num_records": 1,
  "records": [
    {
      "uuid": "245979de-59fc-11e8-ba55-005056b4340f",
      "name": "cluster_mgmt",
      "ip": {
        "address": "10.63.41.6",
        "netmask": "18"
      },
      "enabled": true,
      "scope": "cluster",
      "ipspace": {
        "name": "Default"
      },
      "location": {
        "auto_revert": false,
        "home_port": {
          "name": "e0d",
          "node": {
            "name": "user-cluster-01-a"
          }
        }
      },
      "service_policy": {
        "name": "default-management"
      },
      "_links": {
        "self": {
          "href": "/api/network/ip/interfaces/245979de-59fc-11e8-ba55-
005056b4340f"
        }
      }
    }
  ]
}

```

### Creating an SVM-scoped IP interface without specifying the scope parameter

The following example shows the record returned after creating an IP interface on "e0d" without specifying the scope parameter. The scope is "svm" if the "svm" field is specified.

```
# The API:  
/api/network/ip/interfaces  
  
# The call:  
curl -X POST "https://<mgmt-  
ip>/api/network/ip/interfaces?return_records=true" -H "accept:  
application/hal+json" -d '{ "name": "Data1", "ip": { "address":  
"10.234.101.116", "netmask": "255.255.240.0" }, "enabled": true, "svm": {  
"uuid": "137f3618-1e89-11e9-803e-005056a7646a" }, "location": {  
"auto_revert": true, "broadcast_domain": { "name": "Default" } },  
"service_policy": { "name": "default-data-files" } }'  
  
# The response:  
{  
  "num_records": 1,  
  "records": [  
    {  
      "uuid": "80d271c9-1f43-11e9-803e-005056a7646a",  
      "name": "Data1",  
      "ip": {  
        "address": "10.234.101.116",  
        "netmask": "20"  
      },  
      "enabled": true,  
      "scope": "svm",  
      "svm": {  
        "uuid": "137f3618-1e89-11e9-803e-005056a7646a",  
        "name": "vs0",  
        "_links": {  
          "self": {  
            "href": "/api/svms/137f3618-1e89-11e9-803e-005056a7646a"  
          }  
        }  
      },  
      "location": {  
        "auto_revert": true  
      },  
      "service_policy": {  
        "name": "default-data-files"  
      },  
    }  
  ]  
}
```

```
        "_links": {
            "self": {
                "href": "/api/network/ip/interfaces/80d271c9-1f43-11e9-803e-
005056a7646a"
            }
        }
    ]
}
```

## Updating IP interfaces

You can use the IP interfaces PATCH API to update the attributes of an IP interface.

## Examples

### Updating the auto revert flag of an IP interface

The following example shows how the PATCH request changes the auto revert flag to 'false'.

```
# The API:
/api/network/ip/interfaces/{uuid}

# The call:
curl -X PATCH "https://<mgmt-ip>/api/network/ip/interfaces/80d271c9-1f43-
11e9-803e-005056a7646a" -H "accept: application/hal+json" -d '{
"location": { "auto_revert": "false" } }'
{
```

### Updating the service policy of an IP interface

The following example shows how the PATCH request changes the service policy to 'default-management'.

```
# The API:  
/api/network/ip/interfaces/{uuid}  
  
# The call:  
curl -X PATCH "https://<mgmt-ip>/api/network/ip/interfaces/80d271c9-1f43-  
11e9-803e-005056a7646a" -H "accept: application/hal+json" -d '{  
"service_policy": "default-management" }'  
{  
}
```

## Deleting IP interfaces

You can use the IP interfaces DELETE API to delete an IP interface in the cluster.

### Example

#### Deleting an IP Interface

The following DELETE request deletes a network IP interface.

```
# The API:  
/api/network/ip/interfaces/{uuid}  
  
# The call:  
curl -X DELETE "https://<mgmt-ip>/api/network/ip/interfaces/80d271c9-1f43-  
11e9-803e-005056a7646a"  
{  
}
```

## Retrieve all IP interface details

GET /network/ip/interfaces

Retrieves the details of all IP interfaces.

### Related ONTAP Commands

- `network interface show`

## Learn more

- [DOC /network/ip/interfaces](#)

## Parameters

Name	Type	In	Required	Description
ip.netmask	string	query	False	Filter by ip.netmask
ip.address	string	query	False	Filter by ip.address
ip.family	string	query	False	Filter by ip.family
scope	string	query	False	Filter by scope
vip	boolean	query	False	Filter by vip
service_policy.name	string	query	False	Filter by service_policy.name
service_policy.uuid	string	query	False	Filter by service_policy.uuid
state	string	query	False	Filter by state
name	string	query	False	Filter by name
uuid	string	query	False	Filter by uuid
enabled	boolean	query	False	Filter by enabled
location.failover	string	query	False	Filter by location.failover
location.port.name	string	query	False	Filter by location.port.name
location.port.node.name	string	query	False	Filter by location.port.node.name
location.port.uuid	string	query	False	Filter by location.port.uuid
location.home_node.uuid	string	query	False	Filter by location.home_node.uuid

Name	Type	In	Required	Description
location.home_node.name	string	query	False	Filter by location.home_node.name
location.home_port.name	string	query	False	Filter by location.home_port.name
location.home_port.node.name	string	query	False	Filter by location.home_port.node.name
location.home_port.uuid	string	query	False	Filter by location.home_port.uuid
location.auto_revert	boolean	query	False	Filter by location.auto_revert
location.node.uuid	string	query	False	Filter by location.node.uuid
location.node.name	string	query	False	Filter by location.node.name
location.is_home	boolean	query	False	Filter by location.is_home
ipspace.uuid	string	query	False	Filter by ipspace.uuid
ipspace.name	string	query	False	Filter by ipspace.name
svm.uuid	string	query	False	Filter by svm.uuid
svm.name	string	query	False	Filter by svm.name
services	string	query	False	Filter by services
fields	array[string]	query	False	Specify the fields to return.
max_records	integer	query	False	Limit the number of records returned.

Name	Type	In	Required	Description
return_records	boolean	query	False	The default is true for GET calls. When set to false, only the number of records is returned.
return_timeout	integer	query	False	The number of seconds to allow the call to execute before returning. When iterating over a collection, the default is 15 seconds. ONTAP returns earlier if either max records or the end of the collection is reached.
order_by	array[string]	query	False	Order results by specified fields and optional [asc

## Response

Status: 200, Ok

Name	Type	Description
_links	<a href="#">_links</a>	
num_records	integer	
records	array[ <a href="#">ip_interface</a> ]	

## Example response

```
{  
    "_links": {  
        "next": {  
            "href": "/api/resourcelink"  
        },  
        "self": {  
            "href": "/api/resourcelink"  
        }  
    },  
    "num_records": 1,  
    "records": {  
        "_links": {  
            "self": {  
                "href": "/api/resourcelink"  
            }  
        },  
        "ip": {  
            "address": "10.10.10.7",  
            "family": "ipv4",  
            "netmask": "24"  
        },  
        "ipspace": {  
            "_links": {  
                "self": {  
                    "href": "/api/resourcelink"  
                }  
            },  
            "name": "exchange",  
            "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
        },  
        "location": {  
            "broadcast_domain": {  
                "_links": {  
                    "self": {  
                        "href": "/api/resourcelink"  
                    }  
                },  
                "name": "bd1",  
                "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
            },  
            "failover": "home_port_only",  
            "home_node": {  
                "_links": {  
                    "self": {  
                        "href": "/api/resourcelink"  
                    }  
                }  
            }  
        }  
    }  
}
```

```
        "href": "/api/resourcelink"
    }
},
"name": "node1",
"uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"
},
"home_port": {
    "_links": {
        "self": {
            "href": "/api/resourcelink"
        }
    },
    "name": "elb",
    "node": {
        "name": "node1"
    },
    "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"
},
"node": {
    "_links": {
        "self": {
            "href": "/api/resourcelink"
        }
    },
    "name": "node1",
    "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"
},
"port": {
    "_links": {
        "self": {
            "href": "/api/resourcelink"
        }
    },
    "name": "elb",
    "node": {
        "name": "node1"
    },
    "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"
},
},
"name": "dataLif1",
"scope": "svm",
"service_policy": {
    "_links": {
        "self": {
            "href": "/api/resourcelink"
        }
    }
}
```

```

        }
    },
    "name": "default-intercluster",
    "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"
},
"services": {
},
"state": "up",
"svm": {
    "_links": {
        "self": {
            "href": "/api/resourcelink"
        }
    },
    "name": "svml",
    "uuid": "02c9e252-41be-11e9-81d5-00a0986138f7"
},
"uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"
}
}

```

## Error

Status: Default, Error

Name	Type	Description
error	error	

## Example error

```
{
    "error": {
        "arguments": {
            "code": "string",
            "message": "string"
        },
        "code": "4",
        "message": "entry doesn't exist",
        "target": "uuid"
    }
}
```

## **Definitions**

## See Definitions

href

Name	Type	Description
href	string	

\_links

Name	Type	Description
next	href	
self	href	

\_links

Name	Type	Description
self	href	

ip\_info

IP information

Name	Type	Description
address	string	IPv4 or IPv6 address
family	string	IPv4 or IPv6
netmask	string	Input as netmask length (16) or IPv4 mask (255.255.0.0). For IPv6, you must set the netmask length. The default value is 64. Output is always netmask length.

ipspace

Either the UUID or name must be supplied on POST for cluster-scoped objects.

Name	Type	Description
_links	_links	
name	string	IPspace name
uuid	string	IPspace UUID

broadcast\_domain

Broadcast domain UUID along with a readable name.

Name	Type	Description
_links	<a href="#">_links</a>	
name	string	Name of the broadcast domain, scoped to its IPspace
uuid	string	Broadcast domain UUID

home\_node

Name	Type	Description
_links	<a href="#">_links</a>	
name	string	
uuid	string	

node

Name	Type	Description
name	string	Name of node on which the port is located.

home\_port

Port UUID along with readable names. Either the UUID or both names may be supplied on input.

Name	Type	Description
_links	<a href="#">_links</a>	
name	string	
node	<a href="#">node</a>	
uuid	string	

node

Name	Type	Description
_links	<a href="#">_links</a>	
name	string	
uuid	string	

port

Port UUID along with readable names. Either the UUID or both names may be supplied on input.

Name	Type	Description
_links	<a href="#">_links</a>	
name	string	
node	<a href="#">node</a>	
uuid	string	

## location

Current or home location can be modified. Specifying a port implies a node. Specifying a node allows an appropriate port to be automatically selected. Ports are not valid and not shown for VIP interfaces. For POST, broadcast\_domain can be specified alone or with home\_node.

Name	Type	Description
auto_revert	boolean	
broadcast_domain	<a href="#">broadcast_domain</a>	Broadcast domain UUID along with a readable name.
failover	string	Defines where an interface may failover.
home_node	<a href="#">home_node</a>	
home_port	<a href="#">home_port</a>	Port UUID along with readable names. Either the UUID or both names may be supplied on input.
is_home	boolean	
node	<a href="#">node</a>	
port	<a href="#">port</a>	Port UUID along with readable names. Either the UUID or both names may be supplied on input.

## service\_policy

Name	Type	Description
_links	<a href="#">_links</a>	
name	string	
uuid	string	

## svm

Applies only to SVM-scoped objects. Either the UUID or name must be supplied on POST.

Name	Type	Description
_links	<a href="#">_links</a>	
name	string	The name of the SVM.
uuid	string	The unique identifier of the SVM.

## ip\_interface

Name	Type	Description
_links	<a href="#">_links</a>	
enabled	boolean	The administrative state of the interface.
ip	<a href="#">ip_info</a>	IP information
ipspace	<a href="#">ipspace</a>	Either the UUID or name must be supplied on POST for cluster-scoped objects.
location	<a href="#">location</a>	Current or home location can be modified. Specifying a port implies a node. Specifying a node allows an appropriate port to be automatically selected. Ports are not valid and not shown for VIP interfaces. For POST, broadcast_domain can be specified alone or with home_node.
name	string	Interface name
scope	string	Set to "svm" for interfaces owned by an SVM. Otherwise, set to "cluster".
service_policy	<a href="#">service_policy</a>	
services	array[string]	The services associated with the interface.
state	string	The operational state of the interface.

Name	Type	Description
svm	svm	Applies only to SVM-scoped objects. Either the UUID or name must be supplied on POST.
uuid	string	The UUID that uniquely identifies the interface.
vip	boolean	True for a VIP interface, whose location is announced via BGP.

#### error\_arguments

Name	Type	Description
code	string	Argument code
message	string	Message argument

#### error

Name	Type	Description
arguments	array[error_arguments]	Message arguments
code	string	Error code
message	string	Error message
target	string	The target parameter that caused the error.

## Create a new cluster-scoped or SVM-scoped interface

POST /network/ip/interfaces

Creates a new Cluster-scoped or SVM-scoped interface.

### Required properties

- name - Name of the interface to create.
- ip.address - IP address for the interface.
- ip.netmask - IP subnet of the interface.
- ipspace.name or ipspace.uuid

- Required for Cluster-scoped interfaces.
- Optional for SVM-scoped interfaces.
- `svm.name` or `svm.uuid`
  - Required for an SVM-scoped interface.
  - Invalid for a Cluster-scoped interface.
- `location.home_port` or `location.home_node` or `location.broadcast_domain` - One of these properties must be set to a value to define where the interface will be located.

## Recommended property values

- `service_policy`
  - for SVM scoped interfaces
    - *default-data-files* for interfaces carrying file-oriented NAS data traffic
    - *default-data-blocks* for interfaces carrying block-oriented SAN data traffic
    - *default-management* for interfaces carrying SVM management requests
  - for Cluster scoped interfaces
    - *default-intercluster* for interfaces carrying cluster peering traffic
    - *default-management* for interfaces carrying system management requests
    - *default-route-announce* for interfaces carrying BGP peer connections

## Default property values

If not specified in POST, the following default property values are assigned:

- `scope`
  - *svm* if `svm` parameter is specified.
  - *cluster* if `svm` parameter is not specified
- `enabled` - *true*
- `location.auto_revert` - *true*
- `service_policy`
  - *default-data-files* if scope is `svm`
  - *default-management* if scope is `cluster` and IPspace is not Cluster
  - *default-cluster* if scope is `svm` and IPspace is Cluster
- `failover` - Selects the least restrictive failover policy supported by all the services in the service policy.

## Related ONTAP commands

- `network interface create`

## Learn more

- [DOC /network/ip/interfaces](#)

## Parameters

Name	Type	In	Required	Description
return_records	boolean	query	False	The default is false. If set to true, the records are returned.

## Request Body

Name	Type	Description
_links	<a href="#">_links</a>	
enabled	boolean	The administrative state of the interface.
ip	<a href="#">ip_info</a>	IP information
ipspace	<a href="#">ipspace</a>	Either the UUID or name must be supplied on POST for cluster-scoped objects.
location	<a href="#">location</a>	Current or home location can be modified. Specifying a port implies a node. Specifying a node allows an appropriate port to be automatically selected. Ports are not valid and not shown for VIP interfaces. For POST, broadcast_domain can be specified alone or with home_node.
name	string	Interface name
scope	string	Set to "svm" for interfaces owned by an SVM. Otherwise, set to "cluster".
service_policy	<a href="#">service_policy</a>	
services	array[string]	The services associated with the interface.
state	string	The operational state of the interface.

Name	Type	Description
svm	<a href="#">svm</a>	Applies only to SVM-scoped objects. Either the UUID or name must be supplied on POST.
uuid	string	The UUID that uniquely identifies the interface.
vip	boolean	True for a VIP interface, whose location is announced via BGP.

## Example request

```
{  
    "_links": {  
        "self": {  
            "href": "/api/resourcelink"  
        }  
    },  
    "ip": {  
        "address": "10.10.10.7",  
        "family": "ipv4",  
        "netmask": "24"  
    },  
    "ipspace": {  
        "_links": {  
            "self": {  
                "href": "/api/resourcelink"  
            }  
        },  
        "name": "exchange",  
        "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
    },  
    "location": {  
        "broadcast_domain": {  
            "_links": {  
                "self": {  
                    "href": "/api/resourcelink"  
                }  
            },  
            "name": "bd1",  
            "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
        },  
        "failover": "home_port_only",  
        "home_node": {  
            "_links": {  
                "self": {  
                    "href": "/api/resourcelink"  
                }  
            },  
            "name": "node1",  
            "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
        },  
        "home_port": {  
            "_links": {  
                "self": {  
                    "href": "/api/resourcelink"  
                }  
            }  
        }  
    }  
}
```

```
        }
    },
    "name": "elb",
    "node": {
        "name": "node1"
    },
    "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"
},
"node": {
    "_links": {
        "self": {
            "href": "/api/resourcelink"
        }
    },
    "name": "node1",
    "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"
},
"port": {
    "_links": {
        "self": {
            "href": "/api/resourcelink"
        }
    },
    "name": "elb",
    "node": {
        "name": "node1"
    },
    "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"
}
},
"name": "dataLif1",
"scope": "svm",
"service_policy": {
    "_links": {
        "self": {
            "href": "/api/resourcelink"
        }
    },
    "name": "default-intercluster",
    "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"
},
"services": {
},
"state": "up",
"svm": {
    "_links": {
```

```

    "self": {
        "href": "/api/resourcelink"
    },
    "name": "svm1",
    "uuid": "02c9e252-41be-11e9-81d5-00a0986138f7"
},
"uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"
}

```

## Response

Status: 201, Created

## Error

Status: Default

## ONTAP Error Response Codes

Error Code	Description
1376656	Cluster interfaces must be in the same subnet. Verify the address and netmask are set to the correct values.
1376963	Duplicate IP address.
1966138	The same IP address may not be used for both a mgmt interface and a gateway address.
1966140	An interface with the same name already exists.
1966987	The Vserver Broadcast-Domain Home-Node and Home-Port combination is not valid.
1967081	The specified SVM must exist in the specified IPspace.
1967082	The specified ipspace.name does not match the IPspace name of ipspace.uuid.
1967102	POST operation might have left configuration in an inconsistent state. Check the configuration.
1967106	The specified location.home_port.name does not match the specified port name of location.home_port.uuid.
1967107	The location.home_port.uuid specified is not valid.

Error Code	Description
1967108	The specified location.home_node.name does not match the node name of location.home_node.uuid.
1967109	The specified location.home_port.node.name does not match the node name of location.home_node.uuid.
1967110	The specified location.home_port.node.name does not match location.home_node.name.
1967111	Home node must be specified by at least one location.home_node, location.home_port, or location.broadcast_domain field.
1967112	The specified location.home_node.name does not match the node name of location.home_port.uuid.
1967120	The specified service_policy.name does not match the specified service policy name of service_policy.uuid.
1967121	Invalid service_policy.uuid specified.
1967122	The specified location.broadcast_domain.name does not match the specified broadcast domain name of location.broadcast_domain.uuid.
1967123	The specified IPspace does not match the IPspace name of location.broadcast_domain.uuid.
1967124	The location.broadcast_domain.uuid specified is not valid.
1967127	svm.uuid or svm.name must be provided if scope is "svm".
1967128	ipspace.uuid or ipspace.name must be provided if scope is "cluster".
1967129	The specified location.home_port.uuid is not valid.
1967130	The specified location.home_port.name is not valid.
1967131	The specified location.home_port.uuid and location.home_port.name are not valid.
1967135	The specified location.broadcast_domain.uuid is not valid.
1967136	The specified location.broadcast_domain.name (and ipspace name) is not valid.
1967137	The specified location.broadcast_domain.uuid and location.broadcast_domain.name (and IPspace name) are not valid.
1967145	The specified location.failover is not valid.
1967146	The specified svm.name is not valid.
1967147	The specified svm.uuid is not valid.

Error Code	Description
1967153	No suitable port exists on location.home_node to host the interface.
1967154	Interfaces cannot be created on ports that are down. If a broadcast domain is specified, ensure that it contains at least one port that is operationally up.
1967381	Post VIP interfaces requires an effective cluster version of 9.7 or later.
1967382	VIP interfaces only reside in SVM scope.
1967383	Neither location.home_port.uuid or location.home_port.name should be set with vip=true.
1967384	Failed to create VIP interface because the home node does not have active BGP sessions to support Virtual IP (VIP) traffic.
1967385	VIP interfaces with an IPv4 address must use ip.netmask=32. VIP interfaces with an IPv6 address must use ip.netmask=128.
1967387	The specified IP address is in use by a subnet in this IPspace.
5373966	An iSCSI interface cannot be created in an SVM configured for NVMe.
53281065	The service_policy does not exist in the SVM.

Name	Type	Description
error	error	

### Example error

```
{
  "error": {
    "arguments": {
      "code": "string",
      "message": "string"
    },
    "code": "4",
    "message": "entry doesn't exist",
    "target": "uuid"
  }
}
```

## **Definitions**

## See Definitions

href

Name	Type	Description
href	string	

\_links

Name	Type	Description
self	href	

ip\_info

IP information

Name	Type	Description
address	string	IPv4 or IPv6 address
family	string	IPv4 or IPv6
netmask	string	Input as netmask length (16) or IPv4 mask (255.255.0.0). For IPv6, you must set the netmask length. The default value is 64. Output is always netmask length.

ipspace

Either the UUID or name must be supplied on POST for cluster-scoped objects.

Name	Type	Description
_links	_links	
name	string	IPspace name
uuid	string	IPspace UUID

broadcast\_domain

Broadcast domain UUID along with a readable name.

Name	Type	Description
_links	_links	

Name	Type	Description
name	string	Name of the broadcast domain, scoped to its IPspace
uuid	string	Broadcast domain UUID

home\_node

Name	Type	Description
_links	<a href="#">_links</a>	
name	string	
uuid	string	

node

Name	Type	Description
name	string	Name of node on which the port is located.

home\_port

Port UUID along with readable names. Either the UUID or both names may be supplied on input.

Name	Type	Description
_links	<a href="#">_links</a>	
name	string	
node	<a href="#">node</a>	
uuid	string	

node

Name	Type	Description
_links	<a href="#">_links</a>	
name	string	
uuid	string	

port

Port UUID along with readable names. Either the UUID or both names may be supplied on input.

Name	Type	Description
_links	<a href="#">_links</a>	

Name	Type	Description
name	string	
node	<a href="#">node</a>	
uuid	string	

## location

Current or home location can be modified. Specifying a port implies a node. Specifying a node allows an appropriate port to be automatically selected. Ports are not valid and not shown for VIP interfaces. For POST, broadcast\_domain can be specified alone or with home\_node.

Name	Type	Description
auto_revert	boolean	
broadcast_domain	<a href="#">broadcast_domain</a>	Broadcast domain UUID along with a readable name.
failover	string	Defines where an interface may failover.
home_node	<a href="#">home_node</a>	
home_port	<a href="#">home_port</a>	Port UUID along with readable names. Either the UUID or both names may be supplied on input.
is_home	boolean	
node	<a href="#">node</a>	
port	<a href="#">port</a>	Port UUID along with readable names. Either the UUID or both names may be supplied on input.

## service\_policy

Name	Type	Description
_links	<a href="#">_links</a>	
name	string	
uuid	string	

## svm

Applies only to SVM-scoped objects. Either the UUID or name must be supplied on POST.

Name	Type	Description
_links	<a href="#">_links</a>	

Name	Type	Description
name	string	The name of the SVM.
uuid	string	The unique identifier of the SVM.

## ip\_interface

Name	Type	Description
_links	<a href="#">_links</a>	
enabled	boolean	The administrative state of the interface.
ip	<a href="#">ip_info</a>	IP information
ipspace	<a href="#">ipspace</a>	Either the UUID or name must be supplied on POST for cluster-scoped objects.
location	<a href="#">location</a>	Current or home location can be modified. Specifying a port implies a node. Specifying a node allows an appropriate port to be automatically selected. Ports are not valid and not shown for VIP interfaces. For POST, broadcast_domain can be specified alone or with home_node.
name	string	Interface name
scope	string	Set to "svm" for interfaces owned by an SVM. Otherwise, set to "cluster".
service_policy	<a href="#">service_policy</a>	
services	array[string]	The services associated with the interface.
state	string	The operational state of the interface.
svm	<a href="#">svm</a>	Applies only to SVM-scoped objects. Either the UUID or name must be supplied on POST.

Name	Type	Description
uuid	string	The UUID that uniquely identifies the interface.
vip	boolean	True for a VIP interface, whose location is announced via BGP.

#### error\_arguments

Name	Type	Description
code	string	Argument code
message	string	Message argument

#### error

Name	Type	Description
arguments	array[error_arguments]	Message arguments
code	string	Error code
message	string	Error message
target	string	The target parameter that caused the error.

## Delete an IP interface

`DELETE /network/ip/interfaces/{uuid}`

Deletes an IP interface.

### Related ONTAP commands

- `network interface delete`

### Learn more

- [DOC /network/ip/interfaces](#)

### Parameters

Name	Type	In	Required	Description
uuid	string	path	True	

## Response

Status: 200, Ok

## Retrieve details for an IP interface

GET /network/ip/interfaces/{uuid}

Retrieves details for a specific IP interface.

### Related ONTAP commands

- `network interface show`

### Learn more

- [DOC /network/ip/interfaces](#)

### Parameters

Name	Type	In	Required	Description
uuid	string	path	True	IP interface UUID
fields	array[string]	query	False	Specify the fields to return.

## Response

Status: 200, Ok

Name	Type	Description
_links	<a href="#">_links</a>	
enabled	boolean	The administrative state of the interface.
ip	<a href="#">ip_info</a>	IP information
ipspace	<a href="#">ipspace</a>	Either the UUID or name must be supplied on POST for cluster-scoped objects.

Name	Type	Description
location	location	Current or home location can be modified. Specifying a port implies a node. Specifying a node allows an appropriate port to be automatically selected. Ports are not valid and not shown for VIP interfaces. For POST, broadcast_domain can be specified alone or with home_node.
name	string	Interface name
scope	string	Set to "svm" for interfaces owned by an SVM. Otherwise, set to "cluster".
service_policy	service_policy	
services	array[string]	The services associated with the interface.
state	string	The operational state of the interface.
svm	svm	Applies only to SVM-scoped objects. Either the UUID or name must be supplied on POST.
uuid	string	The UUID that uniquely identifies the interface.
vip	boolean	True for a VIP interface, whose location is announced via BGP.

## Example response

```
{  
    "_links": {  
        "self": {  
            "href": "/api/resourcelink"  
        }  
    },  
    "ip": {  
        "address": "10.10.10.7",  
        "family": "ipv4",  
        "netmask": "24"  
    },  
    "ipspace": {  
        "_links": {  
            "self": {  
                "href": "/api/resourcelink"  
            }  
        },  
        "name": "exchange",  
        "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
    },  
    "location": {  
        "broadcast_domain": {  
            "_links": {  
                "self": {  
                    "href": "/api/resourcelink"  
                }  
            },  
            "name": "bd1",  
            "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
        },  
        "failover": "home_port_only",  
        "home_node": {  
            "_links": {  
                "self": {  
                    "href": "/api/resourcelink"  
                }  
            },  
            "name": "node1",  
            "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
        },  
        "home_port": {  
            "_links": {  
                "self": {  
                    "href": "/api/resourcelink"  
                }  
            }  
        }  
    }  
}
```

```
        }
    },
    "name": "elb",
    "node": {
        "name": "node1"
    },
    "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"
},
"node": {
    "_links": {
        "self": {
            "href": "/api/resourcelink"
        }
    },
    "name": "node1",
    "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"
},
"port": {
    "_links": {
        "self": {
            "href": "/api/resourcelink"
        }
    },
    "name": "elb",
    "node": {
        "name": "node1"
    },
    "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"
}
},
"name": "dataLif1",
"scope": "svm",
"service_policy": {
    "_links": {
        "self": {
            "href": "/api/resourcelink"
        }
    },
    "name": "default-intercluster",
    "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"
},
"services": {
},
"state": "up",
"svm": {
    "_links": {
```

```

    "self": {
      "href": "/api/resourcelink"
    },
    "name": "svml1",
    "uuid": "02c9e252-41be-11e9-81d5-00a0986138f7"
  },
  "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"
}

```

## Error

Status: Default, Error

Name	Type	Description
error	error	

## Example error

```
{
  "error": {
    "arguments": {
      "code": "string",
      "message": "string"
    },
    "code": "4",
    "message": "entry doesn't exist",
    "target": "uuid"
  }
}
```

## Definitions

## See Definitions

href

Name	Type	Description
href	string	

\_links

Name	Type	Description
self	href	

ip\_info

IP information

Name	Type	Description
address	string	IPv4 or IPv6 address
family	string	IPv4 or IPv6
netmask	string	Input as netmask length (16) or IPv4 mask (255.255.0.0). For IPv6, you must set the netmask length. The default value is 64. Output is always netmask length.

ipspace

Either the UUID or name must be supplied on POST for cluster-scoped objects.

Name	Type	Description
_links	_links	
name	string	IPspace name
uuid	string	IPspace UUID

broadcast\_domain

Broadcast domain UUID along with a readable name.

Name	Type	Description
_links	_links	

Name	Type	Description
name	string	Name of the broadcast domain, scoped to its IPspace
uuid	string	Broadcast domain UUID

home\_node

Name	Type	Description
_links	<a href="#">_links</a>	
name	string	
uuid	string	

node

Name	Type	Description
name	string	Name of node on which the port is located.

home\_port

Port UUID along with readable names. Either the UUID or both names may be supplied on input.

Name	Type	Description
_links	<a href="#">_links</a>	
name	string	
node	<a href="#">node</a>	
uuid	string	

node

Name	Type	Description
_links	<a href="#">_links</a>	
name	string	
uuid	string	

port

Port UUID along with readable names. Either the UUID or both names may be supplied on input.

Name	Type	Description
_links	<a href="#">_links</a>	

Name	Type	Description
name	string	
node	<a href="#">node</a>	
uuid	string	

## location

Current or home location can be modified. Specifying a port implies a node. Specifying a node allows an appropriate port to be automatically selected. Ports are not valid and not shown for VIP interfaces. For POST, broadcast\_domain can be specified alone or with home\_node.

Name	Type	Description
auto_revert	boolean	
broadcast_domain	<a href="#">broadcast_domain</a>	Broadcast domain UUID along with a readable name.
failover	string	Defines where an interface may failover.
home_node	<a href="#">home_node</a>	
home_port	<a href="#">home_port</a>	Port UUID along with readable names. Either the UUID or both names may be supplied on input.
is_home	boolean	
node	<a href="#">node</a>	
port	<a href="#">port</a>	Port UUID along with readable names. Either the UUID or both names may be supplied on input.

## service\_policy

Name	Type	Description
_links	<a href="#">_links</a>	
name	string	
uuid	string	

## svm

Applies only to SVM-scoped objects. Either the UUID or name must be supplied on POST.

Name	Type	Description
_links	<a href="#">_links</a>	

Name	Type	Description
name	string	The name of the SVM.
uuid	string	The unique identifier of the SVM.

error\_arguments

Name	Type	Description
code	string	Argument code
message	string	Message argument

error

Name	Type	Description
arguments	array[error_arguments]	Message arguments
code	string	Error code
message	string	Error message
target	string	The target parameter that caused the error.

## Update an IP interface

PATCH /network/ip/interfaces/{uuid}

Updates an IP interface.

### Related ONTAP commands

- `network interface migrate`
- `network interface modify`
- `network interface rename`
- `network interface revert`

### Learn more

- [DOC /network/ip/interfaces](#)

## Parameters

Name	Type	In	Required	Description
uuid	string	path	True	IP interface UUID

## Request Body

Name	Type	Description
_links	<a href="#">_links</a>	
enabled	boolean	The administrative state of the interface.
ip	<a href="#">ip_info</a>	IP information
ipspace	<a href="#">ipspace</a>	Either the UUID or name must be supplied on POST for cluster-scoped objects.
location	<a href="#">location</a>	Current or home location can be modified. Specifying a port implies a node. Specifying a node allows an appropriate port to be automatically selected. Ports are not valid and not shown for VIP interfaces. For POST, broadcast_domain can be specified alone or with home_node.
name	string	Interface name
scope	string	Set to "svm" for interfaces owned by an SVM. Otherwise, set to "cluster".
service_policy	<a href="#">service_policy</a>	
services	array[string]	The services associated with the interface.
state	string	The operational state of the interface.
svm	<a href="#">svm</a>	Applies only to SVM-scoped objects. Either the UUID or name must be supplied on POST.

Name	Type	Description
uuid	string	The UUID that uniquely identifies the interface.
vip	boolean	True for a VIP interface, whose location is announced via BGP.

## Example request

```
{  
    "_links": {  
        "self": {  
            "href": "/api/resourcelink"  
        }  
    },  
    "ip": {  
        "address": "10.10.10.7",  
        "family": "ipv4",  
        "netmask": "24"  
    },  
    "ipspace": {  
        "_links": {  
            "self": {  
                "href": "/api/resourcelink"  
            }  
        },  
        "name": "exchange",  
        "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
    },  
    "location": {  
        "broadcast_domain": {  
            "_links": {  
                "self": {  
                    "href": "/api/resourcelink"  
                }  
            },  
            "name": "bd1",  
            "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
        },  
        "failover": "home_port_only",  
        "home_node": {  
            "_links": {  
                "self": {  
                    "href": "/api/resourcelink"  
                }  
            },  
            "name": "node1",  
            "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
        },  
        "home_port": {  
            "_links": {  
                "self": {  
                    "href": "/api/resourcelink"  
                }  
            }  
        }  
    }  
}
```

```

        }
    },
    "name": "elb",
    "node": {
        "name": "node1"
    },
    "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"
},
"node": {
    "_links": {
        "self": {
            "href": "/api/resourcelink"
        }
    },
    "name": "node1",
    "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"
},
"port": {
    "_links": {
        "self": {
            "href": "/api/resourcelink"
        }
    },
    "name": "elb",
    "node": {
        "name": "node1"
    },
    "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"
}
},
"name": "dataLif1",
"scope": "svm",
"service_policy": {
    "_links": {
        "self": {
            "href": "/api/resourcelink"
        }
    },
    "name": "default-intercluster",
    "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"
},
"services": {
},
"state": "up",
"svm": {
    "_links": {

```

```

    "self": {
        "href": "/api/resourcelink"
    },
    "name": "svm1",
    "uuid": "02c9e252-41be-11e9-81d5-00a0986138f7"
},
"uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"
}

```

## Response

Status: 200, Ok

## Error

Status: Default

### ONTAP Error Response Codes

Error Code	Description
1376963	Duplicate IP address.
1966138	The same IP address may not be used for both a mgmt interface and a gateway address.
1967106	The specified location.home_port.name does not match the specified port name of location.home_port.uuid.
1967107	The specified location.home_port.uuid is not valid.
1967111	A home node must be specified by at least one location.home_node, location.home_port, or location.broadcast_domain field.
1967113	The specified location.port.name does not match the port name of location.port.uuid.
1967114	The specified location.port.uuid is not valid.
1967115	The specified location.node.name does not match the node name of location.node.uuid.
1967116	The specified location.port.node.name does not match the node name of location.node.uuid.
1967117	The specified location.port.node.name does not match location.node.name.

Error Code	Description
1967118	A node must be specified by at least one location.node or location.port field.
1967119	The specified location.node.name does not match the node name of location.port.uuid.
1967120	The specified service_policy.name does not match the specified service policy name of service_policy.uuid.
1967121	The specified service_policy.uuid is not valid.
1967125	You cannot patch the "location.node" or "location.port" fields to migrate interfaces using the iSCSI data protocol. Instead perform the following PATCH operations on the interface: set the "enabled" field to "false"; change one or more "location.home_port" fields to migrate the interface; and then set the "enabled" field to "true".
1967129	The specified location.home_port.uuid is not valid.
1967130	The specified location.home_port.name is not valid.
1967131	The specified location.home_port.uuid and location.home_port.name are not valid.
1967132	The specified location.port.uuid is not valid.
1967133	The specified location.port.name is not valid.
1967134	The specified location.port.uuid and location.port.name are not valid.
1967138	Cannot patch port for a VIP interface. The specified parameter location.port.uuid is not valid.
1967139	Cannot patch port for a VIP interface. The specified parameter location.port.name is not valid.
1967140	Cannot patch port for a VIP interface. The specified parameters location.port.uuid and location.port.name are not valid.
1967141	Cannot patch home_port for a VIP interface. The specified parameter location.home_port.uuid is not valid.
1967142	Cannot patch home_port for a VIP interface. The specified parameter location.home_port.name is not valid.
1967143	Cannot patch home_port for a VIP interface. The specified parameters location.home_port.uuid and location.home_port.name are not valid.
1967145	The specified location.failover is not valid.
1967153	No suitable port exists on location.home_node to host the interface.

Error Code	Description
1967380	Cannot patch home_port for a VIP interface. The specified parameter location.home_port.node.name is not valid. Consider using location.home_node.name instead.
1967386	Cannot patch port for a VIP interface. The specified parameter location.port.node.name is not valid. Consider using location.node.name instead.
1967387	The specified IP address is in use by a subnet in this IPspace.
53281065	The service_policy does not exist in the SVM.

## Definitions

## See Definitions

href

Name	Type	Description
href	string	

\_links

Name	Type	Description
self	href	

ip\_info

IP information

Name	Type	Description
address	string	IPv4 or IPv6 address
family	string	IPv4 or IPv6
netmask	string	Input as netmask length (16) or IPv4 mask (255.255.0.0). For IPv6, you must set the netmask length. The default value is 64. Output is always netmask length.

ipspace

Either the UUID or name must be supplied on POST for cluster-scoped objects.

Name	Type	Description
_links	_links	
name	string	IPspace name
uuid	string	IPspace UUID

broadcast\_domain

Broadcast domain UUID along with a readable name.

Name	Type	Description
_links	_links	

Name	Type	Description
name	string	Name of the broadcast domain, scoped to its IPspace
uuid	string	Broadcast domain UUID

home\_node

Name	Type	Description
_links	<a href="#">_links</a>	
name	string	
uuid	string	

node

Name	Type	Description
name	string	Name of node on which the port is located.

home\_port

Port UUID along with readable names. Either the UUID or both names may be supplied on input.

Name	Type	Description
_links	<a href="#">_links</a>	
name	string	
node	<a href="#">node</a>	
uuid	string	

node

Name	Type	Description
_links	<a href="#">_links</a>	
name	string	
uuid	string	

port

Port UUID along with readable names. Either the UUID or both names may be supplied on input.

Name	Type	Description
_links	<a href="#">_links</a>	

Name	Type	Description
name	string	
node	<a href="#">node</a>	
uuid	string	

## location

Current or home location can be modified. Specifying a port implies a node. Specifying a node allows an appropriate port to be automatically selected. Ports are not valid and not shown for VIP interfaces. For POST, broadcast\_domain can be specified alone or with home\_node.

Name	Type	Description
auto_revert	boolean	
broadcast_domain	<a href="#">broadcast_domain</a>	Broadcast domain UUID along with a readable name.
failover	string	Defines where an interface may failover.
home_node	<a href="#">home_node</a>	
home_port	<a href="#">home_port</a>	Port UUID along with readable names. Either the UUID or both names may be supplied on input.
is_home	boolean	
node	<a href="#">node</a>	
port	<a href="#">port</a>	Port UUID along with readable names. Either the UUID or both names may be supplied on input.

## service\_policy

Name	Type	Description
_links	<a href="#">_links</a>	
name	string	
uuid	string	

## svm

Applies only to SVM-scoped objects. Either the UUID or name must be supplied on POST.

Name	Type	Description
_links	<a href="#">_links</a>	

Name	Type	Description
name	string	The name of the SVM.
uuid	string	The unique identifier of the SVM.

## ip\_interface

Name	Type	Description
_links	<a href="#">_links</a>	
enabled	boolean	The administrative state of the interface.
ip	<a href="#">ip_info</a>	IP information
ipspace	<a href="#">ipspace</a>	Either the UUID or name must be supplied on POST for cluster-scoped objects.
location	<a href="#">location</a>	Current or home location can be modified. Specifying a port implies a node. Specifying a node allows an appropriate port to be automatically selected. Ports are not valid and not shown for VIP interfaces. For POST, broadcast_domain can be specified alone or with home_node.
name	string	Interface name
scope	string	Set to "svm" for interfaces owned by an SVM. Otherwise, set to "cluster".
service_policy	<a href="#">service_policy</a>	
services	array[string]	The services associated with the interface.
state	string	The operational state of the interface.
svm	<a href="#">svm</a>	Applies only to SVM-scoped objects. Either the UUID or name must be supplied on POST.

Name	Type	Description
uuid	string	The UUID that uniquely identifies the interface.
vip	boolean	True for a VIP interface, whose location is announced via BGP.

## Manage network IP routes

### Network IP routes endpoint overview

#### Overview

This endpoint supports the following operations: GET (collection and instance), POST, and DELETE.

#### Retrieving network routes

You can use the IP routes GET API to retrieve and display relevant information pertaining to the routes configured in the cluster. The API retrieves the list of all routes configured in the cluster, or a specific route. The fields that are returned in the response will differ with the configuration.

#### Examples

##### Retrieving all routes in the cluster

The following output shows the list of all routes configured in a cluster.

```
# The API:  
/api/network/ip/routes  
  
# The call:  
curl -X GET "https://<mgmt-ip>/api/network/ip/routes?fields=*" -H "accept: application/hal+json"  
  
# The response:  
{  
"records": [  
  {  
    "uuid": "5fdfffb0b-62f8-11e8-853d-005056b4c971",  
    "ipspace": {  
      "uuid": "84f4beb2-616c-11e8-a4df-005056b4c971",  
      "name": "Default",  
      "_links": {
```

```

    "self": {
        "href": "/api/network/ipspaces/84f4beb2-616c-11e8-a4df-
005056b4c971"
    }
},
},
"svm": {
    "uuid": "3243312c-62f8-11e8-853d-005056b4c971",
    "name": "vs1",
    "_links": {
        "self": {
            "href": "/api/svm/svms/3243312c-62f8-11e8-853d-005056b4c971"
        }
    }
},
"scope": "svm",
"destination": {
    "address": "10.4.3.14",
    "netmask": "18",
    "family": "ipv4"
},
"gateway": "10.4.3.1",
"_links": {
    "self": {
        "href": "/api/network/ip/routes/5fdffb0b-62f8-11e8-853d-
005056b4c971"
    }
}
},
{
    "uuid": "84c128d2-62f9-11e8-853d-005056b4c971",
    "ipspace": {
        "uuid": "cc71aadc-62f7-11e8-853d-005056b4c971",
        "name": "ips1",
        "_links": {
            "self": {
                "href": "/api/network/ipspaces/cc71aadc-62f7-11e8-853d-
005056b4c971"
            }
        }
    }
},
"scope": "cluster",
"destination": {
    "address": "::",
    "netmask": "0",
    "family": "ipv6"
}

```

```

},
"gateway": "fd20:8b1e:b255:814e::1",
"_links": {
  "self": {
    "href": "/api/network/ip/routes/84c128d2-62f9-11e8-853d-
005056b4c971"
  }
}
},
{
  "uuid": "8cc72bcd-616c-11e8-a4df-005056b4c971",
  "ipspace": {
    "uuid": "84f4beb2-616c-11e8-a4df-005056b4c971",
    "name": "Default",
    "_links": {
      "self": {
        "href": "/api/network/ipspaces/84f4beb2-616c-11e8-a4df-
005056b4c971"
      }
    }
  },
  "scope": "cluster",
  "destination": {
    "address": "0.0.0.0",
    "netmask": "0",
    "family": "ipv4"
  },
  "gateway": "10.224.64.1",
  "_links": {
    "self": {
      "href": "/api/network/ip/routes/8cc72bcd-616c-11e8-a4df-
005056b4c971"
    }
  }
},
{
  "uuid": "d63b6eee-62f9-11e8-853d-005056b4c971",
  "ipspace": {
    "uuid": "84f4beb2-616c-11e8-a4df-005056b4c971",
    "name": "Default",
    "_links": {
      "self": {
        "href": "/api/network/ipspaces/84f4beb2-616c-11e8-a4df-
005056b4c971"
      }
    }
  }
}

```

```

} ,
"svm": {
  "uuid": "3243312c-62f8-11e8-853d-005056b4c971",
  "name": "vs1",
  "_links": {
    "self": {
      "href": "/api/svm/svms/3243312c-62f8-11e8-853d-005056b4c971"
    }
  }
},
"scope": "svm",
"destination": {
  "address": "fd20:8b1e:b255:814e::",
  "netmask": "64",
  "family": "ipv6"
},
"gateway": "fd20:8b1e:b255:814e::1",
"_links": {
  "self": {
    "href": "/api/network/ip/routes/d63b6eee-62f9-11e8-853d-
005056b4c971"
  }
}
}
],
"num_records": 4,
"_links": {
  "self": {
    "href": "/api/network/ip/routes?fields=*"
  }
}
}

```

#### Retrieving a specific Cluster-scoped route

The following output shows the returned response when a specific Cluster-scoped route is requested. The system returns an error if there is no route with the requested UUID. SVM information is not returned for Cluster-scoped routes.

```

# The API:
/api/network/ip/routes/{uuid}

# The call:
curl -X GET "https://<mgmt-ip>/api/network/ip/routes/84c128d2-62f9-11e8-
853d-005056b4c971?fields=*" -H "accept: application/hal+json"

# The response:
{
  "uuid": "84c128d2-62f9-11e8-853d-005056b4c971",
  "ipspace": {
    "uuid": "cc71aadc-62f7-11e8-853d-005056b4c971",
    "name": "ips1",
    "_links": {
      "self": {
        "href": "/api/network/ipspaces/cc71aadc-62f7-11e8-853d-005056b4c971"
      }
    }
  },
  "scope": "cluster",
  "destination": {
    "address": "::",
    "netmask": "0",
    "family": "ipv6"
  },
  "gateway": "fd20:8b1e:b255:814e::1",
  "_links": {
    "self": {
      "href": "/api/network/ip/routes/84c128d2-62f9-11e8-853d-005056b4c971"
    }
  }
}

```

#### Retrieving a specific SVM-scoped route

The following output shows the returned response when a specific SVM-scoped route is requested. The system returns an error if there is no route with the requested UUID. The SVM object is only included for SVM-scoped routes.

```

# The API:
/api/network/ip/routes/{uuid}

# The call:
curl -X GET "https://<mgmt-ip>/api/network/ip/routes/d63b6eee-62f9-11e8-
853d-005056b4c971?fields=*" -H "accept: application/hal+json"

# The response:
{
  "uuid": "d63b6eee-62f9-11e8-853d-005056b4c971",
  "ipspace": {
    "uuid": "84f4beb2-616c-11e8-a4df-005056b4c971",
    "name": "Default",
    "_links": {
      "self": {
        "href": "/api/network/ipspaces/84f4beb2-616c-11e8-a4df-005056b4c971"
      }
    }
  },
  "svm": {
    "uuid": "3243312c-62f8-11e8-853d-005056b4c971",
    "name": "vs1",
    "_links": {
      "self": {
        "href": "/api/svm/svms/3243312c-62f8-11e8-853d-005056b4c971"
      }
    }
  },
  "scope": "svm",
  "destination": {
    "address": "fd20:8b1e:b255:814e::",
    "netmask": "64",
    "family": "ipv6"
  },
  "gateway": "fd20:8b1e:b255:814e::1",
  "_links": {
    "self": {
      "href": "/api/network/ip/routes/d63b6eee-62f9-11e8-853d-005056b4c971"
    }
  }
}

```

## Creating network routes

You can use the POST API to create an SVM-scoped route by specifying the associated SVM, or a Cluster-scoped route by specifying the associated IPspace.

## Examples

### Creating a Cluster-scoped route

IPspace is required to create a Cluster-scoped route. If the IPspace is not specified, the route will be created in the Default IPspace. The default destination will be set to "0.0.0.0/0" for IPv4 gateway addresses or "::/0" for IPv6 gateway addresses.

```
# The API:  
/api/network/ip/routes  
  
# The call:  
curl -X POST "https://<mgmt-ip>/api/network/ip/routes?return_records=true"  
-H "accept: application/json" -d '{ "ipspace": { "name":"ips1" },  
"gateway": "10.10.10.1"}'  
  
# The response:  
{  
  "num_records": 1,  
  "records": [  
    {  
      "uuid": "ae583c9e-9ac7-11e8-8bc9-005056bb531",  
      "ipspace": {  
        "name": "ips1"  
      },  
      "gateway": "10.10.10.1"  
    }  
  ]  
}
```

### Creating an SVM-scoped route

To create an SVM-scoped route, the associated SVM can be identified by either its UUID or name.

```

# The API:
/api/network/ip/routes

# The call:
curl -X POST "https://<mgmt-ip>/api/network/ip/routes?return_records=true"
-H "accept: application/json" -d '{ "svm": { "name":"vs0" }, "gateway":
"10.10.10.1" }'

# The response:
{
  "num_records": 1,
  "records": [
    {
      "uuid": "38805a91-9ac9-11e8-8bc9-005056bbd531",
      "svm": {
        "name": "vs0"
      },
      "gateway": "10.10.10.1"
    }
  ]
}

```

## Deleting network routes

You can use the DELETE API to delete a specific route identified by its UUID.

### Example

#### Deleting a specific route

```

# The API:
/api/network/ip/routes/{uuid}

# The call:
curl -X DELETE "https://<mgmt-ip>/api/network/ip/routes/38805a91-9ac9-
11e8-8bc9-005056bbd531"

```

## Retrieve IP routes

GET /network/ip/routes

Retrieves the collection of IP routes.

## Related ONTAP commands

- `network route show`

## Learn more

- [DOC /network/ip/routes](#)

## Parameters

Name	Type	In	Required	Description
ipspace.uuid	string	query	False	Filter by ipspace.uuid
ipspace.name	string	query	False	Filter by ipspace.name
scope	string	query	False	Filter by scope
uuid	string	query	False	Filter by uuid
gateway	string	query	False	Filter by gateway
destination.netmask	string	query	False	Filter by destination.netmask
destination.address	string	query	False	Filter by destination.address
destination.family	string	query	False	Filter by destination.family
svm.uuid	string	query	False	Filter by svm.uuid
svm.name	string	query	False	Filter by svm.name
fields	array[string]	query	False	Specify the fields to return.
max_records	integer	query	False	Limit the number of records returned.

Name	Type	In	Required	Description
return_records	boolean	query	False	The default is true for GET calls. When set to false, only the number of records is returned.
return_timeout	integer	query	False	The number of seconds to allow the call to execute before returning. When iterating over a collection, the default is 15 seconds. ONTAP returns earlier if either max records or the end of the collection is reached.
order_by	array[string]	query	False	Order results by specified fields and optional [asc

## Response

Status: 200, Ok

Name	Type	Description
_links	<a href="#">_links</a>	
error	<a href="#">error</a>	
num_records	integer	Number of records
records	array[ <a href="#">network_route</a> ]	

## Example response

```
{  
    "_links": {  
        "next": {  
            "href": "/api/resourcelink"  
        },  
        "self": {  
            "href": "/api/resourcelink"  
        }  
    },  
    "error": {  
        "arguments": {  
            "code": "string",  
            "message": "string"  
        },  
        "code": "4",  
        "message": "entry doesn't exist",  
        "target": "uuid"  
    },  
    "num_records": 1,  
    "records": {  
        "_links": {  
            "self": {  
                "href": "/api/resourcelink"  
            }  
        },  
        "destination": {  
            "address": "10.10.10.7",  
            "family": "ipv4",  
            "netmask": "24"  
        },  
        "gateway": "10.1.1.1",  
        "ipspace": {  
            "_links": {  
                "self": {  
                    "href": "/api/resourcelink"  
                }  
            },  
            "name": "exchange",  
            "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
        },  
        "scope": "svm",  
        "svm": {  
            "_links": {  
                "self": {  
                    "href": "/api/resourcelink"  
                }  
            }  
        }  
    }  
}
```

```

        "href": "/api/resourcelink"
    }
},
"name": "svm1",
"uuid": "02c9e252-41be-11e9-81d5-00a0986138f7"
},
"uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"
}
}

```

## Error

Status: Default, Error

Name	Type	Description
error	error	

## Example error

```
{
  "error": {
    "arguments": {
      "code": "string",
      "message": "string"
    },
    "code": "4",
    "message": "entry doesn't exist",
    "target": "uuid"
  }
}
```

## Definitions

## See Definitions

href

Name	Type	Description
href	string	

\_links

Name	Type	Description
next	href	
self	href	

error\_arguments

Name	Type	Description
code	string	Argument code
message	string	Message argument

error

Name	Type	Description
arguments	array[error_arguments]	Message arguments
code	string	Error code
message	string	Error message
target	string	The target parameter that caused the error.

\_links

Name	Type	Description
self	href	

ip\_info

IP information

Name	Type	Description
address	string	IPv4 or IPv6 address

Name	Type	Description
family	string	IPv4 or IPv6
netmask	string	Input as netmask length (16) or IPv4 mask (255.255.0.0). For IPv6, you must set the netmask length. The default value is 64. Output is always netmask length.

## ipspace

Applies to both SVM and cluster-scoped objects. Either the UUID or name may be supplied on input.

Name	Type	Description
_links	<a href="#">_links</a>	
name	string	IPspace name
uuid	string	IPspace UUID

## svm

Name	Type	Description
_links	<a href="#">_links</a>	
name	string	The name of the SVM.
uuid	string	The unique identifier of the SVM.

## network\_route

Name	Type	Description
_links	<a href="#">_links</a>	
destination	<a href="#">ip_info</a>	IP information
gateway	string	The IP address of the gateway router leading to the destination.
ipspace	<a href="#">ipspace</a>	Applies to both SVM and cluster-scoped objects. Either the UUID or name may be supplied on input.

Name	Type	Description
scope	string	Set to "svm" for interfaces owned by an SVM. Otherwise, set to "cluster".
svm	svm	
uuid	string	The UUID that uniquely identifies the route.

## Create a cluster-scoped or SVM-scoped static route

POST /network/ip/routes

Creates a Cluster-scoped or SVM-scoped static route.

### Required properties

- gateway - IP address to route packets to.
- SVM-scoped routes
  - svm.name or svm.uuid - SVM that route is applied to.
- cluster-scoped routes
  - There are no additional required fields for Cluster-scoped routes.

### Default property values

If not specified in POST, the following default property values are assigned:

- destination - 0.0.0.0/0 for IPv4 or ::/0 for IPv6.
- ipspace.name
  - *Default* for Cluster-scoped routes.
  - Name of the SVM's IPspace for SVM-scoped routes.

### Related ONTAP commands

- network route create

### Learn more

- [DOC /network/ip/routes](#)

### Parameters

Name	Type	In	Required	Description
return_records	boolean	query	False	The default is false. If set to true, the records are returned.

## Request Body

Name	Type	Description
_links	<a href="#">_links</a>	
destination	<a href="#">ip_info</a>	IP information
gateway	string	The IP address of the gateway router leading to the destination.
ipspace	<a href="#">ipspace</a>	Applies to both SVM and cluster-scoped objects. Either the UUID or name may be supplied on input.
scope	string	Set to "svm" for interfaces owned by an SVM. Otherwise, set to "cluster".
svm	<a href="#">svm</a>	
uuid	string	The UUID that uniquely identifies the route.

## Example request

```
{  
    "_links": {  
        "self": {  
            "href": "/api/resourcelink"  
        }  
    },  
    "destination": {  
        "address": "10.10.10.7",  
        "family": "ipv4",  
        "netmask": "24"  
    },  
    "gateway": "10.1.1.1",  
    "ipspace": {  
        "_links": {  
            "self": {  
                "href": "/api/resourcelink"  
            }  
        },  
        "name": "exchange",  
        "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
    },  
    "scope": "svm",  
    "svm": {  
        "_links": {  
            "self": {  
                "href": "/api/resourcelink"  
            }  
        },  
        "name": "svml1",  
        "uuid": "02c9e252-41be-11e9-81d5-00a0986138f7"  
    },  
    "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
}
```

## Response

Status: 201, Created

Name	Type	Description
_links	_links	

Name	Type	Description
error	error	
num_records	integer	Number of records
records	array[ <a href="#">network_route</a> ]	

## Example response

```
{  
    "_links": {  
        "next": {  
            "href": "/api/resourcelink"  
        },  
        "self": {  
            "href": "/api/resourcelink"  
        }  
    },  
    "error": {  
        "arguments": {  
            "code": "string",  
            "message": "string"  
        },  
        "code": "4",  
        "message": "entry doesn't exist",  
        "target": "uuid"  
    },  
    "num_records": 1,  
    "records": {  
        "_links": {  
            "self": {  
                "href": "/api/resourcelink"  
            }  
        },  
        "destination": {  
            "address": "10.10.10.7",  
            "family": "ipv4",  
            "netmask": "24"  
        },  
        "gateway": "10.1.1.1",  
        "ipspace": {  
            "_links": {  
                "self": {  
                    "href": "/api/resourcelink"  
                }  
            },  
            "name": "exchange",  
            "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
        },  
        "scope": "svm",  
        "svm": {  
            "_links": {  
                "self": {  
                    "href": "/api/resourcelink"  
                }  
            }  
        }  
    }  
}
```

```

        "href": "/api/resourcelink"
    }
},
"name": "svm1",
"uuid": "02c9e252-41be-11e9-81d5-00a0986138f7"
},
"uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"
}
}

```

## Error

Status: Default

### ONTAP Error Response Codes

Error Code	Description
1966345	Duplicate route exists.
1967080	The destination.address is missing.
1967081	The specified SVM must exist in the specified IPspace.
1967082	The specified ipspace.uuid and ipspace.name refer to different IPspaces.
1967146	The specified svm.name is not valid.
2	The specified svm.uuid is not valid.

Name	Type	Description
error	error	

## Example error

```
{  
  "error": {  
    "arguments": {  
      "code": "string",  
      "message": "string"  
    },  
    "code": "4",  
    "message": "entry doesn't exist",  
    "target": "uuid"  
  }  
}
```

## Definitions

## See Definitions

href

Name	Type	Description
href	string	

\_links

Name	Type	Description
self	href	

ip\_info

IP information

Name	Type	Description
address	string	IPv4 or IPv6 address
family	string	IPv4 or IPv6
netmask	string	Input as netmask length (16) or IPv4 mask (255.255.0.0). For IPv6, you must set the netmask length. The default value is 64. Output is always netmask length.

ipspace

Applies to both SVM and cluster-scoped objects. Either the UUID or name may be supplied on input.

Name	Type	Description
_links	_links	
name	string	IPspace name
uuid	string	IPspace UUID

svm

Name	Type	Description
_links	_links	
name	string	The name of the SVM.
uuid	string	The unique identifier of the SVM.

## network\_route

Name	Type	Description
_links	_links	
destination	ip_info	IP information
gateway	string	The IP address of the gateway router leading to the destination.
ipspace	ipspace	Applies to both SVM and cluster-scoped objects. Either the UUID or name may be supplied on input.
scope	string	Set to "svm" for interfaces owned by an SVM. Otherwise, set to "cluster".
svm	svm	
uuid	string	The UUID that uniquely identifies the route.

## \_links

Name	Type	Description
next	href	
self	href	

## error\_arguments

Name	Type	Description
code	string	Argument code
message	string	Message argument

## error

Name	Type	Description
arguments	array[error_arguments]	Message arguments
code	string	Error code
message	string	Error message

Name	Type	Description
target	string	The target parameter that caused the error.

## Delete an IP route

DELETE /network/ip/routes/{uuid}

Deletes a specific IP route.

### Related ONTAP commands

- `network route delete`

### Learn more

- [DOC /network/ip/routes](#)

### Parameters

Name	Type	In	Required	Description
uuid	string	path	True	

### Response

Status: 200, Ok

### Error

Status: Default, Error

Name	Type	Description
error	<a href="#">error</a>	

## Example error

```
{  
  "error": {  
    "arguments": {  
      "code": "string",  
      "message": "string"  
    },  
    "code": "4",  
    "message": "entry doesn't exist",  
    "target": "uuid"  
  }  
}
```

## Definitions

### See Definitions

#### error\_arguments

Name	Type	Description
code	string	Argument code
message	string	Message argument

#### error

Name	Type	Description
arguments	array[error_arguments]	Message arguments
code	string	Error code
message	string	Error message
target	string	The target parameter that caused the error.

## Retrieve details for an IP route

GET /network/ip/routes/{uuid}

Retrieves the details of a specific IP route.

## Related ONTAP commands

- `network route show`

## Learn more

- [DOC /network/ip/routes](#)

## Parameters

Name	Type	In	Required	Description
uuid	string	path	True	Route UUID
fields	array[string]	query	False	Specify the fields to return.

## Response

```
Status: 200, Ok
```

Name	Type	Description
_links	<a href="#">_links</a>	
destination	<a href="#">ip_info</a>	IP information
gateway	string	The IP address of the gateway router leading to the destination.
ipspace	<a href="#">ipspace</a>	Applies to both SVM and cluster-scoped objects. Either the UUID or name may be supplied on input.
scope	string	Set to "svm" for interfaces owned by an SVM. Otherwise, set to "cluster".
svm	<a href="#">svm</a>	
uuid	string	The UUID that uniquely identifies the route.

## Example response

```
{  
    "_links": {  
        "self": {  
            "href": "/api/resourcelink"  
        }  
    },  
    "destination": {  
        "address": "10.10.10.7",  
        "family": "ipv4",  
        "netmask": "24"  
    },  
    "gateway": "10.1.1.1",  
    "ipspace": {  
        "_links": {  
            "self": {  
                "href": "/api/resourcelink"  
            }  
        },  
        "name": "exchange",  
        "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
    },  
    "scope": "svm",  
    "svm": {  
        "_links": {  
            "self": {  
                "href": "/api/resourcelink"  
            }  
        },  
        "name": "svml1",  
        "uuid": "02c9e252-41be-11e9-81d5-00a0986138f7"  
    },  
    "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
}
```

## Error

Status: Default, Error

Name	Type	Description
error	error	

## Example error

```
{  
  "error": {  
    "arguments": {  
      "code": "string",  
      "message": "string"  
    },  
    "code": "4",  
    "message": "entry doesn't exist",  
    "target": "uuid"  
  }  
}
```

## Definitions

## See Definitions

href

Name	Type	Description
href	string	

\_links

Name	Type	Description
self	href	

ip\_info

IP information

Name	Type	Description
address	string	IPv4 or IPv6 address
family	string	IPv4 or IPv6
netmask	string	Input as netmask length (16) or IPv4 mask (255.255.0.0). For IPv6, you must set the netmask length. The default value is 64. Output is always netmask length.

ipspace

Applies to both SVM and cluster-scoped objects. Either the UUID or name may be supplied on input.

Name	Type	Description
_links	_links	
name	string	IPspace name
uuid	string	IPspace UUID

svm

Name	Type	Description
_links	_links	
name	string	The name of the SVM.
uuid	string	The unique identifier of the SVM.

## error\_arguments

Name	Type	Description
code	string	Argument code
message	string	Message argument

## error

Name	Type	Description
arguments	array[error_arguments]	Message arguments
code	string	Error code
message	string	Error message
target	string	The target parameter that caused the error.

# Manage network IP service policies

## Network IP service-policies endpoint overview

### Overview

Service policies are named groupings that define what services are supported by an IP interface. The network IP service-policies GET API retrieves and displays relevant information pertaining to the service policies configured in the cluster. The API retrieves the list of all service policies configured in the cluster or a specific service policy.

### Examples

#### Retrieving all service policies in the cluster

The following output shows the collection of all service policies configured in a 2-node cluster. By default (without 'field='\* parameter), only the UUID and name fields are shown for each entry.

```
# The API:  
/api/network/ethernet/ip/service-policies  
  
# The call:  
curl -X GET "https://<mgmt-ip>/api/network/ip/service-policies" -H  
"accept: application/hal+json"
```

```

# The response:
{
"records": [
{
  "uuid": "e4e2f193-c1a3-11e8-bb9d-005056bb88c8",
  "name": "net-intercluster",
  "_links": {
    "self": {
      "href": "/api/network/ip/service-policies/e4e2f193-c1a3-11e8-bb9d-005056bb88c8"
    }
  }
},
{
  "uuid": "e4e3f6da-c1a3-11e8-bb9d-005056bb88c8",
  "name": "net-route-announce",
  "_links": {
    "self": {
      "href": "/api/network/ip/service-policies/e4e3f6da-c1a3-11e8-bb9d-005056bb88c8"
    }
  }
},
{
  "uuid": "e5111111-c1a3-11e8-bb9d-005056bb88c8",
  "name": "vserver-route-announce",
  "_links": {
    "self": {
      "href": "/api/network/ip/service-policies/e5111111-c1a3-11e8-bb9d-005056bb88c8"
    }
  }
},
{
  "uuid": "e6111111-c1a3-11e8-bb9d-005056bb88c8",
  "name": "data-route-announce",
  "_links": {
    "self": {
      "href": "/api/network/ip/service-policies/e6111111-c1a3-11e8-bb9d-005056bb88c8"
    }
  }
}
],
"num_records": 4,

```

```
"_links": {
  "self": {
    "href": "/api/network/ip/service-
policies/?return_records=true&return_timeout=15"
  }
}
```

#### Retrieving a specific service policy (scope=svm)

The following output displays the response when a specific "svm" scoped service policy is requested. Among other parameters, the response contains the svm parameters associated with the service policy. The system returns an error when there is no service policy with the requested UUID.

```

# The API:
/api/network/ip/service-policies/{uuid}

# The call:
curl -X GET "http://<mgmt-ip>/api/network/ip/service-policies/dad323ff-
4ce0-11e9-9372-005056bb91a8?fields=*" -H "accept: application/hal+json"

# The response:
{
  "uuid": "dad323ff-4ce0-11e9-9372-005056bb91a8",
  "name": "default-data-files",
  "scope": "svm",
  "svm": {
    "uuid": "d9060680-4ce0-11e9-9372-005056bb91a8",
    "name": "vs0",
    "_links": {
      "self": {
        "href": "/api/svm/svms/d9060680-4ce0-11e9-9372-005056bb91a8"
      }
    }
  },
  "ipspace": {
    "uuid": "45ec2dee-4ce0-11e9-9372-005056bb91a8",
    "name": "Default",
    "_links": {
      "self": {
        "href": "/api/network/ispaces/45ec2dee-4ce0-11e9-9372-005056bb91a8"
      }
    }
  },
  "services": [
    "data_core",
    "data_nfs",
    "data_cifs",
    "data_flexcache"
  ],
  "_links": {
    "self": {
      "href": "/api/network/ip/service-policies/dad323ff-4ce0-11e9-9372-
005056bb91a8"
    }
  }
}

```

#### **Retrieving a specific service policy (scope=svm) when requesting commonly used fields**

The following output displays the response when commonly used fields are requested for a specific "svm" scoped service policy. Among other parameters, the response contains the svm parameters associated with the service policy. The system returns an error when there is no service policy with the requested UUID.

```
# The API:  
/api/network/ip/service-policies/{uuid}  
  
# The call:  
curl -X GET "https://<mgmt-ip>/api/network/ip/service-policies/e0889ce6-  
1e6a-11e9-89d6-005056bbdc04?fields=name,scope,svm.name,ipspace.name" -H  
"accept: application/hal+json"  
  
# The response:  
{  
  "uuid": "e0889ce6-1e6a-11e9-89d6-005056bbdc04",  
  "name": "test_policy",  
  "scope": "svm",  
  "svm": {  
    "name": "vs0",  
  },  
  "ipspace": {  
    "name": "Default",  
  },  
  "_links": {  
    "self": {  
      "href": "/api/network/ip/service-policies/e0889ce6-1e6a-11e9-89d6-  
005056bbdc04"  
    }  
  }  
}
```

#### **Retrieving a specific service policy (scope=cluster)**

The following output displays the response when a specific cluster-scoped service policy is requested. The SVM object is not included for cluster-scoped service policies. A service policy with a scope of "cluster" is associated with an IPspace. The system returns an error when there is no service policy with the requested UUID.

```

# The API:
/api/network/ip/service-policies/{uuid}

# The call:
curl -X GET "https://<mgmt-ip>/api/network/ip/service-policies/4c6b72b9-
0f6c-11e9-875d-005056bb21b8?fields=*" -H "accept: application/hal+json"

# The response:
{
  "uuid": "4c6b72b9-0f6c-11e9-875d-005056bb21b8",
  "name": "net-intercluster",
  "scope": "cluster",
  "ipspace": {
    "uuid": "4051f13e-0f6c-11e9-875d-005056bb21b8",
    "name": "Default",
    "_links": {
      "self": {
        "href": "/api/network/ipspaces/4051f13e-0f6c-11e9-875d-005056bb21b8"
      }
    }
  },
  "services": [
    "intercluster_core"
  ],
  "_links": {
    "self": {
      "href": "/api/network/ip/service-policies/4c6b72b9-0f6c-11e9-875d-
005056bb21b8"
    }
  }
}

```

#### **Retrieving a specific service policy (scope=cluster) when requesting commonly used fields**

The following output displays the response when commonly used fields are requested for a specific "cluster" scoped service policy. The SVM object is not included for cluster-scoped service policies. A service policy with a scope of "cluster" is associated with an IPspace. The system returns an error when there is no service policy with the requested UUID.

```

# The API:
/api/network/ip/service-policies/{uuid}

# The call:
curl -X GET "https://<mgmt-ip>/api/network/ip/service-policies/4c6b72b9-
0f6c-11e9-875d-005056bb21b8?fields=name,scope,ipspace.name" -H "accept:
application/hal+json"

# The response:
{
  "uuid": "4c6b72b9-0f6c-11e9-875d-005056bb21b8",
  "name": "net-intercluster",
  "scope": "cluster",
  "ipspace": {
    "name": "Default",
  },
  "services": [
    "intercluster_core"
  ],
  "_links": {
    "self": {
      "href": "/api/network/ip/service-policies/4c6b72b9-0f6c-11e9-875d-
005056bb21b8"
    }
  }
}

```

## Retrieve service policies

GET /network/ip/service-policies

Retrieves a collection of service policies.

### Related ONTAP commands

- `network interface service-policy show`

### Learn more

- [DOC /network/ip/service-policies](#)

### Parameters

Name	Type	In	Required	Description
name	string	query	False	Filter by name
services	string	query	False	Filter by services
svm.uuid	string	query	False	Filter by svm.uuid
svm.name	string	query	False	Filter by svm.name
ipspace.uuid	string	query	False	Filter by ipspace.uuid
ipspace.name	string	query	False	Filter by ipspace.name
scope	string	query	False	Filter by scope
uuid	string	query	False	Filter by uuid
fields	array[string]	query	False	Specify the fields to return.
max_records	integer	query	False	Limit the number of records returned.
return_records	boolean	query	False	The default is true for GET calls. When set to false, only the number of records is returned.
return_timeout	integer	query	False	The number of seconds to allow the call to execute before returning. When iterating over a collection, the default is 15 seconds. ONTAP returns earlier if either max records or the end of the collection is reached.
order_by	array[string]	query	False	Order results by specified fields and optional [asc]

## Response

Status: 200, Ok

Name	Type	Description
_links	<a href="#">_links</a>	
num_records	integer	
records	array[ <a href="#">ip_service_policy</a> ]	

## Example response

```
{  
    "_links": {  
        "next": {  
            "href": "/api/resourcelink"  
        },  
        "self": {  
            "href": "/api/resourcelink"  
        }  
    },  
    "records": {  
        "_links": {  
            "self": {  
                "href": "/api/resourcelink"  
            }  
        },  
        "ipspace": {  
            "_links": {  
                "self": {  
                    "href": "/api/resourcelink"  
                }  
            },  
            "name": "exchange",  
            "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
        },  
        "name": "default-intercluster",  
        "scope": "svm",  
        "services": {  
        },  
        "svm": {  
            "_links": {  
                "self": {  
                    "href": "/api/resourcelink"  
                }  
            },  
            "name": "svm1",  
            "uuid": "02c9e252-41be-11e9-81d5-00a0986138f7"  
        },  
        "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
    }  
}
```

## Error

Status: Default, Error

Name	Type	Description
error	error	

### Example error

```
{  
  "error": {  
    "arguments": {  
      "code": "string",  
      "message": "string"  
    },  
    "code": "4",  
    "message": "entry doesn't exist",  
    "target": "uuid"  
  }  
}
```

## Definitions

## See Definitions

href

Name	Type	Description
href	string	

\_links

Name	Type	Description
next	href	
self	href	

\_links

Name	Type	Description
self	href	

ipspace

Applies to both SVM and cluster-scoped objects. Either the UUID or name may be supplied on input.

Name	Type	Description
_links	_links	
name	string	IPspace name
uuid	string	IPspace UUID

svm

Name	Type	Description
_links	_links	
name	string	The name of the SVM.
uuid	string	The unique identifier of the SVM.

ip\_service\_policy

Name	Type	Description
_links	_links	

Name	Type	Description
ipspace	ipspace	Applies to both SVM and cluster-scoped objects. Either the UUID or name may be supplied on input.
name	string	
scope	string	Set to "svm" for interfaces owned by an SVM. Otherwise, set to "cluster".
services	array[string]	
svm	svm	
uuid	string	

#### error\_arguments

Name	Type	Description
code	string	Argument code
message	string	Message argument

#### error

Name	Type	Description
arguments	array[error_arguments]	Message arguments
code	string	Error code
message	string	Error message
target	string	The target parameter that caused the error.

## Retrieve a service policy

GET /network/ip/service-policies/{uuid}

Retrieves a specific service policy.

### Related ONTAP commands

- network interface service-policy show

## Learn more

- [DOC /network/ip/service-policies](#)

## Parameters

Name	Type	In	Required	Description
uuid	string	path	True	Service policy UUID
fields	array[string]	query	False	Specify the fields to return.
max_records	integer	query	False	Limit the number of records returned.
return_records	boolean	query	False	The default is true for GET calls. When set to false, only the number of records is returned.
return_timeout	integer	query	False	The number of seconds to allow the call to execute before returning. When iterating over a collection, the default is 15 seconds. ONTAP returns earlier if either max records or the end of the collection is reached.
order_by	array[string]	query	False	Order results by specified fields and optional [asc

## Response

Status: 200, Ok

Name	Type	Description
_links	<a href="#">_links</a>	

Name	Type	Description
ipspace	<a href="#">ipspace</a>	Applies to both SVM and cluster-scoped objects. Either the UUID or name may be supplied on input.
name	string	
scope	string	Set to "svm" for interfaces owned by an SVM. Otherwise, set to "cluster".
services	array[string]	
svm	<a href="#">svm</a>	
uuid	string	

## Example response

```
{  
    "_links": {  
        "self": {  
            "href": "/api/resourcelink"  
        }  
    },  
    "ipspace": {  
        "_links": {  
            "self": {  
                "href": "/api/resourcelink"  
            }  
        },  
        "name": "exchange",  
        "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
    },  
    "name": "default-intercluster",  
    "scope": "svm",  
    "services": {  
    },  
    "svm": {  
        "_links": {  
            "self": {  
                "href": "/api/resourcelink"  
            }  
        },  
        "name": "svm1",  
        "uuid": "02c9e252-41be-11e9-81d5-00a0986138f7"  
    },  
    "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
}
```

## Error

Status: Default, Error

Name	Type	Description
error	error	

## Example error

```
{  
  "error": {  
    "arguments": {  
      "code": "string",  
      "message": "string"  
    },  
    "code": "4",  
    "message": "entry doesn't exist",  
    "target": "uuid"  
  }  
}
```

## Definitions

## See Definitions

href

Name	Type	Description
href	string	

\_links

Name	Type	Description
self	href	

ipspace

Applies to both SVM and cluster-scoped objects. Either the UUID or name may be supplied on input.

Name	Type	Description
_links	_links	
name	string	IPspace name
uuid	string	IPspace UUID

svm

Name	Type	Description
_links	_links	
name	string	The name of the SVM.
uuid	string	The unique identifier of the SVM.

error\_arguments

Name	Type	Description
code	string	Argument code
message	string	Message argument

error

Name	Type	Description
arguments	array[error_arguments]	Message arguments

Name	Type	Description
code	string	Error code
message	string	Error message
target	string	The target parameter that caused the error.

# Manage network IPspaces

## Network ipspaces endpoint overview

### Overview

An IPspace is an addressing domain within which each IP address is unique. The same address may appear in a different IPspace, but the matching addresses are considered to be distinct. SVMs and broadcast domains, and therefore IP interfaces and Ethernet ports, are associated with a single IPspace. This endpoint supports the following operations: GET (collection and instance), POST, PATCH, and DELETE.

### Retrieving IPspace information

You can use the IPspaces GET API to retrieve all IPspaces configured in the cluster, including built-in and custom IPspaces, and specifically requested IPspaces.

### Examples

#### Retrieving a list of the IPspaces in the cluster

The following example returns the requested list of IPspaces configured in the cluster.

```
# The API:  
/api/network/ipspaces  
  
# The call:  
curl -X GET "https://<mgmt-ip>/api/network/ipspaces?fields=*" -H "accept: application/hal+json"  
  
# The response:  
{  
  "records": [  
    {  
      "uuid": "dcc7e79c-5acc-11e8-b9de-005056b42b32",  
      "name": "Default",  
      "_links": {  
        "self": {  
          "href": "/api/network/ipspaces/dcc7e79c-5acc-11e8-b9de-
```

```

005056b42b32"
    }
}
},
{
  "uuid": "dfd3c1b2-5acc-11e8-b9de-005056b42b32",
  "name": "Cluster",
  "_links": {
    "self": {
      "href": "/api/network/ipspaces/dfd3c1b2-5acc-11e8-b9de-
005056b42b32"
    }
  }
},
{
  "uuid": "dedec1be-5aec-1eee-beee-0eee56be2b3e",
  "name": "Ipspace1",
  "_links": {
    "self": {
      "href": "/api/network/ipspaces/dedec1be-5aec-1eee-beee-
0eee56be2b3e"
    }
  }
}
],
"num_records": 3,
"_links": {
  "self": {
    "href": "/api/network/ipspaces?fields=*"
  }
}
}

```

#### **Retrieving a specific IPspace in the cluster**

The following example returns the specific IPspace requested. The system returns an error if there is no IPspace with the requested UUID.

```
# The API:  
/api/network/ipspaces/{uuid}  
  
# The call:  
curl -X GET "https://<mgmt-ip>/api/network/ipspaces/dfd3c1b2-5acc-11e8-  
b9de-005056b42b32?fields=*" -H "accept: application/hal+json"  
  
# The response:  
{  
    "uuid": "dcc7e79c-5acc-11e8-b9de-005056b42b32",  
    "name": "Default",  
    "_links": {  
        "self": {  
            "href": "/api/network/ipspaces/dcc7e79c-5acc-11e8-b9de-005056b42b32"  
        }  
    }  
}
```

## Creating IPspaces

You can use the network IPspaces POST API to create IPspaces.

## Example

### Creating an IPspace

The following output displays the record returned after the creation of an IPspace with the name "ipspace1".

```

# The API:
/api/network/ipspaces

# The call:
curl -X POST "https://<mgmt-ip>/api/network/ipspaces?return_records=true"
-H "accept: application/hal+json" -d "{  \"name\": \"ipspace2\"}"

# The response:
{
  "num_records": 1,
  "records": [
    {
      "uuid": "4165655e-0528-11e9-bd68-005056bb046a",
      "name": "ipspace2",
      "_links": {
        "self": {
          "href": "/api/network/ipspaces/4165655e-0528-11e9-bd68-
005056bb046a"
        }
      }
    }
  ]
}

```

## Updating IPspaces

You can use the IPspaces PATCH API to update the attributes of the IPspace.

---

### Example

#### Updating the name of an IPspace

The following PATCH request is used to update the name of the IPspace from "ipspace2" to "ipspace20".

```
# The API:  
/api/network/ipspaces/{uuid}  
  
# The call:  
curl -X PATCH "https://<mgmt-ip>/api/network/ipspaces/4165655e-0528-11e9-  
bd68-005056bb046a" -H "accept: application/hal+json" -d "{ \"name\":  
\"ipspace20\"}"
```

## Deleting IPspaces

You can use the IPspaces DELETE API to delete an IPspace.

## Example

### Deleting an IPspace

The following DELETE request is used to delete an IPspace.

```
# The API:  
/api/network/ipspaces/{uuid}  
  
# The call:  
curl -X DELETE "https://<mgmt-ip>/api/network/ipspaces/4165655e-0528-11e9-  
bd68-005056bb046a" -H "accept: application/hal+json" -H "Content-Type:  
application/json"
```

## Retrieve IPspaces for a cluster

GET /network/ipspaces

Retrieves a collection of IPspaces for the entire cluster.

## Related ONTAP commands

- `network ipspace show`

## Learn more

- [DOC /network/ipspaces](#)

## Parameters

Name	Type	In	Required	Description
name	string	query	False	Filter by name
uuid	string	query	False	Filter by uuid
fields	array[string]	query	False	Specify the fields to return.
max_records	integer	query	False	Limit the number of records returned.
return_records	boolean	query	False	The default is true for GET calls. When set to false, only the number of records is returned.
return_timeout	integer	query	False	The number of seconds to allow the call to execute before returning. When iterating over a collection, the default is 15 seconds. ONTAP returns earlier if either max records or the end of the collection is reached.
order_by	array[string]	query	False	Order results by specified fields and optional [asc]

## Response

Status: 200, Ok

Name	Type	Description
_links	<a href="#">_links</a>	
num_records	integer	
records	array[ <a href="#">ipspace</a> ]	

## Example response

```
{  
  "_links": {  
    "next": {  
      "href": "/api/resourcelink"  
    },  
    "self": {  
      "href": "/api/resourcelink"  
    }  
  },  
  "num_records": 1,  
  "records": {  
    "_links": {  
      "self": {  
        "href": "/api/resourcelink"  
      }  
    },  
    "name": "ipspacel",  
    "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
  }  
}
```

## Error

Status: Default, Error

Name	Type	Description
error	error	

## Example error

```
{  
  "error": {  
    "arguments": {  
      "code": "string",  
      "message": "string"  
    },  
    "code": "4",  
    "message": "entry doesn't exist",  
    "target": "uuid"  
  }  
}
```

## Definitions

## See Definitions

href

Name	Type	Description
href	string	

\_links

Name	Type	Description
next	href	
self	href	

\_links

Name	Type	Description
self	href	

ipspace

Name	Type	Description
_links	_links	
name	string	IPspace name
uuid	string	The UUID that uniquely identifies the IPspace.

error\_arguments

Name	Type	Description
code	string	Argument code
message	string	Message argument

error

Name	Type	Description
arguments	array[error_arguments]	Message arguments
code	string	Error code
message	string	Error message

Name	Type	Description
target	string	The target parameter that caused the error.

## Create a new domain with unique IP addresses

POST /network/ipspaces

Creates a new domain within which IP addresses are unique. SVMs, ports, and networks are scoped to a single IPspace.

### Required properties

- name - Name of the IPspace to create.

### Related ONTAP commands

- `network ipspace create`

### Learn more

- [DOC /network/ipspaces](#)

### Parameters

Name	Type	In	Required	Description
return_records	boolean	query	False	The default is false. If set to true, the records are returned.

### Request Body

Name	Type	Description
_links	<a href="#">_links</a>	
name	string	IPspace name
uuid	string	The UUID that uniquely identifies the IPspace.

## Example request

```
{  
  "_links": {  
    "self": {  
      "href": "/api/resourcelink"  
    }  
  },  
  "name": "ipspace1",  
  "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
}
```

## Response

Status: 201, Created

## Error

Status: Default

### ONTAP Error Response Codes

Error Code	Description
1967102	A POST operation might have left the configuration in an inconsistent state. Check the configuration.

### ONTAP Error Response Codes

Error Code	Description
9240591	The name is not valid. The name is already in use by a cluster node, Vserver, or it is the name of the local cluster.

Name	Type	Description
error	error	

## Example error

```
{  
  "error": {  
    "arguments": {  
      "code": "string",  
      "message": "string"  
    },  
    "code": "4",  
    "message": "entry doesn't exist",  
    "target": "uuid"  
  }  
}
```

## Definitions

## See Definitions

href

Name	Type	Description
href	string	

\_links

Name	Type	Description
self	href	

ipspace

Name	Type	Description
_links	_links	
name	string	IPspace name
uuid	string	The UUID that uniquely identifies the IPspace.

error\_arguments

Name	Type	Description
code	string	Argument code
message	string	Message argument

error

Name	Type	Description
arguments	array[error_arguments]	Message arguments
code	string	Error code
message	string	Error message
target	string	The target parameter that caused the error.

## Delete an IPspace object

`DELETE /network/ipspaces/{uuid}`

Deletes an IPspace object.

### Related ONTAP commands

- `network ipspace delete`

### Learn more

- [DOC /network/ipspaces](#)

### Parameters

Name	Type	In	Required	Description
uuid	string	path	True	

### Response

Status: 200, Ok

## Retrieve information about an IPspace

`GET /network/ipspaces/{uuid}`

Retrieves information about a specific IPspace.

### Related ONTAP commands

- `network ipspace show`

### Learn more

- [DOC /network/ipspaces](#)

### Parameters

Name	Type	In	Required	Description
uuid	string	path	True	IPspace UUID
fields	array[string]	query	False	Specify the fields to return.

### Response

Status: 200, Ok

Name	Type	Description
_links	<a href="#">_links</a>	
name	string	IPspace name
uuid	string	The UUID that uniquely identifies the IPspace.

### Example response

```
{  
  "_links": {  
    "self": {  
      "href": "/api/resourcelink"  
    }  
  },  
  "name": "ipspace1",  
  "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
}
```

### Error

Status: Default, Error

Name	Type	Description
error	<a href="#">error</a>	

## Example error

```
{  
  "error": {  
    "arguments": {  
      "code": "string",  
      "message": "string"  
    },  
    "code": "4",  
    "message": "entry doesn't exist",  
    "target": "uuid"  
  }  
}
```

## Definitions

## See Definitions

href

Name	Type	Description
href	string	

\_links

Name	Type	Description
self	href	

error\_arguments

Name	Type	Description
code	string	Argument code
message	string	Message argument

error

Name	Type	Description
arguments	array[error_arguments]	Message arguments
code	string	Error code
message	string	Error message
target	string	The target parameter that caused the error.

## Update an IPspace object

PATCH /network/ipspaces/{uuid}

Updates an IPspace object.

### Related ONTAP commands

- `network ipspace rename`

### Learn more

- [DOC /network/ipspaces](#)

## Parameters

Name	Type	In	Required	Description
uuid	string	path	True	IPspace UUID

## Request Body

Name	Type	Description
_links	_links	
name	string	IPspace name
uuid	string	The UUID that uniquely identifies the IPspace.

## Example request

```
{
  "_links": {
    "self": {
      "href": "/api/resourcelink"
    }
  },
  "name": "ipspace1",
  "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"
}
```

## Response

```
Status: 200, Ok
```

## Definitions

## See Definitions

href

Name	Type	Description
href	string	

\_links

Name	Type	Description
self	<a href="#">href</a>	

ipspace

Name	Type	Description
_links	<a href="#">_links</a>	
name	string	IPspace name
uuid	string	The UUID that uniquely identifies the IPspace.

## **Copyright information**

Copyright © 2024 NetApp, Inc. All Rights Reserved. Printed in the U.S. No part of this document covered by copyright may be reproduced in any form or by any means—graphic, electronic, or mechanical, including photocopying, recording, taping, or storage in an electronic retrieval system—with prior written permission of the copyright owner.

Software derived from copyrighted NetApp material is subject to the following license and disclaimer:

THIS SOFTWARE IS PROVIDED BY NETAPP “AS IS” AND WITHOUT ANY EXPRESS OR IMPLIED WARRANTIES, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE, WHICH ARE HEREBY DISCLAIMED. IN NO EVENT SHALL NETAPP BE LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO, PROCUREMENT OF SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA, OR PROFITS; OR BUSINESS INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE) ARISING IN ANY WAY OUT OF THE USE OF THIS SOFTWARE, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE.

NetApp reserves the right to change any products described herein at any time, and without notice. NetApp assumes no responsibility or liability arising from the use of products described herein, except as expressly agreed to in writing by NetApp. The use or purchase of this product does not convey a license under any patent rights, trademark rights, or any other intellectual property rights of NetApp.

The product described in this manual may be protected by one or more U.S. patents, foreign patents, or pending applications.

LIMITED RIGHTS LEGEND: Use, duplication, or disclosure by the government is subject to restrictions as set forth in subparagraph (b)(3) of the Rights in Technical Data -Noncommercial Items at DFARS 252.227-7013 (FEB 2014) and FAR 52.227-19 (DEC 2007).

Data contained herein pertains to a commercial product and/or commercial service (as defined in FAR 2.101) and is proprietary to NetApp, Inc. All NetApp technical data and computer software provided under this Agreement is commercial in nature and developed solely at private expense. The U.S. Government has a non-exclusive, non-transferrable, nonsublicensable, worldwide, limited irrevocable license to use the Data only in connection with and in support of the U.S. Government contract under which the Data was delivered. Except as provided herein, the Data may not be used, disclosed, reproduced, modified, performed, or displayed without the prior written approval of NetApp, Inc. United States Government license rights for the Department of Defense are limited to those rights identified in DFARS clause 252.227-7015(b) (FEB 2014).

## **Trademark information**

NETAPP, the NETAPP logo, and the marks listed at <http://www.netapp.com/TM> are trademarks of NetApp, Inc. Other company and product names may be trademarks of their respective owners.