



# Retrieve FC port information

## REST API reference

NetApp  
February 06, 2026

This PDF was generated from [https://docs.netapp.com/us-en/ontap-restapi/network\\_fc\\_logins\\_endpoint\\_overview.html](https://docs.netapp.com/us-en/ontap-restapi/network_fc_logins_endpoint_overview.html) on February 06, 2026. Always check [docs.netapp.com](https://docs.netapp.com) for the latest.

# Table of Contents

Retrieve FC port information .....	1
Retrieve FC port information .....	1
Overview .....	1
Performance monitoring .....	1
Examples .....	1
Retrieve FC ports .....	9
Expensive properties .....	9
Related ONTAP commands .....	9
Learn more .....	9
Parameters .....	10
Response .....	15
Error .....	19
Definitions .....	19
Retrieve historical performance metrics for an FC port .....	29
Parameters .....	29
Response .....	32
Error .....	34
Definitions .....	34
Retrieve historical performance metrics for an FC port for a specific time .....	38
Parameters .....	38
Response .....	38
Error .....	40
Definitions .....	41
Retrieve an FC port .....	44
Expensive properties .....	44
Related ONTAP commands .....	44
Learn more .....	44
Parameters .....	44
Response .....	44
Error .....	49
Definitions .....	49
Update an FC port .....	57
Related ONTAP commands .....	58
Learn more .....	58
Parameters .....	58
Request Body .....	58
Response .....	60
Error .....	61
Definitions .....	61

# Retrieve FC port information

## Retrieve FC port information

### Overview

Fibre Channel (FC) ports are the physical ports of FC adapters on ONTAP cluster nodes that can be connected to FC networks to provide FC network connectivity. An FC port defines the location of an FC interface within the ONTAP cluster.

The Fibre Channel port REST API allows you to discover FC ports, obtain status information for FC ports, and configure FC port properties. POST and DELETE requests are not supported. You must physically add and remove FC adapters to ONTAP nodes to create and remove ports from the ONTAP cluster.

### Performance monitoring

Performance of an FC port can be monitored by observing the `metric.*` and `statistics.*` properties. These properties show the performance of an FC port in terms of IOPS, latency, and throughput. The `metric.*` properties denote an average, whereas `statistics.*` properties denote a real-time monotonically increasing value aggregated across all nodes.

### Examples

#### Retrieving all FC ports

```
# The API:  
GET /api/network/fc/ports  
  
# The call:  
curl -X GET "https://<mgmt-ip>/api/network/fc/ports" -H "Accept:  
application/hal+json"  
  
# The response:  
{  
  "records": [  
    {  
      "node": {  
        "name": "node1",  
        "uuid": "3c768e01-1abc-4b3b-b7c0-629ceb62a497",  
        "_links": {  
          "self": {  
            "href": "/api/cluster/nodes/3c768e01-1abc-4b3b-b7c0-  
629ceb62a497"  
          }  
        }  
      },  
      "uuid": "931b20f8-b047-11e8-9af3-005056bb838e",
```

```

  "name": "0a",
  "_links": {
    "self": {
      "href": "/api/network/fc/ports/931b20f8-b047-11e8-9af3-
005056bb838e"
    }
  }
},
{
  "node": {
    "name": "node1",
    "uuid": "3c768e01-1abc-4b3b-b7c0-629ceb62a497",
    "_links": {
      "self": {
        "href": "/api/cluster/nodes/3c768e01-1abc-4b3b-b7c0-
629ceb62a497"
      }
    }
  },
  "uuid": "931b23f7-b047-11e8-9af3-005056bb838e",
  "name": "0b",
  "_links": {
    "self": {
      "href": "/api/network/fc/ports/931b23f7-b047-11e8-9af3-
005056bb838e"
    }
  }
},
{
  "node": {
    "name": "node1",
    "uuid": "3c768e01-1abc-4b3b-b7c0-629ceb62a497",
    "_links": {
      "self": {
        "href": "/api/cluster/nodes/3c768e01-1abc-4b3b-b7c0-
629ceb62a497"
      }
    }
  },
  "uuid": "931b25ba-b047-11e8-9af3-005056bb838e",
  "name": "0c",
  "_links": {
    "self": {
      "href": "/api/network/fc/ports/931b25ba-b047-11e8-9af3-
005056bb838e"
    }
  }
}

```

```

        }
    },
    {
        "node": {
            "name": "node1",
            "uuid": "3c768e01-1abc-4b3b-b7c0-629ceb62a497",
            "_links": {
                "self": {
                    "href": "/api/cluster/nodes/3c768e01-1abc-4b3b-b7c0-629ceb62a497"
                }
            }
        },
        "uuid": "931b2748-b047-11e8-9af3-005056bb838e",
        "name": "0d",
        "_links": {
            "self": {
                "href": "/api/network/fc/ports/931b2748-b047-11e8-9af3-005056bb838e"
            }
        }
    },
    {
        "node": {
            "name": "node1",
            "uuid": "3c768e01-1abc-4b3b-b7c0-629ceb62a497",
            "_links": {
                "self": {
                    "href": "/api/cluster/nodes/3c768e01-1abc-4b3b-b7c0-629ceb62a497"
                }
            }
        },
        "uuid": "931b28c2-b047-11e8-9af3-005056bb838e",
        "name": "0e",
        "_links": {
            "self": {
                "href": "/api/network/fc/ports/931b28c2-b047-11e8-9af3-005056bb838e"
            }
        }
    },
    {
        "node": {
            "name": "node1",
            "uuid": "3c768e01-1abc-4b3b-b7c0-629ceb62a497",

```

```

    "_links": {
        "self": {
            "href": "/api/cluster/nodes/3c768e01-1abc-4b3b-b7c0-
629ceb62a497"
        }
    }
},
"uuid": "931b2a7b-b047-11e8-9af3-005056bb838e",
"name": "0f",
"_links": {
    "self": {
        "href": "/api/network/fc/ports/931b2a7b-b047-11e8-9af3-
005056bb838e"
    }
}
},
{
    "node": {
        "name": "node1",
        "uuid": "3c768e01-1abc-4b3b-b7c0-629ceb62a497",
        "_links": {
            "self": {
                "href": "/api/cluster/nodes/3c768e01-1abc-4b3b-b7c0-
629ceb62a497"
            }
        }
    },
    "uuid": "931b2e2b-b047-11e8-9af3-005056bb838e",
    "name": "1b",
    "_links": {
        "self": {
            "href": "/api/network/fc/ports/931b2e2b-b047-11e8-9af3-
005056bb838e"
        }
    }
}
],
"num_records": 8,
"_links": {
    "self": {
        "href": "/api/network/fc/ports"
    }
}
}

```

## Retrieving all FC ports with state *online*

The state query parameter is used to perform the query.

```
# The API:  
GET /api/network/fc/ports  
  
# The call:  
curl -X GET "https://<mgmt-ip>/api/network/fc/ports?state=online" -H  
"Accept: application/hal+json"  
  
# The response:  
{  
  "records": [  
    {  
      "node": {  
        "name": "node1",  
        "uuid": "3c768e01-1abc-4b3b-b7c0-629ceb62a497",  
        "_links": {  
          "self": {  
            "href": "/api/cluster/nodes/3c768e01-1abc-4b3b-b7c0-  
629ceb62a497"  
          }  
        }  
      },  
      "uuid": "931b20f8-b047-11e8-9af3-005056bb838e",  
      "name": "0a",  
      "state": "online",  
      "_links": {  
        "self": {  
          "href": "/api/network/fc/ports/931b20f8-b047-11e8-9af3-  
005056bb838e"  
        }  
      }  
    },  
    {  
      "node": {  
        "name": "node1",  
        "uuid": "3c768e01-1abc-4b3b-b7c0-629ceb62a497",  
        "_links": {  
          "self": {  
            "href": "/api/cluster/nodes/3c768e01-1abc-4b3b-b7c0-  
629ceb62a497"  
          }  
        }  
      },  
    }  
  ]  
}
```

```

"uuid": "931b23f7-b047-11e8-9af3-005056bb838e",
"name": "0b",
"state": "online",
"_links": {
  "self": {
    "href": "/api/network/fc/ports/931b23f7-b047-11e8-9af3-005056bb838e"
  }
},
{
  "node": {
    "name": "node1",
    "uuid": "3c768e01-1abc-4b3b-b7c0-629ceb62a497",
    "_links": {
      "self": {
        "href": "/api/cluster/nodes/3c768e01-1abc-4b3b-b7c0-629ceb62a497"
      }
    }
  },
  "uuid": "931b25ba-b047-11e8-9af3-005056bb838e",
  "name": "0c",
  "state": "online",
  "_links": {
    "self": {
      "href": "/api/network/fc/ports/931b25ba-b047-11e8-9af3-005056bb838e"
    }
  }
},
],
"num_records": 3,
"_links": {
  "self": {
    "href": "/api/network/fc/ports?state=online"
  }
}
}

```

## Retrieving an FC port

```

# The API:
GET /api/network/fc/ports/{uuid}

```

```

# The call:
curl -X GET "https://<mgmt-ip>/api/network/fc/ports/931b20f8-b047-11e8-
9af3-005056bb838e" -H "Accept: application/hal+json"

# The response:
{
  "node": {
    "name": "node1",
    "uuid": "5a534a72-b047-11e8-9af3-005056bb838e",
    "_links": {
      "self": {
        "href": "/api/cluster/nodes/5a534a72-b047-11e8-9af3-005056bb838e"
      }
    }
  },
  "uuid": "931b20f8-b047-11e8-9af3-005056bb838e",
  "name": "0a",
  "description": "Fibre Channel Target Adapter 0a (ACME Fibre Channel
Adapter, rev. 1.0.0, 8G)",
  "enabled": true,
  "fabric": {
    "connected": true,
    "connected_speed": 8,
    "name": "55:0e:b1:a0:20:40:80:00",
    "port_address": "52100",
    "switch_port": "ssan-g620-03:1"
  },
  "physical_protocol": "fibre_channel",
  "speed": {
    "maximum": "8",
    "configured": "auto"
  },
  "state": "online",
  "supported_protocols": [
    "fcp"
  ],
  "transceiver": {
    "form_factor": "SFP",
    "manufacturer": "ACME",
    "capabilities": [
      4,
      8
    ],
    "part_number": "1000"
  },
}

```

```
"wwnn": "50:0a:09:80:bb:83:8e:00",
"wwpn": "50:0a:09:82:bb:83:8e:00",
"metric": {
  "timestamp": "2019-04-09T05:50:15Z",
  "duration": "PT15S",
  "status": "ok",
  "latency": {
    "other": 0,
    "total": 0,
    "read": 0,
    "write": 0
  },
  "iops": {
    "read": 0,
    "write": 0,
    "other": 0,
    "total": 0
  },
  "throughput": {
    "read": 0,
    "write": 0,
    "total": 0
  }
},
"statistics": {
  "timestamp": "2019-04-09T05:50:42Z",
  "status": "ok",
  "latency_raw": {
    "other": 38298,
    "total": 38298,
    "read": 0,
    "write": 0
  },
  "iops_raw": {
    "read": 0,
    "write": 0,
    "other": 3,
    "total": 3
  },
  "throughput_raw": {
    "read": 0,
    "write": 0,
    "total": 0
  }
},
"_links": {
```

```
  "self": {
    "href": "/api/network/fc/ports/931b20f8-b047-11e8-9af3-005056bb838e"
  }
}
```

## Disabling an FC port

If an active FC interface exists on an FC port, the port cannot be disabled.

```
# The API:
PATCH /api/network/fc/ports/{uuid}

# The call:
curl -X PATCH "http://<mgmt-ip>/api/network/fc/ports/931b20f8-b047-11e8-9af3-005056bb838e" -H "Accept: application/hal+json" -d '{ "enabled": false }'
```

## Retrieve FC ports

GET /network/fc/ports

**Introduced In:** 9.6

Retrieves FC ports.

## Expensive properties

There is an added computational cost to retrieving values for these properties. They are not included by default in GET results and must be explicitly requested using the `fields` query parameter. See [Requesting specific fields](#) to learn more.

- `fabric.name`
- `statistics.*`
- `metric.*`

## Related ONTAP commands

- `network fcp adapter show`

## Learn more

- [DOC /network/fc/ports](#)

## Parameters

Name	Type	In	Required	Description
transceiver.capabilities	integer	query	False	Filter by transceiver.capabilities
transceiver.form_factor	string	query	False	Filter by transceiver.form_factor <ul style="list-style-type: none"> <li>• Introduced in: 9.8</li> </ul>
transceiver.part_number	string	query	False	Filter by transceiver.part_number
transceiver.manufacturer	string	query	False	Filter by transceiver.manufacturer
fabric.connected_speed	integer	query	False	Filter by fabric.connected_speed
fabric.switch_port	string	query	False	Filter by fabric.switch_port
fabric.connected	boolean	query	False	Filter by fabric.connected
fabric.name	string	query	False	Filter by fabric.name
fabric.port_address	string	query	False	Filter by fabric.port_address
supported_protocols	string	query	False	Filter by supported_protocols
physical_protocol	string	query	False	Filter by physical_protocol
metric.latency.other	integer	query	False	Filter by metric.latency.other <ul style="list-style-type: none"> <li>• Introduced in: 9.8</li> </ul>

Name	Type	In	Required	Description
metric.latency.total	integer	query	False	Filter by metric.latency.total <ul style="list-style-type: none"> <li>• Introduced in: 9.8</li> </ul>
metric.latency.write	integer	query	False	Filter by metric.latency.write <ul style="list-style-type: none"> <li>• Introduced in: 9.8</li> </ul>
metric.latency.read	integer	query	False	Filter by metric.latency.read <ul style="list-style-type: none"> <li>• Introduced in: 9.8</li> </ul>
metric.iops.other	integer	query	False	Filter by metric.iops.other <ul style="list-style-type: none"> <li>• Introduced in: 9.8</li> </ul>
metric.iops.total	integer	query	False	Filter by metric.iops.total <ul style="list-style-type: none"> <li>• Introduced in: 9.8</li> </ul>
metric.iops.write	integer	query	False	Filter by metric.iops.write <ul style="list-style-type: none"> <li>• Introduced in: 9.8</li> </ul>
metric.iops.read	integer	query	False	Filter by metric.iops.read <ul style="list-style-type: none"> <li>• Introduced in: 9.8</li> </ul>
metric.timestamp	string	query	False	Filter by metric.timestamp <ul style="list-style-type: none"> <li>• Introduced in: 9.8</li> </ul>

Name	Type	In	Required	Description
metric.throughput.write	integer	query	False	Filter by metric.throughput.write <ul style="list-style-type: none"> <li>• Introduced in: 9.8</li> </ul>
metric.throughput.read	integer	query	False	Filter by metric.throughput.read <ul style="list-style-type: none"> <li>• Introduced in: 9.8</li> </ul>
metric.throughput.total	integer	query	False	Filter by metric.throughput.total <ul style="list-style-type: none"> <li>• Introduced in: 9.8</li> </ul>
metric.duration	string	query	False	Filter by metric.duration <ul style="list-style-type: none"> <li>• Introduced in: 9.8</li> </ul>
metric.status	string	query	False	Filter by metric.status <ul style="list-style-type: none"> <li>• Introduced in: 9.8</li> </ul>
interface_count	integer	query	False	Filter by interface_count <ul style="list-style-type: none"> <li>• Introduced in: 9.10</li> </ul>
uuid	string	query	False	Filter by uuid
wwnn	string	query	False	Filter by wwnn
statistics.latency_raw.other	integer	query	False	Filter by statistics.latency_raw.other <ul style="list-style-type: none"> <li>• Introduced in: 9.8</li> </ul>

Name	Type	In	Required	Description
statistics.latency_rw.total	integer	query	False	Filter by statistics.latency_rw.total <ul style="list-style-type: none"> <li>• Introduced in: 9.8</li> </ul>
statistics.latency_rw.write	integer	query	False	Filter by statistics.latency_rw.write <ul style="list-style-type: none"> <li>• Introduced in: 9.8</li> </ul>
statistics.latency_rw.read	integer	query	False	Filter by statistics.latency_rw.read <ul style="list-style-type: none"> <li>• Introduced in: 9.8</li> </ul>
statistics.iops_raw.other	integer	query	False	Filter by statistics.iops_raw.other <ul style="list-style-type: none"> <li>• Introduced in: 9.8</li> </ul>
statistics.iops_raw.total	integer	query	False	Filter by statistics.iops_raw.total <ul style="list-style-type: none"> <li>• Introduced in: 9.8</li> </ul>
statistics.iops_raw.write	integer	query	False	Filter by statistics.iops_raw.write <ul style="list-style-type: none"> <li>• Introduced in: 9.8</li> </ul>
statistics.iops_raw.read	integer	query	False	Filter by statistics.iops_raw.read <ul style="list-style-type: none"> <li>• Introduced in: 9.8</li> </ul>

Name	Type	In	Required	Description
statistics.throughput._raw.write	integer	query	False	Filter by statistics.throughput._raw.write <ul style="list-style-type: none"> <li>• Introduced in: 9.8</li> </ul>
statistics.throughput._raw.read	integer	query	False	Filter by statistics.throughput._raw.read <ul style="list-style-type: none"> <li>• Introduced in: 9.8</li> </ul>
statistics.throughput._raw.total	integer	query	False	Filter by statistics.throughput._raw.total <ul style="list-style-type: none"> <li>• Introduced in: 9.8</li> </ul>
statistics.status	string	query	False	Filter by statistics.status <ul style="list-style-type: none"> <li>• Introduced in: 9.8</li> </ul>
statistics.timestamp	string	query	False	Filter by statistics.timestamp <ul style="list-style-type: none"> <li>• Introduced in: 9.8</li> </ul>
description	string	query	False	Filter by description
speed.maximum	string	query	False	Filter by speed.maximum
speed.configured	string	query	False	Filter by speed.configured
name	string	query	False	Filter by name
state	string	query	False	Filter by state
enabled	boolean	query	False	Filter by enabled

Name	Type	In	Required	Description
wwpn	string	query	False	Filter by wwpn
node.name	string	query	False	Filter by node.name
node.uuid	string	query	False	Filter by node.uuid
fields	array[string]	query	False	Specify the fields to return.
max_records	integer	query	False	Limit the number of records returned.
return_records	boolean	query	False	<p>The default is true for GET calls. When set to false, only the number of records is returned.</p> <ul style="list-style-type: none"> <li>Default value: 1</li> </ul>
return_timeout	integer	query	False	<p>The number of seconds to allow the call to execute before returning. When iterating over a collection, the default is 15 seconds. ONTAP returns earlier if either max records or the end of the collection is reached.</p> <ul style="list-style-type: none"> <li>Default value: 15</li> <li>Max value: 120</li> <li>Min value: 0</li> </ul>
order_by	array[string]	query	False	Order results by specified fields and optional [asc

## Response

Status: 200, Ok

Name	Type	Description
_links	<a href="#">_links</a>	
num_records	integer	The number of records in the response.
records	array[ <a href="#">fc_port</a> ]	

## Example response

```
{  
  "_links": {  
    "next": {  
      "href": "/api/resourcelink"  
    },  
    "self": {  
      "href": "/api/resourcelink"  
    }  
  },  
  "num_records": 1,  
  "records": [  
    {  
      "_links": {  
        "self": {  
          "href": "/api/resourcelink"  
        }  
      },  
      "description": "Fibre Channel Target Adapter 0a (ACME Fibre  
Channel Adapter, rev. 1.0.0, 8G)",  
      "fabric": {  
        "connected_speed": 16,  
        "name": "string",  
        "port_address": "52100A",  
        "switch_port": "ssan-g620-03:33"  
      },  
      "interface_count": 0,  
      "metric": {  
        "_links": {  
          "self": {  
            "href": "/api/resourcelink"  
          }  
        },  
        "duration": "PT15S",  
        "iops": {  
          "read": 200,  
          "total": 1000,  
          "write": 100  
        },  
        "latency": {  
          "read": 200,  
          "total": 1000,  
          "write": 100  
        },  
        "status": "ok",  
        "value": 1000  
      }  
    }  
  ]  
}
```

```

"throughput": {
    "read": 200,
    "total": 1000,
    "write": 100
},
"timestamp": "2017-01-25 11:20:13 +0000"
},
"name": "0a",
"node": {
    "_links": {
        "self": {
            "href": "/api/resourcelink"
        }
    },
    "name": "node1",
    "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"
},
"physical_protocol": "string",
"speed": {
    "configured": "auto",
    "maximum": "32"
},
"state": "online",
"statistics": {
    "iops_raw": {
        "read": 200,
        "total": 1000,
        "write": 100
    },
    "latency_raw": {
        "read": 200,
        "total": 1000,
        "write": 100
    },
    "status": "ok",
    "throughput_raw": {
        "read": 200,
        "total": 1000,
        "write": 100
    },
    "timestamp": "2017-01-25 11:20:13 +0000"
},
"supported_protocols": [
    "string"
],
"transceiver": {

```

```

"capabilities": [
  16
],
"form_factor": "string",
"manufacturer": "Acme, Inc.",
"part_number": "string"
},
"uuid": "1cd8a442-86d1-11e0-ae1c-123478563412",
"wwnn": "20:00:00:50:56:b4:13:a8",
"wwpn": "20:00:00:50:56:b4:13:a8"
}
]
}

```

## Error

Status: Default, Error

Name	Type	Description
error	returned_error	

### Example error

```

{
  "error": {
    "arguments": [
      {
        "code": "string",
        "message": "string"
      }
    ],
    "code": "4",
    "message": "entry doesn't exist",
    "target": "uuid"
  }
}

```

## Definitions

## See Definitions

href

Name	Type	Description
href	string	

\_links

Name	Type	Description
next	<a href="#">href</a>	
self	<a href="#">href</a>	

\_links

Name	Type	Description
self	<a href="#">href</a>	

fabric

Properties of the fabric to which the FC port is attached.

Name	Type	Description
connected	boolean	Reports if the physical port has established a connection with the FC fabric.
connected_speed	integer	The negotiated data rate between the target FC port and the fabric in gigabits per second.
name	string	<p>The name of the fabric to which the port is connected. This is only available when the FC port is connected to a fabric.</p> <p>There is an added computational cost to retrieving this property's value. It is not populated for a GET request unless it is explicitly requested using the <code>fields</code> query parameter. See <a href="#">Requesting specific fields</a> to learn more.</p>

Name	Type	Description
port_address	string	<p>The FC port address of the host bus adapter (HBA) physical port.</p> <p>Each FC port in an FC switched fabric has its own unique FC port address for routing purposes. The FC port address is assigned by a switch in the fabric when that port logs in to the fabric. This property refers to the FC port address given to the physical host bus adapter (HBA) port when the port performs a fabric login (FLOGI).</p> <p>This is useful for obtaining statistics and diagnostic information from FC switches.</p> <p>This is a six-digit hexadecimal encoded numeric value.</p>
switch_port	string	The switch port to which the FC port is connected.

## iops

The rate of I/O operations observed at the storage object.

Name	Type	Description
other	integer	Performance metric for other I/O operations. Other I/O operations can be metadata operations, such as directory lookups and so on.
read	integer	Performance metric for read I/O operations.
total	integer	Performance metric aggregated over all types of I/O operations.
write	integer	Performance metric for write I/O operations.

## latency

The round trip latency in microseconds observed at the storage object.

Name	Type	Description
other	integer	Performance metric for other I/O operations. Other I/O operations can be metadata operations, such as directory lookups and so on.
read	integer	Performance metric for read I/O operations.
total	integer	Performance metric aggregated over all types of I/O operations.
write	integer	Performance metric for write I/O operations.

## throughput

The rate of throughput bytes per second observed at the storage object.

Name	Type	Description
read	integer	Performance metric for read I/O operations.
total	integer	Performance metric aggregated over all types of I/O operations.
write	integer	Performance metric for write I/O operations.

## metric

Performance numbers, such as IOPS latency and throughput

Name	Type	Description
_links	<a href="#">_links</a>	
duration	string	The duration over which this sample is calculated. The time durations are represented in the ISO-8601 standard format. Samples can be calculated over the following durations:
iops	<a href="#">iops</a>	The rate of I/O operations observed at the storage object.

Name	Type	Description
latency	latency	The round trip latency in microseconds observed at the storage object.
status	string	Any errors associated with the sample. For example, if the aggregation of data over multiple nodes fails then any of the partial errors might be returned, "ok" on success, or "error" on any internal uncategorized failure. Whenever a sample collection is missed but done at a later time, it is back filled to the previous 15 second timestamp and tagged with "backfilled_data". "Inconsistent_delta_time" is encountered when the time between two collections is not the same for all nodes. Therefore, the aggregated value might be over or under inflated. "Negative_delta" is returned when an expected monotonically increasing value has decreased in value. "Inconsistent_old_data" is returned when one or more nodes do not have the latest data.
throughput	throughput	The rate of throughput bytes per second observed at the storage object.
timestamp	string	The timestamp of the performance data.

## node

Name	Type	Description
_links	_links	
name	string	
uuid	string	

## speed

The physical device speed related properties of the FC port.

Name	Type	Description
configured	string	The configured speed of the FC port in gigabits per second.
maximum	string	The maximum speed supported by the FC port in gigabits per second.

#### iops\_raw

The number of I/O operations observed at the storage object. This should be used along with delta time to calculate the rate of I/O operations per unit of time.

Name	Type	Description
other	integer	Performance metric for other I/O operations. Other I/O operations can be metadata operations, such as directory lookups and so on.
read	integer	Performance metric for read I/O operations.
total	integer	Performance metric aggregated over all types of I/O operations.
write	integer	Performance metric for write I/O operations.

#### latency\_raw

The raw latency in microseconds observed at the storage object. This should be divided by the raw IOPS value to calculate the average latency per I/O operation.

Name	Type	Description
other	integer	Performance metric for other I/O operations. Other I/O operations can be metadata operations, such as directory lookups and so on.
read	integer	Performance metric for read I/O operations.
total	integer	Performance metric aggregated over all types of I/O operations.

Name	Type	Description
write	integer	Performance metric for write I/O operations.

### throughput\_raw

Throughput bytes observed at the storage object. This should be used along with delta time to calculate the rate of throughput bytes per unit of time.

Name	Type	Description
read	integer	Performance metric for read I/O operations.
total	integer	Performance metric aggregated over all types of I/O operations.
write	integer	Performance metric for write I/O operations.

### statistics

These are raw performance numbers, such as IOPS latency and throughput. These numbers are aggregated across all nodes in the cluster and increase with the uptime of the cluster.

Name	Type	Description
iops_raw	iops_raw	The number of I/O operations observed at the storage object. This should be used along with delta time to calculate the rate of I/O operations per unit of time.
latency_raw	latency_raw	The raw latency in microseconds observed at the storage object. This should be divided by the raw IOPS value to calculate the average latency per I/O operation.

Name	Type	Description
status	string	<p>Any errors associated with the sample. For example, if the aggregation of data over multiple nodes fails then any of the partial errors might be returned, "ok" on success, or "error" on any internal uncategorized failure. Whenever a sample collection is missed but done at a later time, it is back filled to the previous 15 second timestamp and tagged with "backfilled_data".</p> <p>"Inconsistent_delta_time" is encountered when the time between two collections is not the same for all nodes. Therefore, the aggregated value might be over or under inflated.</p> <p>"Negative_delta" is returned when an expected monotonically increasing value has decreased in value. "Inconsistent_old_data" is returned when one or more nodes do not have the latest data.</p>
throughput_raw	<a href="#">throughput_raw</a>	Throughput bytes observed at the storage object. This should be used along with delta time to calculate the rate of throughput bytes per unit of time.
timestamp	string	The timestamp of the performance data.

## transceiver

Properties of the transceiver connected to the FC port.

Name	Type	Description
capabilities	array[integer]	The speeds of which the transceiver is capable in gigabits per second.

Name	Type	Description
form_factor	string	<p>The form factor of the transceiver. Possible values are:</p> <ul style="list-style-type: none"> <li><i>sfp</i> - Small Form Factor - Pluggable</li> <li><i>sff</i> - Small Form Factor</li> <li><i>unknown</i> - Unknown</li> </ul>
manufacturer	string	The manufacturer of the transceiver.
part_number	string	The part number of the transceiver.

## fc\_port

A Fibre Channel (FC) port is the physical port of an FC adapter on an ONTAP cluster node that can be connected to an FC network to provide FC network connectivity. An FC port defines the location of an FC interface within the ONTAP cluster.

Name	Type	Description
_links	<a href="#">_links</a>	
description	string	A description of the FC port.
enabled	boolean	The administrative state of the FC port. If this property is set to <i>false</i> , all FC connectivity to FC interfaces are blocked. Optional in PATCH.
fabric	<a href="#">fabric</a>	Properties of the fabric to which the FC port is attached.
interface_count	integer	The number of FC interfaces currently provisioned on this port. This property is not supported in an SVM context.
metric	<a href="#">metric</a>	Performance numbers, such as IOPS latency and throughput
name	string	The FC port name.
node	<a href="#">node</a>	

Name	Type	Description
physical_protocol	string	The physical network protocol of the FC port.
speed	<a href="#">speed</a>	The physical device speed related properties of the FC port.
state	string	<p>The operational state of the FC port.</p> <ul style="list-style-type: none"> <li>• startup - The port is booting up.</li> <li>• link_not_connected - The port has finished initialization, but a link with the fabric is not established.</li> <li>• online - The port is initialized and a link with the fabric has been established.</li> <li>• link_disconnected - The link was present at one point on this port but is currently not established.</li> <li>• offlined_by_user - The port is administratively disabled.</li> <li>• offlined_by_system - The port is set to offline by the system. This happens when the port encounters too many errors.</li> <li>• node_offline - The state information for the port cannot be retrieved. The node is offline or inaccessible.</li> </ul>
statistics	<a href="#">statistics</a>	These are raw performance numbers, such as IOPS latency and throughput. These numbers are aggregated across all nodes in the cluster and increase with the uptime of the cluster.
supported_protocols	array[string]	The network protocols supported by the FC port.
transceiver	<a href="#">transceiver</a>	Properties of the transceiver connected to the FC port.

Name	Type	Description
uuid	string	The unique identifier of the FC port.
wwnn	string	The base world wide node name (WWNN) for the FC port.
wwpn	string	The base world wide port name (WWPN) for the FC port.

error\_arguments

Name	Type	Description
code	string	Argument code
message	string	Message argument

returned\_error

Name	Type	Description
arguments	array[error_arguments]	Message arguments
code	string	Error code
message	string	Error message
target	string	The target parameter that caused the error.

## Retrieve historical performance metrics for an FC port

GET /network/fc/ports/{fc\_port.uuid}/metrics

**Introduced In:** 9.14

Retrieves historical performance metrics for a Fibre Channel port.

### Parameters

Name	Type	In	Required	Description
iops.other	integer	query	False	Filter by iops.other

Name	Type	In	Required	Description
iops.total	integer	query	False	Filter by iops.total
iops.write	integer	query	False	Filter by iops.write
iops.read	integer	query	False	Filter by iops.read
latency.other	integer	query	False	Filter by latency.other
latency.total	integer	query	False	Filter by latency.total
latency.write	integer	query	False	Filter by latency.write
latency.read	integer	query	False	Filter by latency.read
timestamp	string	query	False	Filter by timestamp
throughput.write	integer	query	False	Filter by throughput.write
throughput.read	integer	query	False	Filter by throughput.read
throughput.total	integer	query	False	Filter by throughput.total
status	string	query	False	Filter by status
uuid	string	query	False	Filter by uuid
duration	string	query	False	Filter by duration
fc_port.uuid	string	path	True	The unique identifier of the Fibre Channel port.

Name	Type	In	Required	Description
interval	string	query	False	<p>The time range for the data. Examples can be 1h, 1d, 1m, 1w, 1y. The period for each time range is as follows:</p> <ul style="list-style-type: none"> <li>• 1h: Metrics over the most recent hour sampled over 15 seconds.</li> <li>• 1d: Metrics over the most recent day sampled over 5 minutes.</li> <li>• 1w: Metrics over the most recent week sampled over 30 minutes.</li> <li>• 1m: Metrics over the most recent month sampled over 2 hours.</li> <li>• 1y: Metrics over the most recent year sampled over a day.</li> <li>• Default value: 1</li> <li>• enum: ["1h", "1d", "1w", "1m", "1y"]</li> </ul>

Name	Type	In	Required	Description
return_timeout	integer	query	False	<p>The number of seconds to allow the call to execute before returning. When iterating over a collection, the default is 15 seconds. ONTAP returns earlier if either max records or the end of the collection is reached.</p> <ul style="list-style-type: none"> <li>• Default value: 15</li> <li>• Max value: 120</li> <li>• Min value: 0</li> </ul>
fields	array[string]	query	False	Specify the fields to return.
max_records	integer	query	False	Limit the number of records returned.
order_by	array[string]	query	False	Order results by specified fields and optional [asc]
desc] direction. Default direction is 'asc' for ascending.	return_records	boolean	query	False

## Response

Status: 200, Ok

Name	Type	Description
_links	<a href="#">_links</a>	
num_records	integer	Number of records
records	array[records]	

## Example response

```
{  
  "_links": {  
    "next": {  
      "href": "/api/resourcelink"  
    },  
    "self": {  
      "href": "/api/resourcelink"  
    }  
  },  
  "num_records": 1,  
  "records": [  
    {  
      "_links": {  
        "self": {  
          "href": "/api/resourcelink"  
        }  
      },  
      "duration": "PT15S",  
      "iops": {  
        "read": 200,  
        "total": 1000,  
        "write": 100  
      },  
      "latency": {  
        "read": 200,  
        "total": 1000,  
        "write": 100  
      },  
      "status": "ok",  
      "throughput": {  
        "read": 200,  
        "total": 1000,  
        "write": 100  
      },  
      "timestamp": "2017-01-25 11:20:13 +0000",  
      "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
    }  
  ]  
}
```

## Error

Status: Default

### ONTAP Error Response Codes

Error Code	Description
8585947	No metrics are available for the requested object.
8586225	An unexpected error occurred retrieving metrics for the requested object.

Also see the table of common errors in the [Response body](#) overview section of this documentation.

Name	Type	Description
error	<a href="#">returned_error</a>	

### Example error

```
{  
  "error": {  
    "arguments": [  
      {  
        "code": "string",  
        "message": "string"  
      }  
    ],  
    "code": "4",  
    "message": "entry doesn't exist",  
    "target": "uuid"  
  }  
}
```

## Definitions

## See Definitions

href

Name	Type	Description
href	string	

\_links

Name	Type	Description
next	<a href="#">href</a>	
self	<a href="#">href</a>	

\_links

Name	Type	Description
self	<a href="#">href</a>	

iops

The rate of I/O operations observed at the storage object.

Name	Type	Description
other	integer	Performance metric for other I/O operations. Other I/O operations can be metadata operations, such as directory lookups and so on.
read	integer	Performance metric for read I/O operations.
total	integer	Performance metric aggregated over all types of I/O operations.
write	integer	Performance metric for write I/O operations.

latency

The round trip latency in microseconds observed at the storage object.

Name	Type	Description
other	integer	Performance metric for other I/O operations. Other I/O operations can be metadata operations, such as directory lookups and so on.
read	integer	Performance metric for read I/O operations.
total	integer	Performance metric aggregated over all types of I/O operations.
write	integer	Performance metric for write I/O operations.

## throughput

The rate of throughput bytes per second observed at the storage object.

Name	Type	Description
read	integer	Performance metric for read I/O operations.
total	integer	Performance metric aggregated over all types of I/O operations.
write	integer	Performance metric for write I/O operations.

## records

Performance numbers, such as IOPS latency and throughput

Name	Type	Description
_links	<a href="#">_links</a>	
duration	string	The duration over which this sample is calculated. The time durations are represented in the ISO-8601 standard format. Samples can be calculated over the following durations:
iops	<a href="#">iops</a>	The rate of I/O operations observed at the storage object.

Name	Type	Description
latency	latency	The round trip latency in microseconds observed at the storage object.
status	string	Any errors associated with the sample. For example, if the aggregation of data over multiple nodes fails then any of the partial errors might be returned, "ok" on success, or "error" on any internal uncategorized failure. Whenever a sample collection is missed but done at a later time, it is back filled to the previous 15 second timestamp and tagged with "backfilled_data". "Inconsistent_delta_time" is encountered when the time between two collections is not the same for all nodes. Therefore, the aggregated value might be over or under inflated. "Negative_delta" is returned when an expected monotonically increasing value has decreased in value. "Inconsistent_old_data" is returned when one or more nodes do not have the latest data.
throughput	throughput	The rate of throughput bytes per second observed at the storage object.
timestamp	string	The timestamp of the performance data.
uuid	string	The unique identifier of the FC port.

#### error\_arguments

Name	Type	Description
code	string	Argument code
message	string	Message argument

#### returned\_error

Name	Type	Description
arguments	array[error_arguments]	Message arguments
code	string	Error code
message	string	Error message
target	string	The target parameter that caused the error.

## Retrieve historical performance metrics for an FC port for a specific time

GET /network/fc/ports/{fc\_port.uuid}/metrics/{timestamp}

**Introduced In:** 9.14

Retrieves historical performance metrics for a Fibre Channel port for a specific time.

### Parameters

Name	Type	In	Required	Description
fc_port.uuid	string	path	True	The unique identifier of the Fibre Channel port.
timestamp	string	path	True	The timestamp of the performance data. <ul style="list-style-type: none"> <li>format: date-time</li> </ul>
fields	array[string]	query	False	Specify the fields to return.

### Response

Status: 200, Ok

Name	Type	Description
_links	_links	

Name	Type	Description
duration	string	The duration over which this sample is calculated. The time durations are represented in the ISO-8601 standard format. Samples can be calculated over the following durations:
iops	<a href="#">iops</a>	The rate of I/O operations observed at the storage object.
latency	<a href="#">latency</a>	The round trip latency in microseconds observed at the storage object.
status	string	Any errors associated with the sample. For example, if the aggregation of data over multiple nodes fails then any of the partial errors might be returned, "ok" on success, or "error" on any internal uncategorized failure. Whenever a sample collection is missed but done at a later time, it is back filled to the previous 15 second timestamp and tagged with "backfilled_data". "Inconsistent_delta_time" is encountered when the time between two collections is not the same for all nodes. Therefore, the aggregated value might be over or under inflated. "Negative_delta" is returned when an expected monotonically increasing value has decreased in value. "Inconsistent_old_data" is returned when one or more nodes do not have the latest data.
throughput	<a href="#">throughput</a>	The rate of throughput bytes per second observed at the storage object.
timestamp	string	The timestamp of the performance data.
uuid	string	The unique identifier of the FC port.

## Example response

```
{  
  "_links": {  
    "self": {  
      "href": "/api/resourcelink"  
    }  
  },  
  "duration": "PT15S",  
  "iops": {  
    "read": 200,  
    "total": 1000,  
    "write": 100  
  },  
  "latency": {  
    "read": 200,  
    "total": 1000,  
    "write": 100  
  },  
  "status": "ok",  
  "throughput": {  
    "read": 200,  
    "total": 1000,  
    "write": 100  
  },  
  "timestamp": "2017-01-25 11:20:13 +0000",  
  "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
}
```

## Error

Status: Default

### ONTAP Error Response Codes

Error Code	Description
8585947	No metrics are available for the requested object.
8586225	An unexpected error occurred retrieving metrics for the requested object.

Also see the table of common errors in the [Response body](#) overview section of this documentation.

Name	Type	Description
error	returned_error	

## Example error

```
{  
  "error": {  
    "arguments": [  
      {  
        "code": "string",  
        "message": "string"  
      }  
    ],  
    "code": "4",  
    "message": "entry doesn't exist",  
    "target": "uuid"  
  }  
}
```

## Definitions

## See Definitions

href

Name	Type	Description
href	string	

\_links

Name	Type	Description
self	href	

iops

The rate of I/O operations observed at the storage object.

Name	Type	Description
other	integer	Performance metric for other I/O operations. Other I/O operations can be metadata operations, such as directory lookups and so on.
read	integer	Performance metric for read I/O operations.
total	integer	Performance metric aggregated over all types of I/O operations.
write	integer	Performance metric for write I/O operations.

latency

The round trip latency in microseconds observed at the storage object.

Name	Type	Description
other	integer	Performance metric for other I/O operations. Other I/O operations can be metadata operations, such as directory lookups and so on.
read	integer	Performance metric for read I/O operations.

Name	Type	Description
total	integer	Performance metric aggregated over all types of I/O operations.
write	integer	Performance metric for write I/O operations.

### throughput

The rate of throughput bytes per second observed at the storage object.

Name	Type	Description
read	integer	Performance metric for read I/O operations.
total	integer	Performance metric aggregated over all types of I/O operations.
write	integer	Performance metric for write I/O operations.

### error\_arguments

Name	Type	Description
code	string	Argument code
message	string	Message argument

### returned\_error

Name	Type	Description
arguments	array[error_arguments]	Message arguments
code	string	Error code
message	string	Error message
target	string	The target parameter that caused the error.

# Retrieve an FC port

GET /network/fc/ports/{uuid}

**Introduced In:** 9.6

Retrieves an FC port.

## Expensive properties

There is an added computational cost to retrieving values for these properties. They are not included by default in GET results and must be explicitly requested using the `fields` query parameter. See [Requesting specific fields](#) to learn more.

- `fabric.name`
- `statistics.*`
- `metric.*`

## Related ONTAP commands

- `network fcp adapter show`

## Learn more

- [DOC /network/fc/ports](#)

## Parameters

Name	Type	In	Required	Description
uuid	string	path	True	The unique identifier for the FC port.
fields	array[string]	query	False	Specify the fields to return.

## Response

Status: 200, Ok

Name	Type	Description
<code>_links</code>	<a href="#">_links</a>	
<code>description</code>	string	A description of the FC port.

Name	Type	Description
enabled	boolean	The administrative state of the FC port. If this property is set to <i>false</i> , all FC connectivity to FC interfaces are blocked. Optional in PATCH.
fabric	fabric	Properties of the fabric to which the FC port is attached.
interface_count	integer	The number of FC interfaces currently provisioned on this port. This property is not supported in an SVM context.
metric	metric	Performance numbers, such as IOPS latency and throughput
name	string	The FC port name.
node	node	
physical_protocol	string	The physical network protocol of the FC port.
speed	speed	The physical device speed related properties of the FC port.

Name	Type	Description
state	string	<p>The operational state of the FC port.</p> <ul style="list-style-type: none"> <li>• startup - The port is booting up.</li> <li>• link_not_connected - The port has finished initialization, but a link with the fabric is not established.</li> <li>• online - The port is initialized and a link with the fabric has been established.</li> <li>• link_disconnected - The link was present at one point on this port but is currently not established.</li> <li>• offlined_by_user - The port is administratively disabled.</li> <li>• offlined_by_system - The port is set to offline by the system. This happens when the port encounters too many errors.</li> <li>• node_offline - The state information for the port cannot be retrieved. The node is offline or inaccessible.</li> </ul>
statistics	<a href="#">statistics</a>	These are raw performance numbers, such as IOPS latency and throughput. These numbers are aggregated across all nodes in the cluster and increase with the uptime of the cluster.
supported_protocols	array[string]	The network protocols supported by the FC port.
transceiver	<a href="#">transceiver</a>	Properties of the transceiver connected to the FC port.
uuid	string	The unique identifier of the FC port.
wwnn	string	The base world wide node name (WWNN) for the FC port.
wwpn	string	The base world wide port name (WWPN) for the FC port.

## Example response

```
{  
  "_links": {  
    "self": {  
      "href": "/api/resourcelink"  
    }  
  },  
  "description": "Fibre Channel Target Adapter 0a (ACME Fibre Channel  
Adapter, rev. 1.0.0, 8G)",  
  "fabric": {  
    "connected_speed": 16,  
    "name": "string",  
    "port_address": "52100A",  
    "switch_port": "ssan-g620-03:33"  
  },  
  "interface_count": 0,  
  "metric": {  
    "_links": {  
      "self": {  
        "href": "/api/resourcelink"  
      }  
    },  
    "duration": "PT15S",  
    "iops": {  
      "read": 200,  
      "total": 1000,  
      "write": 100  
    },  
    "latency": {  
      "read": 200,  
      "total": 1000,  
      "write": 100  
    },  
    "status": "ok",  
    "throughput": {  
      "read": 200,  
      "total": 1000,  
      "write": 100  
    },  
    "timestamp": "2017-01-25 11:20:13 +0000"  
  },  
  "name": "0a",  
  "node": {  
    "_links": {  
      "self": {  
        "href": "/api/resourcelink"  
      }  
    }  
  }  
}
```

```
        "href": "/api/resourcelink"
    },
},
"name": "node1",
"uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"
},
"physical_protocol": "string",
"speed": {
    "configured": "auto",
    "maximum": "32"
},
"state": "online",
"statistics": {
    "iops_raw": {
        "read": 200,
        "total": 1000,
        "write": 100
    },
    "latency_raw": {
        "read": 200,
        "total": 1000,
        "write": 100
    },
    "status": "ok",
    "throughput_raw": {
        "read": 200,
        "total": 1000,
        "write": 100
    },
    "timestamp": "2017-01-25 11:20:13 +0000"
},
"supported_protocols": [
    "string"
],
"transceiver": {
    "capabilities": [
        16
    ],
    "form_factor": "string",
    "manufacturer": "Acme, Inc.",
    "part_number": "string"
},
"uuid": "1cd8a442-86d1-11e0-ae1c-123478563412",
"wwnn": "20:00:00:50:56:b4:13:a8",
"wwpn": "20:00:00:50:56:b4:13:a8"
}
```

## Error

Status: Default, Error

Name	Type	Description
error	returned_error	

### Example error

```
{  
  "error": {  
    "arguments": [  
      {  
        "code": "string",  
        "message": "string"  
      }  
    ],  
    "code": "4",  
    "message": "entry doesn't exist",  
    "target": "uuid"  
  }  
}
```

## Definitions

## See Definitions

href

Name	Type	Description
href	string	

\_links

Name	Type	Description
self	href	

fabric

Properties of the fabric to which the FC port is attached.

Name	Type	Description
connected	boolean	Reports if the physical port has established a connection with the FC fabric.
connected_speed	integer	The negotiated data rate between the target FC port and the fabric in gigabits per second.
name	string	<p>The name of the fabric to which the port is connected. This is only available when the FC port is connected to a fabric.</p> <p>There is an added computational cost to retrieving this property's value. It is not populated for a GET request unless it is explicitly requested using the <code>fields</code> query parameter. See <a href="#">Requesting specific fields</a> to learn more.</p>

Name	Type	Description
port_address	string	<p>The FC port address of the host bus adapter (HBA) physical port.</p> <p>Each FC port in an FC switched fabric has its own unique FC port address for routing purposes. The FC port address is assigned by a switch in the fabric when that port logs in to the fabric. This property refers to the FC port address given to the physical host bus adapter (HBA) port when the port performs a fabric login (FLOGI).</p> <p>This is useful for obtaining statistics and diagnostic information from FC switches.</p> <p>This is a six-digit hexadecimal encoded numeric value.</p>
switch_port	string	The switch port to which the FC port is connected.

## iops

The rate of I/O operations observed at the storage object.

Name	Type	Description
other	integer	Performance metric for other I/O operations. Other I/O operations can be metadata operations, such as directory lookups and so on.
read	integer	Performance metric for read I/O operations.
total	integer	Performance metric aggregated over all types of I/O operations.
write	integer	Performance metric for write I/O operations.

## latency

The round trip latency in microseconds observed at the storage object.

Name	Type	Description
other	integer	Performance metric for other I/O operations. Other I/O operations can be metadata operations, such as directory lookups and so on.
read	integer	Performance metric for read I/O operations.
total	integer	Performance metric aggregated over all types of I/O operations.
write	integer	Performance metric for write I/O operations.

## throughput

The rate of throughput bytes per second observed at the storage object.

Name	Type	Description
read	integer	Performance metric for read I/O operations.
total	integer	Performance metric aggregated over all types of I/O operations.
write	integer	Performance metric for write I/O operations.

## metric

Performance numbers, such as IOPS latency and throughput

Name	Type	Description
_links	<a href="#">_links</a>	
duration	string	The duration over which this sample is calculated. The time durations are represented in the ISO-8601 standard format. Samples can be calculated over the following durations:
iops	<a href="#">iops</a>	The rate of I/O operations observed at the storage object.

Name	Type	Description
latency	latency	The round trip latency in microseconds observed at the storage object.
status	string	Any errors associated with the sample. For example, if the aggregation of data over multiple nodes fails then any of the partial errors might be returned, "ok" on success, or "error" on any internal uncategorized failure. Whenever a sample collection is missed but done at a later time, it is back filled to the previous 15 second timestamp and tagged with "backfilled_data". "Inconsistent_delta_time" is encountered when the time between two collections is not the same for all nodes. Therefore, the aggregated value might be over or under inflated. "Negative_delta" is returned when an expected monotonically increasing value has decreased in value. "Inconsistent_old_data" is returned when one or more nodes do not have the latest data.
throughput	throughput	The rate of throughput bytes per second observed at the storage object.
timestamp	string	The timestamp of the performance data.

## node

Name	Type	Description
_links	_links	
name	string	
uuid	string	

## speed

The physical device speed related properties of the FC port.

Name	Type	Description
configured	string	The configured speed of the FC port in gigabits per second.
maximum	string	The maximum speed supported by the FC port in gigabits per second.

#### iops\_raw

The number of I/O operations observed at the storage object. This should be used along with delta time to calculate the rate of I/O operations per unit of time.

Name	Type	Description
other	integer	Performance metric for other I/O operations. Other I/O operations can be metadata operations, such as directory lookups and so on.
read	integer	Performance metric for read I/O operations.
total	integer	Performance metric aggregated over all types of I/O operations.
write	integer	Performance metric for write I/O operations.

#### latency\_raw

The raw latency in microseconds observed at the storage object. This should be divided by the raw IOPS value to calculate the average latency per I/O operation.

Name	Type	Description
other	integer	Performance metric for other I/O operations. Other I/O operations can be metadata operations, such as directory lookups and so on.
read	integer	Performance metric for read I/O operations.
total	integer	Performance metric aggregated over all types of I/O operations.

Name	Type	Description
write	integer	Performance metric for write I/O operations.

### throughput\_raw

Throughput bytes observed at the storage object. This should be used along with delta time to calculate the rate of throughput bytes per unit of time.

Name	Type	Description
read	integer	Performance metric for read I/O operations.
total	integer	Performance metric aggregated over all types of I/O operations.
write	integer	Performance metric for write I/O operations.

### statistics

These are raw performance numbers, such as IOPS latency and throughput. These numbers are aggregated across all nodes in the cluster and increase with the uptime of the cluster.

Name	Type	Description
iops_raw	iops_raw	The number of I/O operations observed at the storage object. This should be used along with delta time to calculate the rate of I/O operations per unit of time.
latency_raw	latency_raw	The raw latency in microseconds observed at the storage object. This should be divided by the raw IOPS value to calculate the average latency per I/O operation.

Name	Type	Description
status	string	<p>Any errors associated with the sample. For example, if the aggregation of data over multiple nodes fails then any of the partial errors might be returned, "ok" on success, or "error" on any internal uncategorized failure. Whenever a sample collection is missed but done at a later time, it is back filled to the previous 15 second timestamp and tagged with "backfilled_data".</p> <p>"Inconsistent_delta_time" is encountered when the time between two collections is not the same for all nodes. Therefore, the aggregated value might be over or under inflated.</p> <p>"Negative_delta" is returned when an expected monotonically increasing value has decreased in value. "Inconsistent_old_data" is returned when one or more nodes do not have the latest data.</p>
throughput_raw	<a href="#">throughput_raw</a>	Throughput bytes observed at the storage object. This should be used along with delta time to calculate the rate of throughput bytes per unit of time.
timestamp	string	The timestamp of the performance data.

## transceiver

Properties of the transceiver connected to the FC port.

Name	Type	Description
capabilities	array[integer]	The speeds of which the transceiver is capable in gigabits per second.

Name	Type	Description
form_factor	string	<p>The form factor of the transceiver. Possible values are:</p> <ul style="list-style-type: none"> <li><i>sfp</i> - Small Form Factor - Pluggable</li> <li><i>sff</i> - Small Form Factor</li> <li><i>unknown</i> - Unknown</li> </ul>
manufacturer	string	The manufacturer of the transceiver.
part_number	string	The part number of the transceiver.

#### error\_arguments

Name	Type	Description
code	string	Argument code
message	string	Message argument

#### returned\_error

Name	Type	Description
arguments	array[error_arguments]	Message arguments
code	string	Error code
message	string	Error message
target	string	The target parameter that caused the error.

## Update an FC port

PATCH /network/fc/ports/{uuid}

**Introduced In:** 9.6

Updates an FC port.

## Related ONTAP commands

- `network fcp adapter modify`

## Learn more

- [DOC /network/fc/ports](#)

## Parameters

Name	Type	In	Required	Description
uuid	string	path	True	The unique identifier for the FC port.

## Request Body

Name	Type	Description
description	string	A description of the FC port.
enabled	boolean	The administrative state of the FC port. If this property is set to <code>false</code> , all FC connectivity to FC interfaces are blocked. Optional in PATCH.
fabric	fabric	Properties of the fabric to which the FC port is attached.
interface_count	integer	The number of FC interfaces currently provisioned on this port. This property is not supported in an SVM context.
name	string	The FC port name.
node	node	
physical_protocol	string	The physical network protocol of the FC port.
speed	speed	The physical device speed related properties of the FC port.

Name	Type	Description
state	string	<p>The operational state of the FC port.</p> <ul style="list-style-type: none"> <li>• startup - The port is booting up.</li> <li>• link_not_connected - The port has finished initialization, but a link with the fabric is not established.</li> <li>• online - The port is initialized and a link with the fabric has been established.</li> <li>• link_disconnected - The link was present at one point on this port but is currently not established.</li> <li>• offlined_by_user - The port is administratively disabled.</li> <li>• offlined_by_system - The port is set to offline by the system. This happens when the port encounters too many errors.</li> <li>• node_offline - The state information for the port cannot be retrieved. The node is offline or inaccessible.</li> </ul>
supported_protocols	array[string]	The network protocols supported by the FC port.
transceiver	<a href="#">transceiver</a>	Properties of the transceiver connected to the FC port.
uuid	string	The unique identifier of the FC port.
wwnn	string	The base world wide node name (WWNN) for the FC port.
wwpn	string	The base world wide port name (WWPN) for the FC port.

## Example request

```
{  
  "description": "Fibre Channel Target Adapter 0a (ACME Fibre Channel  
Adapter, rev. 1.0.0, 8G)",  
  "fabric": {  
    "connected_speed": 16,  
    "name": "string",  
    "port_address": "52100A",  
    "switch_port": "ssan-g620-03:33"  
  },  
  "interface_count": 0,  
  "name": "0a",  
  "node": {  
    "name": "node1",  
    "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
  },  
  "physical_protocol": "string",  
  "speed": {  
    "configured": "auto",  
    "maximum": "32"  
  },  
  "state": "online",  
  "supported_protocols": [  
    "string"  
  ],  
  "transceiver": {  
    "capabilities": [  
      16  
    ],  
    "form_factor": "string",  
    "manufacturer": "Acme, Inc.",  
    "part_number": "string"  
  },  
  "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412",  
  "wwnn": "20:00:00:50:56:b4:13:a8",  
  "wwpn": "20:00:00:50:56:b4:13:a8"  
}
```

## Response

```
Status: 200, Ok
```

## Error

Status: Default

### ONTAP Error Response Codes

Error Code	Description
5374085	The node where the Fibre Channel port is located is offline.
5374087	The Fibre Channel port has active Fibre Channel interfaces and cannot be disabled.

## Definitions

## See Definitions

href

Name	Type	Description
href	string	

\_links

fabric

Properties of the fabric to which the FC port is attached.

Name	Type	Description
connected	boolean	Reports if the physical port has established a connection with the FC fabric.
connected_speed	integer	The negotiated data rate between the target FC port and the fabric in gigabits per second.
name	string	<p>The name of the fabric to which the port is connected. This is only available when the FC port is connected to a fabric.</p> <p>There is an added computational cost to retrieving this property's value. It is not populated for a GET request unless it is explicitly requested using the <code>fields</code> query parameter. See <a href="#">Requesting specific fields</a> to learn more.</p>

Name	Type	Description
port_address	string	<p>The FC port address of the host bus adapter (HBA) physical port.</p> <p>Each FC port in an FC switched fabric has its own unique FC port address for routing purposes. The FC port address is assigned by a switch in the fabric when that port logs in to the fabric. This property refers to the FC port address given to the physical host bus adapter (HBA) port when the port performs a fabric login (FLOGI).</p> <p>This is useful for obtaining statistics and diagnostic information from FC switches.</p> <p>This is a six-digit hexadecimal encoded numeric value.</p>
switch_port	string	The switch port to which the FC port is connected.

## iops

The rate of I/O operations observed at the storage object.

Name	Type	Description
other	integer	Performance metric for other I/O operations. Other I/O operations can be metadata operations, such as directory lookups and so on.
read	integer	Performance metric for read I/O operations.
total	integer	Performance metric aggregated over all types of I/O operations.
write	integer	Performance metric for write I/O operations.

## latency

The round trip latency in microseconds observed at the storage object.

Name	Type	Description
other	integer	Performance metric for other I/O operations. Other I/O operations can be metadata operations, such as directory lookups and so on.
read	integer	Performance metric for read I/O operations.
total	integer	Performance metric aggregated over all types of I/O operations.
write	integer	Performance metric for write I/O operations.

## throughput

The rate of throughput bytes per second observed at the storage object.

Name	Type	Description
read	integer	Performance metric for read I/O operations.
total	integer	Performance metric aggregated over all types of I/O operations.
write	integer	Performance metric for write I/O operations.

## metric

Performance numbers, such as IOPS latency and throughput

Name	Type	Description
duration	string	The duration over which this sample is calculated. The time durations are represented in the ISO-8601 standard format. Samples can be calculated over the following durations:
iops	iops	The rate of I/O operations observed at the storage object.

Name	Type	Description
latency	latency	The round trip latency in microseconds observed at the storage object.
status	string	Any errors associated with the sample. For example, if the aggregation of data over multiple nodes fails then any of the partial errors might be returned, "ok" on success, or "error" on any internal uncategorized failure. Whenever a sample collection is missed but done at a later time, it is back filled to the previous 15 second timestamp and tagged with "backfilled_data". "Inconsistent_delta_time" is encountered when the time between two collections is not the same for all nodes. Therefore, the aggregated value might be over or under inflated. "Negative_delta" is returned when an expected monotonically increasing value has decreased in value. "Inconsistent_old_data" is returned when one or more nodes do not have the latest data.
throughput	throughput	The rate of throughput bytes per second observed at the storage object.
timestamp	string	The timestamp of the performance data.

## node

Name	Type	Description
name	string	
uuid	string	

## speed

The physical device speed related properties of the FC port.

Name	Type	Description
configured	string	The configured speed of the FC port in gigabits per second.
maximum	string	The maximum speed supported by the FC port in gigabits per second.

#### iops\_raw

The number of I/O operations observed at the storage object. This should be used along with delta time to calculate the rate of I/O operations per unit of time.

Name	Type	Description
other	integer	Performance metric for other I/O operations. Other I/O operations can be metadata operations, such as directory lookups and so on.
read	integer	Performance metric for read I/O operations.
total	integer	Performance metric aggregated over all types of I/O operations.
write	integer	Performance metric for write I/O operations.

#### latency\_raw

The raw latency in microseconds observed at the storage object. This should be divided by the raw IOPS value to calculate the average latency per I/O operation.

Name	Type	Description
other	integer	Performance metric for other I/O operations. Other I/O operations can be metadata operations, such as directory lookups and so on.
read	integer	Performance metric for read I/O operations.
total	integer	Performance metric aggregated over all types of I/O operations.

Name	Type	Description
write	integer	Performance metric for write I/O operations.

### throughput\_raw

Throughput bytes observed at the storage object. This should be used along with delta time to calculate the rate of throughput bytes per unit of time.

Name	Type	Description
read	integer	Performance metric for read I/O operations.
total	integer	Performance metric aggregated over all types of I/O operations.
write	integer	Performance metric for write I/O operations.

### statistics

These are raw performance numbers, such as IOPS latency and throughput. These numbers are aggregated across all nodes in the cluster and increase with the uptime of the cluster.

Name	Type	Description
iops_raw	iops_raw	The number of I/O operations observed at the storage object. This should be used along with delta time to calculate the rate of I/O operations per unit of time.
latency_raw	latency_raw	The raw latency in microseconds observed at the storage object. This should be divided by the raw IOPS value to calculate the average latency per I/O operation.

Name	Type	Description
status	string	<p>Any errors associated with the sample. For example, if the aggregation of data over multiple nodes fails then any of the partial errors might be returned, "ok" on success, or "error" on any internal uncategorized failure. Whenever a sample collection is missed but done at a later time, it is back filled to the previous 15 second timestamp and tagged with "backfilled_data".</p> <p>"Inconsistent_delta_time" is encountered when the time between two collections is not the same for all nodes. Therefore, the aggregated value might be over or under inflated.</p> <p>"Negative_delta" is returned when an expected monotonically increasing value has decreased in value. "Inconsistent_old_data" is returned when one or more nodes do not have the latest data.</p>
throughput_raw	<a href="#">throughput_raw</a>	Throughput bytes observed at the storage object. This should be used along with delta time to calculate the rate of throughput bytes per unit of time.
timestamp	string	The timestamp of the performance data.

## transceiver

Properties of the transceiver connected to the FC port.

Name	Type	Description
capabilities	array[integer]	The speeds of which the transceiver is capable in gigabits per second.

Name	Type	Description
form_factor	string	<p>The form factor of the transceiver. Possible values are:</p> <ul style="list-style-type: none"> <li>• <i>sfp</i> - Small Form Factor - Pluggable</li> <li>• <i>sff</i> - Small Form Factor</li> <li>• <i>unknown</i> - Unknown</li> </ul>
manufacturer	string	The manufacturer of the transceiver.
part_number	string	The part number of the transceiver.

## fc\_port

A Fibre Channel (FC) port is the physical port of an FC adapter on an ONTAP cluster node that can be connected to an FC network to provide FC network connectivity. An FC port defines the location of an FC interface within the ONTAP cluster.

Name	Type	Description
description	string	A description of the FC port.
enabled	boolean	The administrative state of the FC port. If this property is set to <i>false</i> , all FC connectivity to FC interfaces are blocked. Optional in PATCH.
fabric	fabric	Properties of the fabric to which the FC port is attached.
interface_count	integer	The number of FC interfaces currently provisioned on this port. This property is not supported in an SVM context.
name	string	The FC port name.
node	node	
physical_protocol	string	The physical network protocol of the FC port.
speed	speed	The physical device speed related properties of the FC port.

Name	Type	Description
state	string	<p>The operational state of the FC port.</p> <ul style="list-style-type: none"> <li>• startup - The port is booting up.</li> <li>• link_not_connected - The port has finished initialization, but a link with the fabric is not established.</li> <li>• online - The port is initialized and a link with the fabric has been established.</li> <li>• link_disconnected - The link was present at one point on this port but is currently not established.</li> <li>• offlined_by_user - The port is administratively disabled.</li> <li>• offlined_by_system - The port is set to offline by the system. This happens when the port encounters too many errors.</li> <li>• node_offline - The state information for the port cannot be retrieved. The node is offline or inaccessible.</li> </ul>
supported_protocols	array[string]	The network protocols supported by the FC port.
transceiver	<a href="#">transceiver</a>	Properties of the transceiver connected to the FC port.
uuid	string	The unique identifier of the FC port.
wwnn	string	The base world wide node name (WWNN) for the FC port.
wwpn	string	The base world wide port name (WWPN) for the FC port.

error\_arguments

Name	Type	Description
code	string	Argument code
message	string	Message argument

returned\_error

Name	Type	Description
arguments	array[error_arguments]	Message arguments
code	string	Error code
message	string	Error message
target	string	The target parameter that caused the error.

## Copyright information

Copyright © 2026 NetApp, Inc. All Rights Reserved. Printed in the U.S. No part of this document covered by copyright may be reproduced in any form or by any means—graphic, electronic, or mechanical, including photocopying, recording, taping, or storage in an electronic retrieval system—without prior written permission of the copyright owner.

Software derived from copyrighted NetApp material is subject to the following license and disclaimer:

THIS SOFTWARE IS PROVIDED BY NETAPP “AS IS” AND WITHOUT ANY EXPRESS OR IMPLIED WARRANTIES, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE, WHICH ARE HEREBY DISCLAIMED. IN NO EVENT SHALL NETAPP BE LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO, PROCUREMENT OF SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA, OR PROFITS; OR BUSINESS INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE) ARISING IN ANY WAY OUT OF THE USE OF THIS SOFTWARE, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE.

NetApp reserves the right to change any products described herein at any time, and without notice. NetApp assumes no responsibility or liability arising from the use of products described herein, except as expressly agreed to in writing by NetApp. The use or purchase of this product does not convey a license under any patent rights, trademark rights, or any other intellectual property rights of NetApp.

The product described in this manual may be protected by one or more U.S. patents, foreign patents, or pending applications.

**LIMITED RIGHTS LEGEND:** Use, duplication, or disclosure by the government is subject to restrictions as set forth in subparagraph (b)(3) of the Rights in Technical Data -Noncommercial Items at DFARS 252.227-7013 (FEB 2014) and FAR 52.227-19 (DEC 2007).

Data contained herein pertains to a commercial product and/or commercial service (as defined in FAR 2.101) and is proprietary to NetApp, Inc. All NetApp technical data and computer software provided under this Agreement is commercial in nature and developed solely at private expense. The U.S. Government has a non-exclusive, non-transferrable, nonsublicensable, worldwide, limited irrevocable license to use the Data only in connection with and in support of the U.S. Government contract under which the Data was delivered. Except as provided herein, the Data may not be used, disclosed, reproduced, modified, performed, or displayed without the prior written approval of NetApp, Inc. United States Government license rights for the Department of Defense are limited to those rights identified in DFARS clause 252.227-7015(b) (FEB 2014).

## Trademark information

NETAPP, the NETAPP logo, and the marks listed at <http://www.netapp.com/TM> are trademarks of NetApp, Inc. Other company and product names may be trademarks of their respective owners.