



# **Grid node decommissioning**

## **StorageGRID 11.5**

NetApp  
August 30, 2024

This PDF was generated from <https://docs.netapp.com/us-en/storagegrid-115/maintain/considerations-for-decommissioning-admin-or-gateway-nodes.html> on August 30, 2024. Always check docs.netapp.com for the latest.

# Table of Contents

- Grid node decommissioning ..... 1
  - Preparing to decommission grid nodes ..... 3
  - Gathering required materials ..... 9
  - Accessing the Decommission Nodes page ..... 10
  - Decommissioning disconnected grid nodes ..... 13
  - Decommissioning connected grid nodes ..... 19
  - Pausing and resuming the decommission process for Storage Nodes ..... 23
  - Troubleshooting node decommissioning ..... 24

# Grid node decommissioning


You can use the node decommission procedure to remove one or more Storage Nodes, Gateway Nodes, or non-primary Admin Nodes at one or more sites. You cannot decommission the primary Admin Node or an Archive Node.

In general, you should decommission grid nodes only while they are connected to the StorageGRID system and all nodes are in normal health (have green icons on the **Nodes** pages and on the **Decommission Nodes** page). However, if required, you can decommission a grid node that is disconnected. Before removing a disconnected node, make sure you understand the implications and restrictions of that process.

Use the node decommission procedure when any of the following are true:

- You have added a larger Storage Node to the system and you want to remove one or more smaller Storage Nodes, while at the same time preserving objects.
- You require less total storage.
- You no longer require a Gateway Node.
- You no longer require a non-primary Admin Node.
- Your grid includes a disconnected node that you cannot recover or bring back online.

The flowchart shows the high-level steps for decommissioning grid nodes.



## Steps

- Preparing to decommission grid nodes
- Gathering required materials
- Accessing the Decommission Nodes page
- Decommissioning disconnected grid nodes
- Decommissioning connected grid nodes
- Pausing and resuming the decommission process for Storage Nodes
- Troubleshooting node decommissioning

# Preparing to decommission grid nodes

You must review the considerations for removing grid nodes and confirm no repair jobs are active for erasure-coded data.

## Steps

- [Considerations for decommissioning Storage Nodes](#)
- [Checking data repair jobs](#)

## Considerations for decommissioning grid nodes

Before you start this procedure to decommission one or more nodes, you must understand the implications of removing each type of node. Upon the successful decommissioning of a node, its services will be disabled and the node will be automatically shut down.

You cannot decommission a node if doing so will leave the StorageGRID in an invalid state. The following rules are enforced:

- You cannot decommission the primary Admin Node.
- You cannot decommission Archive Nodes.
- You cannot decommission an Admin Node or a Gateway Node if one of its network interfaces is part of a high availability (HA) group.
- You cannot decommission a Storage Node if its removal would affect the ADC quorum.
- You cannot decommission a Storage Node if it is required for the active ILM policy.
- You should not decommission more than 10 Storage Nodes in a single Decommission Node procedure.
- You cannot decommission a connected node if your grid includes any disconnected nodes (nodes whose health is Unknown or Administratively Down). You must decommission or recover the disconnected nodes first.
- If your grid contains multiple disconnected nodes, the software requires you to decommission them at all the same time, which increases the potential for unexpected results.
- If a disconnected node cannot be removed (for example, a Storage Node that is required for the ADC quorum), no other disconnected node can be removed.
- If you want to replace an older appliance with a newer appliance, consider using the appliance node cloning procedure instead of decommissioning the old node and adding the new node in an expansion.

### [Appliance node cloning](#)



Do not remove a grid node's virtual machine or other resources until instructed to do so in decommission procedures.

## Considerations for decommissioning Admin Nodes or a Gateway Nodes

Review the following considerations before decommissioning an Admin Node or a Gateway Node.

- The decommission procedure requires exclusive access to some system resources, so you must confirm that no other maintenance procedures are running.
- You cannot decommission the primary Admin Node.
- You cannot decommission an Admin Node or a Gateway Node if one of its network interfaces is part of a high availability (HA) group. You must first remove the network interfaces from the HA group. See the instructions for administering StorageGRID.
- As required, you can safely change the ILM policy while decommissioning a Gateway Node or an Admin Node.
- If you decommission an Admin Node and single sign-on (SSO) is enabled for your StorageGRID system, you must remember to remove the node's relying party trust from Active Directory Federation Services (AD FS).

## Related information

[Administer StorageGRID](#)

## Considerations for decommissioning Storage Nodes

If you plan to decommission a Storage Node, you must understand how StorageGRID manages the object data and metadata on that node.

The following considerations and restrictions apply when decommissioning Storage Nodes:

- The system must, at all times, include enough Storage Nodes to satisfy operational requirements, including the ADC quorum and the active ILM policy. To satisfy this restriction, you might need to add a new Storage Node in an expansion operation before you can decommission an existing Storage Node.
- If the Storage Node is disconnected when you decommission it, the system must reconstruct the data using data from the connected Storage Nodes, which can result in data loss.
- When you remove a Storage Node, large volumes of object data must be transferred over the network. Although these transfers should not affect normal system operations, they can have an impact on the total amount of network bandwidth consumed by the StorageGRID system.
- Tasks associated with Storage Node decommissioning are given a lower priority than tasks associated with normal system operations. This means that decommissioning does not interfere with normal StorageGRID system operations, and does not need to be scheduled for a period of system inactivity. Because decommissioning is performed in the background, it is difficult to estimate how long the process will take to complete. In general, decommissioning finishes more quickly when the system is quiet, or if only one Storage Node is being removed at a time.
- It might take days or weeks to decommission a Storage Node. Plan this procedure accordingly. While the decommission process is designed to not impact system operations, it can limit other procedures. In general, you should perform any planned system upgrades or expansions before you remove grid nodes.
- Decommission procedures that involve Storage Nodes can be paused during certain stages to allow other maintenance procedures to run if needed, and resumed once they are complete.
- You cannot run data repair operations on any grid nodes when a decommission task is running.
- You should not make any changes to the ILM policy while a Storage Node is being decommissioned.
- When you remove a Storage Node, data on the node is migrated to other grid nodes; however, this data is not completely removed from the decommissioned grid node. To permanently and securely remove data, you must wipe the decommissioned grid node's drives after the decommission procedure is complete.
- When you decommission a Storage Node, the following alerts and alarms might be raised and you might receive related email and SNMP notifications:

- **Unable to communicate with node** alert. This alert is triggered when you decommission a Storage Node that includes the ADC service. The alert is resolved when the decommission operation completes.
- VSTU (Object Verification Status) alarm. This notice-level alarm indicates that the Storage Node is going into maintenance mode during the decommission process.
- CASA (Data Store Status) alarm. This major-level alarm indicates that the Cassandra database is going down because services have stopped.

### Related information

[Restoring object data to a storage volume, if required](#)

[Understanding the ADC quorum](#)

[Reviewing the ILM policy and storage configuration](#)

[Decommissioning disconnected Storage Nodes](#)

[Consolidating Storage Nodes](#)

[Decommissioning multiple Storage Nodes](#)

### Understanding the ADC quorum

You might not be able to decommission certain Storage Nodes at a data center site if too few Administrative Domain Controller (ADC) services would remain after the decommissioning. This service, which is found on some Storage Nodes, maintains grid topology information and provides configuration services to the grid. The StorageGRID system requires a quorum of ADC services to be available at each site and at all times.

You cannot decommission a Storage Node if removing the node would cause the ADC quorum to no longer be met. To satisfy the ADC quorum during a decommissioning, a minimum of three Storage Nodes at each data center site must have the ADC service. If a data center site has more than three Storage Nodes with the ADC service, a simple majority of those nodes must remain available after the decommissioning ( $(0.5 * \text{Storage Nodes with ADC}) + 1$ ).

For example, suppose a data center site currently includes six Storage Nodes with ADC services and you want to decommission three Storage Nodes. Because of the ADC quorum requirement, you must complete two decommission procedures, as follows:

- In the first decommission procedure, you must ensure that four Storage Nodes with ADC services remain available ( $(0.5 * 6) + 1$ ). This means that you can only decommission two Storage Nodes initially.
- In the second decommission procedure, you can remove the third Storage Node because the ADC quorum now only requires three ADC services to remain available ( $(0.5 * 4) + 1$ ).

If you need to decommission a Storage Node but are unable to because of the ADC quorum requirement, you must add a new Storage Node in an expansion and specify that it should have an ADC service. Then, you can decommission the existing Storage Node.

### Related information

[Expand your grid](#)

## Reviewing the ILM policy and storage configuration

If you plan to decommission a Storage Node, you should review your StorageGRID system's ILM policy before starting the decommissioning process.

During decommissioning, all object data is migrated from the decommissioned Storage Node to other Storage Nodes.



The ILM policy you have *during* the decommission will be the one used *after* the decommission. You must ensure this policy meets your data requirements both before you start the decommission and after the decommission is complete.

You should review the rules in the active ILM policy to ensure that the StorageGRID system will continue to have enough capacity of the correct type and in the correct locations to accommodate the decommissioning of a Storage Node.

Consider the following:

- Will it be possible for ILM evaluation services to copy object data such that ILM rules are satisfied?
- What happens if a site becomes temporarily unavailable while decommissioning is in progress? Can additional copies be made in an alternate location?
- How will the decommissioning process affect the final distribution of content? As described in "Consolidating Storage Nodes," you should add new Storage Nodes before decommissioning old ones. If you add a larger replacement Storage Node after decommissioning a smaller Storage Node, the old Storage Nodes could be close to capacity and the new Storage Node could have almost no content. Most write operations for new object data would then be directed at the new Storage Node, reducing the overall efficiency of system operations.
- Will the system, at all times, include enough Storage Nodes to satisfy the active ILM policy?



An ILM policy that cannot be satisfied will lead to backlogs and alarms, and can halt operation of the StorageGRID system.

Verify that the proposed topology that will result from the decommissioning process satisfies the ILM policy by assessing the factors listed in the table.

Area to assess	Notes
Available capacity	Will there be enough storage capacity to accommodate all of the object data stored in the StorageGRID system, including the permanent copies of object data currently stored on the Storage Node to be decommissioned? Will there be enough capacity to handle the anticipated growth in stored object data for a reasonable interval of time after decommissioning is complete?
Location of storage	If enough capacity remains in the StorageGRID system as a whole, is the capacity in the right locations to satisfy the StorageGRID system's business rules?



Area to assess	Notes
Storage type	Will there be enough storage of the appropriate type after decommissioning is complete? For example, ILM rules might dictate that content be moved from one type of storage to another as content ages. If so, you must ensure that enough storage of the appropriate type is available in the final configuration of the StorageGRID system.

### Related information

[Consolidating Storage Nodes](#)

[Manage objects with ILM](#)

[Expand your grid](#)

### Decommissioning disconnected Storage Nodes

You must understand what can happen if you decommission a Storage Node while it is disconnected (health is Unknown or Administratively Down).

When you decommission a Storage Node that is disconnected from the grid, StorageGRID uses data from other Storage Nodes to reconstruct the object data and metadata that was on the disconnected node. It does this by automatically starting data repair jobs at the end of the decommissioning process.

Before decommissioning a disconnected Storage Node, be aware of the following:

- You should never decommission a disconnected node unless you are sure it cannot be brought online or recovered.



Do not perform this procedure if you believe it might be possible to recover object data from the node. Instead, contact technical support to determine if node recovery is possible.

- If a disconnected Storage Node contains the only copy of an object, that object will be lost when you decommission the node. The data repair jobs can only reconstruct and recover objects if at least one replicated copy or enough erasure-coded fragments exist on Storage Nodes that are currently connected.
- When you decommission a disconnected Storage Node, the decommission procedure completes relatively quickly. However, the data repair jobs can take days or weeks to run and are not monitored by the decommission procedure. You must manually monitor these jobs and restart them as needed. See the instructions on monitoring data repair.

### Checking data repair jobs

- If you decommission more than one disconnected Storage Node at a time, data loss might occur. The system might not be able to reconstruct data if too few copies of object data, metadata, or erasure-coded fragments remain available.



If you have more than one disconnected Storage Node that you cannot recover, contact technical support to determine the best course of action.

## Consolidating Storage Nodes

You can consolidate Storage Nodes to reduce the Storage Node count for a site or deployment while increasing storage capacity.

When you consolidate Storage Nodes, you expand the StorageGRID system to add new, larger capacity Storage Nodes and then decommission the old, smaller capacity Storage Nodes. During the decommission procedure, objects are migrated from the old Storage Nodes to the new Storage Nodes.

For example, you might add two new, larger capacity Storage Nodes to replace three older Storage Nodes. You would first use the expansion procedure to add the two new, larger Storage Nodes, and then use the decommission procedure to remove the three old, smaller capacity Storage Nodes.

By adding new capacity before removing existing Storage Nodes, you ensure a more balanced distribution of data across the StorageGRID system. You also reduce the possibility that an existing Storage Node might be pushed beyond the storage watermark level.

### Related information

[Expand your grid](#)

## Decommissioning multiple Storage Nodes

If you need to remove more than one Storage Node, you can decommission them either sequentially or in parallel.

- If you decommission Storage Nodes sequentially, you must wait for the first Storage Node to complete decommissioning before starting to decommission the next Storage Node.
- If you decommission Storage Nodes in parallel, the Storage Nodes simultaneously process decommission tasks for all Storage Nodes being decommissioned. This can result in a situation where all permanent copies of a file are marked as “read-only,” temporarily disabling deletion in grids where this functionality is enabled.

## Checking data repair jobs

Before decommissioning a grid node, you must confirm that no data repair jobs are active. If any repairs have failed, you must restart them and allow them to complete before performing the decommission procedure.

If you need to decommission a disconnected Storage Node, you will also complete these steps after the decommission procedure completes in order to ensure the data repair job has completed successfully. You must ensure that any erasure-coded fragments that were on the removed node have been restored successfully.

These steps only apply to systems that have erasure-coded objects.

1. Log in to the primary Admin Node:

- a. Enter the following command: `ssh admin@grid_node_IP`

When you are logged in as root, the prompt changes from `$` to `#`.

- b. Enter the password listed in the `Passwords.txt` file.

- c. Enter the following command to switch to root: `su -`
- d. Enter the password listed in the `Passwords.txt` file.

2. Check for running repairs: `repair-data show-ec-repair-status`

- If you have never run a data repair job, the output is `No job found`. You do not need to restart any repair jobs.
- If the data repair job was run previously or is running currently, the output lists information for the repair. Each repair has a unique repair ID. Go to the next step.

```

root@DC1-ADM1:~ # repair-data show-ec-repair-status

Repair ID Scope Start Time End Time State Est/Affected Bytes Repaired
Retry Repair
=====
=====
949283 DC1-S-99-10 (Volumes: 1,2) 2016-11-30T15:27:06.9 Success 17359
17359 No
949292 DC1-S-99-10 (Volumes: 1,2) 2016-11-30T15:37:06.9 Failure 17359 0
Yes
949294 DC1-S-99-10 (Volumes: 1,2) 2016-11-30T15:47:06.9 Failure 17359 0
Yes
949299 DC1-S-99-10 (Volumes: 1,2) 2016-11-30T15:57:06.9 Failure 17359 0
Yes

```

- 3. If the State for all repairs is `Success`, you do not need to restart any repair jobs.
- 4. If the State for any repair is `Failure`, you must restart that repair.
  - a. Obtain the repair ID for the failed repair from the output.
  - b. Run the `repair-data start-ec-node-repair` command.

Use the `--repair-id` option to specify the Repair ID. For example, if you want to retry a repair with repair ID 949292, run this command: `repair-data start-ec-node-repair --repair-id 949292`

- c. Continue to track the status of EC data repairs until the State for all repairs is `Success`.

## Gathering required materials

Before performing a grid node decommission, you must obtain the following information.

Item	Notes
Recovery Package .zip file	You must download the most recent Recovery Package .zip file ( <code>sgws-recovery-package-id-revision.zip</code> ). You can use the Recovery Package file to restore the system if a failure occurs.

Item	Notes
Passwords.txt file	This file contains the passwords required to access grid nodes on the command line and is included in the Recovery Package.
Provisioning passphrase	The passphrase is created and documented when the StorageGRID system is first installed. The provisioning passphrase is not in the Passwords.txt file.
Description of StorageGRID system's topology before decommissioning	If available, obtain any documentation that describes the system's current topology.

### Related information

[Web browser requirements](#)

[Downloading the Recovery Package](#)

## Accessing the Decommission Nodes page

When you access the Decommission Nodes page in the Grid Manager, you can see at a glance which nodes can be decommissioned.

### What you'll need

- You must be signed in to the Grid Manager using a supported browser.
- You must have the Maintenance or Root Access permission.

### Steps

1. Select **Maintenance > Maintenance Tasks > Decommission**.

The Decommission page appears.

#### Decommission

Select **Decommission Nodes** to remove one or more nodes from a single site. Select **Decommission Site** to remove an entire data center site.

Learn important details about removing grid nodes and sites in the "Decommission procedure" section of the [recovery and maintenance instructions](#).



2. Click the **Decommission Nodes** button.

The Decommission Nodes page appears. From this page, you can:

- Determine which grid nodes can be decommissioned currently.
- See the health of all grid nodes
- Sort the list in ascending or descending order by **Name**, **Site**, **Type**, or **Has ADC**.
- Enter search terms to quickly find particular nodes. For example, this page shows all grid nodes in a single data center. The Decommission Possible column indicates that you can decommission the non-primary Admin Node, the Gateway Node, and two of the five Storage Nodes.

#### Decommission Nodes

Before decommissioning a grid node, review the health of all nodes. If possible, resolve any issues or alarms before proceeding.

Select the checkbox for each grid node you want to decommission. If decommission is not possible for a node, see the Recovery and Maintenance Guide to learn how to proceed.

#### Grid Nodes

Search <input type="text"/>							
	Name	Site	Type	Has ADC	Health	Decommission Possible	
	DC1-ADM1	Data Center 1	Admin Node	-		No, primary Admin Node decommissioning is not supported.	
<input type="checkbox"/>	DC1-ADM2	Data Center 1	Admin Node	-			
<input type="checkbox"/>	DC1-G1	Data Center 1	API Gateway Node	-			
	DC1-S1	Data Center 1	Storage Node	Yes		No, site Data Center 1 requires a minimum of 3 Storage Nodes with ADC services.	
	DC1-S2	Data Center 1	Storage Node	Yes		No, site Data Center 1 requires a minimum of 3 Storage Nodes with ADC services.	
	DC1-S3	Data Center 1	Storage Node	Yes		No, site Data Center 1 requires a minimum of 3 Storage Nodes with ADC services.	
<input type="checkbox"/>	DC1-S4	Data Center 1	Storage Node	No			
<input type="checkbox"/>	DC1-S5	Data Center 1	Storage Node	No			

#### Passphrase



Provisioning  
Passphrase

[Start Decommission](#)

### 3. Review the **Decommission Possible** column for each node you want to decommission.

If a grid node can be decommissioned, this column includes a green check mark, and the left-most column includes a check box. If a node cannot be decommissioned, this column describes the issue. If there is more than one reason a node cannot be decommissioned, the most critical reason is shown.

Decommission Possible reason	Description	Steps to resolve
No, node type decommissioning is not supported.	You cannot decommission the primary Admin Node or an Archive Node.	None.

Decommission Possible reason	Description	Steps to resolve
<p>No, at least one grid node is disconnected.</p> <p><b>Note:</b> This message is shown for connected grid nodes only.</p>	<p>You cannot decommission a connected grid node if any grid node is disconnected.</p> <p>The <b>Health</b> column includes one of these icons for grid nodes that are disconnected:</p> <ul style="list-style-type: none"> <li>•  (gray): Administratively Down</li> <li>•  (blue): Unknown</li> </ul>	<p>Go to the <a href="#">step that lists the decommission procedure choices</a>.</p>
<p>No, one or more required nodes is currently disconnected and must be recovered.</p> <p><b>Note:</b> This message is shown for disconnected grid nodes only.</p>	<p>You cannot decommission a disconnected grid node if one or more required nodes is also disconnected (for example, a Storage Node that is required for the ADC quorum).</p>	<ol style="list-style-type: none"> <li>a. Review the Decommission Possible messages for all disconnected nodes.</li> <li>b. Determine which nodes cannot be decommissioned because they are required. <ul style="list-style-type: none"> <li>◦ If the Health of a required node is Administratively Down, bring the node back online.</li> <li>◦ If the health of a required node is Unknown, perform a node recovery procedure to recover the required node.</li> </ul> </li> </ol>
<p>No, member of HA group(s): <math>x</math>. Before you can decommission this node, you must remove it from all HA groups.</p>	<p>You cannot decommission an Admin Node or a Gateway Node if a node interface belongs to a high availability (HA) group.</p>	<p>Edit the HA group to remove the node's interface or remove the entire HA group. See the instructions for administering StorageGRID.</p>
<p>No, site <math>x</math> requires a minimum of <math>n</math> Storage Nodes with ADC services.</p>	<p><b>Storage Nodes only.</b> You cannot decommission a Storage Node if insufficient nodes would remain at the site to support ADC quorum requirements.</p>	<p>Perform an expansion. Add a new Storage Node to the site, and specify that it should have an ADC service. See information about the ADC quorum.</p>

Decommission Possible reason	Description	Steps to resolve
<p>No, one or more Erasure Coding profiles need at least <math>n</math> Storage Nodes. If the profile is not used in an ILM rule, you can deactivate it.</p>	<p><b>Storage Nodes only.</b> You cannot decommission a Storage Node unless enough nodes would remain for the existing Erasure Coding profiles.</p> <p>For example, if an Erasure Coding profile exists for 4+2 erasure coding, at least 6 Storage Nodes must remain.</p>	<p>For each affected Erasure Coding profile, perform one of the following steps, based on how the profile is being used:</p> <ul style="list-style-type: none"> <li>• <b>Used in the active ILM policy:</b> Perform an expansion. Add enough new Storage Nodes to allow erasure coding to continue. See the instructions for expanding StorageGRID.</li> <li>• <b>Used in an ILM rule but not in the active ILM policy:</b> Edit or delete the rule and then deactivate the Erasure Coding profile.</li> <li>• <b>Not used in any ILM rule:</b> Deactivate the Erasure Coding profile.</li> </ul> <p><b>Note:</b> An error message appears if you attempt to deactivate an Erasure Coding profile and object data is still associated with the profile. You might need to wait several weeks before trying the deactivation process again.</p> <p>Learn about deactivating an Erasure Coding profile in the instructions for managing objects with information lifecycle management.</p>

4. If decommissioning is possible for the node, determine which procedure you need to perform:

If your grid includes...	Go to...
Any disconnected grid nodes	<a href="#">Decommissioning disconnected grid nodes</a>
Only connected grid nodes	<a href="#">Decommissioning connected grid nodes</a>

#### Related information

[Checking data repair jobs](#)

[Understanding the ADC quorum](#)

[Manage objects with ILM](#)

[Expand your grid](#)

[Administer StorageGRID](#)

## Decommissioning disconnected grid nodes

You might need to decommission a node that is not currently connected to the grid (one

whose Health is Unknown or Administratively Down).

### What you'll need

- You understand the requirements and considerations for decommissioning grid nodes.

#### Considerations for decommissioning grid nodes

- You have obtained all prerequisite items.
- You have ensured that no data repair jobs are active.

#### Checking data repair jobs


- You have confirmed that Storage Node recovery is not in progress anywhere in the grid. If it is, you must wait until any Cassandra rebuild performed as part of the recovery is complete. You can then proceed with decommissioning.
- You have ensured that other maintenance procedures will not be run while the node decommission procedure is running, unless the node decommission procedure is paused.
- The **Decommission Possible** column for the disconnected node or nodes you want to decommission includes a green check mark.
- You must have the provisioning passphrase.

You can identify disconnected nodes by looking for Unknown (blue) or Administratively Down (gray) icons in the **Health** column. In the example, the Storage Node named DC1-S4 is disconnected; all of the other nodes are connected.



## Decommission Nodes



Before decommissioning a grid node, review the health of all nodes. If possible, resolve any issues or alarms before proceeding.

 A grid node is disconnected (has a blue or gray health icon). Try to bring it back online or recover it. Data loss might occur if you decommission a node that is disconnected.

See the [Recovery and Maintenance Guide](#) for details. Contact Support if you cannot recover a node and do not want to decommission it.

Select the checkbox for each grid node you want to decommission. If decommission is not possible for a node, see the [Recovery and Maintenance Guide](#) to learn how to proceed.

### Grid Nodes

Name	Site	Type	Has ADC	Health	Decommission Possible
DC1-ADM1	Data Center 1	Admin Node	-		No, primary Admin Node decommissioning is not supported.
DC1-ADM2	Data Center 1	Admin Node	-		No, at least one grid node is disconnected.
DC1-G1	Data Center 1	API Gateway Node	-		No, at least one grid node is disconnected.
DC1-S1	Data Center 1	Storage Node	Yes		No, site Data Center 1 requires a minimum of 3 Storage Nodes with ADC services.
DC1-S2	Data Center 1	Storage Node	Yes		No, site Data Center 1 requires a minimum of 3 Storage Nodes with ADC services.
DC1-S3	Data Center 1	Storage Node	Yes		No, site Data Center 1 requires a minimum of 3 Storage Nodes with ADC services.
<input type="checkbox"/> DC1-S4	Data Center 1	Storage Node	No		

### Passphrase

Provisioning  
Passphrase

Start Decommission

Before decommissioning any disconnected node, note the following:

- This procedure is primarily intended for removing a single disconnected node. If your grid contains multiple disconnected nodes, the software requires you to decommission them at all the same time, which increases the potential for unexpected results.



Be very careful when decommissioning more than one disconnected grid node at a time, especially if you are selecting multiple disconnected Storage Nodes.

- If a disconnected node cannot be removed (for example, a Storage Node that is required for the ADC quorum), no other disconnected node can be removed.

Before decommissioning a disconnected **Storage Node**, note the following

- You should never decommission a disconnected Storage Node unless you are sure it cannot be brought online or recovered.



If you believe that object data can still be recovered from the node, do not perform this procedure. Instead, contact technical support to determine if node recovery is possible.

- If you decommission more than one disconnected Storage Node, data loss might occur. The system might not be able to reconstruct data if not enough object copies, erasure-coded fragments, or object metadata remain available.



If you have more than one disconnected Storage Node that you cannot recover, contact technical support to determine the best course of action.

- When you decommission a disconnected Storage Node, StorageGRID starts data repair jobs at the end of the decommissioning process. These jobs attempt to reconstruct the object data and metadata that was stored on the disconnected node.
- When you decommission a disconnected Storage Node, the decommission procedure completes relatively quickly. However, the data repair jobs can take days or weeks to run and are not monitored by the decommission procedure. You must manually monitor these jobs and restart them as needed. See the instructions on monitoring data repair.

### Checking data repair jobs

- If you decommission a disconnected Storage Node that contains the only copy of an object, the object will be lost. The data repair jobs can only reconstruct and recover objects if at least one replicated copy or enough erasure-coded fragments exist on Storage Nodes that are currently connected.

Before decommissioning a disconnected **Admin Node** or **Gateway Node**, note the following:

- When you decommission a disconnected Admin Node, you will lose the audit logs from that node; however, these logs should also exist on the primary Admin Node.
- You can safely decommission a Gateway Node while it is disconnected.

### Steps

1. Attempt to bring any disconnected grid nodes back online or to recover them.

See the recovery procedures for instructions.

2. If you are unable to recover a disconnected grid node and you want to decommission it while it is disconnected, select the check box for that node.



If your grid contains multiple disconnected nodes, the software requires you to decommission them at all the same time, which increases the potential for unexpected results.



Be very careful when selecting to decommission more than one disconnected grid node at a time, especially if you are selecting multiple disconnected Storage Nodes. If you have more than one disconnected Storage Node that you cannot recover, contact technical support to determine the best course of action.

3. Enter the provisioning passphrase.

The **Start Decommission** button is enabled.

4. Click **Start Decommission**.

A warning appears, indicating that you have selected a disconnected node and that object data will be lost if the node has the only copy of an object.

## Warning

The selected nodes are disconnected (health is Unknown or Administratively Down). If you continue and the node has the only copy of an object, the object will be lost when the node is removed.

The following grid nodes have been selected for decommissioning and will be permanently removed from the StorageGRID Webscale system.

DC1-S4

Do you want to continue?

Cancel

OK

5. Review the list of nodes, and click **OK**.

The decommission procedure starts, and the progress is displayed for each node. During the procedure, a new Recovery Package is generated containing the grid configuration change.

Decommission Nodes

 A new Recovery Package has been generated as a result of the configuration change. Go to the [Recovery Package page](#) to download it.

The progress for each node is displayed while the decommission procedure is running. When all tasks are complete, the node selection list is redisplayed.

Name	Type	Progress	Stage
DC1-S4	Storage Node	<div style="width: 10%;"></div>	Prepare Task

Search

Pause Resume

6. As soon as the new Recovery Package is available, click the link or select **Maintenance > System > Recovery Package** to access the Recovery Package page. Then, download the .zip file.

See the instructions for downloading the Recovery Package.



Download the Recovery Package as soon as possible to ensure you can recover your grid if something goes wrong during the decommission procedure.



The Recovery Package file must be secured because it contains encryption keys and passwords that can be used to obtain data from the StorageGRID system.

7. Periodically monitor the Decommission page to ensure that all selected nodes are decommissioned successfully.

Storage Nodes can take days or weeks to decommission. When all tasks are complete, the node selection list is redisplayed with a success message. If you decommissioned a disconnected Storage Node, an

information message indicates that the repair jobs have been started.

#### Decommission Nodes

The previous decommission procedure completed successfully.

**i** Repair jobs for replicated and erasure-coded data have been started. These jobs restore object data that might have been on any disconnected Storage Nodes. To monitor the progress of these jobs and restart them as needed, see the Decommissioning section of the Recovery and Maintenance Guide.

Before decommissioning a grid node, review the health of all nodes. If possible, resolve any issues or alarms before proceeding.

Select the checkbox for each grid node you want to decommission. If decommission is not possible for a node, see the Recovery and Maintenance Guide to learn how to proceed.

#### Grid Nodes

Name	Site	Type	Has ADC	Health	Decommission Possible
DC1-ADM1	Data Center 1	Admin Node	-		No, primary Admin Node decommissioning is not supported.
<input type="checkbox"/> DC1-ADM2	Data Center 1	Admin Node	-		
<input type="checkbox"/> DC1-G1	Data Center 1	API Gateway Node	-		
DC1-S1	Data Center 1	Storage Node	Yes		No, site Data Center 1 requires a minimum of 3 Storage Nodes with ADC services.
DC1-S2	Data Center 1	Storage Node	Yes		No, site Data Center 1 requires a minimum of 3 Storage Nodes with ADC services.
DC1-S3	Data Center 1	Storage Node	Yes		No, site Data Center 1 requires a minimum of 3 Storage Nodes with ADC services.

#### Passphrase

Provisioning  
Passphrase

- After the nodes have shut down automatically as part of the decommission procedure, remove any remaining virtual machines or other resources that are associated with the decommissioned node.



Do not perform this step until the nodes have shut down automatically.

- If you are decommissioning a Storage Node, monitor the status of the data repair jobs that are automatically started during the decommissioning process.
  - Select **Support > Tools > Grid Topology**.
  - Select **StorageGRID deployment** at the top of the Grid Topology tree.
  - On the Overview tab, locate the ILM Activity section.
  - Use a combination of the following attributes to determine, as well as possible, if replicated repairs are complete.



Cassandra inconsistencies might be present, and failed repairs are not tracked.

- Repairs Attempted (XRPA):** Use this attribute to track the progress of replicated repairs. This attribute increases each time a Storage Node tries to repair a high-risk object. When this attribute does not increase for a period longer than the current scan period (provided by the **Scan Period — Estimated** attribute), it means that ILM scanning found no high-risk objects that need to be repaired on any nodes.



High-risk objects are objects that are at risk of being completely lost. This does not include objects that do not satisfy their ILM configuration.

- **Scan Period — Estimated (XSCM)**: Use this attribute to estimate when a policy change will be applied to previously ingested objects. If the **Repairs Attempted** attribute does not increase for a period longer than the current scan period, it is probable that replicated repairs are done. Note that the scan period can change. The **Scan Period — Estimated (XSCM)** attribute applies to the entire grid and is the maximum of all node scan periods. You can query the **Scan Period — Estimated** attribute history for the grid to determine an appropriate time frame.

e. Use the following commands to track or restart repairs:

- Use the `repair-data show-ec-repair-status` command to track repairs of erasure coded data.
- Use the `repair-data start-ec-node-repair` command with the `--repair-id` option to restart a failed repair. See the instructions for checking data repair jobs.

10. Continue to track the status of EC data repairs until all repair jobs have completed successfully.

As soon as the disconnected nodes have been decommissioned and all data repair jobs have been completed, you can decommission any connected grid nodes as required.

Complete these steps after you complete the decommission procedure:

- Ensure that the drives of the decommissioned grid node are wiped clean. Use a commercially available data wiping tool or service to permanently and securely remove data from the drives.
- If you decommissioned an appliance node and the data on the appliance was protected using node encryption, use the StorageGRID Appliance Installer to clear the key management server configuration (Clear KMS). You must clear the KMS configuration if you want to add the appliance to another grid.

[SG100 & SG1000 services appliances](#)

[SG5600 storage appliances](#)

[SG5700 storage appliances](#)

[SG6000 storage appliances](#)

#### Related information

[Grid node recovery procedures](#)

[Downloading the Recovery Package](#)

[Checking data repair jobs](#)


## Decommissioning connected grid nodes





You can decommission and permanently remove nodes that are connected to the grid.

#### What you'll need

- You understand the requirements and considerations for decommissioning grid nodes.

[Considerations for decommissioning grid nodes](#)

- You have gathered all required materials.
- You have ensured that no data repair jobs are active.
- You have confirmed that Storage Node recovery is not in progress anywhere in the grid. If it is, you must wait until any Cassandra rebuild performed as part of the recovery is complete. You can then proceed with decommissioning.
- You have ensured that other maintenance procedures will not be run while the node decommission procedure is running, unless the node decommission procedure is paused.
- You have the provisioning passphrase.
- Grid nodes are connected.
- The **Decommission Possible** column for the node or nodes you want to decommission include a green checkmark.
- All grid nodes have Normal (green) health . If you see one of these icons in the **Health** column, you must try to resolve the issue:

Icon	Color	Severity
	Yellow	Notice
	Light orange	Minor
	Dark orange	Major
	Red	Critical

- If you previously decommissioned a disconnected Storage Node, the data repair jobs have all completed successfully. See the instructions for checking data repair jobs.



Do not remove a grid node's virtual machine or other resources until instructed to do so in this procedure.

## Steps

1. From the Decommission Nodes page, select the check box for each grid node you want to decommission.
2. Enter the provisioning passphrase.

The **Start Decommission** button is enabled.

3. Click **Start Decommission**.

A confirmation dialog box appears.

## Info

The following grid nodes have been selected for decommissioning and will be permanently removed from the StorageGRID Webscale system.

DC1-S5

Do you want to continue?

Cancel

OK

4. Review the list of selected nodes, and click **OK**.

The node decommission procedure starts, and the progress is displayed for each node. During the procedure, a new Recovery Package is generated to show the grid configuration change.

Decommission Nodes

 A new Recovery Package has been generated as a result of the configuration change. Go to the [Recovery Package page](#) to download it.

The progress for each node is displayed while the decommission procedure is running. When all tasks are complete, the node selection list is redisplayed.

Name	Type	Progress	Stage
DC1-S5	Storage Node	<div style="width: 10%;"></div>	Prepare Task



Do not take a Storage Node offline after the decommission procedure has started. Changing the state might result in some content not being copied to other locations.

5. As soon as the new Recovery Package is available, click the link or select **Maintenance > System > Recovery Package** to access the Recovery Package page. Then, download the .zip file.

See the instructions for downloading the Recovery Package.



Download the Recovery Package as soon as possible to ensure you can recover your grid if something goes wrong during the decommission procedure.

6. Periodically monitor the Decommission Nodes page to ensure that all selected nodes are decommissioned successfully.

Storage Nodes can take days or weeks to decommission. When all tasks are complete, the node selection list is redisplayed with a success message.

## Decommission Nodes

The previous decommission procedure completed successfully.

Before decommissioning a grid node, review the health of all nodes. If possible, resolve any issues or alarms before proceeding.

Select the checkbox for each grid node you want to decommission. If decommission is not possible for a node, see the Recovery and Maintenance Guide to learn how to proceed.

### Grid Nodes

	Name	Site	Type	Has ADC	Health	Decommission Possible
	DC1-ADM1	Data Center 1	Admin Node	-		No, primary Admin Node decommissioning is not supported.
<input checked="" type="checkbox"/>	DC1-ADM2	Data Center 1	Admin Node	-		
<input type="checkbox"/>	DC1-G1	Data Center 1	API Gateway Node	-		
	DC1-S1	Data Center 1	Storage Node	Yes		No, site Data Center 1 requires a minimum of 3 Storage Nodes with ADC services.
	DC1-S2	Data Center 1	Storage Node	Yes		No, site Data Center 1 requires a minimum of 3 Storage Nodes with ADC services.
	DC1-S3	Data Center 1	Storage Node	Yes		No, site Data Center 1 requires a minimum of 3 Storage Nodes with ADC services.

### Passphrase

Provisioning  
Passphrase

7. Follow the appropriate step for your platform. For example:

- **Linux:** You might want to detach the volumes and delete the node configuration files you created during installation.
- **VMware:** You might want to use the vCenter “Delete from Disk” option to delete the virtual machine. You might also need to delete any data disks that are independent of the virtual machine.
- **StorageGRID appliance:** The appliance node automatically reverts to an undeployed state where you can access the StorageGRID Appliance Installer. You can power off the appliance or add it to another StorageGRID system.

Complete these steps after you complete the node decommission procedure:

- Ensure that the drives of the decommissioned grid node are wiped clean. Use a commercially available data wiping tool or service to permanently and securely remove data from the drives.
- If you decommissioned an appliance node and the data on the appliance was protected using node encryption, use the StorageGRID Appliance Installer to clear the key management server configuration (Clear KMS). You must clear the KMS configuration if you want to use the appliance in another grid.

[SG100 & SG1000 services appliances](#)

[SG5600 storage appliances](#)

[SG5700 storage appliances](#)

[SG6000 storage appliances](#)

## Related information



[Checking data repair jobs](#)

[Downloading the Recovery Package](#)

[Install Red Hat Enterprise Linux or CentOS](#)

## Pausing and resuming the decommission process for Storage Nodes

If necessary, you can pause the decommission procedure for a Storage Node during certain stages. You must pause decommissioning on a Storage Node before you can start a second maintenance procedure. After the other procedure is finished, you can resume decommissioning.

### What you'll need

- You must be signed in to the Grid Manager using a supported browser.
- You must have the Maintenance or Root Access permission.

### Steps

1. Select **Maintenance > Maintenance Tasks > Decommission**.

The Decommission page appears.

2. Click **Decommission Nodes**.


The Decommission Nodes page appears. When the decommission procedure reaches either of the following stages, the **Pause** button is enabled.


- Evaluating ILM
- Decommissioning Erasure Coded data

3. Click **Pause** to suspend the procedure.

The current stage is paused, and the **Resume** button is enabled.

Decommission Nodes

 A new Recovery Package has been generated as a result of the configuration change. Go to the [Recovery Package](#) page to download it.

 Decommissioning procedure has been paused. Click 'Resume' to resume the procedure.

The progress for each node is displayed while the decommission procedure is running. When all tasks are complete, the node selection list is redisplayed.

Name	Type	Progress	Stage
DC1-S5	Storage Node	<div style="width: 50%; background-color: orange;"></div>	Evaluating ILM

4. After the other maintenance procedure is finished, click **Resume** to proceed with the decommission.

## Troubleshooting node decommissioning

If the node decommission procedure stops because of an error, you can take specific steps to troubleshoot the problem.

### What you'll need

You must be signed in to the Grid Manager using a supported browser.

### About this task

If you shut down the grid node being decommissioned, the task stops until the grid node is restarted. The grid node must be online.

### Steps

1. Select **Support > Tools > Grid Topology**.
2. In the Grid Topology tree, expand each Storage Node entry, and verify that the DDS and LDR services are both online.

To perform Storage Node decommissioning, the StorageGRID system's DDS services (hosted by Storage Nodes) must be online. This is a requirement of the ILM re-evaluation.

3. To view the active grid tasks, select **primary Admin Node > CMN > Grid Tasks > Overview**.
4. Check the status of the decommissioning grid task.
  - a. If the status of the decommissioning grid task indicates a problem with saving grid task bundles, select **primary Admin Node > CMN > Events > Overview**
  - b. Check the number of Available Audit Relays.

If the attribute Available Audit Relay is one or greater, the CMN service is connected to at least one ADC service. ADC services act as Audit Relays.

The CMN service must be connected to at least one ADC service and a majority (50 percent plus one) of the StorageGRID system's ADC services must be available in order for a grid task to move from one stage of decommissioning to another and finish.

- c. If the CMN service is not connected to enough ADC services, ensure that Storage Nodes are online, and check network connectivity between the primary Admin Node and Storage Nodes.

## Copyright information

Copyright © 2024 NetApp, Inc. All Rights Reserved. Printed in the U.S. No part of this document covered by copyright may be reproduced in any form or by any means—graphic, electronic, or mechanical, including photocopying, recording, taping, or storage in an electronic retrieval system—without prior written permission of the copyright owner.

Software derived from copyrighted NetApp material is subject to the following license and disclaimer:

THIS SOFTWARE IS PROVIDED BY NETAPP “AS IS” AND WITHOUT ANY EXPRESS OR IMPLIED WARRANTIES, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE, WHICH ARE HEREBY DISCLAIMED. IN NO EVENT SHALL NETAPP BE LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO, PROCUREMENT OF SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA, OR PROFITS; OR BUSINESS INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE) ARISING IN ANY WAY OUT OF THE USE OF THIS SOFTWARE, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE.

NetApp reserves the right to change any products described herein at any time, and without notice. NetApp assumes no responsibility or liability arising from the use of products described herein, except as expressly agreed to in writing by NetApp. The use or purchase of this product does not convey a license under any patent rights, trademark rights, or any other intellectual property rights of NetApp.

The product described in this manual may be protected by one or more U.S. patents, foreign patents, or pending applications.

LIMITED RIGHTS LEGEND: Use, duplication, or disclosure by the government is subject to restrictions as set forth in subparagraph (b)(3) of the Rights in Technical Data -Noncommercial Items at DFARS 252.227-7013 (FEB 2014) and FAR 52.227-19 (DEC 2007).

Data contained herein pertains to a commercial product and/or commercial service (as defined in FAR 2.101) and is proprietary to NetApp, Inc. All NetApp technical data and computer software provided under this Agreement is commercial in nature and developed solely at private expense. The U.S. Government has a non-exclusive, non-transferrable, nonsublicensable, worldwide, limited irrevocable license to use the Data only in connection with and in support of the U.S. Government contract under which the Data was delivered. Except as provided herein, the Data may not be used, disclosed, reproduced, modified, performed, or displayed without the prior written approval of NetApp, Inc. United States Government license rights for the Department of Defense are limited to those rights identified in DFARS clause 252.227-7015(b) (FEB 2014).

## Trademark information

NETAPP, the NETAPP logo, and the marks listed at <http://www.netapp.com/TM> are trademarks of NetApp, Inc. Other company and product names may be trademarks of their respective owners.