



配置软件 Install and maintain

NetApp
February 13, 2026

目录

- 配置软件 1
 - Cisco Nexus 3232C 存储交换机的软件安装工作流程 1
 - 配置 3232C 存储交换机 1
 - 准备安装 NX-OS 软件和参考配置文件 (RCF) 4
 - 安装 NX-OS 软件 10
 - 审查要求 10
 - 安装软件 10
 - 安装参考配置文件（RCF） 30
 - 步骤 1：在交换机上安装 RCF 31
 - 步骤 2：验证交换机连接 33
 - 步骤 3：设置ONTAP集群 36
 - 请检查您的 SSH 配置 36
 - 将 3232C 存储交换机重置为出厂默认值 38

配置软件

Cisco Nexus 3232C 存储交换机的软件安装工作流程

要安装和配置Cisco Nexus 3232C 交换机的软件并安装或升级参考配置文件 (RCF)，请按照以下步骤操作：

1

"配置交换机"

配置 3232C 存储交换机。

2

"准备安装 **NX-OS** 软件和 **RCF**"

必须在 Cisco 3232C 存储交换机上安装 Cisco NX-OS 软件和参考配置文件 (RCF)。

3

"安装 **NX-OS** 软件"

在 Cisco 3232C 存储交换机上下载并安装或升级 NX-OS 软件。

4

"安装 **RCF**"

首次设置 Cisco 3232C 存储交换机后安装 RCF。

5

"验证 **SSH** 配置"

验证交换机上是否启用了 SSH 以使用以太网交换机健康监视器 (CSHM) 和日志收集功能。

6

"将交换机重置为出厂默认设置"

清除 3232C 存储开关设置。

配置 3232C 存储交换机

按照以下步骤设置和配置Cisco Nexus 3232C 交换机。

开始之前

- 在安装现场访问 HTTP、FTP 或 TFTP 服务器，以下载适用的 NX-OS 和参考配置文件 (RCF) 版本。
- 适用的NX-OS版本，可从以下网址下载：["Cisco软件下载"](#)页。
- 所需的集群网络和管理网络交换机文档。

有关更多信息，请参见 ["所需文件"](#)。

- 需要提供控制器文档和ONTAP文档。

"NetApp文档"

- 适用的许可证、网络和配置信息以及线缆。
- 已完成布线工作表。
- 适用的NetApp集群网络和管理网络 RCF，可从NetApp支持站点下载。 ["mysupport.netapp.com"](https://mysupport.netapp.com)对于您收到的交换机。所有Cisco集群网络和管理网络交换机均采用Cisco标准出厂默认配置。这些交换机也安装了最新版本的 NX-OS 软件，但没有加载 RCF。

步骤

1. 将集群网络和管理网络交换机及控制器安装到机架上。

如果您正在安装.....	操作
NetApp系统机柜中的Cisco Nexus 3232C	有关在 NetApp 机柜中安装交换机的说明，请参阅 <i>Installing a Cisco Nexus 3232C switch and pass-through panel in a NetApp cabinet</i> 指南。
电信机架中的设备	请参阅交换机硬件安装指南和NetApp安装设置说明中提供的步骤。

2. 使用已完成的布线工作表，将集群网络和管理网络交换机连接到控制器。
3. 启动集群网络和管理网络交换机及控制器。
4. 对集群网络交换机进行初始配置。

首次启动交换机时，请对以下初始设置问题提供相应的答案。您网站的安全策略定义了要启用的响应和服务。

迅速的	响应
中止自动配置并继续进行正常设置？（是/否）	请回答“是”。默认值为否。
您是否希望强制执行安全密码标准？（是/否）	请回答“是”。默认值为“是”。
请输入管理员密码。	默认密码为“admin”；您必须创建一个新的、强密码。弱密码可能会被拒绝。
您想进入基本配置对话框吗？（是/否）	在交换机的初始配置阶段，请回答“是”。
创建另一个登录帐户？（是/否）	答案取决于您网站关于备用管理员的政策。默认值为*否*。
配置只读 SNMP 团体字符串？（是/否）	回答“不”。默认值为否。

迅速的	响应
配置读写 SNMP 团体字符串？（是/否）	回答“不”。默认值为否。
请输入交换机名称。	交换机名称限制为 63 个字母数字字符。
继续进行带外（mgmt0）管理配置？（是/否）	在该提示出现时，请回答“是”（默认值）。在 mgmt0 IPv4 地址提示符处，输入您的 IP 地址：ip_address。
配置默认网关？（是/否）	请回答“是”。在默认网关的 IPv4 地址提示符处，输入您的默认网关。
配置高级 IP 选项？（是/否）	回答“不”。默认值为否。
启用 Telnet 服务？（是/否）	回答“不”。默认值为否。
已启用 SSH 服务？（是/否）	请回答“是”。默认值为“是”。  使用以太网交换机健康监视器 (CSHM) 时，建议使用 SSH 进行日志收集。为了提高安全性，建议使用 SSHv2。
请输入要生成的 SSH 密钥类型（dsa/rsa/rsa1）。	默认值为 rsa 。
请输入密钥位数（1024-2048）。	请输入1024-2048之间的密钥位数。
配置NTP服务器？（是/否）	回答“不”。默认值为否。
配置默认接口层（L3/L2）：	请用*L2*回复。默认值为 L2。
配置交换机端口接口的默认状态（关闭/不关闭）：	回复 noshut 。默认设置为 noshut。
配置 CoPP 系统配置文件（严格/中等/宽松/严格）：	回复时请使用 strict 。默认设置为严格。
您想修改配置吗？（是/否）	此时您应该可以看到新的配置。请检查并对您刚刚输入的配置进行必要的更改。如果对配置满意，请在提示时回答“否”。如果要编辑配置设置，请回复“是”。
使用此配置并保存？（是/否）	回复“是”以保存配置。这会自动更新启动镜像和系统镜像。  如果此时不保存配置，下次重启交换机时，所有更改都将失效。

5. 在设置结束时显示的界面中，确认您所做的配置选择，并确保保存配置。
6. 检查集群网络交换机上的版本，如有必要，从 ["Cisco软件下载"](#) 页面将 NetApp 支持的软件版本下载到交换机。

下一步是什么？

配置好交换机后，您就可以["准备安装 NX-OS 和 RCF"](#)了。

准备安装 NX-OS 软件和参考配置文件 (RCF)

在安装 NX-OS 软件和参考配置文件 (RCF) 之前，请按照以下步骤操作。

关于示例

本流程中的示例使用了两个节点。这些节点使用两个 10GbE 集群互连端口 e0a 和 e0b。

参见["Hardware Universe"](#)验证平台上的集群端口是否正确。看 ["安装HWU中没有的设备还需要哪些额外信息？"](#) 有关交换机安装要求的更多信息。



命令输出可能因ONTAP版本不同而有所差异。

交换机和节点命名法

本流程中的示例使用以下开关和节点命名规则：

- 这两台Cisco交换机的名称是：cs1 和 cs2。
- 节点名称是 cluster1-01 和 cluster1-02。
- 集群 LIF 名称为 cluster1-01_clus1 和 cluster1-01_clus2 针对 cluster1-01 和 cluster1-02_clus1 和 cluster1-02_clus2 适用于集群1-02。
- 这 cluster1::*> 提示指示集群名称。

关于此任务

该过程需要同时使用ONTAP命令和Cisco Nexus 3000 系列交换机命令；除非另有说明，否则使用ONTAP命令。

步骤

1. 如果此集群上启用了AutoSupport，则通过调用AutoSupport消息来抑制自动创建案例：`system node autosupport invoke -node * -type all -message MAINT=x h`

其中 *x* 为维护窗口的持续时间（小时）。



AutoSupport消息会通知技术支持此维护任务，以便在维护窗口期间抑制自动创建案例。

2. 将权限级别更改为高级，并在提示继续时输入 **y**：

```
set -privilege advanced
```

高级提示(*>)出现。

3. 显示每个节点上每个集群互连交换机配置的集群互连接口数量：

```
network device-discovery show -protocol cdp
```

显示示例

```
cluster1::*> network device-discovery show -protocol cdp

Node/          Local  Discovered
Protocol      Port   Device (LLDP: ChassisID)  Interface
Platform
-----
cluster1-02/cdp
              e0a    cs1                      Eth1/2      N3K-
C3232C
              e0b    cs2                      Eth1/2      N3K-
C3232C
cluster1-01/cdp
              e0a    cs1                      Eth1/1      N3K-
C3232C
              e0b    cs2                      Eth1/1      N3K-
C3232C

4 entries were displayed.
```

4. 检查每个集群接口的管理或运行状态。

a. 显示网络端口属性：

```
network port show -ipspace Cluster
```

```
cluster1::*> network port show -ipspace Cluster
```

```
Node: cluster1-02
```

Port	IPspace	Broadcast Domain	Link	MTU	Speed(Mbps) Admin/Oper	Health Status
e0a	Cluster	Cluster	up	9000	auto/10000	healthy
e0b	Cluster	Cluster	up	9000	auto/10000	healthy

```
Node: cluster1-01
```

Port	IPspace	Broadcast Domain	Link	MTU	Speed(Mbps) Admin/Oper	Health Status
e0a	Cluster	Cluster	up	9000	auto/10000	healthy
e0b	Cluster	Cluster	up	9000	auto/10000	healthy

```
4 entries were displayed.
```

a. 显示有关 LIF 的信息: `network interface show -vserver Cluster`

显示示例

```
cluster1::*> network interface show -vserver Cluster
```

Current Vserver Port	Logical Current Is Interface Home	Status Admin/Oper	Network Address/Mask	Node

Cluster				
	cluster1-01_clus1	up/up	169.254.209.69/16	
cluster1-01	e0a true			
	cluster1-01_clus2	up/up	169.254.49.125/16	
cluster1-01	e0b true			
	cluster1-02_clus1	up/up	169.254.47.194/16	
cluster1-02	e0a true			
	cluster1-02_clus2	up/up	169.254.19.183/16	
cluster1-02	e0b true			

4 entries were displayed.

5. 验证远程集群接口的连接性:

ONTAP 9.9.1 及更高版本

你可以使用 `network interface check cluster-connectivity` 执行命令以启动集群连接性检查，然后显示详细信息：

`network interface check cluster-connectivity start` 和 `network interface check cluster-connectivity show`

```
cluster1::*> network interface check cluster-connectivity start
```

*注意：*运行程序前请等待几秒钟 `show` 显示详细信息的命令。

```
cluster1::*> network interface check cluster-connectivity show
```

			Source	Destination
Packet			LIF	LIF
Node	Date			
Loss				
-----	-----	-----	-----	-----
cluster1-01				
	3/5/2022 19:21:18 -06:00		cluster1-01_clus2	cluster1-02_clus1
none				
	3/5/2022 19:21:20 -06:00		cluster1-01_clus2	cluster1-02_clus2
none				
.				
.				
cluster1-02				
	3/5/2022 19:21:18 -06:00		cluster1-02_clus2	cluster1-01_clus1
none				
	3/5/2022 19:21:20 -06:00		cluster1-02_clus2	cluster1-01_clus2
none				

所有ONTAP版本

对于所有ONTAP版本，您也可以使用 `cluster ping-cluster -node <name>` 检查连接性的命令：

```
cluster ping-cluster -node <name>
```

```

cluster1::*> cluster ping-cluster -node local
Host is cluster1-02
Getting addresses from network interface table...
Cluster cluster1-01_clus1 169.254.209.69 cluster1-01 e0a
Cluster cluster1-01_clus2 169.254.49.125 cluster1-01 e0b
Cluster cluster1-02_clus1 169.254.47.194 cluster1-02 e0a
Cluster cluster1-02_clus2 169.254.19.183 cluster1-02 e0b
Local = 169.254.47.194 169.254.19.183
Remote = 169.254.209.69 169.254.49.125
Cluster Vserver Id = 4294967293
Ping status:....
Basic connectivity succeeds on 4 path(s)
Basic connectivity fails on 0 path(s)
.....
Detected 9000 byte MTU on 4 path(s):
    Local 169.254.19.183 to Remote 169.254.209.69
    Local 169.254.19.183 to Remote 169.254.49.125
    Local 169.254.47.194 to Remote 169.254.209.69
    Local 169.254.47.194 to Remote 169.254.49.125
Larger than PMTU communication succeeds on 4 path(s)
RPC status:
2 paths up, 0 paths down (tcp check)
2 paths up, 0 paths down (udp check)

```

1. 步骤6: 验证 auto-revert`该命令已在所有集群 LIF 上启用: `network interface show -vserver Cluster -fields auto-revert

显示示例

```

cluster1::*> network interface show -vserver Cluster -fields auto-
revert

```

Vserver	Logical Interface	Auto-revert
Cluster	cluster1-01_clus1	true
	cluster1-01_clus2	true
	cluster1-02_clus1	true
	cluster1-02_clus2	true

4 entries were displayed.

下一步是什么？

在您准备好安装 NX-OS 软件和 RCF 之后，您就可以["安装 NX-OS 软件"](#)了。

安装 NX-OS 软件

您可以使用此过程在 Nexus 3232C 存储交换机上安装 NX-OS 软件。

审查要求

开始之前

验证您是否具有以下内容：* 交换机配置的当前备份。* 功能齐全的集群（日志中没有错误或类似问题）。* ["Cisco 以太网交换机页面"](#)。有关支持的 ONTAP 和 NX-OS 版本，请参见交换机兼容性表。* ["Cisco Nexus 3000 系列交换机"](#)。有关 Cisco 交换机升级和降级过程的完整文档，请参见 Cisco 网站上提供的相应软件和升级指南。

安装软件

该过程需要同时使用 ONTAP 命令和 Cisco Nexus 3000 系列交换机命令；除非另有说明，否则使用 ONTAP 命令。

完成 ["准备安装 NX-OS 和 RCF"](#) 中的步骤，然后按照以下步骤操作。

步骤

1. 将集群交换机连接到管理网络。
2. 使用 `ping` 用于验证与托管 NX-OS 软件和 RCF 的服务器的连接性的命令。

显示示例

此示例验证交换机可以访问 IP 地址为 172.19.2.1 的服务器：

```
cs2# ping 172.19.2.1
Pinging 172.19.2.1 with 0 bytes of data:

Reply From 172.19.2.1: icmp_seq = 0. time= 5910 usec.
```

3. 显示每个节点上连接到集群交换机的集群端口：

```
network device-discovery show
```

```
cluster1::*> network device-discovery show
Node/          Local  Discovered
Protocol      Port   Device (LLDP: ChassisID)  Interface
Platform
-----
-----
cluster1-01/cdp
              e0a    cs1                      Ethernet1/7      N3K-
C3232C
              e0d    cs2                      Ethernet1/7      N3K-
C3232C
cluster1-02/cdp
              e0a    cs1                      Ethernet1/8      N3K-
C3232C
              e0d    cs2                      Ethernet1/8      N3K-
C3232C
cluster1-03/cdp
              e0a    cs1                      Ethernet1/1/1    N3K-
C3232C
              e0b    cs2                      Ethernet1/1/1    N3K-
C3232C
cluster1-04/cdp
              e0a    cs1                      Ethernet1/1/2    N3K-
C3232C
              e0b    cs2                      Ethernet1/1/2    N3K-
C3232C
cluster1::*>
```

4. 检查每个集群端口的管理和运行状态。
 - a. 确认集群所有端口均已启动且状态正常：


```
network port show -role cluster
```

```
cluster1::*> network port show -role cluster
```

```
Node: cluster1-01
```

```
Ignore
```

						Speed (Mbps)
Health	Health					
Port	IPspace	Broadcast	Domain	Link	MTU	Admin/Oper
Status	Status					
-----	-----	-----	-----	-----	-----	-----
e0a	Cluster	Cluster		up	9000	auto/100000
healthy	false					
e0d	Cluster	Cluster		up	9000	auto/100000
healthy	false					

```
Node: cluster1-02
```

```
Ignore
```

						Speed (Mbps)
Health	Health					
Port	IPspace	Broadcast	Domain	Link	MTU	Admin/Oper
Status	Status					
-----	-----	-----	-----	-----	-----	-----
e0a	Cluster	Cluster		up	9000	auto/100000
healthy	false					
e0d	Cluster	Cluster		up	9000	auto/100000
healthy	false					

```
8 entries were displayed.
```

```
Node: cluster1-03
```

```
Ignore
```

						Speed (Mbps)
Health	Health					
Port	IPspace	Broadcast	Domain	Link	MTU	Admin/Oper
Status	Status					
-----	-----	-----	-----	-----	-----	-----
e0a	Cluster	Cluster		up	9000	auto/10000
healthy	false					
e0b	Cluster	Cluster		up	9000	auto/10000
healthy	false					

Node: cluster1-04

Ignore

Health	Health					Speed (Mbps)
Port	IPspace	Broadcast	Domain	Link	MTU	Admin/Oper
Status	Status					
-----	-----	-----	-----	-----	-----	-----
e0a	Cluster	Cluster		up	9000	auto/10000
healthy	false					
e0b	Cluster	Cluster		up	9000	auto/10000
healthy	false					

cluster1::*>

b. 确认所有集群接口（LIF）都位于主端口上：

```
network interface show -role cluster
```

```

cluster1::*> network interface show -role cluster

```

Current	Logical	Status	Network	
Current Is				
Vserver	Interface	Admin/Oper	Address/Mask	Node
Port	Home			

Cluster				
	cluster1-01_clus1	up/up	169.254.3.4/23	
cluster1-01	e0a true			
	cluster1-01_clus2	up/up	169.254.3.5/23	
cluster1-01	e0d true			
	cluster1-02_clus1	up/up	169.254.3.8/23	
cluster1-02	e0a true			
	cluster1-02_clus2	up/up	169.254.3.9/23	
cluster1-02	e0d true			
	cluster1-03_clus1	up/up	169.254.1.3/23	
cluster1-03	e0a true			
	cluster1-03_clus2	up/up	169.254.1.1/23	
cluster1-03	e0b true			
	cluster1-04_clus1	up/up	169.254.1.6/23	
cluster1-04	e0a true			
	cluster1-04_clus2	up/up	169.254.1.7/23	
cluster1-04	e0b true			
8 entries were displayed.				
cluster1::*>				

c. 确认集群显示两个集群交换机的信息：

```

system cluster-switch show -is-monitoring-enabled-operational true

```



```

cluster1::*> system cluster-switch show -is-monitoring-enabled
-operational true
Switch                                     Type                                     Address
Model
-----
-----
cs1                                     cluster-network       10.233.205.90       N3K-
C3232C
    Serial Number: FOCXXXXXXGD
    Is Monitored: true
    Reason: None
    Software Version: Cisco Nexus Operating System (NX-OS) Software,
Version
                        9.3(5)
    Version Source: CDP

cs2                                     cluster-network       10.233.205.91       N3K-
C3232C
    Serial Number: FOCXXXXXXGS
    Is Monitored: true
    Reason: None
    Software Version: Cisco Nexus Operating System (NX-OS) Software,
Version
                        9.3(5)
    Version Source: CDP
cluster1::*>

```

5. 禁用集群 LIF 的自动回滚功能。集群 LIF 会故障转移到伙伴集群交换机，并在您对目标交换机执行升级过程时保留在该交换机上：

```
network interface modify -vserver Cluster -lif * -auto-revert false
```

6. 将 NX-OS 软件和 EPLD 映像复制到 Nexus 3232C 交换机。

```
cs2# copy sftp: bootflash: vrf management
Enter source filename: /code/nxos.9.3.4.bin
Enter hostname for the sftp server: 172.19.2.1
Enter username: user1

Outbound-ReKey for 172.19.2.1:22
Inbound-ReKey for 172.19.2.1:22
user1@172.19.2.1's password:
sftp> progress
Progress meter enabled
sftp> get    /code/nxos.9.3.4.bin    /bootflash/nxos.9.3.4.bin
/code/nxos.9.3.4.bin  100% 1261MB    9.3MB/s    02:15
sftp> exit
Copy complete, now saving to disk (please wait)...
Copy complete.

cs2# copy sftp: bootflash: vrf management
Enter source filename: /code/n9000-epld.9.3.4.img
Enter hostname for the sftp server: 172.19.2.1
Enter username: user1

Outbound-ReKey for 172.19.2.1:22
Inbound-ReKey for 172.19.2.1:22
user1@172.19.2.1's password:
sftp> progress
Progress meter enabled
sftp> get    /code/n9000-epld.9.3.4.img    /bootflash/n9000-
epld.9.3.4.img
/code/n9000-epld.9.3.4.img  100%  161MB    9.5MB/s    00:16
sftp> exit
Copy complete, now saving to disk (please wait)...
Copy complete.
```

7. 请确认NX-OS软件的运行版本:

```
show version
```

```
cs2# show version
Cisco Nexus Operating System (NX-OS) Software
TAC support: http://www.cisco.com/tac
Copyright (C) 2002-2019, Cisco and/or its affiliates.
All rights reserved.
The copyrights to certain works contained in this software are
owned by other third parties and used and distributed under their
own
licenses, such as open source. This software is provided "as is,"
and unless
otherwise stated, there is no warranty, express or implied,
including but not
limited to warranties of merchantability and fitness for a
particular purpose.
Certain components of this software are licensed under
the GNU General Public License (GPL) version 2.0 or
GNU General Public License (GPL) version 3.0 or the GNU
Lesser General Public License (LGPL) Version 2.1 or
Lesser General Public License (LGPL) Version 2.0.
A copy of each such license is available at
http://www.opensource.org/licenses/gpl-2.0.php and
http://opensource.org/licenses/gpl-3.0.html and
http://www.opensource.org/licenses/lgpl-2.1.php and
http://www.gnu.org/licenses/old-licenses/library.txt.

Software
  BIOS: version 08.37
  NXOS: version 9.3(3)
  BIOS compile time: 01/28/2020
  NXOS image file is: bootflash:///nxos.9.3.3.bin
  NXOS compile time: 12/22/2019 2:00:00 [12/22/2019 14:00:37]

Hardware
  cisco Nexus3000 C3232C Chassis (Nexus 9000 Series)
  Intel(R) Xeon(R) CPU E5-2403 v2 @ 1.80GHz with 8154432 kB of
memory.
  Processor Board ID FOCXXXXXXGD

  Device name: cs2
  bootflash: 53298520 kB
Kernel uptime is 0 day(s), 0 hour(s), 3 minute(s), 36 second(s)

Last reset at 74117 usecs after Tue Nov 24 06:24:23 2020
Reason: Reset Requested by CLI command reload
```

```
System version: 9.3(3)
```

```
Service:
```

```
plugin
```

```
Core Plugin, Ethernet Plugin
```

```
Active Package(s):
```

```
cs2#
```

8. 安装 NX-OS 镜像。

安装镜像文件后，每次交换机重启时都会加载该文件。

```

cs2# install all nxos bootflash:nxos.9.3.4.bin
Installer will perform compatibility check first. Please wait.
Installer is forced disruptive

Verifying image bootflash:/nxos.9.3.4.bin for boot variable "nxos".
[] 100% -- SUCCESS

Verifying image type.
[] 100% -- SUCCESS

Preparing "nxos" version info using image bootflash:/nxos.9.3.4.bin.
[] 100% -- SUCCESS

Preparing "bios" version info using image bootflash:/nxos.9.3.4.bin.
[] 100% -- SUCCESS

Performing module support checks.
[] 100% -- SUCCESS

Notifying services about system upgrade.
[] 100% -- SUCCESS

Compatibility check is done:
Module  bootable          Impact          Install-type  Reason
-----  -
1      Yes                Disruptive          Reset          Default
upgrade is not hitless

Images will be upgraded according to following table:
Module      Image      Running-Version(pri:alt)
New-Version      Upg-Required
-----  -
1      nxos      9.3(3)
9.3(4)      yes
1      bios      v08.37(01/28/2020):v08.32(10/18/2016)
v08.37(01/28/2020)  no

Switch will be reloaded for disruptive upgrade.
Do you want to continue with the installation (y/n)? [n] y

```

```
Install is in progress, please wait.
```

```
Performing runtime checks.
```

```
[] 100% -- SUCCESS
```

```
Setting boot variables.
```

```
[] 100% -- SUCCESS
```

```
Performing configuration copy.
```

```
[] 100% -- SUCCESS
```

```
Module 1: Refreshing compact flash and upgrading  
bios/loader/bootrom.
```

```
Warning: please do not remove or power off the module at this time.
```

```
[] 100% -- SUCCESS
```

```
Finishing the upgrade, switch will reboot in 10 seconds.
```

```
cs2#
```

9. 交换机重启后，请验证NX-OS软件的新版本：

```
show version
```

```
cs2# show version
Cisco Nexus Operating System (NX-OS) Software
TAC support: http://www.cisco.com/tac
Copyright (C) 2002-2020, Cisco and/or its affiliates.
All rights reserved.
The copyrights to certain works contained in this software are
owned by other third parties and used and distributed under their
own
licenses, such as open source. This software is provided "as is,"
and unless
otherwise stated, there is no warranty, express or implied,
including but not
limited to warranties of merchantability and fitness for a
particular purpose.
Certain components of this software are licensed under
the GNU General Public License (GPL) version 2.0 or
GNU General Public License (GPL) version 3.0 or the GNU
Lesser General Public License (LGPL) Version 2.1 or
Lesser General Public License (LGPL) Version 2.0.
A copy of each such license is available at
http://www.opensource.org/licenses/gpl-2.0.php and
http://opensource.org/licenses/gpl-3.0.html and
http://www.opensource.org/licenses/lgpl-2.1.php and
http://www.gnu.org/licenses/old-licenses/library.txt.

Software
  BIOS: version 08.37
  NXOS: version 9.3(4)
  BIOS compile time: 01/28/2020
  NXOS image file is: bootflash:///nxos.9.3.4.bin
  NXOS compile time: 4/28/2020 21:00:00 [04/29/2020 06:28:31]

Hardware
  cisco Nexus3000 C3232C Chassis (Nexus 9000 Series)
  Intel(R) Xeon(R) CPU E5-2403 v2 @ 1.80GHz with 8154432 kB of
memory.
  Processor Board ID FOCXXXXXXGS

  Device name: rtpnpi-mcc01-8200-ms-A1
  bootflash: 53298520 kB
Kernel uptime is 0 day(s), 0 hour(s), 3 minute(s), 14 second(s)

Last reset at 196755 usecs after Tue Nov 24 06:37:36 2020
Reason: Reset due to upgrade
```

```
System version: 9.3(3)
```

```
Service:
```

```
plugin
```

```
Core Plugin, Ethernet Plugin
```

```
Active Package(s):
```

```
cs2#
```

10. 升级EPLD镜像并重启交换机。


```
cs2# show version module 1 epld
```

EPLD Device	Version
MI FPGA	0x12
IO FPGA	0x11

```
cs2# install epld bootflash:n9000-epld.9.3.4.img module 1
```

Compatibility check:

Module	Type	Upgradable	Impact	Reason
1	SUP	Yes	Disruptive	Module Upgradable

Retrieving EPLD versions.... Please wait.

Images will be upgraded according to following table:

Module	Type	EPLD	Running-Version	New-Version	Upg-Required
1	SUP	MI FPGA	0x12	0x12	No
1	SUP	IO FPGA	0x11	0x12	Yes

The above modules require upgrade.

The switch will be reloaded at the end of the upgrade

Do you want to continue (y/n) ? [n] **y**

Proceeding to upgrade Modules.

Starting Module 1 EPLD Upgrade

Module 1 : IO FPGA [Programming] : 100.00% (64 of 64 sectors)

Module 1 EPLD upgrade is successful.

Module	Type	Upgrade-Result
1	SUP	Success

Module 1 EPLD upgrade is successful.

```
cs2#
```

- 如果您要升级到 NX-OS 版本 9.3(11), 则必须升级 EPLD。`golden`镜像并再次重启交换机。否则, 跳至步骤 12。

看 "EPLD 升级版本说明, 版本 9.3(11)"更多详情请见下文。

显示示例

```
cs2# install epld bootflash:n9000-epld.9.3.11.img module 1 golden
Digital signature verification is successful
Compatibility check:
Module          Type          Upgradable      Impact          Reason
-----
-----
          1          SUP          Yes          Disruptive      Module
Upgradable

Retrieving EPLD versions.... Please wait.
The above modules require upgrade.
The switch will be reloaded at the end of the upgrade
Do you want to continue (y/n) ?  [n] y

Proceeding to upgrade Modules.

Starting Module 1 EPLD Upgrade

Module 1 : MI FPGA [Programming] : 100.00% (      64 of      64 sect)
Module 1 : IO FPGA [Programming] : 100.00% (      64 of      64 sect)
Module 1 EPLD upgrade is successful.
Module          Type          Upgrade-Result
-----
-----
          1          SUP          Success

EPLDs upgraded.

Module 1 EPLD upgrade is successful.
cs2#
```

12. 交换机重启后，登录以验证新版本的 EPLD 是否已成功加载。

显示示例

```
cs2# show version module 1 epld
```

EPLD Device		Version

MI	FPGA	0x12
IO	FPGA	0x12

13. 检查集群上集群端口的运行状况。

a. 确认集群中所有节点的集群端口均已启动且运行状况良好：

```
network port show -role cluster
```

```
cluster1::*> network port show -role cluster
```

```
Node: cluster1-01
```

```
Ignore
```

						Speed (Mbps)
Health	Health					
Port	IPspace	Broadcast	Domain	Link	MTU	Admin/Oper
Status	Status					
-----	-----	-----	-----	-----	-----	-----
e0a	Cluster	Cluster		up	9000	auto/10000
healthy	false					
e0b	Cluster	Cluster		up	9000	auto/10000
healthy	false					

```
Node: cluster1-02
```

```
Ignore
```

						Speed (Mbps)
Health	Health					
Port	IPspace	Broadcast	Domain	Link	MTU	Admin/Oper
Status	Status					
-----	-----	-----	-----	-----	-----	-----
e0a	Cluster	Cluster		up	9000	auto/10000
healthy	false					
e0b	Cluster	Cluster		up	9000	auto/10000
healthy	false					

```
Node: cluster1-03
```

```
Ignore
```

						Speed (Mbps)
Health	Health					
Port	IPspace	Broadcast	Domain	Link	MTU	Admin/Oper
Status	Status					
-----	-----	-----	-----	-----	-----	-----
e0a	Cluster	Cluster		up	9000	auto/100000
healthy	false					
e0d	Cluster	Cluster		up	9000	auto/100000
healthy	false					

Node: cluster1-04

Ignore

Health	Health				Speed (Mbps)
Port	IPspace	Broadcast	Domain	Link	MTU
Status	Status				Admin/Oper
-----	-----	-----	-----	-----	-----
e0a	Cluster	Cluster		up	9000
healthy	false				auto/100000
e0d	Cluster	Cluster		up	9000
healthy	false				auto/100000

8 entries were displayed.

b. 从集群中验证交换机的运行状况。

```
network device-discovery show -protocol cdp
```

```
cluster1::*> network device-discovery show -protocol cdp
```

Node/	Local	Discovered		
Protocol	Port	Device (LLDP: ChassisID)	Interface	
Platform				
cluster1-01/cdp				
	e0a	cs1	Ethernet1/7	N3K-
C3232C				
	e0d	cs2	Ethernet1/7	N3K-
C3232C				
cluster01-2/cdp				
	e0a	cs1	Ethernet1/8	N3K-
C3232C				
	e0d	cs2	Ethernet1/8	N3K-
C3232C				
cluster01-3/cdp				
	e0a	cs1	Ethernet1/1/1	N3K-
C3232C				
	e0b	cs2	Ethernet1/1/1	N3K-
C3232C				
cluster1-04/cdp				
	e0a	cs1	Ethernet1/1/2	N3K-
C3232C				
	e0b	cs2	Ethernet1/1/2	N3K-
C3232C				

```
cluster1::*> system cluster-switch show -is-monitoring-enabled
-operational true
```

Switch	Type	Address	
Model			
cs1	cluster-network	10.233.205.90	N3K-
C3232C			
Serial Number: FOCXXXXXXGD			
Is Monitored: true			
Reason: None			
Software Version: Cisco Nexus Operating System (NX-OS) Software,			
Version			
9.3(5)			
Version Source: CDP			
cs2	cluster-network	10.233.205.91	N3K-

```

C3232C
  Serial Number: FOCXXXXXXGS
    Is Monitored: true
      Reason: None
  Software Version: Cisco Nexus Operating System (NX-OS) Software,
Version
                      9.3(5)
  Version Source: CDP

2 entries were displayed.

```

根据交换机上先前加载的 RCF 版本，您可能会在 cs1 交换机控制台上看到以下输出：

```

2020 Nov 17 16:07:18 cs1 %$ VDC-1 %$ %STP-2-UNBLOCK_CONSIST_PORT:
Unblocking port port-channel1 on VLAN0092. Port consistency
restored.
2020 Nov 17 16:07:23 cs1 %$ VDC-1 %$ %STP-2-BLOCK_PVID_PEER:
Blocking port-channel1 on VLAN0001. Inconsistent peer vlan.
2020 Nov 17 16:07:23 cs1 %$ VDC-1 %$ %STP-2-BLOCK_PVID_LOCAL:
Blocking port-channel1 on VLAN0092. Inconsistent local vlan.

```

14. 验证集群是否运行正常：

```
cluster show
```

显示示例

```

cluster1::*> cluster show
Node           Health    Eligibility    Epsilon
-----
cluster1-01    true     true           false
cluster1-02    true     true           false
cluster1-03    true     true           true
cluster1-04    true     true           false
4 entries were displayed.
cluster1::*>

```

15. 在交换机 cs1 上重复步骤 6 至 14。

16. 启用集群 LIF 的自动回滚功能。

```
network interface modify -vserver Cluster -lif * -auto-revert true
```

17. 确认集群 LIF 已恢复到其原端口：

```
network interface show -role cluster
```

显示示例

```
cluster1::*> network interface show -role cluster
```

	Logical	Status	Network	Current
Current Is				
Vserver	Interface	Admin/Oper	Address/Mask	Node
Port	Home			

Cluster				
	cluster1-01_clus1	up/up	169.254.3.4/23	
cluster1-01	e0d	true		
	cluster1-01_clus2	up/up	169.254.3.5/23	
cluster1-01	e0d	true		
	cluster1-02_clus1	up/up	169.254.3.8/23	
cluster1-02	e0d	true		
	cluster1-02_clus2	up/up	169.254.3.9/23	
cluster1-02	e0d	true		
	cluster1-03_clus1	up/up	169.254.1.3/23	
cluster1-03	e0b	true		
	cluster1-03_clus2	up/up	169.254.1.1/23	
cluster1-03	e0b	true		
	cluster1-04_clus1	up/up	169.254.1.6/23	
cluster1-04	e0b	true		
	cluster1-04_clus2	up/up	169.254.1.7/23	
cluster1-04	e0b	true		

8 entries were displayed.

```
cluster1::*>
```

如果任何集群 LIF 尚未返回到其源端口，请从本地节点手动将其还原：

```
network interface revert -vserver Cluster -lif <lif_name>
```

下一步是什么？

安装 NX-OS 软件后，您可以["安装或升级参考配置文件（RCF）"](#)。

安装参考配置文件（RCF）

首次设置 Nexus 3232C 交换机后，安装参考配置文件 (RCF)。

开始之前

请核实以下安装和连接：

- 交换机配置的当前备份。
- 一个功能齐全的集群（日志中没有错误或类似问题）。
- 当前的RCF。
- 与交换机的控制台连接，这是安装 RCF 时需要的。

关于此任务

该过程需要同时使用ONTAP命令和Cisco Nexus 3000 系列交换机命令；除非另有说明，否则使用ONTAP命令。

在此过程中不需要任何可操作的交换机间链路 (ISL)。这是设计使然，因为 RCF 版本的更改可能会暂时影响 ISL 连接。为了实现无中断集群操作，以下步骤将所有集群 LIF 迁移到可操作的合作伙伴交换机，同时在目标交换机上执行步骤。

完成 "准备安装 NX-OS 和 RCF" 中的步骤，然后按照以下步骤操作。

步骤 1：在交换机上安装 RCF

1. 使用 SSH 或串行控制台登录到 switch cs2。
2. 使用以下传输协议之一将 RCF 复制到交换机 cs2 的 bootflash：FTP、TFTP、SFTP 或 SCP。有关Cisco命令的更多信息，请参阅 "[Cisco Nexus 3000 系列 NX-OS 命令参考](#)"。

显示示例

此示例展示了如何使用 TFTP 将 RCF 文件复制到交换机 cs2 的启动闪存中：

```
cs2# copy tftp: bootflash: vrf management
Enter source filename: Nexus_3232C_RCF_v1.6-Cluster-HA-Breakout.txt
Enter hostname for the tftp server: 172.22.201.50
Trying to connect to tftp server.....Connection to Server
Established.
TFTP get operation was successful
Copy complete, now saving to disk (please wait)...
```

3. 将之前下载的 RCF 文件应用到启动闪存中。

有关Cisco命令的更多信息，请参阅 "[Cisco Nexus 3000 系列 NX-OS 命令参考](#)"。

显示示例

此示例展示了 RCF 文件 `Nexus\_3232C\_RCF\_v1.6-Cluster-HA-Breakout.txt` 正在交换机 cs2 上安装：

```
cs2# copy Nexus_3232C_RCF_v1.6-Cluster-HA-Breakout.txt running-  
config echo-commands
```



请务必仔细阅读 RCF 的 **Installation notes**、**Important Notes** 和 **banner** 部分。您必须阅读并遵循这些说明来验证交换机的正确配置和操作。

4. 检查横幅输出 `show banner motd` 命令。您必须阅读并遵循“重要提示”下的说明，以确保交换机的正确配置和操作。
5. 请确认 RCF 是否为正确的最新版本：

```
show running-config
```

检查输出结果以验证是否拥有正确的 RCF 时，请确保以下信息正确：

- RCF 横幅
- 节点和端口设置
- 定制

输出结果会根据您的网站配置而有所不同。检查端口设置，并参考发行说明，了解您安装的 RCF 版本是否有任何特定更改。

6. 将之前对交换机配置所做的任何自定义设置重新应用。
7. 保存基本配置详细信息 `write\_erase.cfg` 启动闪存上的文件。



确保配置以下内容：* 用户名和密码* 管理 IP 地址* 默认网关* 交换机名称

```
cs2# show run | section "switchname" > bootflash:write_erase.cfg
```

```
cs2# show run | section "hostname" >> bootflash:write_erase.cfg
```

```
cs2# show run | i "username admin password" >> bootflash:write_erase.cfg
```

```
cs2# show run | section "vrf context management" >> bootflash:write_erase.cfg
```

```
cs2# show run | section "interface mgmt0" >> bootflash:write_erase.cfg
```

8. 安装 RCF 1.12 及更高版本时，请运行以下命令：

```
cs2# echo "hardware access-list tcam region racl-lite 512" >>  
bootflash:write_erase.cfg
```

```
cs2# echo "hardware access-list tcam region qos 256" >>
```

```
bootflash:write_erase.cfg
```

请参阅知识库文章 ["如何在保持远程连接的情况下清除Cisco互连交换机上的配置"](#)更多详情请见下文。

9. 确认 `write\_erase.cfg` 文件已按预期填充:

```
show file bootflash:write_erase.cfg
```

10. 问题 `write erase` 清除当前已保存配置的命令:

```
cs2# write erase
```

```
Warning: This command will erase the startup-configuration.
```

```
Do you wish to proceed anyway? (y/n) [n] y
```

11. 将之前保存的基本配置复制到启动配置中。

```
cs2# copy bootflash:write_erase.cfg startup-config
```

12. 重启交换机cs2:

```
cs2# reload
```

```
This command will reboot the system. (y/n)? [n] y
```

13. 在交换机 cs1 上重复步骤 1 至 12。

14. 将ONTAP集群中所有节点的集群端口连接到交换机 cs1 和 cs2。

步骤 2: 验证交换机连接

1. 确认连接到集群端口的交换机端口已启用。

```
show interface brief | grep up
```

显示示例

```
cs1# show interface brief | grep up
.
.
Eth1/1/1      1      eth  access up      none
10G(D)  --
Eth1/1/2      1      eth  access up      none
10G(D)  --
Eth1/7        1      eth  trunk  up      none
100G(D)  --
Eth1/8        1      eth  trunk  up      none
100G(D)  --
.
.
```

2. 验证 cs1 和 cs2 之间的 ISL 连接是否正常:

```
show port-channel summary
```

显示示例

```
cs1# show port-channel summary
Flags:  D - Down          P - Up in port-channel (members)
        I - Individual    H - Hot-standby (LACP only)
        s - Suspended     r - Module-removed
        b - BFD Session Wait
        S - Switched      R - Routed
        U - Up (port-channel)
        p - Up in delay-lacp mode (member)
        M - Not in use. Min-links not met

-----
-----
Group Port-          Type      Protocol  Member Ports
Channel
-----
-----
1      Po1(SU)        Eth      LACP      Eth1/31(P)  Eth1/32(P)
cs1#
```

3. 确认集群 LIF 已恢复到其原端口:

```
network interface show -role cluster
```

```
cluster1::*> network interface show -role cluster
```

	Logical	Status	Network	Current
Current Is				
Vserver	Interface	Admin/Oper	Address/Mask	Node
Port	Home			

Cluster				
	cluster1-01_clus1	up/up	169.254.3.4/23	
cluster1-01	e0d	true		
	cluster1-01_clus2	up/up	169.254.3.5/23	
cluster1-01	e0d	true		
	cluster1-02_clus1	up/up	169.254.3.8/23	
cluster1-02	e0d	true		
	cluster1-02_clus2	up/up	169.254.3.9/23	
cluster1-02	e0d	true		
	cluster1-03_clus1	up/up	169.254.1.3/23	
cluster1-03	e0b	true		
	cluster1-03_clus2	up/up	169.254.1.1/23	
cluster1-03	e0b	true		
	cluster1-04_clus1	up/up	169.254.1.6/23	
cluster1-04	e0b	true		
	cluster1-04_clus2	up/up	169.254.1.7/23	
cluster1-04	e0b	true		
8 entries were displayed.				
cluster1::*>				

如果任何集群 LIFS 尚未返回其主端口，请手动将其恢复： network interface revert -vserver <vserver_name> -lif <lif_name>

4. 验证集群是否运行正常：

```
cluster show
```

```
cluster1::*> cluster show
Node                Health  Eligibility  Epsilon
-----
cluster1-01         true    true         false
cluster1-02         true    true         false
cluster1-03         true    true         true
cluster1-04         true    true         false
4 entries were displayed.
cluster1::*>
```

步骤 3：设置ONTAP集群

NetApp建议您使用系统管理器来设置新的集群。

系统管理器为集群设置和配置提供了简单易行的工作流程，包括分配节点管理 IP 地址、初始化集群、创建本地层、配置协议和配置初始存储。

参考 ["使用 System Manager 在新集群上配置ONTAP"](#)了解设置说明。

下一步是什么？

安装完 RCF 后，您可以..... ["验证 SSH 配置"](#)。

请检查您的 SSH 配置

如果您正在使用以太网交换机健康监视器 (CSHM) 和日志收集功能，请确认集群交换机上已启用 SSH 和 SSH 密钥。

步骤

1. 确认 SSH 已启用：

```
(switch) show ssh server
ssh version 2 is enabled
```

2. 请确认 SSH 密钥已启用：

```
show ssh key
```

```
(switch) # show ssh key

rsa Keys generated:Fri Jun 28 02:16:00 2024

ssh-rsa
AAAAB3NzaC1yc2EAAAADAQABAAQGDINrD52Q586wTGJjFABjBlFaA23EpDrZ2sDCew
17nwlioC6HBejxluIObAH8hrW8kR+gj0ZAfPpNeLGTg3APj/yIPTBoIZZxbWRShywAM5
PqyxWwRb7kp9Zt1YHzVuHYpSO82KUDowKrL6lox/YtpKoZUDZjrZjAp8hTv3JZsPgQ==

bitcount:1024
fingerprint:
SHA256:aHwhpzo7+YCDSrp3isJv2uVGz+mjMMokqdMeXVVXfdo

could not retrieve dsa key information

ecdsa Keys generated:Fri Jun 28 02:30:56 2024

ecdsa-sha2-nistp521
AAAAE2VjZHNhLXNoYTItbmlzdHA1MjEAAAIAbm1zdHA1MjEAAACFBABJ+ZX5SFKhS57e
vKE273e0VoqZi4/32dt+f14fBuKv80MjMsmLfjKtCWylwgVt1Zi+C5TIBbugpzez529z
kFSF0ADb8JaGCoaAYe2HvWR/f6QLbKbqVIewCdqWgxzrIY5BPP5GBdxQJMBiOwEdnHg1
u/9Pzh/Vz9cHDcCW9qGE780QHA==

bitcount:521
fingerprint:
SHA256:TFGe2hXn6QIpcs/vyHzftHJ7Dceg0vQaULYRA1ZeHwQ

(switch) # show feature | include scpServer
scpServer          1          enabled
(switch) # show feature | include ssh
sshServer           1          enabled
(switch) #
```



启用 FIPS 时，必须使用以下命令将交换机上的位计数更改为 256。ssh key ecdsa 256 force。看 ["使用 FIPS 配置网络安全"](#) 更多详情请见下文。

下一步是什么？

验证完 SSH 配置后，您可以..... ["配置交换机健康监控"](#)。

将 3232C 存储交换机重置为出厂默认值

要将 3232C 存储开关重置为出厂默认值，必须擦除 3232C 存储开关设置。

关于此任务

- 您必须使用串口控制台连接到交换机。
- 此任务会重置管理网络的配置。

步骤

1. 清除现有配置：

```
write erase
```

```
(cs2)# write erase
```

```
Warning: This command will erase the startup-configuration.  
Do you wish to proceed anyway? (y/n) [n] y
```

2. 重新加载交换机软件：

```
reload
```

```
(cs2)# reload
```

```
This command will reboot the system. (y/n)? [n] y
```

系统重新启动并进入配置向导。在启动过程中，如果收到提示“中止自动配置并继续正常设置？”(yes/no)[n]，您应该回答*yes*才能继续。

下一步

重置开关后，您可以根据自己的要求[重新配置](#)它。

版权信息

版权所有 © 2026 NetApp, Inc.。保留所有权利。中国印刷。未经版权所有者事先书面许可，本文档中受版权保护的任何部分不得以任何形式或通过任何手段（图片、电子或机械方式，包括影印、录音、录像或存储在电子检索系统中）进行复制。

从受版权保护的 NetApp 资料派生的软件受以下许可和免责声明的约束：

本软件由 NetApp 按“原样”提供，不含任何明示或暗示担保，包括但不限于适销性以及针对特定用途的适用性的隐含担保，特此声明不承担任何责任。在任何情况下，对于因使用本软件而以任何方式造成的任何直接性、间接性、偶然性、特殊性、惩罚性或后果性损失（包括但不限于购买替代商品或服务；使用、数据或利润方面的损失；或者业务中断），无论原因如何以及基于何种责任理论，无论出于合同、严格责任或侵权行为（包括疏忽或其他行为），NetApp 均不承担责任，即使已被告知存在上述损失的可能性。

NetApp 保留在不另行通知的情况下随时对本文档所述的任何产品进行更改的权利。除非 NetApp 以书面形式明确同意，否则 NetApp 不承担因使用本文档所述产品而产生的任何责任或义务。使用或购买本产品不表示获得 NetApp 的任何专利权、商标权或任何其他知识产权许可。

本手册中描述的产品可能受一项或多项美国专利、外国专利或正在申请的专利的保护。

有限权利说明：政府使用、复制或公开本文档受 DFARS 252.227-7013（2014 年 2 月）和 FAR 52.227-19（2007 年 12 月）中“技术数据权利 — 非商用”条款第 (b)(3) 条规定的限制条件的约束。

本文档中所含数据与商业产品和/或商业服务（定义见 FAR 2.101）相关，属于 NetApp, Inc. 的专有信息。根据本协议提供的所有 NetApp 技术数据和计算机软件具有商业性质，并完全由私人出资开发。美国政府对这些数据的使用权具有非排他性、全球性、受限且不可撤销的许可，该许可既不可转让，也不可再许可，但仅限在与交付数据所依据的美国政府合同有关且受合同支持的情况下使用。除本文档规定的情形外，未经 NetApp, Inc. 事先书面批准，不得使用、披露、复制、修改、操作或显示这些数据。美国政府对国防部的授权仅限于 DFARS 的第 252.227-7015(b)（2014 年 2 月）条款中明确的权利。

商标信息

NetApp、NetApp 标识和 <http://www.netapp.com/TM> 上所列的商标是 NetApp, Inc. 的商标。其他公司和产品名称可能是其各自所有者的商标。