Exemples de réponse

Element Software

NetApp
November 19, 2025

This PDF was generated from https://docs.netapp.com/fr-fr/element-software-123/api/reference_element_api_response_example_getconfig.html on November 19, 2025. Always check docs.netapp.com for the latest.

Sommaire

Exemples de réponse . . . 1
- Trouvez plus d’informations . . . 1
- Getconfig . . . 1
- GetClusterHardwareInfo . . . 4
- GetLldpInfo . . . 17
- GetNetworkConfig . . . 47
- GetNodeHardwareInfo (sortie pour iSCSI) . . . 51
- GetNodeHardwareInfo (sortie pour nœuds Fibre Channel) . . . 53
- GetNvramInfo . . . 60
- ListenActiveNodes . . . 69
- ActivéNon . . . 72
- TestHardwareConfig . . . 82

Exemples de réponse

Vous trouverez des exemples de réponse complets ici.

- Getconfig
- GetClusterHardwareInfo
- GetLldpInfo
- GetNetworkConfig
- GetNodeHardwareInfo (sortie pour iSCSI)
- GetNodeHardwareInfo (sortie pour nœuds Fibre Channel)
- GetNvramInfo
- ListenActiveNodes
- ActivéNon
- TestHardwareConfig

Trouvez plus d'informations

- "Documentation SolidFire et Element"
- "Documentation relative aux versions antérieures des produits NetApp SolidFire et Element"

Getconfig

Le `GetConfig` la méthode renvoie une réponse similaire à l'exemple suivant. Du fait de sa longueur, la réponse contient des informations relatives à un seul nœud du cluster.


```
{
    "id": 1,
    "result": {
        "config": {
            "cluster": {
                "cipi": "Bond10G",
                "cluster": "AutoTest2-Fjqt",
                "encryptionCapable": true,
                "ensemble": [
                    "1:10.1.1.0",
                    "3:10.1.1.0",
                    "4:10.1.1.0"
                ],
                "mipi": "Bond1G",
                "name": "NLABP2605",
                "nodeID": 1,
                "pendingNodeID": 0,
                "role": "Storage",
```

```
                "sipi": "Bond10G",
                "state": "Active",
                "version": "11.0"
            },
            "network": {
            "Bond10G": {
                "#default": false,
                "address": "10.1.1.0",
                "auto": true,
                "bond-downdelay": "0",
                "bond-fail_over_mac": "None",
                "bond-miimon": "100",
                "bond-mode": "ActivePassive",
                "bond-primary_reselect": "Failure",
                "bond-slaves": "eth0 eth1",
                "bond-updelay": "200",
                "dns-nameservers": "10.1.1.0, 10.1.1.0",
                "dns-search": "ten.test.company.net., company.net.",
                "family": "inet",
                "gateway": "10.1.1.0",
                "linkSpeed": 10000,
                "macAddress": "c8:1f:66:ee:59:b9",
                "macAddressPermanent": "00:00:00:00:00:00",
                "method": "static",
                "mtu": "9000",
                "netmask": "255.255.240.0",
                "network": "10.1.1.0",
                "physical": {
                    "address": "10.1.1.0",
                    "macAddress": "c8:1f:66:ee:59:b9",
                    "macAddressPermanent": "00:00:00:00:00:00",
                    "mtu": "9000",
                    "netmask": "255.255.240.0",
                    "network": "10.1.1.0",
                    "upAndRunning": true
                },
                "routes": [],
                "status": "UpAndRunning",
                "symmetricRouteRules": [
                    "ip route add 10.1.1.1/20 dev Bond1G src 10.1.2.2
table Bond1G",
                    "ip rule add from 10.1.1.1 table Bond1G",
                    "ip route add default via 10.1.1.254"
                ],
                "upAndRunning": true,
                "virtualNetworkTag": "0"
```

```
            },
            "eth0": {
                "auto": true,
                "bond-master": "Bond10G",
                "family": "inet",
                "linkSpeed": 10000,
                "macAddress": "c8:1f:66:ee:59:b9",
                "macAddressPermanent": "c8:1f:66:ee:59:b9",
                "method": "bond",
                "physical": {
                    "address": "0.0.0.0",
                    "macAddress": "c8:1f:66:ee:59:b9",
                    "macAddressPermanent": "c8:1f:66:ee:59:b9",
                    "netmask": "N/A",
                    "network": "N/A",
                    "upAndRunning": true
                },
                "status": "UpAndRunning",
                "upAndRunning": true
            },
            "lo": {
                "auto": true,
                "family": "inet",
                "linkSpeed": 0,
                "macAddress": "00:00:00:00:00:00",
                "macAddressPermanent": "00:00:00:00:00:00",
                "method": "loopback",
                "physical": {
                    "address": "0.0.0.0",
                    "macAddress": "00:00:00:00:00:00",
                    "macAddressPermanent": "00:00:00:00:00:00",
                    "netmask": "N/A",
                    "network": "N/A",
                    "upAndRunning": true
                },
                "status": "UpAndRunning",
                "upAndRunning": true
            }
        }
        }
    }
}
```

GetClusterHardwareInfo

Le `GetClusterHardwareInfo` la méthode renvoie une réponse similaire à l'exemple suivant.

```
{
 "id": null,
  "result": {
   "clusterHardwareInfo": {
     "drives": {
      "1": {
        "description": "ATA      Drive",
        "dev": "8:0",
        "devpath": "/dev/disk/by-id/scsi-SATA_VRFSD3400GNCVMT205121562-
part4",
        "driveSecurityAtMaximum": false,
        "driveSecurityFrozen": true,
        "driveSecurityLocked": false,
        "logicalname": "/dev/sda",
        "product": "VRFSD3400GNCVMTJS1",
        "securityFeatureEnabled": false,
        "securityFeatureSupported": true,
        "serial": "205121562",
        "size": 299988156416,
        "uuid": "febe39ae-4984-edc0-e3a7-3c47608cface",
        "version": "515ABBF0"
      },
      "2": {...
      },
      "3": {...
      },
      "4": {...
      },
      "5": {...
      },
      "6": {...
      },
         .
         .
         .
    "44": {...
      }
      },
"nodes":{
  "1":{                      Storage Node
```

```
    "core_DMI:0200": {
    "description": "Motherboard",
    "physid": "0",
    "vendor": "SolidFire"
  },
    "fiber:0_PCI:0000:04:00.0": {
      "businfo": "pci@0000:04:00.0",
      "clock": "33000000",
      "description": "Fibre Channel",
      "physid": "0",
      "product": "ISP8324-based 16Gb Fibre Channel to PCI Express
Adapter",
      "vendor": "QLogic Corp.",
      "version": "02",
      "width": "64"
  },
    "Repeat fiber information": {...}
    "Repeat fiber": {...},
    "Repeat fiber": {...},
   }
 },
   "fans": {
     "Fan1A RPM": {
     "baseUnit": "RPM",
     "threshold": 840,
     "value": 4800
 },
     "Fan1B RPM": {...},
         .
         .
         .
     "Fan7B RPM": {...
     },
     "fibreChannelPorts": [
       {
        "firmware": "7.04.00 (d0d5)",
        "hbaPort": 1,
        "model": "QLE2672",
        "nPortID": "0x110c36",
        "pciSlot": 3,
        "serial": "BFE1341E09329",
        "speed": "8 Gbit",
        "state": "Online",
        "switchWwn": "20:01:00:2a:6a:a0:25:01",
        "wwnn": "5f:47:ac:c8:82:23:e0:00",
        "wwpn": "5f:47:ac:c0:82:23:e0:02"
```

```
      },
      {
       "firmware": "7.04.00 (d0d5)", {...}
       "firmware": "7.04.00 (d0d5)", {...}
       "firmware": "7.04.00 (d0d5)", {...}
      }
    ],
    "hardwareConfig": {
      "BIOS_REVISION": {
       "Passed": true,
       "actual": "1.1",
       "comparator": ">=",
       "expected": "1.0"
      },
      "BIOS_VENDOR": {
       "Passed": true,
       "actual": "SolidFire",
       "comparator": "==",
       "expected": "SolidFire"
      },
      "BIOS_VERSION": {
       "Passed": true,
       "actual": "1.1.2",
       "comparator": ">=",
       "expected": "1.1.2"
      },
      "BMC_FIRMWARE_REVISION": {
       "Passed": true,
       "actual": "1.6",
       "comparator": ">=",
       "expected": "1.6"
      },
      "BMC_IPMI_VERSION": {
       "Passed": true,
       "actual": "2.0",
       "comparator": ">=",
       "expected": "2.0"
      },
      "CHASSIS_TYPE": {
       "Passed": true,
       "actual": "R620",
       "comparator": "==",
       "expected": "R620"
      },
      "CPU_CORES_00": {
       "Passed": true,
```

```
        "actual": "6",
        "comparator": "==",
        "expected": "6"
       },
       "CPU_CORES_01": {
        "Passed": true,
        "actual": "6",
        "comparator": "==",
        "expected": "6"
       },
       "CPU_CORES_ENABLED_00": {
        "Passed": true,
        "actual": "6",
        "comparator": "==",
        "expected": "6"
       },
       "CPU_CORES_ENABLED_01": {
        "Passed": true,
        "actual": "6",
        "comparator": "==",
        "expected": "6"
       },
       "CPU_MODEL_00": {
        "Passed": true,
        "actual": "Intel(R) Xeon(R) CPU E5-2640 0 @ 2.50GHz",
        "comparator": "==",
        "expected": "Intel(R) Xeon(R) CPU E5-2640 0 @ 2.50GHz"
       },
       "CPU_MODEL_01": {
        "Passed": true,
        "actual": "Intel(R) Xeon(R) CPU E5-2640 0 @ 2.50GHz",
        "comparator": "==",
        "expected": "Intel(R) Xeon(R) CPU E5-2640 0 @ 2.50GHz"
       },
       "CPU_THREADS_00": {
        "Passed": true,
        "actual": "12",
        "comparator": "==",
        "expected": "12"
       },
       "CPU_THREADS_01": {
        "Passed": true,
        "actual": "12",
        "comparator": "==",
        "expected": "12"
       },
```

```
"DRIVE_SIZE_BYTES_SDIMM0": {
 "Passed": true,
 "actual": "100030242816",
 "comparator": ">=",
 "expected": "100030242816"
},
"FIBRE_CHANNEL_FIRMWARE_REVISION": {
 "Passed": true,
 "actual": "FW:v7.04.00",
 "comparator": "==",
 "expected": "FW:v7.04.00"
},
"FIBRE_CHANNEL_MODEL": {
 "Passed": true,
 "actual": "QLE2672",
 "comparator": "==",
 "expected": "QLE2672"
},
"IDRAC_VERSION": {
 "Passed": true,
 "actual": "1.06.06",
 "comparator": ">=",
 "expected": "1.06.06"
},
"LIFECYCLE_VERSION": {
 "Passed": true,
 "actual": "1.0.0.5747",
 "comparator": ">=",
 "expected": "1.0.0.5747"
},
"MEMORY_GB": {
 "Passed": true,
 "actual": "32",
 "comparator": ">=",
 "expected": "32"
},
"MEMORY_MHZ_00": {
 "Passed": true,
 "actual": "1333",
 "comparator": ">=",
 "expected": "1333"
},
"MEMORY_MHZ_01": {
 "Passed": true,
 "actual": "1333",
 "comparator": ">=",
```

```
        "expected": "1333"
       },
       "MEMORY_MHZ_02": {
       "Passed": true,
       "actual": "1333",
       "comparator": ">=",
       "expected": "1333"
      },
      "MEMORY_MHZ_03": {
       "Passed": true,
       "actual": "1333",
       "comparator": ">=",
       "expected": "1333"
      },
      "NETWORK_DRIVER_ETH0": {
       "Passed": true,
       "actual": "bnx2x",
       "comparator": "=~",
       "expected": "^bnx2x$"
      },
      {
       "NETWORK_DRIVER_ETH1":, {...
      },
       "NETWORK_DRIVER_ETH2":, {...
      },
       "NETWORK_DRIVER_ETH3":, {...
      },
       "NETWORK_DRIVER_ETH4":, {...
      },
       "NETWORK_DRIVER_ETH5":, {...
      },
       "NODE_TYPE": {
       "Passed": true,
       "actual": "FC0025",
       "comparator": "==",
       "expected": "FC0025"
      },
      "NUM_CPU": {
       "Passed": true,
       "actual": "2",
       "comparator": "==",
       "expected": "2"
      },
      "NUM_DRIVES": {
       "Passed": true,
       "actual": "0",
```

```
 "comparator": "==",
 "expected": "0"
},
"NUM_DRIVES_INTERNAL": {
 "Passed": true,
 "actual": "1",
 "comparator": "==",
 "expected": "1"
},
"NUM_FIBRE_CHANNEL_PORTS": {
 "Passed": true,
 "actual": "4",
 "comparator": "==",
 "expected": "4"
},
"NVRAM_VENDOR": {
 "Passed": true,
 "actual": "",
 "comparator": "==",
 "expected": ""
},
"ROOT_DRIVE_REMOVABLE": {
 "Passed": true,
 "actual": "false",
 "comparator": "==",
 "expected": "false"
}
},
"memory": {
  "firmware_": {
   "capacity": "8323072",
   "date": "03/08/2012",
   "description": "BIOS",
   "physid": "0",
   "size": "65536",
   "vendor": "SolidFire",
   "version": "1.1.2"
},
"memory_DMI:1000": {
  "description": "System Memory",
  "physid": "1000",
  "size": "34359738368",
  "slot": "System board or motherboard"
}
},
"network": {
```

```
      "network:0_PCI:0000:01:00.0": {
       "businfo": "pci@0000:01:00.0",
       "capacity": "1000000000",
       "clock": "33000000",
       "description": "Ethernet interface",
       "logicalname": "eth0",
       "physid": "0",
       "product": "NetXtreme II BCM57800 1/10 Gigabit Ethernet",
       "serial": "c8:1f:66:e0:97:2a",
       "vendor": "Broadcom Corporation",
       "version": "10",
       "width": "64"
      },
      "network:0_PCI:0000:41:00.0": {...
      },
      "network:1_PCI:0000:01:00.1": {...
      },
      "network:1_PCI:0000:41:00.1": {...
      },
      "network:2_PCI:0000:01:00.2": {...
      },
      "network:3_PCI:0000:01:00.3": {...
      }
      },
      "networkInterfaces": {
      "Bond10G": {
       "isConfigured": true,
       "isUp": true
      },
      "Bond1G": {
      "isConfigured": true,
      "isUp": true
      },
      "eth0": {
      "isConfigured": true,
      "isUp": true
      },
      "eth1": {...
      },
      "eth2": {...
      },
      "eth3": {...
      },
      "eth4": {...
      },
      "eth5": {...
```

```
      }
     },
     "nvram": {
       "errors": {
        "numOfErrorLogEntries": "0"
       },
       "extended": {
        "dialogVersion": "4",
        "event": [
        {
         "name": "flushToFlash",
         "time": "2015-08-06 01:19:39",
         "value": "0"
        },
        {
         "name": "flushToFlash",
         "time": "2015-08-06 01:26:44",
         "value": "0"
        },
        {... next "flushToFlash"
        },
        {... next "flushToFlash"
        },
        {... next "flushToFlash"
        },
        {... next "flushToFlash"
        },
        {... next "flushToFlash"
        },
        {... next "flushToFlash"
        },
        {... next "flushToFlash"
        }
       ],
       "eventOccurrences": [
         {
           "count": "740",
           "name": "flushToFlash"
         },
         {
           "count": "1",
           "name": "excessiveCurrent"
         }
       ],
       "initialCapacitance": "6.630 F",
       "initialEsr": "0.101 Ohm",
```

```
"measurement": [
 {
   "level_0": " 0",
   "level_1": " 3969",
   "level_2": " 4631",
   "level_3": " 12875097",
   "level_4": " 1789948",
   "level_5": " 0",
   "level_6": " 0",
   "level_7": " 0",
   "level_8": " 0",
   "level_9": " 0",
   "name": "enterpriseFlashControllerTemperature",
   "recent": "66 C"
},
{
   "level_0": " 0",
   "level_1": " 58",
   "level_2": " 1479058",
   "level_3": " 12885356",
   "level_4": " 308293",
   "level_5": " 851",
   "level_6": " 29",
   "level_7": " 0",
   "level_8": " 0",
   "level_9": " 0",
   "name": "capacitor1And2Temperature",
   "recent": "30.69 C"
},
{...next temp measurement
},
{...next temp measurement
},
{...next temp measurement
},
}
 "name": "voltageOfCapacitor1",
 "recent": "2.198 V"
},
{
 "name": "voltageOfCapacitor2",
 "recent": "2.181 V"
},
{
 "name": "voltageOfCapacitor3",
 "recent": "2.189 V"
```

```
      },
      {
       "name": "voltageOfCapacitor4",
       "recent": "2.195 V"
      },
      {
       "level_0": " 4442034",
       "level_1": " 6800018",
       "level_2": " 2846869",
       "level_3": " 119140",
       "level_4": " 29506",
       "level_5": " 428935",
       "level_6": " 7143",
       "level_7": " 0",
       "level_8": " 0",
       "level_9": " 0",
       "name": "capacitorPackVoltage",
       "recent": "8.763 V"
      },
      {
       "level_0": " 0",
       "level_1": " 0",
       "level_2": " 0",
       "level_3": " 0",
       "level_4": " 189",
       "level_5": " 17",
       "level_6": " 36",
       "level_7": " 0",
       "level_8": " 2",
       "level_9": " 490",
       "name": "capacitorPackVoltageAtEndOfFlushToFlash",
       "recent": "4.636 V"
      },
      {
       "name": "currentDerivedFromV3V4",
       "recent": "-0.004 A"
      },
      {
       "level_0": " 230",
       "level_1": " 482",
       "level_2": " 22",
       "level_3": " 0",
       "level_4": " 0",
       "level_5": " 0",
       "level_6": " 0",
       "level_7": " 0",
```

```
      "level_8": " 0",
      "level_9": " 0",
      "name": "derivedEnergy",
      "recent": "172 Joules"
     },
     {...next voltage measurement
     },
     {...next voltage measurement
     },
     {...next voltage measurement
     },
   ],
   "smartCounters": [
     {
      "name": "numberOf512ByteBlocksReadFromDdr",
      "value": "10530088847"
     },
     {
      "name": "numberOf512ByteBlocksWrittenToDdr",
      "value": "1752499453837"
     },
     {
      "name": "numberOfHostReadCommands",
      "value": "235317769"
     },
     {...next smartCounters measurement
     },
     {...next smartCounters measurement
     },
     {...next smartCounters measurement
     },
   ],
   "snapshotTime": "2015-08-20 16:30:01"
  },
  "firmware": {
    "activeSlotNumber": "2",
    "slot1Version": "1e5817bc",
    "slot2Version": "5fb7565c",
    "slot3Version": "1e5817bc",
    "slot4Version": "1e5817bc"
  },
  "identify": {
    "firmwareVersion": "5fb7565c on slot 2",
    "hardwareRevision": "B04",
    "modelNumber": "RMS-200",
    "serialNumber": "0000862"
```

```
    },
    "smart": {
      "availableSpace": "0%",
      "availableSpaceThreshold": "0%",
      "controllerBusyTimeMinutes": "6793",
      "criticalErrorVector": "0x0",
      "mediaErrors": "0",
      "numberOf512ByteBlocksRead": "10530088847",
      "numberOf512ByteBlocksWritten": "1752499439063",
      "numberOfErrorInfoLogs": "1",
      "numberOfHostReadCommands": "235317769",
      "numberOfHostWriteCommands": "126030374065",
      "numberOfPowerCycles": "709",
      "powerOnHours": "11223",
      "temperature": "324 Kelvin",
      "unsafeShutdowns": "357"
       }
       },
       "origin": null,
       "platform": {
        "chassisType": "R620",
        "cpuModel": "Intel(R) Xeon(R) CPU E5-2640 0 @ 2.50GHz",
        "nodeMemoryGB": 32,
        "nodeType": "FC0025"
       },
       "powerSupplies": {
        "PS1 status": {
         "powerSupplyFailureDetected": false,
         "powerSupplyHasAC": true,
         "powerSupplyPredictiveFailureDetected": false,
         "powerSupplyPresent": true,
         "powerSupplyPresentLastCheck": true
       },
        "PS2 status": {
         "powerSupplyFailureDetected": false,
         "powerSupplyHasAC": true,
         "powerSupplyPredictiveFailureDetected": false,
         "powerSupplyPresent": true,
         "powerSupplyPresentLastCheck": true
       }
       },
       "storage": {
        "storage_PCI:0000:00:1f.2": {
         "businfo": "pci@0000:00:1f.2",
         "clock": "66000000",
         "description": "SATA controller",
```

```
        "physid": "1f.2",
        "product": "C600/X79 series chipset 6-Port SATA AHCI Controller",
        "vendor": "Intel Corporation",
        "version": "05",
        "width": "32"
      }
      },
      "system": {
       "ubuntu_DMI:0100": {
        "description": "Rack Mount Chassis",
        "product": "SFx010 ()",
        "serial": "HTW1DZ1",
        "vendor": "SolidFire",
        "width": "64"
      }
      },
      "temperatures": {
       "Exhaust Temp": {
        "baseUnit": "C",
        "threshold": 70,
        "value": 41
      },
      "Inlet Temp": {
       "baseUnit": "C",
       "threshold": 42,
       "value": 18
      }
      },
      "uuid": "4C4C4544-0054-5710-8031-C8C04F445A31"
    },
  "2": {...},                    Storage Node "2"
  "3": {...},                    Storage Node "3"
  "4": {...},                    Storage Node "4"
  "5": {                      Fibre Channel Node
       }
      }
    }
  }
```

GetLldpInfo

Le `GetLldpInfo` la méthode renvoie une réponse similaire à l'exemple suivant.

```
{
  "id": null,
```

```
  "result": {
    "lldpInfo": {
        "lldpChassis": {
        "local-chassis": [
        {
          "chassis": [
            {
              "capability": [
                {
                  "enabled": false,
                  "type": "Bridge"
                },
                {
                  "enabled": false,
                  "type": "Router"
                },
                {
                  "enabled": false,
                  "type": "Wlan"
                },
                {
                  "enabled": true,
                  "type": "Station"
                }
              ],
              "descr": [
                {
                  "value": "Element OS 11.0"
                }
              ],
              "id": [
                {
                  "type": "mac",
                  "value": "08:00:27:3c:0a:f4"
                }
              ],
              "mgmt-ip": [
                {
                  "value": "10.0.2.15"
                },
                {
                  "value": "fe80::a00:27ff:fe3c:af4"
                }
              ],
              "name": [
                {
```

```
                "value": "SF-93FF"
              }
            ]
          }
        ],
        "lldp-med": [
          {
            "capability": [
              {
                "available": true,
                "type": "Capabilities"
              },
              {
                "available": true,
                "type": "Policy"
              },
              {
                "available": true,
                "type": "Location"
              },
              {
                "available": true,
                "type": "MDI/PSE"
              },
              {
                "available": true,
                "type": "MDI/PD"
              },
              {
                "available": true,
                "type": "Inventory"
              }
            ],
            "device-type": [
              {
                "value": "Generic Endpoint (Class I)"
              }
            ],
            "inventory": [
              {
                "firmware": [
                  {
                    "value": "VirtualBox"
                  }
                ],
                "hardware": [
```

```
                    {
                      "value": "1.2"
                    }
                  ],
                  "manufacturer": [
                    {
                      "value": "innotek GmbH"
                    }
                  ],
                  "model": [
                    {
                      "value": "VirtualBox"
                    }
                  ],
                  "serial": [
                    {
                      "value": "0"
                    }
                  ],
                  "software": [
                    {
                      "value": "4.14.27-solidfire2"
                    }
                  ]
                }
              ]
            }
          ]
        }
      ]
    },
    "lldpInterfaces": {
      "lldp": [
        {
          "interface": [
            {
              "age": "0 day, 00:01:04",
              "chassis": [
                {
                  "capability": [
                    {
                      "enabled": false,
                      "type": "Bridge"
                    },
                    {
                      "enabled": false,
```

```
                "type": "Router"
              },
              {
                "enabled": false,
                "type": "Wlan"
              },
              {
                "enabled": true,
                "type": "Station"
              }
            ],
            "descr": [
              {
                "value": "Element OS 11.0"
              }
            ],
            "id": [
              {
                "type": "mac",
                "value": "08:00:27:3c:0a:f4"
              }
            ],
            "mgmt-ip": [
              {
                "value": "10.0.2.15"
              },
              {
                "value": "fe80::a00:27ff:fe3c:af4"
              }
            ],
            "name": [
              {
                "value": "SF-93FF"
              }
            ]
          }
        ],
        "lldp-med": [
          {
            "capability": [
              {
                "available": true,
                "type": "Capabilities"
              },
              {
                "available": true,
```

```
        "type": "Policy"
      },
      {
        "available": true,
        "type": "Location"
      },
      {
        "available": true,
        "type": "MDI/PSE"
      },
      {
        "available": true,
        "type": "MDI/PD"
      },
      {
        "available": true,
        "type": "Inventory"
      }
    ],
    "device-type": [
      {
        "value": "Generic Endpoint (Class I)"
      }
    ],
    "inventory": [
      {
        "firmware": [
          {
            "value": "VirtualBox"
          }
        ],
        "hardware": [
          {
            "value": "1.2"
          }
        ],
        "manufacturer": [
          {
            "value": "innotek GmbH"
          }
        ],
        "model": [
          {
            "value": "VirtualBox"
          }
        ],
```

```
                    "serial": [
                      {
                        "value": "0"
                      }
                    ],
                    "software": [
                      {
                        "value": "4.14.27-solidfire2"
                      }
                    ]
                  }
                ]
              }
            ],
            "name": "eth0",
            "port": [
              {
                "aggregation": [
                  {
                    "value": "7"
                  }
                ],
                "auto-negotiation": [
                  {
                    "advertised": [
                      {
                        "fd": true,
                        "hd": true,
                        "type": "10Base-T"
                      },
                      {
                        "fd": true,
                        "hd": true,
                        "type": "100Base-TX"
                      },
                      {
                        "fd": true,
                        "hd": false,
                        "type": "1000Base-T"
                      }
                    ],
                    "current": [
                      {
                        "value": "full duplex mode"
                      }
                    ],
```

```
                "enabled": true,
                "supported": true
              }
            ],
            "descr": [
              {
                "value": "eth0"
              }
            ],
            "id": [
              {
                "type": "mac",
                "value": "08:00:27:3c:0a:f4"
              }
            ]
          }
        ],
        "ttl": [
          {
            "ttl": "120"
          }
        ],
        "via": "unknown"
      },
      {
        "age": "17722 days, 17:14:28",
        "chassis": [
          {
            "capability": [
              {
                "enabled": false,
                "type": "Bridge"
              },
              {
                "enabled": false,
                "type": "Router"
              },
              {
                "enabled": false,
                "type": "Wlan"
              },
              {
                "enabled": true,
                "type": "Station"
              }
            ],
```

```
            "descr": [
              {
                "value": "Element OS 11.0"
              }
            ],
            "id": [
              {
                "type": "mac",
                "value": "08:00:27:3c:0a:f4"
              }
            ],
            "mgmt-ip": [
              {
                "value": "10.0.2.15"
              },
              {
                "value": "fe80::a00:27ff:fe3c:af4"
              }
            ],
            "name": [
              {
                "value": "SF-93FF"
              }
            ]
          }
        ],
        "lldp-med": [
          {
            "capability": [
              {
                "available": true,
                "type": "Capabilities"
              },
              {
                "available": true,
                "type": "Policy"
              },
              {
                "available": true,
                "type": "Location"
              },
              {
                "available": true,
                "type": "MDI/PSE"
              },
              {
```

```
        "available": true,
        "type": "MDI/PD"
      },
      {
        "available": true,
        "type": "Inventory"
      }
    ],
    "device-type": [
      {
        "value": "Generic Endpoint (Class I)"
      }
    ],
    "inventory": [
      {
        "firmware": [
          {
            "value": "VirtualBox"
          }
        ],
        "hardware": [
          {
            "value": "1.2"
          }
        ],
        "manufacturer": [
          {
            "value": "innotek GmbH"
          }
        ],
        "model": [
          {
            "value": "VirtualBox"
          }
        ],
        "serial": [
          {
            "value": "0"
          }
        ],
        "software": [
          {
            "value": "4.14.27-solidfire2"
          }
        ]
      }
```

```
        ]
      }
    ],
    "name": "eth1",
    "port": [
      {
        "aggregation": [
          {
            "value": "7"
          }
        ],
        "auto-negotiation": [
          {
            "advertised": [
              {
                "fd": true,
                "hd": true,
                "type": "10Base-T"
              },
              {
                "fd": true,
                "hd": true,
                "type": "100Base-TX"
              },
              {
                "fd": true,
                "hd": false,
                "type": "1000Base-T"
              }
            ],
            "current": [
              {
                "value": "unknown"
              }
            ],
            "enabled": true,
            "supported": true
          }
        ],
        "descr": [
          {
            "value": "eth1"
          }
        ],
        "id": [
          {
```

```
                    "type": "mac",
                    "value": "08:00:27:36:79:78"
                  }
                ]
              }
            ],
            "ttl": [
              {
                "ttl": "120"
              }
            ],
            "via": "unknown"
          },
          {
            "age": "0 day, 00:01:01",
            "chassis": [
              {
                "capability": [
                  {
                    "enabled": false,
                    "type": "Bridge"
                  },
                  {
                    "enabled": false,
                    "type": "Router"
                  },
                  {
                    "enabled": false,
                    "type": "Wlan"
                  },
                  {
                    "enabled": true,
                    "type": "Station"
                  }
                ],
                "descr": [
                  {
                    "value": "Element OS 11.0"
                  }
                ],
                "id": [
                  {
                    "type": "mac",
                    "value": "08:00:27:3c:0a:f4"
                  }
                ],
```

```
            "mgmt-ip": [
              {
                "value": "10.0.2.15"
              },
              {
                "value": "fe80::a00:27ff:fe3c:af4"
              }
            ],
            "name": [
              {
                "value": "SF-93FF"
              }
            ]
          }
        ],
        "lldp-med": [
          {
            "capability": [
              {
                "available": true,
                "type": "Capabilities"
              },
              {
                "available": true,
                "type": "Policy"
              },
              {
                "available": true,
                "type": "Location"
              },
              {
                "available": true,
                "type": "MDI/PSE"
              },
              {
                "available": true,
                "type": "MDI/PD"
              },
              {
                "available": true,
                "type": "Inventory"
              }
            ],
            "device-type": [
              {
                "value": "Generic Endpoint (Class I)"
```

```
          }
        ],
        "inventory": [
          {
            "firmware": [
              {
                "value": "VirtualBox"
              }
            ],
            "hardware": [
              {
                "value": "1.2"
              }
            ],
            "manufacturer": [
              {
                "value": "innotek GmbH"
              }
            ],
            "model": [
              {
                "value": "VirtualBox"
              }
            ],
            "serial": [
              {
                "value": "0"
              }
            ],
            "software": [
              {
                "value": "4.14.27-solidfire2"
              }
            ]
          }
        ]
      }
    ],
    "name": "eth2",
    "port": [
      {
        "aggregation": [
          {
            "value": "6"
          }
        ],
```

```
        "auto-negotiation": [
          {
            "advertised": [
              {
                "fd": true,
                "hd": true,
                "type": "10Base-T"
              },
              {
                "fd": true,
                "hd": true,
                "type": "100Base-TX"
              },
              {
                "fd": true,
                "hd": false,
                "type": "1000Base-T"
              }
            ],
            "current": [
              {
                "value": "full duplex mode"
              }
            ],
            "enabled": true,
            "supported": true
          }
        ],
        "descr": [
          {
            "value": "eth2"
          }
        ],
        "id": [
          {
            "type": "mac",
            "value": "08:00:27:fc:f0:a9"
          }
        ]
      }
    ],
    "ttl": [
      {
        "ttl": "120"
      }
    ],
```

```
      "via": "LLDP"
    },
    {
      "age": "0 day, 00:01:01",
      "chassis": [
        {
          "capability": [
            {
              "enabled": false,
              "type": "Bridge"
            },
            {
              "enabled": false,
              "type": "Router"
            },
            {
              "enabled": false,
              "type": "Wlan"
            },
            {
              "enabled": true,
              "type": "Station"
            }
          ],
          "descr": [
            {
              "value": "Element OS 11.0"
            }
          ],
          "id": [
            {
              "type": "mac",
              "value": "08:00:27:3c:0a:f4"
            }
          ],
          "mgmt-ip": [
            {
              "value": "10.0.2.15"
            },
            {
              "value": "fe80::a00:27ff:fe3c:af4"
            }
          ],
          "name": [
            {
              "value": "SF-93FF"
```

```
                }
              ]
            }
          ],
          "lldp-med": [
            {
              "capability": [
                {
                  "available": true,
                  "type": "Capabilities"
                },
                {
                  "available": true,
                  "type": "Policy"
                },
                {
                  "available": true,
                  "type": "Location"
                },
                {
                  "available": true,
                  "type": "MDI/PSE"
                },
                {
                  "available": true,
                  "type": "MDI/PD"
                },
                {
                  "available": true,
                  "type": "Inventory"
                }
              ],
              "device-type": [
                {
                  "value": "Generic Endpoint (Class I)"
                }
              ],
              "inventory": [
                {
                  "firmware": [
                    {
                      "value": "VirtualBox"
                    }
                  ],
                  "hardware": [
                    {
```

```
                    "value": "1.2"
                  }
                ],
                "manufacturer": [
                  {
                    "value": "innotek GmbH"
                  }
                ],
                "model": [
                  {
                    "value": "VirtualBox"
                  }
                ],
                "serial": [
                  {
                    "value": "0"
                  }
                ],
                "software": [
                  {
                    "value": "4.14.27-solidfire2"
                  }
                ]
              }
            ]
          }
        ],
        "name": "eth3",
        "port": [
          {
            "aggregation": [
              {
                "value": "6"
              }
            ],
            "auto-negotiation": [
              {
                "advertised": [
                  {
                    "fd": true,
                    "hd": true,
                    "type": "10Base-T"
                  },
                  {
                    "fd": true,
                    "hd": true,
```

```
                        "type": "100Base-TX"
                      },
                      {
                        "fd": true,
                        "hd": false,
                        "type": "1000Base-T"
                      }
                    ],
                    "current": [
                      {
                        "value": "full duplex mode"
                      }
                    ],
                    "enabled": true,
                    "supported": true
                  }
                ],
                "descr": [
                  {
                    "value": "eth3"
                  }
                ],
                "id": [
                  {
                    "type": "mac",
                    "value": "08:00:27:2c:e4:f8"
                  }
                ]
              }
            ],
            "ttl": [
              {
                "ttl": "120"
              }
            ],
            "via": "LLDP"
          }
        ]
      }
    ]
  },
  "lldpNeighbors": {
    "lldp": [
      {
        "interface": [
          {
```

```
            "age": "0 day, 00:04:34",
            "chassis": [
              {
                "capability": [
                  {
                    "enabled": true,
                    "type": "Bridge"
                  },
                  {
                    "enabled": true,
                    "type": "Router"
                  },
                  {
                    "enabled": true,
                    "type": "Wlan"
                  },
                  {
                    "enabled": false,
                    "type": "Station"
                  }
                ],
                "descr": [
                  {
                    "value": "x86_64"
                  }
                ],
                "id": [
                  {
                    "type": "mac",
                    "value": "50:7b:9d:2b:36:84"
                  }
                ],
                "mgmt-ip": [
                  {
                    "value": "192.168.100.1"
                  },
                  {
                    "value": "fe80::a58e:843:952e:d8eb"
                  }
                ],
                "name": [
                  {
                    "value": "ConventionalWisdom.wlan.netapp.com"
                  }
                ]
              }
```

```
      ],
      "name": "eth2",
      "port": [
        {
          "auto-negotiation": [
            {
              "current": [
                {
                  "value": "full duplex mode"
                }
              ],
              "enabled": false,
              "supported": false
            }
          ],
          "descr": [
            {
              "value": "vboxnet1"
            }
          ],
          "id": [
            {
              "type": "mac",
              "value": "0a:00:27:00:00:01"
            }
          ],
          "ttl": [
            {
              "value": "120"
            }
          ]
        }
      ],
      "rid": "2",
      "via": "LLDP"
    },
    {
      "age": "0 day, 00:01:01",
      "chassis": [
        {
          "capability": [
            {
              "enabled": false,
              "type": "Bridge"
            },
            {
```

```
                "enabled": false,
                "type": "Router"
              },
              {
                "enabled": false,
                "type": "Wlan"
              },
              {
                "enabled": true,
                "type": "Station"
              }
            ],
            "descr": [
              {
                "value": "Element OS 11.0"
              }
            ],
            "id": [
              {
                "type": "mac",
                "value": "08:00:27:3c:0a:f4"
              }
            ],
            "mgmt-ip": [
              {
                "value": "10.0.2.15"
              },
              {
                "value": "fe80::a00:27ff:fe3c:af4"
              }
            ],
            "name": [
              {
                "value": "SF-93FF"
              }
            ]
          }
        ],
        "lldp-med": [
          {
            "capability": [
              {
                "available": true,
                "type": "Capabilities"
              },
              {
```

```
          "available": true,
          "type": "Policy"
        },
        {
          "available": true,
          "type": "Location"
        },
        {
          "available": true,
          "type": "MDI/PSE"
        },
        {
          "available": true,
          "type": "MDI/PD"
        },
        {
          "available": true,
          "type": "Inventory"
        }
      ],
      "device-type": [
        {
          "value": "Generic Endpoint (Class I)"
        }
      ],
      "inventory": [
        {
          "firmware": [
            {
              "value": "VirtualBox"
            }
          ],
          "hardware": [
            {
              "value": "1.2"
            }
          ],
          "manufacturer": [
            {
              "value": "innotek GmbH"
            }
          ],
          "model": [
            {
              "value": "VirtualBox"
            }
```

```
                ],
                "serial": [
                  {
                    "value": "0"
                  }
                ],
                "software": [
                  {
                    "value": "4.14.27-solidfire2"
                  }
                ]
              }
            ]
          }
        ],
        "name": "eth2",
        "port": [
          {
            "aggregation": [
              {
                "value": "6"
              }
            ],
            "auto-negotiation": [
              {
                "advertised": [
                  {
                    "fd": true,
                    "hd": true,
                    "type": "10Base-T"
                  },
                  {
                    "fd": true,
                    "hd": true,
                    "type": "100Base-TX"
                  },
                  {
                    "fd": true,
                    "hd": false,
                    "type": "1000Base-T"
                  }
                ],
                "current": [
                  {
                    "value": "full duplex mode"
                  }
```

```
                ],
                "enabled": true,
                "supported": true
              }
            ],
            "descr": [
              {
                "value": "eth3"
              }
            ],
            "id": [
              {
                "type": "mac",
                "value": "08:00:27:2c:e4:f8"
              }
            ],
            "ttl": [
              {
                "value": "120"
              }
            ]
          }
        ],
        "rid": "1",
        "via": "LLDP"
      },
      {
        "age": "0 day, 00:04:34",
        "chassis": [
          {
            "capability": [
              {
                "enabled": true,
                "type": "Bridge"
              },
              {
                "enabled": true,
                "type": "Router"
              },
              {
                "enabled": true,
                "type": "Wlan"
              },
              {
                "enabled": false,
                "type": "Station"
```

```
            }
          ],
          "descr": [
            {
              "value": "x86_64"
            }
          ],
          "id": [
            {
              "type": "mac",
              "value": "50:7b:9d:2b:36:84"
            }
          ],
          "mgmt-ip": [
            {
              "value": "192.168.100.1"
            },
            {
              "value": "fe80::a58e:843:952e:d8eb"
            }
          ],
          "name": [
            {
              "value": ""
            }
          ]
        }
      ],
      "name": "eth3",
      "port": [
        {
          "auto-negotiation": [
            {
              "current": [
                {
                  "value": "full duplex mode"
                }
              ],
              "enabled": false,
              "supported": false
            }
          ],
          "descr": [
            {
              "value": "vboxnet1"
            }
```

```
            ],
            "id": [
              {
                "type": "mac",
                "value": "0a:00:27:00:00:01"
              }
            ],
            "ttl": [
              {
                "value": "120"
              }
            ]
          }
        ],
        "rid": "2",
        "via": "LLDP"
      },
      {
        "age": "0 day, 00:01:01",
        "chassis": [
          {
            "capability": [
              {
                "enabled": false,
                "type": "Bridge"
              },
              {
                "enabled": false,
                "type": "Router"
              },
              {
                "enabled": false,
                "type": "Wlan"
              },
              {
                "enabled": true,
                "type": "Station"
              }
            ],
            "descr": [
              {
                "value": "Element OS 11.0"
              }
            ],
            "id": [
              {
```

```
                    "type": "mac",
                    "value": "08:00:27:3c:0a:f4"
                  }
                ],
                "mgmt-ip": [
                  {
                    "value": "10.0.2.15"
                  },
                  {
                    "value": "fe80::a00:27ff:fe3c:af4"
                  }
                ],
                "name": [
                  {
                    "value": "SF-93FF"
                  }
                ]
              }
            ],
            "lldp-med": [
              {
                "capability": [
                  {
                    "available": true,
                    "type": "Capabilities"
                  },
                  {
                    "available": true,
                    "type": "Policy"
                  },
                  {
                    "available": true,
                    "type": "Location"
                  },
                  {
                    "available": true,
                    "type": "MDI/PSE"
                  },
                  {
                    "available": true,
                    "type": "MDI/PD"
                  },
                  {
                    "available": true,
                    "type": "Inventory"
                  }
```

```
        ],
        "device-type": [
          {
            "value": "Generic Endpoint (Class I)"
          }
        ],
        "inventory": [
          {
            "firmware": [
              {
                "value": "VirtualBox"
              }
            ],
            "hardware": [
              {
                "value": "1.2"
              }
            ],
            "manufacturer": [
              {
                "value": "innotek GmbH"
              }
            ],
            "model": [
              {
                "value": "VirtualBox"
              }
            ],
            "serial": [
              {
                "value": "0"
              }
            ],
            "software": [
              {
                "value": "4.14.27-solidfire2"
              }
            ]
          }
        ]
      }
    ],
    "name": "eth3",
    "port": [
      {
        "aggregation": [
```

```
      {
        "value": "6"
      }
    ],
    "auto-negotiation": [
      {
        "advertised": [
          {
            "fd": true,
            "hd": true,
            "type": "10Base-T"
          },
          {
            "fd": true,
            "hd": true,
            "type": "100Base-TX"
          },
          {
            "fd": true,
            "hd": false,
            "type": "1000Base-T"
          }
        ],
        "current": [
          {
            "value": "1000BaseTFD"
          }
        ],
        "enabled": true,
        "supported": true
      }
    ],
    "descr": [
      {
        "value": "eth2"
      }
    ],
    "id": [
      {
        "type": "mac",
        "value": "08:00:27:fc:f0:a9"
      }
    ],
    "ttl": [
      {
        "value": "120"
```

```
                    }
                  ]
                }
              ],
              "rid": "1",
              "via": "LLDP"
            }
          ]
        }
      ]
    }
    }
 }
}
```

GetNetworkConfig

Le `GetNetworkConfig` la méthode renvoie une réponse similaire à l'exemple suivant.

```
{
    "id": 1,
    "result": {
        "network": {
            "Bond10G": {
                "#default": false,
                "address": "10.1.1.0",
                "auto": true,
                "bond-downdelay": "0",
                "bond-fail_over_mac": "None",
                "bond-miimon": "100",
                "bond-mode": "ActivePassive",
                "bond-primary_reselect": "Failure",
                "bond-slaves": "eth0 eth1",
                "bond-updelay": "200",
                "dns-nameservers": "10.1.1.0, 10.1.1.0",
                "dns-search": "ten.test.company.net., company.net.",
                "family": "inet",
                "gateway": "10.1.1.0",
                "linkSpeed": 10000,
                "macAddress": "c8:1f:66:ee:59:b9",
                "macAddressPermanent": "00:00:00:00:00:00",
                "method": "static",
                "mtu": "9000",
                "netmask": "255.255.240.0",
                "network": "10.1.1.0",
```

```
                "physical": {
                    "address": "10.1.1.0",
                    "macAddress": "c8:1f:66:ee:59:b9",
                    "macAddressPermanent": "00:00:00:00:00:00",
                    "mtu": "9000",
                    "netmask": "255.255.240.0",
                    "network": "10.1.1.0",
                    "upAndRunning": true
                },
                "routes": [],
                "status": "UpAndRunning",
                "symmetricRouteRules": [
                    "ip route add 10.1.1.1/20 dev Bond1G src 10.1.2.2
table Bond1G",
                    "ip rule add from 10.1.1.1 table Bond1G",
                    "ip route add default via 10.1.1.254"
                ],
                "upAndRunning": true,
                "virtualNetworkTag": "0"
            },
            "Bond1G": {
                "#default": true,
                "address": "10.1.1.0",
                "addressV6": "",
                "auto": true,
                "bond-downdelay": "0",
                "bond-fail_over_mac": "None",
                "bond-miimon": "100",
                "bond-mode": "ActivePassive",
                "bond-primary_reselect": "Failure",
                "bond-slaves": "eth2 eth3",
                "bond-updelay": "200",
                "dns-nameservers": "10.1.1.0, 10.1.1.0",
                "dns-search": "ten.test.company.net., company.net.",
                "family": "inet",
                "gateway": "10.1.1.254",
                "gatewayV6": "",
                "linkSpeed": 1000,
                "macAddress": "c8:1f:66:ee:59:bd",
                "macAddressPermanent": "00:00:00:00:00:00",
                "method": "static",
                "mtu": "1500",
                "netmask": "255.255.240.0",
                "network": "10.1.1.0",
                "physical": {
                    "address": "10.1.1.0",
```

```
                    "macAddress": "c8:1f:66:ee:59:bd",
                    "macAddressPermanent": "00:00:00:00:00:00",
                    "mtu": "1500",
                    "netmask": "255.255.240.0",
                    "network": "10.1.1.0",
                    "upAndRunning": true
                },
                "routes": [],
                "status": "UpAndRunning",
                "symmetricRouteRules": [
                    "ip route add 10.1.1.1/20 dev Bond1G src 10.1.2.2
table Bond1G",
                    "ip rule add from 10.1.1.1 table Bond1G",
                    "ip route add default via 10.1.1.254"
                ],
                "upAndRunning": true,
                "virtualNetworkTag": "0"
            },
            "eth0": {
                "auto": true,
                "bond-master": "Bond10G",
                "family": "inet",
                "linkSpeed": 10000,
                "macAddress": "c8:1f:66:ee:59:b9",
                "macAddressPermanent": "c8:1f:66:ee:59:b9",
                "method": "bond",
                "physical": {
                    "address": "0.0.0.0",
                    "macAddress": "c8:1f:66:ee:59:b9",
                    "macAddressPermanent": "c8:1f:66:ee:59:b9",
                    "netmask": "N/A",
                    "network": "N/A",
                    "upAndRunning": true
                },
                "status": "UpAndRunning",
                "upAndRunning": true
            },
            "eth1": {
                "auto": true,
                "bond-master": "Bond10G",
                "family": "inet",
                "linkSpeed": 10000,
                "macAddress": "c8:1f:66:ee:59:b9",
                "macAddressPermanent": "c8:1f:66:ee:59:bb",
                "method": "bond",
                "physical": {
```

```
                "address": "0.0.0.0",
                "macAddress": "c8:1f:66:ee:59:b9",
                "macAddressPermanent": "c8:1f:66:ee:59:bb",
                "netmask": "N/A",
                "network": "N/A",
                "upAndRunning": true
            },
            "status": "UpAndRunning",
            "upAndRunning": true
        },
        "eth2": {
            "auto": true,
            "bond-master": "Bond1G",
            "family": "inet",
            "linkSpeed": 1000,
            "macAddress": "c8:1f:66:ee:59:bd",
            "macAddressPermanent": "c8:1f:66:ee:59:bd",
            "method": "bond",
            "physical": {
                "address": "0.0.0.0",
                "macAddress": "c8:1f:66:ee:59:bd",
                "macAddressPermanent": "c8:1f:66:ee:59:bd",
                "netmask": "N/A",
                "network": "N/A",
                "upAndRunning": true
            },
            "status": "UpAndRunning",
            "upAndRunning": true
        },
        "eth3": {
            "auto": true,
            "bond-master": "Bond1G",
            "family": "inet",
            "linkSpeed": 1000,
            "macAddress": "c8:1f:66:ee:59:bd",
            "macAddressPermanent": "c8:1f:66:ee:59:bf",
            "method": "bond",
            "physical": {
                "address": "0.0.0.0",
                "macAddress": "c8:1f:66:ee:59:bd",
                "macAddressPermanent": "c8:1f:66:ee:59:bf",
                "netmask": "N/A",
                "network": "N/A",
                "upAndRunning": true
            },
            "status": "UpAndRunning",
```

```
                "upAndRunning": true
            },
            "lo": {
                "auto": true,
                "family": "inet",
                "linkSpeed": 0,
                "macAddress": "00:00:00:00:00:00",
                "macAddressPermanent": "00:00:00:00:00:00",
                "method": "loopback",
                "physical": {
                    "address": "0.0.0.0",
                    "macAddress": "00:00:00:00:00:00",
                    "macAddressPermanent": "00:00:00:00:00:00",
                    "netmask": "N/A",
                    "network": "N/A",
                    "upAndRunning": true
                },
                "status": "UpAndRunning",
                "upAndRunning": true
            }
        }
    }
}
```

GetNodeHardwareInfo (sortie pour iSCSI)

Le `GetNodeHardwareInfo` La méthode pour iSCSI renvoie une réponse similaire à l'exemple suivant.

```
{
    "id": 1,
    "result": {
        "nodeHardwareInfo": {
            "bus": {
                "core_DMI:0200": {
                    "description": "Motherboard",
                    "physid": "0",
                    "product": "0H47HH",
                    "serial": "..CN7475141I0271.",
                    "vendor": "SolidFire",
                    "version": "A07"
                }
            },
            "driveHardware": [
                {
```

```
"canonicalName": "sda",
"connected": true,
"dev": 2048,
"devPath": "/dev/slot0",
"driveEncryptionCapability": "fips",
"driveType": "Slice",
"lifeRemainingPercent": 98,
"lifetimeReadBytes": 0,
"lifetimeWriteBytes": 14012129342144,
"name": "scsi-SATA_SAMSUNG_MZ7GE24S1M9NWAG501251",
"path": "/dev/sda",
"pathLink": "/dev/slot0",
"powerOnHours": 15489,
"product": "SAMSUNG MZ7GE240HMGR-00003",
"reallocatedSectors": 0,
"reserveCapacityPercent": 100,
"scsiCompatId": "scsi-SATA_SAMSUNG_MZ7GE24S1M9NWAG501251",
"scsiState": "Running",
"securityAtMaximum": false,
"securityEnabled": true,
"securityFrozen": false,
"securityLocked": false,
"securitySupported": true,
"serial": "S1M9NWAG501251",
"size": 240057409536,
"slot": 0,
"uncorrectableErrors": 0,
"uuid": "789aa05d-e49b-ff4f-f821-f60eed8e43bd",
"vendor": "Samsung",
"version": "EXT1303Q"
},
{
"canonicalName": "sda",
"connected": true,
"dev": 2048,
"devPath": "/dev/slot1",
"driveEncryptionCapability": "fips",
"driveType": "Slice",
"lifeRemainingPercent": 98,
"lifetimeReadBytes": 0,
"lifetimeWriteBytes": 14112129567184,
"name": "scsi-SATA_SAMSUNG_MZ7GE24S1M9NWAG501251",
"path": "/dev/sda",
"pathLink": "/dev/slot0",
"powerOnHours": 15489,
"product": "SAMSUNG MZ7GE240HMGR-00003",
```

```
                "reallocatedSectors": 0,
                "reserveCapacityPercent": 100,
                "scsiCompatId": "scsi-SATA_SAMSUNG_MZ7GE24S1M9NWAG501251",
                "scsiState": "Running",
                "securityAtMaximum": false,
                "securityEnabled": true,
                "securityFrozen": false,
                "securityLocked": false,
                "securitySupported": true,
                "serial": "S1M9NWAG501252",
                "size": 240057409536,
                "slot": 0,
                "uncorrectableErrors": 0,
                "uuid": "789aa05d-e49b-ff4f-f821-f60eed8e43bd",
                "vendor": "Samsung",
                "version": "EXT1303Q"
                }
    }
```


GetNodeHardwareInfo (sortie pour nœuds Fibre Channel)

Le `GetNodeHardwareInfo` Méthode pour les nœuds Fibre Channel renvoie une réponse similaire à l'exemple suivant.


```
{
"id": null,
"result": {
"nodeHardwareInfo": {
"bus": {
"core_DMI:0200": {
"description": "Motherboard",
"physid": "0",
"product": "0H47HH",
"serial": "..CN747513AA0541.",
"version": "A07"
},
"fiber:0_PCI:0000:04:00.0": {
"businfo": "pci@0000:04:00.0",
"clock": "33000000",
"description": "Fibre Channel",
"physid": "0",
"product": "ISP8324-based 16Gb Fibre Channel to PCI Express Adapter",
"vendor": "QLogic Corp.",
"version": "02",
"width": "64"
```

```
},
"fiber:0_PCI:0000:42:00.0": {
"businfo": "pci@0000:42:00.0",
"clock": "33000000",
"description": "Fibre Channel",
"physid": "0",
"product": "ISP8324-based 16Gb Fibre Channel to PCI Express Adapter",
"vendor": "QLogic Corp.",
"version": "02",
"width": "64"
},
"fiber:1_PCI:0000:04:00.1": {
"businfo": "pci@0000:04:00.1",
"clock": "33000000",
"description": "Fibre Channel",
"physid": "0.1",
"product": "ISP8324-based 16Gb Fibre Channel to PCI Express Adapter",
"vendor": "QLogic Corp.",
"version": "02",
"width": "64"
},
"fiber:1_PCI:0000:42:00.1": {
"businfo": "pci@0000:42:00.1",
"clock": "33000000",
"description": "Fibre Channel",
"physid": "0.1",
"product": "ISP8324-based 16Gb Fibre Channel to PCI Express Adapter",
"vendor": "QLogic Corp.",
"version": "02",
"width": "64"
}
},
"fans": {
"Fan1A RPM": {
"baseUnit": "RPM",
"threshold": 840,
"value": 3360
},
"Fan1B RPM": {
"baseUnit": "RPM",
"threshold": 840,
"value": 3120
}
},
"fibreChannelPorts": [
{
```

```
"firmware": "7.04.00 (d0d5)",
"hbaPort": 1,
"internalPortID": 2,
"model": "QLE2672",
"nPortID": "0x060019",
"nodeID": 6,
"pciSlot": 3,
"serial": "BFE1335E04217",
"speed": "8 Gbit",
"state": "Online",
"switchWwn": "20:01:00:2a:6a:9c:71:01",
"wwnn": "5f:47:ac:c8:30:26:c9:00",
"wwpn": "5f:47:ac:c0:30:26:c9:0a"
},
{
"firmware": "7.04.00 (d0d5)",
"hbaPort": 2,
"internalPortID": 3,
"model": "QLE2672",
"nPortID": "0xc70019",
"nodeID": 6,
"pciSlot": 3,
"serial": "BFE1335E04217",
"speed": "8 Gbit",
"state": "Online",
"switchWwn": "20:01:00:2a:6a:98:a3:41",
"wwnn": "5f:47:ac:c8:30:26:c9:00",
"wwpn": "5f:47:ac:c0:30:26:c9:0b"
},
{
"firmware": "7.04.00 (d0d5)",
"hbaPort": 1,
"internalPortID": 0,
"model": "QLE2672",
"nPortID": "0xc70017",
"nodeID": 6,
"pciSlot": 2,
"serial": "BFE1341E09515",
"speed": "8 Gbit",
"state": "Online",
"switchWwn": "20:01:00:2a:6a:98:a3:41",
"wwnn": "5f:47:ac:c8:30:26:c9:00",
"wwpn": "5f:47:ac:c0:30:26:c9:08"
},
{
"firmware": "7.04.00 (d0d5)",
```

```
"hbaPort": 2,
"internalPortID": 1,
"model": "QLE2672",
"nPortID": "0x060017",
"nodeID": 6,
"pciSlot": 2,
"serial": "BFE1341E09515",
"speed": "8 Gbit",
"state": "Online",
"switchWwn": "20:01:00:2a:6a:9c:71:01",
"wwnn": "5f:47:ac:c8:30:26:c9:00",
"wwpn": "5f:47:ac:c0:30:26:c9:09"
}
],
"memory": {
"firmware_": {
"capacity": "8323072",
"date": "08/29/2013",
"description": "BIOS",
"physid": "0",
"size": "65536",
"version": "2.0.19"
},
"memory_DMI:1000": {
"description": "System Memory",
"physid": "1000",
"size": "34359738368",
"slot": "System board or motherboard"
}
},
"network": {
"network:0_": {
"description": "Ethernet interface",
"logicalname": "Bond1G",
"physid": "1",
"serial": "c8:1f:66:df:04:da"
},
"network:0_PCI:0000:01:00.0": {
"businfo": "pci@0000:01:00.0",
"capacity": "1000000000",
"clock": "33000000",
"description": "Ethernet interface",
"logicalname": "eth0",
"physid": "0",
"product": "NetXtreme II BCM57800 1/10 Gigabit Ethernet",
"serial": "c8:1f:66:df:04:d6",
```

```
"vendor": "Broadcom Corporation",
"version": "10",
"width": "64"
},
"network:0_PCI:0000:41:00.0": {
"businfo": "pci@0000:41:00.0",
"capacity": "1000000000",
"clock": "33000000",
"description": "Ethernet interface",
"logicalname": "eth4",
"physid": "0",
"product": "NetXtreme II BCM57810 10 Gigabit Ethernet",
"serial": "00:0a:f7:41:7a:30",
"vendor": "Broadcom Corporation",
"version": "10",
"width": "64"
},
"network:1_": {
"description": "Ethernet interface",
"logicalname": "Bond10G",
"physid": "2",
"serial": "c8:1f:66:df:04:d6"
},
"network:1_PCI:0000:01:00.1": {
"businfo": "pci@0000:01:00.1",
"capacity": "1000000000",
"clock": "33000000",
"description": "Ethernet interface",
"logicalname": "eth1",
"physid": "0.1",
"product": "NetXtreme II BCM57800 1/10 Gigabit Ethernet",
"serial": "c8:1f:66:df:04:d8",
"vendor": "Broadcom Corporation",
"version": "10",
"width": "64"
},
"network:1_PCI:0000:41:00.1": {
"businfo": "pci@0000:41:00.1",
"capacity": "1000000000",
"clock": "33000000",
"description": "Ethernet interface",
"logicalname": "eth5",
"physid": "0.1",
"product": "NetXtreme II BCM57810 10 Gigabit Ethernet",
"serial": "00:0a:f7:41:7a:32",
"vendor": "Broadcom Corporation",
```

```
"version": "10",
"width": "64"
},
"network:2_PCI:0000:01:00.2": {
"businfo": "pci@0000:01:00.2",
"capacity": "1000000000",
"clock": "33000000",
"description": "Ethernet interface",
"logicalname": "eth2",
"physid": "0.2",
"product": "NetXtreme II BCM57800 1/10 Gigabit Ethernet",
"serial": "c8:1f:66:df:04:da",
"size": "1000000000",
"vendor": "Broadcom Corporation",
"version": "10",
"width": "64"
},
"network:3_PCI:0000:01:00.3": {
"businfo": "pci@0000:01:00.3",
"capacity": "1000000000",
"clock": "33000000",
"description": "Ethernet interface",
"logicalname": "eth3",
"physid": "0.3",
"product": "NetXtreme II BCM57800 1/10 Gigabit Ethernet",
"serial": "c8:1f:66:df:04:dc",
"size": "1000000000",
"vendor": "Broadcom Corporation",
"version": "10",
"width": "64"
}
},
"networkInterfaces": {
"Bond10G": {
"isConfigured": true,
"isUp": true
},
"Bond1G": {
"isConfigured": true,
"isUp": true
},
"eth0": {
"isConfigured": true,
"isUp": true
},
"eth1": {
```

```
"isConfigured": true,
"isUp": true
},
"eth2": {
"isConfigured": true,
"isUp": true
},
"eth3": {
"isConfigured": true,
"isUp": true
},
"eth4": {
"isConfigured": true,
"isUp": true
},
"eth5": {
"isConfigured": true,
"isUp": true
}
},
"platform": {
"chassisType": "R620",
"cpuModel": "Intel(R) Xeon(R) CPU E5-2640 0 @ 2.50GHz",
"nodeMemoryGB": 32,
"nodeType": "SFFC"
},
"powerSupplies": {
"PS1 status": {
"powerSupplyFailureDetected": false,
"powerSupplyHasAC": true,
"powerSupplyPredictiveFailureDetected": false,
"powerSupplyPresent": true
},
"PS2 status": {
"powerSupplyFailureDetected": false,
"powerSupplyHasAC": true,
"powerSupplyPredictiveFailureDetected": false,
"powerSupplyPresent": true
}
},
"storage": {
"storage_PCI:0000:00:1f.2": {
"businfo": "pci@0000:00:1f.2",
"clock": "66000000",
"description": "SATA controller",
"physid": "1f.2",
```

```
"product": "C600/X79 series chipset 6-Port SATA AHCI Controller",
"vendor": "Intel Corporation",
"version": "05",
"width": "32"
}
},
"system": {
"fcn-2_DMI:0100": {
"description": "Rack Mount Chassis",
"product": "(SKU=NotProvided;ModelName=)",
"serial": "HTX1DZ1",
"width": "64"
}
},
"temperatures": {
"Exhaust Temp": {
"baseUnit": "C",
"threshold": 70,
"value": 38
},
"Inlet Temp": {
"baseUnit": "C",
"threshold": 42,
"value": 13
  },
"uuid": "4C4C4544-004D-5310-8052-C4C04F335431"
    }
   }
  }
 }
}
```


GetNvramInfo

Le `GetNvramInfo` la méthode renvoie une réponse similaire à l'exemple suivant.


```
{
  id: 1,
  result: {
    nvramInfo: {
      details: {
         errors: {
           numOfErrorLogEntries: "0"
         },
         extended: {
```

```
            dialogVersion: "4",
            event: [
               {
                    name: "flushToFlash",
                    time: "2014-02-24 20:30:28",
                    value: "0"
          },
          {
                    name: "flushToFlash",
                    time: "1946-02-06 17:16:42",
                    value: "0"
          },
          {
                    name: "flushToFlash",
                    time: "2014-02-25 00:48:06",
                    value: "0"
          },
          {
                    name: "flushToFlash",
                    time: "2014-02-25 15:44:07",
                    value: "0"
          },
          {
                    name: "flushToFlash",
                    time: "2014-03-17 17:21:46",
                    value: "0"
          },
          {
                    name: "flushToFlash",
                    time: "2014-03-17 17:59:30",
                    value: "0"
          },
          {
                    name: "flushToFlash",
                    time: "2014-03-17 18:06:27",
                    value: "0"
          },
          {
                    name: "flushToFlash",
                    time: "2014-03-17 21:43:17",
                    value: "0"
          },
          {
                    name: "excessiveCurrent",
                    time: "2014-02-25 00:00:29",
                    value: "39"
```

```
        },
         {
                  name: "excessiveCurrent",
                  time: "2014-03-01 00:00:24",
                  value: "23"
         }
      ],
           eventOccurrences: [
        {
                 count: "15",
                 name: "flushToFlash"
        },
        {
                 count: "2",
                 name: "excessiveCurrent"
        }
                 initialCapacitance: "6.653 F",
                 initialEsr: "0.097 Ohm",
           measurement: [
        {
                 level_0: " 0",
                 level_1: " 112",
                 level_2: " 670919",
                 level_3: " 455356",
                 level_4: " 90215",
                 level_5: " 0",
                 level_6: " 0",
                 level_7: " 0",
                 level_8: " 0",
                 level_9: " 0",
                 name: "enterpriseFlashControllerTemperature",
                 recent: "64 C"
        },
        {
                 level_0: " 0",
                 level_1: " 27",
                 level_2: " 456896",
                 level_3: " 717565",
                 level_4: " 39422",
                 level_5: " 2692",
                 level_6: " 0",
                 level_7: " 0",
                 level_8: " 0",
                 level_9: " 0",
                 name: "capacitor1And2Temperature",
                 recent: "28.64 C"
```

```
        },
        {
                level_0: " 0",
                level_1: " 2080",
                level_2: " 907196",
                level_3: " 280178",
                level_4: " 26539",
                level_5: " 609",
                level_6: " 0",
                level_7: " 0",
                level_8: " 0",
                level_9: " 0",
                name: "capacitor3And4Temperature",
                recent: "28.60 C"
        },
        {
                errorPeriod: {
                    duration: "24",
                    startTime: "2014-02-06 00:23:54",
                    worst: "8"
                },
                level_0: " 0",
                level_1: " 839",
                level_2: " 272794",
                level_3: " 404758",
                level_4: " 35216",
                level_5: " 377818",
                level_6: " 103891",
                level_7: " 21274",
                level_8: " 12",
                level_9: " 0",
                name: "rearVentAmbientTemperature",
                recent: "46.82 C"
         },
         {
                level_0: " 0",
                level_1: " 742749",
                level_2: " 460016",
                level_3: " 13837",
                level_4: " 0",
                level_5: " 0",
                level_6: " 0",
                level_7: " 0",
                level_8: " 0",
                level_9: " 0",
                name: "rms200BoardTemperature",
```

```
                recent: "50.62 C"
        },
        {
                name: "voltageOfCapacitor1",
                recent: "2.308 V"
        },
        {
                name: "voltageOfCapacitor2",
                recent: "2.305 V"},
        {
                name: "voltageOfCapacitor3",
                recent: "2.314 V"
        },
        {
                name: "voltageOfCapacitor4",
                recent: "2.307 V"
        },
        {
               level_0: " 175052",
               level_1: " 51173",
               level_2: " 435788",
               level_3: " 12766",
               level_4: " 4",
               level_5: " 6",
               level_6: " 541813",
               level_7: " 0",
               level_8: " 0",
               level_9: " 0",
               name: "capacitorPackVoltage",
               recent: "9.233 V"
         },
         {
               level_0: " 0",
               level_1: " 0",
               level_2: " 0",
               level_3: " 0",
               level_4: " 0",
               level_5: " 0",
               level_6: " 4",
               level_7: " 1",
               level_8: " 4",
               level_9: " 6",
               name: "capacitorPackVoltageAtEndOfFlushToFlash",
               recent: "5.605 V"
        },
        {
```

```
                name: "currentDerivedFromV3V4",
                recent: "0.000 A"
        },
        {
                level_0: " 7",
                level_1: " 4",
                level_2: " 3",
                level_3: " 1",
                level_4: " 0",
                level_5: " 0",
                level_6: " 0",
                level_7: " 0",
                level_8: " 0",
                level_9: " 0",
                name: "derivedEnergy",
                recent: "175 Joules"
        },
        {
                level_0: " 0",
                level_1: " 0",
                level_2: " 0",
                level_3: " 0",
                level_4: " 0",
                level_5: " 0",
                level_6: " 0",
                level_7: " 17",
                level_8: " 19",
                level_9: " 7",
                name: "derivedCapacitanceOfThePack",
                recent: "5.959 F"
         },
         {
                level_0: " 0",
                level_1: " 43",
                level_2: " 0",
                level_3: " 0",
                level_4: " 0",
                level_5: " 0",
                level_6: " 0",
                level_7: " 0",
                level_8: " 0",
                level_9: " 0",
                name: "derivedEsrOfCapacitorPack",
                recent: "0.104 Ohm"
        },
        {
```

```
                level_0: " 0",
                level_1: " 0",
                level_2: " 0",
                level_3: " 0",
                level_4: " 15",
                level_5: " 0",
                level_6: " 0",
                level_7: " 0",
                level_8: " 0",
                level_9: " 0",
                name: "timeToRunFlushToFlash",
                recent: "22.40 Seconds"
        },
        {
                level_0: " 0",
                level_1: " 0",
                level_2: " 7",
                level_3: " 0",
                level_4: " 0",
                level_5: " 0",
                level_6: " 0",
                level_7: " 0",
                level_8: " 0",
                level_9: " 0",
                name: "timeToRunRestore",
                recent: "20.44 Seconds"
        },
        {
                level_0: " 0",
                level_1: " 1",
                level_2: " 3",
                level_3: " 2",
                level_4: " 0",
                level_5: " 0",
                level_6: " 0",
                level_7: " 0",
                level_8: " 0",
                level_9: " 1",
                name: "timeToChargeCapacitors",
                recent: "48 Seconds"
        },
        {
                level_0: " 448586",
                level_1: " 2998",
                level_2: " 0",
                level_3: " 0",
```

```
                level_4: " 0",
                level_5: " 0",
                level_6: " 0",
                level_7: " 0",
                level_8: " 0",
                level_9: " 0",
                name: "correctableBitsInErrorOnReadingAPage"
        },
        {
                level_0: " 2998",
                level_1: " 0",
                level_2: " 0",
                level_3: " 0",
                level_4: " 0",
                level_5: " 0",
                level_6: " 0",
                level_7: " 0",
                level_8: " 0",
                level_9: " 0",
                name:
"correctableBitsInErrorOnReadingTheWorstBchRegionOfAPage"
        },
        {
                level_0: " 0",
                level_1: " 37",
                level_2: " 280274",
                level_3: " 422999",
                level_4: " 245814",
                level_5: " 242470",
                level_6: " 24447",
                level_7: " 561",
                level_8: " 0",
                level_9: " 0",
                name: "fanInletAmbientTemperature",
                recent: "41.74 C"
        }
        ],
                predictedCapacitanceDepletion: "504328 uF",
                smartCounters: [
        {
                name: "numberOf512ByteBlocksReadFromDdr",
                value: "218284648"
        },
        {
                name: "numberOf512ByteBlocksWrittenToDdr",
                value: "12031567354"
```

```
        },
        {
                name: "numberOfHostReadCommands",
                value: "5366315"
        },
        {
                name: "numberOfHostWriteCommands",
                value: "1266099334"
        },
        {
                name: "controllerBusyTimeMinutes",
                value: "0"
        },
        {
                name: "numberOfPowerCycles",
                value: "13"
        },
        {
                name: "powerOnHours",
                value: "1009"
        },
        {
                name: "unsafeShutdowns",
                value: "5"
        },
        {
                name: "mediaErrors",
                value: "0"
        },
        {
                name: "numberOfErrorLogs",
                value: "2"
        }
        ],
         snapshotTime: "2014-03-20 16:43:49"
    },
    firmware: {
         activeSlotNumber: "2",
         slot1Version: "1e5817bc",
         slot2Version: "1e0d70ac",
         slot3Version: "1e5817bc",
         slot4Version: "1e5817bc"
   },
    smart: {
        availableSpace: "0%",
        availableSpaceThreshold: "0%",
```

```
          controllerBusyTimeMinutes: "0",
          criticalErrorVector: "0x0",
          mediaErrors: "0",
          numberOf512ByteBlocksRead: "218284648",
          numberOf512ByteBlocksWritten: "12031567354",
          numberOfErrorInfoLogs: "2",
          numberOfHostReadCommands: "5366315",
          numberOfHostWriteCommands: "1266099334",
          numberOfPowerCycles: "13",
          powerOnHours: "1009",
          temperature: "323 Kelvin",
          unsafeShutdowns: "5"
       }
      },
      status: "Warning",
      statusInfo: {
      warning: [
          "excessiveCurrent (2x)"
        ]
      },
      type: "RMS-200"
     }
   }
}
```

ListenActiveNodes

Le `ListActiveNodes` la méthode renvoie une réponse similaire à l'exemple suivant.

```
 {
    "id": 1,
    "result": {
        "nodes": [
            {
                "associatedFServiceID": 0,
                "associatedMasterServiceID": 1,
                "attributes": {},
                "cip": "172.27.21.23",
                "cipi": "Bond10G",
                "fibreChannelTargetPortGroup": null,
                "mip": "172.27.1.23",
                "mipi": "Bond1G",
                "name": "PSN-1-23",
                "nodeID": 1,
                "platformInfo": {
```

```
                    "chassisType": "R620",
                    "cpuModel": "Intel(R) Xeon(R) CPU E5-2640 0 @
2.50GHz",
                    "nodeMemoryGB": 72,
                    "nodeType": "SF3010"
                },
                "sip": "172.27.21.23",
                "sipi": "Bond10G",
                "softwareVersion": "9.0.0.1298",
                "uuid": "4C4C4544-0056-3810-804E-B5C04F4C5631",
                "virtualNetworks": [
                    {
                        "address": "10.1.2.4",
                        "virtualNetworkID": 1
                    },
                    {
                        "address": "10.2.2.10",
                        "virtualNetworkID": 2
                    }
                ]
            },
            {
                "associatedFServiceID": 0,
                "associatedMasterServiceID": 4,
                "attributes": {},
                "cip": "172.27.21.24",
                "cipi": "Bond10G",
                "fibreChannelTargetPortGroup": null,
                "mip": "172.27.1.24",
                "mipi": "Bond1G",
                "name": "PSN-1-24",
                "nodeID": 2,
                "platformInfo": {
                    "chassisType": "R620",
                    "cpuModel": "Intel(R) Xeon(R) CPU E5-2640 0 @
2.50GHz",
                    "nodeMemoryGB": 72,
                    "nodeType": "SF3010"
                },
                "sip": "172.27.21.24",
                "sipi": "Bond10G",
                "softwareVersion": "9.0.0.1298",
                "uuid": "4C4C4544-0042-4210-804E-C3C04F4C5631",
                "virtualNetworks": [
                    {
                        "address": "10.1.2.5",
```

```
                        "virtualNetworkID": 1
                    },
                    {
                        "address": "10.2.2.11",
                        "virtualNetworkID": 2
                    }
                ]
            },
            {
                "associatedFServiceID": 0,
                "associatedMasterServiceID": 2,
                "attributes": {},
                "cip": "172.27.21.25",
                "cipi": "Bond10G",
                "fibreChannelTargetPortGroup": null,
                "mip": "172.27.1.25",
                "mipi": "Bond1G",
                "name": "PSN-1-25",
                "nodeID": 3,
                "platformInfo": {
                    "chassisType": "R620",
                    "cpuModel": "Intel(R) Xeon(R) CPU E5-2640 0 @
2.50GHz",
                    "nodeMemoryGB": 72,
                    "nodeType": "SF3010"
                },
                "sip": "172.27.21.25",
                "sipi": "Bond10G",
                "softwareVersion": "9.0.0.1298",
                "uuid": "4C4C4544-0053-4210-8051-C6C04F515631",
                "virtualNetworks": [
                    {
                        "address": "10.1.2.6",
                        "virtualNetworkID": 1
                    },
                    {
                        "address": "10.2.2.12",
                        "virtualNetworkID": 2
                    }
                ]
            },
            {
                "associatedFServiceID": 0,
                "associatedMasterServiceID": 3,
                "attributes": {},
                "cip": "172.27.21.26",
```

```
                "cipi": "Bond10G",
                "fibreChannelTargetPortGroup": null,
                "mip": "172.27.1.26",
                "mipi": "Bond1G",
                "name": "PSN-1-26",
                "nodeID": 4,
                "platformInfo": {
                    "chassisType": "R620",
                    "cpuModel": "Intel(R) Xeon(R) CPU E5-2640 0 @
2.50GHz",
                    "nodeMemoryGB": 72,
                    "nodeType": "SF3010"
                },
                "sip": "172.27.21.26",
                "sipi": "Bond10G",
                "softwareVersion": "9.0.0.1298",
                "uuid": "4C4C4544-0056-3810-804E-B4C04F4C5631",
                "virtualNetworks": [
                    {
                        "address": "10.1.2.7",
                        "virtualNetworkID": 1
                    },
                    {
                        "address": "10.2.2.13",
                        "virtualNetworkID": 2
                    }
                ]
            }
        ]
    }
 }
```

ActivéNon

Le `ListActiveVolumes` la méthode renvoie une réponse similaire à l'exemple suivant.

```
{
    "id": 1,
    "result": {
        "volumes": [
            {
                "access": "readWrite",
                "accountID": 1,
                "attributes": {},
                "blockSize": 4096,
```

```
            "createTime": "2016-06-23T14:19:12Z",
            "deleteTime": "",
            "enable512e": false,
            "iqn": "iqn.2010-01.com.solidfire:0oto.hulkdemo1.1",
            "name": "HulkDemo1",
            "purgeTime": "",
            "qos": {
                "burstIOPS": 1500,
                "burstTime": 60,
                "curve": {
                    "4096": 100,
                    "8192": 160,
                    "16384": 270,
                    "32768": 500,
                    "65536": 1000,
                    "131072": 1950,
                    "262144": 3900,
                    "524288": 7600,
                    "1048576": 15000
                },
                "maxIOPS": 1000,
                "minIOPS": 100
            },
            "scsiEUIDeviceID": "306f746f00000001f47acc0100000000",
            "scsiNAADeviceID": "6f47acc100000000306f746f00000001",
            "sliceCount": 1,
            "status": "active",
            "totalSize": 53687091200,
            "virtualVolumeID": null,
            "volumeAccessGroups": [
                1
            ],
            "volumeID": 1,
            "volumePairs": []
        },
        {
            "access": "readWrite",
            "accountID": 1,
            "attributes": {},
            "blockSize": 4096,
            "createTime": "2016-06-23T14:19:14Z",
            "deleteTime": "",
            "enable512e": false,
            "iqn": "iqn.2010-01.com.solidfire:0oto.hulkdemo6.6",
            "name": "HulkDemo6",
            "purgeTime": "",
```

```
            "qos": {
                "burstIOPS": 1500,
                "burstTime": 60,
                "curve": {
                    "4096": 100,
                    "8192": 160,
                    "16384": 270,
                    "32768": 500,
                    "65536": 1000,
                    "131072": 1950,
                    "262144": 3900,
                    "524288": 7600,
                    "1048576": 15000
                },
                "maxIOPS": 1000,
                "minIOPS": 100
            },
            "scsiEUIDeviceID": "306f746f00000006f47acc0100000000",
            "scsiNAADeviceID": "6f47acc100000000306f746f00000006",
            "sliceCount": 1,
            "status": "active",
            "totalSize": 53687091200,
            "virtualVolumeID": null,
            "volumeAccessGroups": [
                1
            ],
            "volumeID": 6,
            "volumePairs": []
        },
        {
            "access": "readWrite",
            "accountID": 1,
            "attributes": {},
            "blockSize": 4096,
            "createTime": "2016-06-23T14:19:14Z",
            "deleteTime": "",
            "enable512e": false,
            "iqn": "iqn.2010-01.com.solidfire:0oto.hulkdemo7.7",
            "name": "HulkDemo7",
            "purgeTime": "",
            "qos": {
                "burstIOPS": 1500,
                "burstTime": 60,
                "curve": {
                    "4096": 100,
                    "8192": 160,
```

```
                    "16384": 270,
                    "32768": 500,
                    "65536": 1000,
                    "131072": 1950,
                    "262144": 3900,
                    "524288": 7600,
                    "1048576": 15000
                },
                "maxIOPS": 1000,
                "minIOPS": 100
            },
            "scsiEUIDeviceID": "306f746f00000007f47acc0100000000",
            "scsiNAADeviceID": "6f47acc100000000306f746f00000007",
            "sliceCount": 1,
            "status": "active",
            "totalSize": 53687091200,
            "virtualVolumeID": null,
            "volumeAccessGroups": [
                1
            ],
            "volumeID": 7,
            "volumePairs": []
        },
        {
            "access": "readWrite",
            "accountID": 1,
            "attributes": {},
            "blockSize": 4096,
            "createTime": "2016-06-23T14:19:15Z",
            "deleteTime": "",
            "enable512e": false,
            "iqn": "iqn.2010-01.com.solidfire:0oto.hulkdemo8.8",
            "name": "HulkDemo8",
            "purgeTime": "",
            "qos": {
                "burstIOPS": 1500,
                "burstTime": 60,
                "curve": {
                    "4096": 100,
                    "8192": 160,
                    "16384": 270,
                    "32768": 500,
                    "65536": 1000,
                    "131072": 1950,
                    "262144": 3900,
                    "524288": 7600,
```

```
                    "1048576": 15000
                },
                "maxIOPS": 1000,
                "minIOPS": 100
            },
            "scsiEUIDeviceID": "306f746f00000008f47acc0100000000",
            "scsiNAADeviceID": "6f47acc100000000306f746f00000008",
            "sliceCount": 1,
            "status": "active",
            "totalSize": 53687091200,
            "virtualVolumeID": null,
            "volumeAccessGroups": [
                1
            ],
            "volumeID": 8,
            "volumePairs": []
        },
        {
            "access": "readWrite",
            "accountID": 1,
            "attributes": {},
            "blockSize": 4096,
            "createTime": "2016-06-23T14:19:15Z",
            "deleteTime": "",
            "enable512e": false,
            "iqn": "iqn.2010-01.com.solidfire:0oto.hulkdemo9.9",
            "name": "HulkDemo9",
            "purgeTime": "",
            "qos": {
                "burstIOPS": 1500,
                "burstTime": 60,
                "curve": {
                    "4096": 100,
                    "8192": 160,
                    "16384": 270,
                    "32768": 500,
                    "65536": 1000,
                    "131072": 1950,
                    "262144": 3900,
                    "524288": 7600,
                    "1048576": 15000
                },
                "maxIOPS": 1000,
                "minIOPS": 100
            },
            "scsiEUIDeviceID": "306f746f00000009f47acc0100000000",
```

```
            "scsiNAADeviceID": "6f47acc100000000306f746f00000009",
            "sliceCount": 1,
            "status": "active",
            "totalSize": 53687091200,
            "virtualVolumeID": null,
            "volumeAccessGroups": [
                1
            ],
            "volumeID": 9,
            "volumePairs": []
        },
        {
            "access": "readWrite",
            "accountID": 1,
            "attributes": {},
            "blockSize": 4096,
            "createTime": "2016-06-23T14:19:16Z",
            "deleteTime": "",
            "enable512e": false,
            "iqn": "iqn.2010-01.com.solidfire:0oto.hulkdemo12.12",
            "name": "HulkDemo12",
            "purgeTime": "",
            "qos": {
                "burstIOPS": 1500,
                "burstTime": 60,
                "curve": {
                    "4096": 100,
                    "8192": 160,
                    "16384": 270,
                    "32768": 500,
                    "65536": 1000,
                    "131072": 1950,
                    "262144": 3900,
                    "524288": 7600,
                    "1048576": 15000
                },
                "maxIOPS": 1000,
                "minIOPS": 100
            },
            "scsiEUIDeviceID": "306f746f0000000cf47acc0100000000",
            "scsiNAADeviceID": "6f47acc100000000306f746f0000000c",
            "sliceCount": 1,
            "status": "active",
            "totalSize": 53687091200,
            "virtualVolumeID": null,
            "volumeAccessGroups": [
```

```
                1
            ],
            "volumeID": 12,
            "volumePairs": []
        },
        {
            "access": "readWrite",
            "accountID": 1,
            "attributes": {},
            "blockSize": 4096,
            "createTime": "2016-06-23T14:19:18Z",
            "deleteTime": "",
            "enable512e": false,
            "iqn": "iqn.2010-01.com.solidfire:0oto.hulkdemo16.16",
            "name": "HulkDemo16",
            "purgeTime": "",
            "qos": {
                "burstIOPS": 1500,
                "burstTime": 60,
                "curve": {
                    "4096": 100,
                    "8192": 160,
                    "16384": 270,
                    "32768": 500,
                    "65536": 1000,
                    "131072": 1950,
                    "262144": 3900,
                    "524288": 7600,
                    "1048576": 15000
                },
                "maxIOPS": 1000,
                "minIOPS": 100
            },
            "scsiEUIDeviceID": "306f746f00000010f47acc0100000000",
            "scsiNAADeviceID": "6f47acc100000000306f746f00000010",
            "sliceCount": 1,
            "status": "active",
            "totalSize": 53687091200,
            "virtualVolumeID": null,
            "volumeAccessGroups": [
                1
            ],
            "volumeID": 16,
            "volumePairs": []
        },
        {
```

```
            "access": "readWrite",
            "accountID": 1,
            "attributes": {},
            "blockSize": 4096,
            "createTime": "2016-06-23T14:19:18Z",
            "deleteTime": "",
            "enable512e": false,
            "iqn": "iqn.2010-01.com.solidfire:0oto.hulkdemo17.17",
            "name": "HulkDemo17",
            "purgeTime": "",
            "qos": {
                "burstIOPS": 1500,
                "burstTime": 60,
                "curve": {
                    "4096": 100,
                    "8192": 160,
                    "16384": 270,
                    "32768": 500,
                    "65536": 1000,
                    "131072": 1950,
                    "262144": 3900,
                    "524288": 7600,
                    "1048576": 15000
                },
                "maxIOPS": 1000,
                "minIOPS": 100
            },
            "scsiEUIDeviceID": "306f746f00000011f47acc0100000000",
            "scsiNAADeviceID": "6f47acc100000000306f746f00000011",
            "sliceCount": 1,
            "status": "active",
            "totalSize": 53687091200,
            "virtualVolumeID": null,
            "volumeAccessGroups": [
                1
            ],
            "volumeID": 17,
            "volumePairs": []
        },
        {
            "access": "readWrite",
            "accountID": 1,
            "attributes": {},
            "blockSize": 4096,
            "createTime": "2016-06-23T14:19:18Z",
            "deleteTime": "",
```

```
            "enable512e": false,
            "iqn": "iqn.2010-01.com.solidfire:0oto.hulkdemo18.18",
            "name": "HulkDemo18",
            "purgeTime": "",
            "qos": {
                "burstIOPS": 1500,
                "burstTime": 60,
                "curve": {
                    "4096": 100,
                    "8192": 160,
                    "16384": 270,
                    "32768": 500,
                    "65536": 1000,
                    "131072": 1950,
                    "262144": 3900,
                    "524288": 7600,
                    "1048576": 15000
                },
                "maxIOPS": 1000,
                "minIOPS": 100
            },
            "scsiEUIDeviceID": "306f746f00000012f47acc0100000000",
            "scsiNAADeviceID": "6f47acc100000000306f746f00000012",
            "sliceCount": 1,
            "status": "active",
            "totalSize": 53687091200,
            "virtualVolumeID": null,
            "volumeAccessGroups": [
                1
            ],
            "volumeID": 18,
            "volumePairs": []
        },
        {
            "access": "readWrite",
            "accountID": 1,
            "attributes": {},
            "blockSize": 4096,
            "createTime": "2016-06-24T15:21:59Z",
            "deleteTime": "",
            "enable512e": true,
            "iqn": "iqn.2010-01.com.solidfire:0oto.bk.24",
            "name": "BK",
            "purgeTime": "",
            "qos": {
                "burstIOPS": 15000,
```

```
                    "burstTime": 60,
                    "curve": {
                        "4096": 100,
                        "8192": 160,
                        "16384": 270,
                        "32768": 500,
                        "65536": 1000,
                        "131072": 1950,
                        "262144": 3900,
                        "524288": 7600,
                        "1048576": 15000
                    },
                    "maxIOPS": 15000,
                    "minIOPS": 50
                },
                "scsiEUIDeviceID": "306f746f00000018f47acc0100000000",
                "scsiNAADeviceID": "6f47acc100000000306f746f00000018",
                "sliceCount": 1,
                "status": "active",
                "totalSize": 10737418240,
                "virtualVolumeID": null,
                "volumeAccessGroups": [],
                "volumeID": 24,
                "volumePairs": [
                    {
                        "clusterPairID": 2,
                        "remoteReplication": {
                            "mode": "Async",
                            "pauseLimit": 3145728000,
                            "remoteServiceID": 14,
                            "resumeDetails": "",
                            "snapshotReplication": {
                                "state": "Idle",
                                "stateDetails": ""
                            },
                            "state": "Active",
                            "stateDetails": ""
                        },
                        "remoteSliceID": 8,
                        "remoteVolumeID": 8,
                        "remoteVolumeName": "PairingDoc",
                        "volumePairUUID": "229fcbf3-2d35-4625-865a-
d04bb9455cef"
                    }
                ]
            }
```

```
        ]
    }
}
```

TestHardwareConfig

Le `TestHardwareConfig` la méthode renvoie une réponse similaire à l'exemple suivant.

```
{
"id": 1,
"result": {
    "nodes": [
        {
            "nodeID": 1,
            "result": {
                "details": {
                    "BIOS_REVISION": {
                        "Passed": true,
                        "actual": "2.0",
                        "comparator": ">=",
                        "expected": "1.0.0.0"
                    },
                    "BIOS_VENDOR": {
                        "Passed": true,
                        "actual": "SolidFire",
                        "comparator": "==",
                        "expected": "SolidFire"
                    },
                    "BIOS_VERSION": {
                        "Passed": true,
                        "actual": "2.0.19",
                        "comparator": ">=",
                        "expected": "2.0.19"
                    },
                    "CPU_CORES_00": {
                        "Passed": true,
                        "actual": "6",
                        "comparator": "==",
                        "expected": "6"
                    },
                    "CPU_CORES_01": {
                        "Passed": true,
                        "actual": "6",
                        "comparator": "==",
```

```
                        "expected": "6"
                    },
                    "CPU_CORES_ENABLED_00": {
                        "Passed": true,
                        "actual": "6",
                        "comparator": "==",
                        "expected": "6"
                    },
                    "CPU_CORES_ENABLED_01": {
                        "Passed": true,
                        "actual": "6",
                        "comparator": "==",
                        "expected": "6"
                    },
                    "CPU_MODEL_00": {
                        "Passed": true,
                        "actual": "Intel(R) Xeon(R) CPU E5-2620 v2 @
2.10GHz",
                        "comparator": "==",
                        "expected": "Intel(R) Xeon(R) CPU E5-2620 v2 @
2.10GHz"
                    },
                    "CPU_MODEL_01": {
                        "Passed": true,
                        "actual": "Intel(R) Xeon(R) CPU E5-2620 v2 @
2.10GHz",
                        "comparator": "==",
                        "expected": "Intel(R) Xeon(R) CPU E5-2620 v2 @
2.10GHz"
                    },
                    "CPU_THREADS_00": {
                        "Passed": true,
                        "actual": "12",
                        "comparator": "==",
                        "expected": "12"
                    },
                    "CPU_THREADS_01": {
                        "Passed": true,
                        "actual": "12",
                        "comparator": "==",
                        "expected": "12"
                    },
                    "CPU_THREADS_ENABLED": {
                        "Passed": true,
                        "actual": "24",
                        "comparator": "==",
```

```
            "expected": "24"
        },
        "IDRAC_VERSION": {
            "Passed": true,
            "actual": "2.41.40.40",
            "comparator": ">=",
            "expected": "1.06.06"
        },
        "MEMORY_GB": {
            "Passed": true,
            "actual": "64",
            "comparator": ">=",
            "expected": "64"
        },
        "MEMORY_MHZ_00": {
            "Passed": true,
            "actual": "1600",
            "comparator": ">=",
            "expected": "1333"
        },
        "MEMORY_MHZ_01": {
            "Passed": true,
            "actual": "1600",
            "comparator": ">=",
            "expected": "1333"
        },
        "MEMORY_MHZ_02": {
            "Passed": true,
            "actual": "1600",
            "comparator": ">=",
            "expected": "1333"
        },
        "MEMORY_MHZ_03": {
            "Passed": true,
            "actual": "1600",
            "comparator": ">=",
            "expected": "1333"
        },
        "MEMORY_MHZ_04": {
            "Passed": true,
            "actual": "1600",
            "comparator": ">=",
            "expected": "1333"
        },
        "MEMORY_MHZ_05": {
            "Passed": true,
```

```
            "actual": "1600",
            "comparator": ">=",
            "expected": "1333"
        },
        "MEMORY_MHZ_06": {
            "Passed": true,
            "actual": "1600",
            "comparator": ">=",
            "expected": "1333"
        },
        "MEMORY_MHZ_07": {
            "Passed": true,
            "actual": "1600",
            "comparator": ">=",
            "expected": "1333"
        },
        "MPTSAS_BIOS_VERSION": {
            "Passed": true,
            "actual": "07.24.01.00",
            "comparator": "ANY",
            "expected": "7.25.0.0"
        },
        "MPTSAS_FIRMWARE_VERSION": {
            "Passed": true,
            "actual": "13.00.57.00",
            "comparator": "==",
            "expected": "13.0.57.0"
        },
        "NETWORK_DRIVER_ETH0": {
            "Passed": true,
            "actual": "bnx2x",
            "comparator": "==",
            "expected": "bnx2x"
        },
        "NETWORK_DRIVER_ETH1": {
            "Passed": true,
            "actual": "bnx2x",
            "comparator": "==",
            "expected": "bnx2x"
        },
        "NETWORK_DRIVER_ETH2": {
            "Passed": true,
            "actual": "bnx2x",
            "comparator": "==",
            "expected": "bnx2x"
        },
```

```
                "NETWORK_DRIVER_ETH3": {
                    "Passed": true,
                    "actual": "bnx2x",
                    "comparator": "==",
                    "expected": "bnx2x"
                },
                "NETWORK_FIRMWARE_VERSION_ETH0": {
                    "Passed": true,
                    "actual": "7.10.18-solidfire-5f3ccbc781d53",
                    "comparator": "==",
                    "expected": "7.10.18-solidfire-5f3ccbc781d53"
                },
                "NETWORK_FIRMWARE_VERSION_ETH1": {
                    "Passed": true,
                    "actual": "7.10.18-solidfire-5f3ccbc781d53",
                    "comparator": "==",
                    "expected": "7.10.18-solidfire-5f3ccbc781d53"
                },
                "NETWORK_FIRMWARE_VERSION_ETH2": {
                    "Passed": true,
                    "actual": "7.10.18-solidfire-5f3ccbc781d53",
                    "comparator": "==",
                    "expected": "7.10.18-solidfire-5f3ccbc781d53"
                },
                "NETWORK_FIRMWARE_VERSION_ETH3": {
                    "Passed": true,
                    "actual": "7.10.18-solidfire-5f3ccbc781d53",
                    "comparator": "==",
                    "expected": "7.10.18-solidfire-5f3ccbc781d53"
                },
                "NUM_CPU": {
                    "Passed": true,
                    "actual": "2",
                    "comparator": "==",
                    "expected": "2"
                },
                "Parse failure in /var/log/sf-bios.info": {
                    "Passed": true,
                    "actual": "false",
                    "comparator": "==",
                    "expected": "false"
                }
            },
            "duration": "00:00:00.195067",
            "result": "Passed"
        }
```

```
            }
        ]
}
}
```

Informations sur le copyright

Copyright © 2025 NetApp, Inc. Tous droits réservés. Imprimé aux États-Unis. Aucune partie de ce document protégé par copyright ne peut être reproduite sous quelque forme que ce soit ou selon quelque méthode que ce soit (graphique, électronique ou mécanique, notamment par photocopie, enregistrement ou stockage dans un système de récupération électronique) sans l'autorisation écrite préalable du détenteur du droit de copyright.

Les logiciels dérivés des éléments NetApp protégés par copyright sont soumis à la licence et à l'avis de non-responsabilité suivants :

CE LOGICIEL EST FOURNI PAR NETAPP « EN L'ÉTAT » ET SANS GARANTIES EXPRESSES OU TACITES, Y COMPRIS LES GARANTIES TACITES DE QUALITÉ MARCHANDE ET D'ADÉQUATION À UN USAGE PARTICULIER, QUI SONT EXCLUES PAR LES PRÉSENTES. EN AUCUN CAS NETAPP NE SERA TENU POUR RESPONSABLE DE DOMMAGES DIRECTS, INDIRECTS, ACCESSOIRES, PARTICULIERS OU EXEMPLAIRES (Y COMPRIS L'ACHAT DE BIENS ET DE SERVICES DE SUBSTITUTION, LA PERTE DE JOUISSANCE, DE DONNÉES OU DE PROFITS, OU L'INTERRUPTION D'ACTIVITÉ), QUELLES QU'EN SOIENT LA CAUSE ET LA DOCTRINE DE RESPONSABILITÉ, QU'IL S'AGISSE DE RESPONSABILITÉ CONTRACTUELLE, STRICTE OU DÉLICTUELLE (Y COMPRIS LA NÉGLIGENCE OU AUTRE) DÉCOULANT DE L'UTILISATION DE CE LOGICIEL, MÊME SI LA SOCIÉTÉ A ÉTÉ INFORMÉE DE LA POSSIBILITÉ DE TELS DOMMAGES.

NetApp se réserve le droit de modifier les produits décrits dans le présent document à tout moment et sans préavis. NetApp décline toute responsabilité découlant de l'utilisation des produits décrits dans le présent document, sauf accord explicite écrit de NetApp. L'utilisation ou l'achat de ce produit ne concède pas de licence dans le cadre de droits de brevet, de droits de marque commerciale ou de tout autre droit de propriété intellectuelle de NetApp.

Le produit décrit dans ce manuel peut être protégé par un ou plusieurs brevets américains, étrangers ou par une demande en attente.

LÉGENDE DE RESTRICTION DES DROITS : L'utilisation, la duplication ou la divulgation par le gouvernement sont sujettes aux restrictions énoncées dans le sous-paragraphe (b)(3) de la clause Rights in Technical Data-Noncommercial Items du DFARS 252.227-7013 (février 2014) et du FAR 52.227-19 (décembre 2007).

Les données contenues dans les présentes se rapportent à un produit et/ou service commercial (tel que défini par la clause FAR 2.101). Il s'agit de données propriétaires de NetApp, Inc. Toutes les données techniques et tous les logiciels fournis par NetApp en vertu du présent Accord sont à caractère commercial et ont été exclusivement développés à l'aide de fonds privés. Le gouvernement des États-Unis dispose d'une licence limitée irrévocable, non exclusive, non cessible, non transférable et mondiale. Cette licence lui permet d'utiliser uniquement les données relatives au contrat du gouvernement des États-Unis d'après lequel les données lui ont été fournies ou celles qui sont nécessaires à son exécution. Sauf dispositions contraires énoncées dans les présentes, l'utilisation, la divulgation, la reproduction, la modification, l'exécution, l'affichage des données sont interdits sans avoir obtenu le consentement écrit préalable de NetApp, Inc. Les droits de licences du Département de la Défense du gouvernement des États-Unis se limitent aux droits identifiés par la clause 252.227-7015(b) du DFARS (février 2014).

Informations sur les marques commerciales

NETAPP, le logo NETAPP et les marques citées sur le site http://www.netapp.com/TM sont des marques déposées ou des marques commerciales de NetApp, Inc. Les autres noms de marques et de produits sont des marques commerciales de leurs propriétaires respectifs.