



# Journaux d'événements XCP

XCP

NetApp  
May 21, 2024

# Sommaire

- Journaux d'événements XCP ..... 1
- Journaux d'événements NFS XCP ..... 1
- Journaux d'événements SMB XCP ..... 13

# Journaux d'événements XCP

## Journaux d'événements NFS XCP

Examinez des exemples de journaux d'événements pour XCP NFS.

Le tableau suivant présente les journaux d'événements pour XCP NFS.

ID d'événement	Modèle d'événement	Exemple d'événement
401	Mounted on NFS export <mount path> with maximum read block size <read block size> bytes, maximum write block size <write block size> bytes. Mount point has mode value<mode bits> and type: <fattr3 type>.	2020-07-14 03:53:59,811 - INFO {"Event ID":401, "Event Category": "Mounting unmounting file system", "Event Type": "Mount file system information", "ExecutionId": 408249379415, "Event Source": "NETAPP-01", "Description": "Mounted on NFS export <IPaddress of NFS server>:/test1 with maximum read block size 65536 bytes, maximum write block size 65536 bytes. Mount point has mode value 493 and type : Directory"}
181	This license is issued to <username>of <company name>,license type is <license type> with <license status> status, license will expire on <expire date>	2020-07-14 03:53:59,463 - INFO {"Event ID": 181, "Event Category": "Authentication and authorization", "Event Type": "License information", "ExecutionId": 408249379415, "Event Source": "NETAPP-01", "Description": "This license is issued to NetApp User of Network Appliance, Inc, license type is SANDBOX with ACTIVE status, license will expire on Thu Jul 1 00:00:00 2021"}

ID d'événement	Modèle d'événement	Exemple d'événement
183	The license issued to <username> of <company name> will expire in less than one week	2020-07-14 04:02:55,151 - WARNING {"Event ID": 183, "Event Category": "Authentication and authorisation", "Event Type": "License warning", "ExecutionId": 408249519546, "Event Source": "NETAPP-01", "Description": "The license issued to NetApp User of Network Appliance, Inc will expire in less than one week"}
581	Catalog path <catalog volume path> to store catalog directory is not accessible. Refer user guide for configuring catalog volume.	2020-07-14 04:05:00,857 - ERROR {"Event ID": 581, "Event Category": "Catalog and indexing", "Event Type": "Catalog exporting error", "ExecutionId": 408249552351, "Event Source": "NETAPP-01", "Description": "Catalog path <IP address of NFS server>:/test11 to store catalog directory is not accessible. Refer user guide for configuring catalog volume."}
582	Failed creating catalog directory in catalog volume path <catalog volume path>	2020-07-14 04:10:12,895 - ERROR {"Event ID": 582, "Event Category": "Catalog and indexing", "Event Type": "Catalog directory creation error", "ExecutionId": 408249630498, "Event Source": "NETAPP-01", "Description": "Failed creating catalog directory in catalogvolume path 10.234.104.250:/cat_vol"}

ID d'événement	Modèle d'événement	Exemple d'événement
584	Error in creating index directory <index id> for <command>	2020-07-14 04:52:15,918 - ERROR {"Event ID":584, "Event Category": "Catalog and indexing", "Event Type": "Error in index creation", "ExecutionId": 408250278214, "Event Source": "NETAPP-01", "Description": "Error in creating index directory abc7 for scan"}
586	Failed to create index <index id> in catalog volume while executing command : <command>	2020-07-14 04:45:46,275 - ERROR {"Event ID": 586, "Event Category": "Catalog and indexing", "Event Type": "Error in index creation", "ExecutionId": 408250177021, "Event Source": "NETAPP-01", "Description": "Failed to create index abc6 in catalog volume while executing command : scan {- newid: 'abc6'}"}
351	System resources available while executing xcp command: <command>, are : <CPU info>, <memory info>	2020-07-14 05:08:35,393 - INFO {"Event ID":351, "Event Category": "System resource utilization", "Event Type": "Resources available for scan", "ExecutionId": 408250529264, "Event Source": "NETAPP-01", "Description": "System resources available while executing xcp command : scan , are : CPU: count 4, load avg (1/5/15m) 0.0, 0.0, 0.0, System memory (GiB): avail 7.3, total 7.8, free 6.6, buffer 0.1, cache 0.5"}

ID d'événement	Modèle d'événement	Exemple d'événement
13	XCP <command> is running on platform <platform info> for source <source info>	2020-07-14 05:08:35,478 - INFO {"Event ID": 13, "Event Category": "XCP job status", "Event Type": "Starting xcp scan operation", "ExecutionId": 408250529264, "Event Source": "NETAPP-01", "Description": "XCP command : scan {-newid: 'abc7'} is running on platform Linux-2.6.26-2-amd64-x86_64-with-debian- 5.0.10 for source 10.234.104.250:/test1"}
14	XCP scan completed successfully after scanning <scan item count> items. Source : <source scanned>	2020-07-14 05:08:35,653 - INFO {"Event ID": 14, "Event Category": "XCP job status", "Event Type": "XCP scan completion", "ExecutionId": 408250529264, "Event Source": "NETAPP-01", "Description": "XCP scan completed successfully after scanning 479 items. Source : 10.234.104.250:/test1"}
354	System resources available while executing xcp command: <command>, are : <CPU info>, <memory info>	2020-07-14 05:15:13,562 - INFO {"Event ID": 354, "Event Category": "System resource utilization", "Event Type": "Resources available for copy", "ExecutionId": 408250596708, "Event Source": "NETAPP-01", "Description": "System resources available while executing xcp command : copy , are : CPU: count 4, load avg (1/5/15m) 0.0, 0.0, 0.0, System memory (GiB): avail 7.3, total 7.8, free 6.6, buffer 0.1, cache 0.5"}

ID d'événement	Modèle d'événement	Exemple d'événement
25	XCP <command> is running on platform <platform info> for source <copy source> and destination <copy destination/target>	2020-07-14 05:15:13,647 - INFO {"Event ID": 25, "Event Category": "XCP job status", "Event Type": "Starting xcp copy operation", "ExecutionId": 408250596708, "Event Source": "NETAPP-01", "Description": "XCP command : copy {} is running on platform Linux-2.6.26- 2-amd64-x86 64-with-debian-5.0.10 for source <IP address of NFS server>:/source_vol and destination <NFS destination source>:/test1"}
26	XCP copy completed successfully after scanning <scanned item count> of which <matched item count> are matched and <copied item count> items are copied to the destination. Source : <copy source>, destination :<copy destination/target	2020-07-14 05:15:13,885 - INFO {"Event ID":26, "Event Category": "XCP job status", "Event Type": "XCP copy completion", "ExecutionId": 408250596708, "Event Source": "NETAPP-01", "Description": "XCP copy completed successfully after scanning 3 of which 0 are matched and 2 items are copied to the destination. Source : <IP address of NFS server>:/source_vol, destination : <NFS destination source>:/test1"}

ID d'événement	Modèle d'événement	Exemple d'événement
16	XCP <command> is running on platform <platform info> for source <sync source> and destination <sync destination>	2020-07-14 06:41:20,145 - INFO {"Event ID": 16, "Event Category": "XCP job status", "Event Type": "Starting xcp sync operation", "ExecutionId": 408251920146, "Event Source": "NETAPP-01", "Description": "XCP command : sync {-id: 'autoname_copy_2020-07-14_06.22.07.233271'} is running on platform Linux-2.6.26-2-amd64-x86_64-with-debian-5.0.10 for source <IP address of NFS server>:/src_vol and destination <NFS destination source>:/dest_vol"}
352	System resources available while executing xcp command: <command>, are : <CPU info>, <memory info>	2020-07-14 06:41:28,728 - INFO {"Event ID": 352, "Event Category": "System resource utilization", "Event Type": "Resource available for sync", "ExecutionId": 408251920146, "Event Source": "NETAPP-01", "Description": "System resources available while executing xcp command : sync {-id: 'autoname_copy_2020-07-14_06.22.07.233271'} , are : CPU: count 4, load avg (1/5/15m) 0.1, 0.0, 0.0, System memory (GiB): avail 7.2, total 7.8, free 6.6, buffer 0.1, cache 0.5"}



ID d'événement	Modèle d'événement	Exemple d'événement
17	XCP sync is completed. Total scanned <scanned item count>, copied <copied item count>, modification <modification item count>, new file <new file count>, delete item <delete item count>. Command executed : <command>	2020-07-14 06:41:29,245 - INFO {"Event ID":17, "Event Category": "XCP job status", "Event Type": "XCP sync completion", "ExecutionId": 408251920146, "Event Source": "NETAPP-01", "Description": "XCP sync is completed. Total scanned 66, copied 0, modification 1, new file 0, delete item 0. Command executed : sync {-id: 'autoname_copy_2020-07-14_06.22.07.233271'}"}
19	XCP <command> is running on platform <platform info> for source <verify source> and destination <verify destination>	2020-07-14 06:54:59,084 - INFO {"Event ID": 19, "Event Category": "XCP job status", "Event Type": "Starting xcp verify operation", "ExecutionId": 408252130477, "Event Source": "NETAPP-01", "Description": "XCP command : verify {} is running on platform Linux-2.6.26-2-amd64-x86_64-with- debian-5.0.10 for source <IP address of NFS server>:/src_vol and destination <IP address of NFS destination server>:/dest_vol"}
353	System resources available while executing xcp command: <command>, are : <CPU info>, <memory info>	2020-07-14 06:54:59,085 - INFO {"Event ID": 353, "Event Category": "System resource utilization", "Event Type": "Resources available for verify", "ExecutionId": 408252130477, "Event Source": "NETAPP-01", "Description": "System resources available while executing xcp command : verify , are : CPU: count 4, load avg (1/5/15m) 0.0, 0.0, 0.0, System memory (GiB): avail 7.3, total 7.8, free 6.6, buffer 0.1, cache 0.5"}

ID d'événement	Modèle d'événement	Exemple d'événement
211	log file path : <file path> , severity filter level <severity level>, log message sanitization is set as <sanitization value>	2020-07-14 06:40:59,104 - INFO {"Event ID": 211, "Event Category": "Logging and supportability", "Event Type": "XCP logging information", "ExecutionId": 408251920146, "Event Source": "NETAPP-01", "Description": "Log file path : /opt/NetApp/xFiles/xcp/xcplogs/xcp.log, severity filter level INFO, log message sanitization is set as False"}
215	Event file path: <file path>, severity filter level <severity level>, event message sanitization is set as <sanitization value>	2020-07-14 06:40:59,105 - INFO {"Event ID": 215, "Event Category": "Logging and supportability", "Event Type": "XCP event information", "ExecutionId": 408251920146, "Event Source": "NETAPP-01", "Description": "Event file path : /opt/NetApp/xFiles/xcp/xcplogs/xcp_event.log, severity filter level INFO, event message sanitization is set as False"}
54	Catalog volume is left with no free space please increase the size of catalog volume <catalog volume running out of space>	2020-07-14 04:10:12,897 - ERROR {"Event ID":54, "Event Category": "Application failure", "Event Type": "No space left on Catalog volume error", "ExecutionId": 408249630498, "Event Source": "NETAPP-01", "Description": "Catalog volume is left with no free space. Please increase the size of catalog volume<IP address of NFS destination server>:/cat_vol"}

ID d'événement	Modèle d'événement	Exemple d'événement
53	Catalog volume <catalog volume> is left with no free space to store index <index id> while executing <command>. Please increase the size of the catalog volume <catalog volume running out of space>	2020-07-14 04:52:15,922 - ERROR {"Event ID": 53, "Event Category": "Application failure", "Event Type": "No space left for catalog volume error", "ExecutionId": 408250278214, "Event Source": "NETAPP-01", "Description": "Catalog volume 10.234.104.250:/cat_vol is left with no free space to store index abc7 while executing : scan {-newid: 'abc7'}. Please increase the size of the catalog volume <IP address of NFS destination server>:/cat_vol"}
61	NFS LIF <LIF IP> is not reachable for path <volume path without IP> while executing <command>. Please check volume is not offline and is reachable.	2020-07-14 07:38:20,100 - ERROR {"Event ID":61, "Event Category": "Application failure", "Event Type": "NFS mount has failed", "ExecutionId": 408252799101, "Event Source": "NETAPP-01", "Description": "NFS LIF <IP address of NFS destination server> is not reachable for path /test11 while executing : scan {}. Please check volume is not offline and is reachable"}
71	TCP connection could not be established for IP address <IP>. Check network setting and configuration.	2020-07-14 07:44:44,578 - ERROR {"Event ID": 71, "Event Category": "Application failure", "Event Type": "IP is not active", "ExecutionId": 408252889541, "Event Source": "NETAPP-01", "Description": "TCP connection could not be established to the address <IP address of NFS destination server>. Check network setting and configuration."} (UT done)

ID d'événement	Modèle d'événement	Exemple d'événement
51	Target volume is left with no free space while executing: <command>. Please increase the size of target volume <volume running out of space>.	2020-07-14 07:07:07,286 - ERROR {"Event ID": 51, "Event Category": "Application failure", "Event Type": "No space left on destination error", "ExecutionId": 408252316712, "Event Source": "NETAPP-01", "Description": "Target volume is left with no free space while executing : copy {}. Please increase the size of target volume <IP address of NFS destination server>:/cat_vol"}
76	Index id {} is already present . Use new index id and rerun command : <command>	2020-07-14 09:18:41,441 - ERROR {"Event ID": 76, "Event Category": "Application failure", "Event Type": "Index ID problem", "ExecutionId": null, "Event Source": "NETAPP-01", "Description": "Index id asd is already present . Use new index id and rerun command: scan {-newid: 'asd'} "}
362	CPU usage has crossed <percentage CPU used>%	2020-06-16 00:17:28,294 - ERROR {"Event ID": 362, "Event Category": "System resource utilization", "Event Type": "resources available for xcp", "Event Source": "NETAPP- 01 ", "Description": "CPU Usage has crossed 90.07%"}
363	Memory Usage has crossed <percentage memory used>%	2020-06-16 00:17:28,300 - ERROR {"Event ID": 363, "Event Category": "System resource utilization", "Event Type": "resources available for xcp", "Event Source": "NETAPP- 01", "Description": "Memory Usage has crossed 95%"}

ID d'événement	Modèle d'événement	Exemple d'événement
22	XCP <command> is running on platform <platform information> for source <resume source> and destination <resume destination>	<pre>2020-07-14 06:24:26,768 - INFO {"Event ID": 22, "Event Category": "XCP job status", "Event Type": "Starting xcp resume operation", "ExecutionId": 408251663404, "Event Source": "NETAPP-01", "Description": "XCP command : resume {-id: 'autoname_copy_2020-07- 14_06.22.07.233271'} is running on platform Linux-2.6.26-2- amd64- x86_64-with-debian- 5.0.10 for source &lt;IP address for NFS sever&gt;:/src_vol and destination &lt;IP address of NFS destination server&gt;:/dest_vol"} </pre>
356	System resources available while executing xcp command: <command> , are : <CPU info>, <memory information>	<pre>2020-07-14 06:24:26,837 - INFO {"Event ID": 356, "Event Category": "System resource utilization", "Event Type": "Resource available for resume", "ExecutionId": 408251663404, "Event Source": "NETAPP-01", "Description": "System resources available while executing xcp command : resume {-id: 'autoname_copy_2020-07- 14_06.22.07.233271'} , are : CPU: count 4, load avg (1/5/15m) 0.1, 0.1, 0.0, System memory (GiB): avail 7.2,total 7.8, free 6.6, buffer 0.1, cache 0.5"} </pre>

ID d'événement	Modèle d'événement	Exemple d'événement
23	XCP resume is completed. Total scanned items <scanned item count>, total copied items <copied item count>. Command executed :<command>	2020-07-14 06:26:15,608 - INFO {"Event ID": 23, "Event Category": "XCP job status", "Event Type": "XCP resume completion", "ExecutionId": 408251663404, "Event Source": "NETAPP-01", "Description": "XCP resume is completed. Total scanned items 5982, total copied items 5973. Command executed : resume {-id: 'autoname_copy_2020-07-14_06.22.07.233271'} "}
76	Index id <index id> is already present. Use new index id and rerun command : <command>	2020-07-14 09:43:08,381 - ERROR {"Event ID": 76, "Event Category": "Application failure", "Event Type": "Index ID problem", "ExecutionId": null, "Event Source": "NETAPP-01", "Description": "Index id asd is already present . Use new index id and rerun command : scan {-newid: 'asd'} "}
82	Index id <index id> used while executing sync is incomplete. Try resume on the existing index id <index id>	2020-07-14 10:33:09,307 - ERROR {"Event ID": 82, "Event Category": "Application failure", "Event Type": "Incomplete index used for sync", "ExecutionId": null, "Event Source": "NETAPP-01", "Description": "Index id autoname_copy_2020-07-14_10.28.22.323897 used while executing sync is incomplete. Try resume on the existing index id autoname_copy_2020-07-14_10.28.22.323897."}

ID d'événement	Modèle d'événement	Exemple d'événement
365	CPU utilization reduced to <CPU percentage used>%	2020-07-14 09:43:08 381 - ERROR {"Event ID": 364, "Event Category": "System resource utilization", "Event Type": "Resources available for xcp", "ExecutionId": 408251663404, "Event Source": "NETAPP-01", "Description": " CPU utilization reduced to 26%}
364	Memory utilization reduced to <CPU percentage used>%	2020-07-14 09:43:08,381 - INFO {"Event ID": 364, "Event Category": " Resources available for xcp", "Event Type": "Resources available for xcp", "ExecutionId": 408351663478, "Event Source": "NETAPP-01", "Description": " Memory utilization reduced to 16.2%"}
10	XCP command <command> has failed	2020-07-14 09:43:08,381 - INFO {"Event ID": 10, "Event Category": " Xcp job status", "Event Type": "XCP command failure", "ExecutionId":4082516634506, "Event Source": "NETAPP-01", "Description": " XCP command verify has failed"

## Journaux d'événements SMB XCP

Examinez des exemples de journaux d'événements pour XCP SMB.

Le tableau suivant présente les journaux d'événements pour XCP SMB.

ID d'événement	Modèle d'événement	Exemple d'événement
355	CPU usage has crossed <CPU percentage use>%	2020-06-23 12:42:02,705 - INFO {"Event ID": 355, "Event Category": "System resource utilization", "Event Type": "CPU usage for xcp", "Event Source": "NETAPP-01", "Description": "CPU usage has crossed 96%"}

ID d'événement	Modèle d'événement	Exemple d'événement
356	Memory usage has crossed <memory percentage use>%	2020-06-23 12:42:02,705 - INFO { "Event ID": 356, "Event Category": "System resource utilization", "Event Type": "Memory usage for xcp", "Event Source": "NETAPP-01", "Description": "CPU usage has crossed92.5%" }
61	Address was not found: <complete address over which command is fired>	2020-07-15 02:57:06,466 - ERROR { "Event ID": 61, "Event Category": "Application Failure", "Event Type": "Address was not found", "ExecutionId": 408264113696, "Event Source": "NETAPP-01", "Description": "Address was not found: \\\"\\\\\\<IP address of SMB server>\\\\cifs1\""} }
62	Interface cannot be found: < complete address over which command is fired >	2020-07-15 02:52:00,603 - ERROR { "Event ID": 62, "Event Category": "Application Failure", "Event Type": "Interface was not found", "ExecutionId": 408264071616, "Event Source": "NETAPP-01", "Description": "Interface cannot be found: \\\"\\\\\\<IP address of SMB server>\\\\cifs11\""} }
63	Invalid Address. Please make sure that the Address starts with '\\'	2020-07-15 03:00:10,422 - ERROR { "Event ID": 63, "Event Category": "Application Failure", "Event Type": "Invalid Address", "ExecutionId": 408264197308, "Event Source": "NETAPP-01", "Description": "Invalid Address. Please make sure that the Address starts with '\\'" }



ID d'événement	Modèle d'événement	Exemple d'événement
41	Destination volume is left with no free space please increase the size target volume:<destination volume>	2020-06-15 17:12:46,413 - ERROR { "Event ID": 41, "Event Category": "Application Failure", "Event Type": "No space left on destination error", "Event Source": "NETAPP-01", "Description": "Destination volume is left with no free space please increase the size of target volume: <IP address of SMB server>\\to" }
211	Log file path : <file path>, severity filter level <severity level>, log message sanitization is set as <value of sanitization option>	{ "Event ID": 211, "Event Category": "Logging and supportability", "Event Type": "XCP logging information", "ExecutionId": 408252673852, "Event Source": "NETAPP-01", "Description": "Log file path : C:\\NetApp\\XCP\\Logs\\xcp.log, severity filter level DEBUG, log message sanitization is set as False" }
215	Event file path : <file path>, severity filter level <severity level>, Event message sanitization is set as <sanitization option>	{ "Event ID": 215, "Event Category": "Logging and supportability", "Event Type": "XCP event information", "ExecutionId": 408252673852, "Event Source": "NETAPP-01", "Description": "Event file path : C:\\NetApp\\XCP\\Logs\\xcp_event.log, severity filter level INFO, Event message sanitization is set as False" }

ID d'événement	Modèle d'événement	Exemple d'événement
181	This license is issued to <user name> of <company name>, license type is <license type> with <status> status, license will expire expires on <expiration date>	{"Event ID": 181, "Event Category": "Authentication and authorization", "Event Type": "license information", "ExecutionId": 408252673852, "Event Source": "NETAPP-01", "Description": "This license is issued to calin of NetApp Inc, license type is SANDBOX with ACTIVE status, license will expire on Mon Dec 31 00:00:00 2029"}
13	XCP <command> is running on platform <platform information> for source <scan source>	2020-07-15 02:12:56,917 - INFO {"Event ID": 13, "Event Category": "XCP job status", "Event Type": "Starting xcp scan operation", "ExecutionId": 408263470688, "Event Source": "NETAPP-01", "Description": "XCP {scan} is running on platform Windows- 8.1-6.3.9600-SP0 for source \\\\<IP address of SMB server>\\cifs"}
351	System resources available while command : <command>, are : cpu <CPU information>, total memory <total memory on system>, available memory	2020-07-15 02:12:56,917 - INFO {"Event ID": 351, "Event Category": "System resource utilization", "Event Type": "Resources available for scan", "ExecutionId": 408263470688, "Event Source": "NETAPP-01", "Description": "System resources available while executing xcp command : scan, are : cpu 4, total memory 8.00GiB, available memory 6.81GiB"}

ID d'événement	Modèle d'événement	Exemple d'événement
14	XCP scan completed successfully after scanning <scanned items count> items. Source :<scan source>	2020-07-15 02:12:57,932 - INFO {"Event ID": 14, "Event Category": "XCP job status", "Event Type": "XCP scan completion", "ExecutionId": 408263470688, "Event Source": "NETAPP-01", "Description": "XCP scan completed successfully after scanning 29 items. Source : \\<IP address of SMB server>\\cifs"}
25	XCP <command> is running on platform <platform information> for source <copy source> and destination <copy destination>	2020-07-15 02:19:06,562 - INFO {"Event ID": 25, "Event Category": "XCP job status", "Event Type": "Starting xcp copy operation", "ExecutionId": 408263563552, "Event Source": "NETAPP-01", "Description": "XCP {copy} is running on platform Windows- 8.1-6.3.9600-SP0 for source \\<IP address of SMB server>\\cifs and destination \\<IP address of SMB destination server>\\source_vol"}
352	System resources available while executing command :<command>, are : cpu <CPU information>, total memory <Total memory>, available memory <memory available for execution>	2020-07-15 02:19:06,562 - INFO {"Event ID": 352, "Event Category": "System resource utilization", "Event Type": "Resources available for copy", "ExecutionId": 408263563552, "Event Source": "NETAPP-01", "Description": "System resources available while executing xcp command : copy, are : cpu 4, total memory 8.00GiB, available memory 6.82GiB"}

ID d'événement	Modèle d'événement	Exemple d'événement
26	XCP copy completed successfully after copying <copied items count> items. Source :<copy source>, destination : <copy destination>	2020-07-15 02:19:14,500 - INFO {"Event ID": 26, "Event Category": "XCP job status", "Event Type": "XCP copy completion", "ExecutionId": 408263563552, "Event Source": "NETAPP-01", "Description": "XCP copy completed successfully after copying 0 items. Source :
16	XCP <command> is running on platform <platform> for source <sync source> and destination <sync destination>	2020-07-15 02:27:10,490 - INFO {"Event ID": 16, "Event Category": "XCP job status", "Event Type": "Starting xcp sync operation", "ExecutionId": 408263688308, "Event Source": "NETAPP-01", "Description": "XCP {sync} is running on platform Windows- 8.1-6.3.9600-SP0 for source \\<IP address of SMB server>\\cifs and destination \\<IP address of SMB destination server>\\source_vol"}
353	System resources available while executing xcp command: <command>, are : cpu <CPU information>, total memory <total memory>, available memory <available memory>	2020-07-15 02:27:10,490 - INFO {"Event ID": 353, "Event Category": "System resource utilization", "Event Type": "Resources available for sync", "ExecutionId": 408263688308, "Event Source": "NETAPP-01", "Description": "System resources available while executing xcp command : sync, are : cpu 4, total memory 8.00GiB, available memory 6.83GiB"}

ID d'événement	Modèle d'événement	Exemple d'événement
17	XCP sync completed successfully after scanning <scanned item count> items, copying <copied item count> items, comparing <compared item count> items, removing <removed item count> items. Source : <sync source>, destination : <sync destination>	2020-07-15 03:04:14,269 - INFO {"Event ID": 17, "Event Category": "XCP job status", "Event Type": "XCP sync completion", "ExecutionId": 408264256392, "Event Source": "NETAPP-01", "Description": "XCP sync completed successfully after scanning30 items, copying 20 items, comparing 30 items, removing 0 items. Source : \\<IP address of SMB server>\\cifs, destination : \\<IP address of SMB destination server>\\source_vol"}
19	XCP <command> is running on platform <platform information> for source <verify source> and destination <verify destination>	2020-07-15 03:14:04,854 - INFO {"Event ID": 19, "Event Category": "XCP job status", "Event Type": "Starting xcp verify operation", "ExecutionId": 408264409944, "Event Source": "NETAPP-01", "Description": "XCP {verify -noacl} is running on platform Windows-8.1-6.3.9600-SP0 for source \\<IP address of SMB server>\\cifs and destination \\<IP address of SMB destination server>\\source_vol"}
354	System resources available for command : <command>, are : cpu <CPU information>, total memory <total memory>, available memory <available memory for execution>	2020-07-15 03:14:04,854 - INFO {"Event ID": 354, "Event Category": "System resource utilization", "Event Type": "Resources available for verify", "ExecutionId": 408264409944, "Event Source": "NETAPP-01", "Description": "System resources available while executing xcp command : verify, are : cpu 4, total memory 8.00GiB, available memory 6.80GiB"}

ID d'événement	Modèle d'événement	Exemple d'événement
20	XCP verify is completed by scanning <scanned item count> items, comparing <compared item count> items	{"Event ID": 20, "Event Category": "XCP job status", "Event Type": "XCP verify completion", "command Id": 408227440800, "Event Source": "NETAPP-01", "Description": "XCP verify is completed by scanning 59 items, comparing 0 items"}
357	CPU utilization reduced to <CPU utilization percentage>%	{"Event ID": 357, "Event Category": "System resource utilization", "Event Type": "CPU usage for xcp", "Event Source": "NETAPP- 01", "Description": "CPU utilization reduced to 8.2%"}
358	Memory utilization reduced to <memory utilization percentage>%	{"Event ID": 358, "Event Category": "System resource utilization", "Event Type": "Memory usage for xcp", "Event Source": "NETAPP-01", "Description": "Memory utilization reduced to 19%"}
10	XCP command <command> has failed	2020-07-14 09:43:08,381 - INFO {"Event ID": 10, "Event Category": " Xcp job status", "Event Type": "XCP command failure", "Event Source": "NETAPP-01", "Description": " XCP command H:\console_msg\xcp_cifs\xcp\ main .py verify \\\<IP address of SMB server>\cifs \\\<IP address of SMB destination server>\source_vol has failed"

## Informations sur le copyright

Copyright © 2024 NetApp, Inc. Tous droits réservés. Imprimé aux États-Unis. Aucune partie de ce document protégé par copyright ne peut être reproduite sous quelque forme que ce soit ou selon quelque méthode que ce soit (graphique, électronique ou mécanique, notamment par photocopie, enregistrement ou stockage dans un système de récupération électronique) sans l'autorisation écrite préalable du détenteur du droit de copyright.

Les logiciels dérivés des éléments NetApp protégés par copyright sont soumis à la licence et à l'avis de non-responsabilité suivants :

CE LOGICIEL EST FOURNI PAR NETAPP « EN L'ÉTAT » ET SANS GARANTIES EXPRESSES OU TACITES, Y COMPRIS LES GARANTIES TACITES DE QUALITÉ MARCHANDE ET D'ADÉQUATION À UN USAGE PARTICULIER, QUI SONT EXCLUES PAR LES PRÉSENTES. EN AUCUN CAS NETAPP NE SERA TENU POUR RESPONSABLE DE DOMMAGES DIRECTS, INDIRECTS, ACCESSOIRES, PARTICULIERS OU EXEMPLAIRES (Y COMPRIS L'ACHAT DE BIENS ET DE SERVICES DE SUBSTITUTION, LA PERTE DE JOUISSANCE, DE DONNÉES OU DE PROFITS, OU L'INTERRUPTION D'ACTIVITÉ), QUELLES QU'EN SOIENT LA CAUSE ET LA DOCTRINE DE RESPONSABILITÉ, QU'IL S'AGISSE DE RESPONSABILITÉ CONTRACTUELLE, STRICTE OU DÉLICTELLE (Y COMPRIS LA NÉGLIGENCE OU AUTRE) DÉCOULANT DE L'UTILISATION DE CE LOGICIEL, MÊME SI LA SOCIÉTÉ A ÉTÉ INFORMÉE DE LA POSSIBILITÉ DE TELS DOMMAGES.

NetApp se réserve le droit de modifier les produits décrits dans le présent document à tout moment et sans préavis. NetApp décline toute responsabilité découlant de l'utilisation des produits décrits dans le présent document, sauf accord explicite écrit de NetApp. L'utilisation ou l'achat de ce produit ne concède pas de licence dans le cadre de droits de brevet, de droits de marque commerciale ou de tout autre droit de propriété intellectuelle de NetApp.

Le produit décrit dans ce manuel peut être protégé par un ou plusieurs brevets américains, étrangers ou par une demande en attente.

LÉGENDE DE RESTRICTION DES DROITS : L'utilisation, la duplication ou la divulgation par le gouvernement sont sujettes aux restrictions énoncées dans le sous-paragraphe (b)(3) de la clause Rights in Technical Data-Noncommercial Items du DFARS 252.227-7013 (février 2014) et du FAR 52.227-19 (décembre 2007).

Les données contenues dans les présentes se rapportent à un produit et/ou service commercial (tel que défini par la clause FAR 2.101). Il s'agit de données propriétaires de NetApp, Inc. Toutes les données techniques et tous les logiciels fournis par NetApp en vertu du présent Accord sont à caractère commercial et ont été exclusivement développés à l'aide de fonds privés. Le gouvernement des États-Unis dispose d'une licence limitée irrévocable, non exclusive, non cessible, non transférable et mondiale. Cette licence lui permet d'utiliser uniquement les données relatives au contrat du gouvernement des États-Unis d'après lequel les données lui ont été fournies ou celles qui sont nécessaires à son exécution. Sauf dispositions contraires énoncées dans les présentes, l'utilisation, la divulgation, la reproduction, la modification, l'exécution, l'affichage des données sont interdits sans avoir obtenu le consentement écrit préalable de NetApp, Inc. Les droits de licences du Département de la Défense du gouvernement des États-Unis se limitent aux droits identifiés par la clause 252.227-7015(b) du DFARS (février 2014).

## Informations sur les marques commerciales

NETAPP, le logo NETAPP et les marques citées sur le site <http://www.netapp.com/TM> sont des marques déposées ou des marques commerciales de NetApp, Inc. Les autres noms de marques et de produits sont des marques commerciales de leurs propriétaires respectifs.