



Managing scripts

OnCommand Unified Manager 9.5

NetApp

February 12, 2024

This PDF was generated from <https://docs.netapp.com/us-en/oncommand-unified-manager-95/online-help/concept-how-scripts-work-with-alerts.html> on February 12, 2024. Always check docs.netapp.com for the latest.

Table of Contents

- Managing scripts 1
 - How scripts work with alerts 1
 - Adding scripts 2
 - Deleting scripts 2
 - Testing script execution 3
 - Description of script windows and dialog boxes 3

Managing scripts

You can use scripts to automatically modify or update multiple storage objects in Unified Manager. The script is associated with an alert. When an event triggers an alert, the script is executed. You can upload custom scripts and test their execution when an alert is generated.

How scripts work with alerts

You can associate an alert with your script so that the script is executed when an alert is raised for an event in Unified Manager. You can use the scripts to resolve issues with storage objects or identify which storage objects are generating the events.

When an alert is generated for an event in Unified Manager, an alert email is sent to the specified recipients. If you have associated an alert with a script, the script is executed. You can get the details of the arguments passed to the script from the alert email.

The script uses the following arguments for execution:

- -eventID
- -eventName
- -eventSeverity
- -eventSourceID
- -eventSourceName
- -eventSourceType
- -eventState
- -eventArgs

You can use the arguments in your scripts and gather related event information or modify storage objects.

Example for obtaining arguments from scripts

```
print "$ARGV[0] : $ARGV[1]\n"
print "$ARGV[7] : $ARGV[8]\n"
```

When an alert is generated, this script is executed and the following output is displayed:

```
-eventID : 290
-eventSourceID : 4138
```

Adding scripts

You can add scripts in Unified Manager, and associate the scripts with alerts. These scripts are executed automatically when an alert is generated, and enable you to obtain information about storage objects for which the event is generated.

Before you begin

- You must have created and saved the scripts that you want to add to the Unified Manager server.
- The supported file formats for scripts are Perl, Shell, PowerShell, and .bat files.
 - For Perl scripts, Perl must be installed on the Unified Manager server. If Perl was installed after Unified Manager, you must restart the Unified Manager server.
 - For PowerShell scripts, the appropriate PowerShell execution policy must be set on the server so that the scripts can be executed.




If your script creates log files to track the alert script progress, you must make sure that the log files are not created anywhere within the Unified Manager installation folder.

- You must have the OnCommand Administrator or Storage Administrator role.

About this task

You can upload custom scripts and gather event details about the alert.

Steps

1. In the toolbar, click , and then click **Scripts** in the left Management menu.
2. In the **Management/Scripts** page, click **Add**.
3. In the **Add Script** dialog box, click **Browse** to select your script file.
4. Enter a description for the script that you select.
5. Click **Add**.


Deleting scripts

You can delete a script from Unified Manager when the script is no longer required or valid.

Before you begin

- You must have the OnCommand Administrator or Storage Administrator role.
- The script must not be associated with an alert.

Steps

1. In the toolbar, click , and then click **Scripts** in the left Management menu.
2. In the **Management/Scripts** page, select the script that you want to delete, and then click **Delete**.

3. In the **Warning** dialog box, confirm the deletion by clicking **Yes**.


Testing script execution

You can verify that your script is executed correctly when an alert is generated for a storage object.

Before you begin

- You must have the OnCommand Administrator or Storage Administrator role.
- You must have uploaded a script in the supported file format to Unified Manager.

Steps

1. In the toolbar, click , and then click **Scripts** in the left Management menu.
2. In the **Management/Scripts** page page, add your test script.
3. In the **Configuration/Alerting** page, perform one of the following actions:

To...	Do this...
Add an alert	<ol style="list-style-type: none">a. In the Configuration/Alerting page, click Add.b. In the Actions section, associate the alert with your test script.
Edit an alert	<ol style="list-style-type: none">a. In the Configuration/Alerting page, select an alert, and then click Edit.b. In the Actions section, associate the alert with your test script.

4. Click **Save**.
5. In the **Configuration/Alerting** page, select the alert that you added or modified, and then click **Test**.

The script is executed with the “-test” argument, and a notification alert is sent to the email addresses that were specified when the alert was created.

Description of script windows and dialog boxes

The Management/Scripts page enables you to add scripts to Unified Manager.

Management/Scripts page

The Management/Scripts page enables you to add your custom scripts to Unified Manager. You can associate these scripts with alerts to enable automatic reconfiguration of storage objects.

The Management/Scripts page enables you to add or delete scripts from Unified Manager.

Command buttons

- **Add**

Displays the Add Script dialog box, which enables you to add scripts.

- **Delete**

Deletes the selected script.

List view

The list view displays, in tabular format, the scripts that you added to Unified Manager.

- **Name**

Displays the name of the script.

- **Description**

Displays the description of the script.

Add Script dialog box

The Add Script dialog box enables you to add scripts to Unified Manager. You can configure alerts with your scripts to automatically resolve events that are generated for storage objects.

You must have the OnCommand Administrator or Storage Administrator role.

- **Select Script File**

Enables you to select a script for the alert.

- **Description**

Enables you to specify a description for the script.

Supported Unified Manager CLI commands

As a storage administrator you can use the CLI commands to perform queries on the storage objects; for example, on clusters, aggregates, volumes, qtrees, and LUNs. You can use the CLI commands to query the Unified Manager internal database and the ONTAP database. You can also use CLI commands in scripts that are executed at the beginning or end of an operation or are executed when an alert is triggered.

All commands must be preceded with the command `um cli login` and a valid user name and password for authentication.

CLI command	Description	Output
<code>um run cmd [-t <timeout>] <cluster> <command></code>	The simplest way to run a command on one or more hosts. Mainly used for alert scripting to get or perform an operation on ONTAP. The optional timeout argument sets a maximum time limit (in seconds) for the command to complete on the client. The default is 0 (wait forever).	As received from ONTAP.
<code>um run query <sql command></code>	Executes an SQL query. Only queries that read from the database are allowed. Any update, insert, or delete operations are not supported.	Results are displayed in a tabular form. If an empty set is returned, or if there is any syntax error or bad request, it displays the appropriate error message.
<code>um datasource add -u <username> -P <password> [-t <protocol>] [-p <port>] <hostname-or-ip></code>	Adds a datasource to the list of managed storage systems. A datasource describes how connections to storage systems are made. The options -u (username) and -P (password) must be specified when adding a datasource. The option -t (protocol) specifies the protocol used to communicate with the cluster (http or https). If the protocol is not specified, then both protocols will be attempted. The option -p (port) specifies the port used to communicate with the cluster. If the port is not specified, then the default value of the appropriate protocol will be attempted. This command can be executed only by the storage admin.	Prompts for the user accept the certificate and prints the corresponding message.
<code>um datasource list [<datasource-id>]</code>	Displays the datasources for managed storage systems.	Displays the following values in tabular format: ID Address Port, Protocol Acquisition Status, Analysis Status, Communication status, Acquisition Message, and Analysis Message.

CLI command	Description	Output
<code>um datasource modify [-h <hostname-or-ip>] [-u <username>] [-P <password>] [-t <protocol>] [-p <port>] <datasource-id></code>	Modifies one or more datasource options. Can be executed only by the storage admin.	Displays the corresponding message.
<code>um datasource remove <datasource-id></code>	Removes the datasource from Unified Manager.	Displays the corresponding message.
<code>um option list [<option> ..]</code>	Lists options.	Displays the following values in tabular format: Name, Value, Default Value, and Requires Restart.
<code>um option set <option-name>=<option-value> [<option-name>=<option-value> ...]</code>	Sets one or more options. The command can be executed only by the storage admin.	Displays the corresponding message.
<code>um version</code>	Displays the Unified Manager software version .	Version ("7.0")
<code>um lun list [-q] [-ObjectType <object-id>]</code>	<p>Lists the LUNs after filtering on the specified object. -q is applicable for all commands to show no header. ObjectType can be lun, qtree, cluster, volume, quota, svm. For example: <code>um lun list -cluster 1</code></p> <p>In this example, "-cluster" is the objectType and "1" is the objectId. The command lists all the LUNs within the cluster with ID 1.</p>	Displays the following values in tabular format: ID and LUN path.
<code>um svm list [-q] [-ObjectType <object-id>]</code>	<p>Lists the SVMs after filtering on the specified object. ObjectType can be lun, qtree, cluster, volume, quota, svm. For example: <code>um svm list -cluster 1</code></p> <p>In this example, "-cluster" is the objectType and "1" is the objectId. The command lists all the SVMs within the cluster with ID 1.</p>	Displays the following values in tabular format: Name and Cluster ID.

CLI command	Description	Output
<code>um qtree list [-q] [-ObjectType <object-id>]</code>	<p>Lists the qtrees after filtering on the specified object. -q is applicable for all commands to show no header. ObjectType can be lun, qtree, cluster, volume, quota, svm. For example: <code>um qtree list -cluster 1</code></p> <p>In this example, "-cluster" is the objectType and "1" is the objectId. The command lists all the qtrees within the cluster with ID 1.</p>	Displays the following values in tabular format: Qtree ID and Qtree Name.
<code>um disk list [-q] [-ObjectType <object-id>]</code>	<p>Lists the disks after filtering on the specified object. ObjectType can be disk, aggr, node, cluster. For example: <code>um disk list -cluster 1</code></p> <p>In this example, "-cluster" is the objectType and "1" is the objectId. The command lists all the disks within the cluster with ID 1.</p>	Displays the following values in tabular format ObjectType and object-id.
<code>um cluster list [-q] [-ObjectType <object-id>]</code>	<p>Lists the clusters after filtering on the specified object. ObjectType can be disk, aggr, node, cluster, lun, qtree, volume, quota, svm. For example: <code>um cluster list -aggr 1</code></p> <p>In this example, "-aggr" is the objectType and "1" is the objectId. The command lists the cluster to which the aggregate with ID 1 belongs.</p>	Displays the following values in tabular format: Name, Full Name, Serial Number, Datasource Id, Last Refresh Time, and Resource Key.
<code>um cluster node list [-q] [-ObjectType <object-id>]</code>	<p>Lists the cluster nodes after filtering on the specified object. ObjectType can be disk, aggr, node, cluster. For example: <code>um cluster node list -cluster 1</code></p> <p>In this example, "-cluster" is the objectType and "1" is the objectId. The command lists all the nodes within the cluster with ID 1.</p>	Displays the following values in tabular format Name and Cluster ID.

CLI command	Description	Output
<code>um volume list [-q] [-ObjectType <object-id>]</code>	<p>Lists the volumes after filtering on the specified object. ObjectType can be lun, qtree, cluster, volume, quota, svm, aggregate. For example: <code>um volume list -cluster 1</code></p> <p>In this example, "-cluster" is the objectType and "1" is the objectId. The command lists all the volumes within the cluster with ID 1.</p>	Displays the following values in tabular format Volume ID and Volume Name.
<code>um quota user list [-q] [-ObjectType <object-id>]</code>	<p>Lists the quota users after filtering on the specified object. ObjectType can be qtree, cluster, volume, quota, svm. For example: <code>um quota user list -cluster 1</code></p> <p>In this example, "-cluster" is the objectType and "1" is the objectId. The command lists all the quota users within the cluster with ID 1.</p>	Displays the following values in tabular format ID, Name, SID and Email.
<code>um aggr list [-q] [-ObjectType <object-id>]</code>	<p>Lists the aggregates after filtering on the specified object. ObjectType can be disk, aggr, node, cluster, volume. For example: <code>um aggr list -cluster 1</code></p> <p>In this example, "-cluster" is the objectType and "1" is the objectId. The command lists all the aggregates within the cluster with ID 1.</p>	Displays the following values in tabular format Aggr ID, and Aggr Name.
<code>um event ack <event-ids></code>	Acknowledges one or more events.	Displays the corresponding message.
<code>um event resolve <event-ids></code>	Resolves one or more events.	Displays the corresponding message.
<code>um event assign -u <username> <event-id></code>	Assigns an event to a user.	Displays the corresponding message.
<code>um event list [-s <source>] [-S <event-state-filter-list>..] [<event-id> ..]</code>	Lists the events generated by the system or user. Filters events based on source, state, and IDs.	Displays the following values in tabular format Source, Source type, Name, Severity, State, User and Timestamp.

CLI command	Description	Output
um cli login -u <username> [-p <password>]	Logs in to the CLI. The session expires after three hours from the time of login, after which the user must login again.	Displays the corresponding message.
um cli logout	Logs out of the CLI.	Displays the corresponding message.
um backup restore -f <backup_file_path_and_name>	Restores a database backup using .7z files.	Displays the corresponding message.
um help	Displays all first level subcommands.	Displays all first level subcommands.

Copyright information

Copyright © 2024 NetApp, Inc. All Rights Reserved. Printed in the U.S. No part of this document covered by copyright may be reproduced in any form or by any means—graphic, electronic, or mechanical, including photocopying, recording, taping, or storage in an electronic retrieval system—without prior written permission of the copyright owner.

Software derived from copyrighted NetApp material is subject to the following license and disclaimer:

THIS SOFTWARE IS PROVIDED BY NETAPP “AS IS” AND WITHOUT ANY EXPRESS OR IMPLIED WARRANTIES, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE, WHICH ARE HEREBY DISCLAIMED. IN NO EVENT SHALL NETAPP BE LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO, PROCUREMENT OF SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA, OR PROFITS; OR BUSINESS INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE) ARISING IN ANY WAY OUT OF THE USE OF THIS SOFTWARE, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE.

NetApp reserves the right to change any products described herein at any time, and without notice. NetApp assumes no responsibility or liability arising from the use of products described herein, except as expressly agreed to in writing by NetApp. The use or purchase of this product does not convey a license under any patent rights, trademark rights, or any other intellectual property rights of NetApp.

The product described in this manual may be protected by one or more U.S. patents, foreign patents, or pending applications.

LIMITED RIGHTS LEGEND: Use, duplication, or disclosure by the government is subject to restrictions as set forth in subparagraph (b)(3) of the Rights in Technical Data -Noncommercial Items at DFARS 252.227-7013 (FEB 2014) and FAR 52.227-19 (DEC 2007).

Data contained herein pertains to a commercial product and/or commercial service (as defined in FAR 2.101) and is proprietary to NetApp, Inc. All NetApp technical data and computer software provided under this Agreement is commercial in nature and developed solely at private expense. The U.S. Government has a non-exclusive, non-transferrable, nonsublicensable, worldwide, limited irrevocable license to use the Data only in connection with and in support of the U.S. Government contract under which the Data was delivered. Except as provided herein, the Data may not be used, disclosed, reproduced, modified, performed, or displayed without the prior written approval of NetApp, Inc. United States Government license rights for the Department of Defense are limited to those rights identified in DFARS clause 252.227-7015(b) (FEB 2014).

Trademark information

NETAPP, the NETAPP logo, and the marks listed at <http://www.netapp.com/TM> are trademarks of NetApp, Inc. Other company and product names may be trademarks of their respective owners.