



# **network arp commands**

## **ONTAP 9.10.1 commands**

NetApp  
September 27, 2022

# Table of Contents

- network arp commands ..... 1
- network arp create ..... 1
- network arp delete ..... 1
- network arp show ..... 2
- network arp active-entry delete ..... 3
- network arp active-entry show ..... 4

# network arp commands

## network arp create

Create static ARP entry

**Availability:** This command is available to *cluster* and *Vserver* administrators at the *admin* privilege level.

### Description

The `network arp create` command creates a static ARP entry for a given Vserver. Statically created ARP entries will be stored permanently in the Vserver context and will be used by the network stack.

### Parameters

**-vserver <vserver name> - Vserver Name**

Use this parameter to specify the name of the Vserver on which the ARP entry is created.

**-remotehost <IP Address> - Remote IP Address**

Use this parameter to specify the IP address to be added as an ARP entry.

**-mac <MAC Address> - MAC Address**

Use this parameter to specify the MAC address (Ethernet address) for the host specified with `-remotehost`. Specify the MAC address as six hex bytes separated by colons.

### Examples

The following example creates a static ARP entry on Vserver `vs1` for the remote host with the IP address `10.63.0.2` having MAC address `40:55:39:25:27:c1`

```
cluster1::> network arp create -vserver vs1 -remotehost 10.63.0.2 -mac
40:55:39:25:27:c1
```

## network arp delete

Delete static ARP entry

**Availability:** This command is available to *cluster* and *Vserver* administrators at the *admin* privilege level.

### Description

The `network arp delete` command deletes static ARP entries from the Vserver and from the network stack.

### Parameters

**-vserver <vserver name> - Vserver Name**

Use this parameter to specify the name of the Vserver from which the ARP entry is deleted.

**-remotehost <IP Address> - Remote IP Address**

Use this parameter to specify the IP address of the ARP entry being deleted.

## Examples

The following example deletes the ARP entry for IP address 10.63.0.2 from the Vserver vs1.

```
cluster1::> network arp delete -vserver vs1 -remotehost 10.63.0.2
```

## network arp show

Display static ARP entries

**Availability:** This command is available to *cluster* and *Vserver* administrators at the *admin* privilege level.

### Description

The `network arp show` command displays static ARP entries present in a given Vserver. This command will not display dynamically learnt ARP entries in the network stack. Use the [network arp active-entry show](#) command to display dynamically learned ARP entries in the network stack.

### Parameters

{ [-fields <fieldname>,...]

Use this parameter to display only certain fields of the ARP table.

| [-instance ] }

Use this parameter to display all the fields of the ARP table.

[-vserver <vserver name>] - Vserver Name

Use this parameter to display ARP entries that are specific to a given Vserver.

[-remotehost <IP Address>] - Remote IP Address

Use this parameter to display ARP entries for the specified IP address

[-mac <MAC Address>] - MAC Address

Use this parameter to display ARP entry for the specified MAC address

[-ipspace <IPspace>] - IPspace

Use this parameter to specify the IPspace associated with the Vserver

## Examples

The following example displays static ARP entries from the Vserver vs1.

```
cluster1::> network arp show -vserver vs1
Vserver      Remote Host      MAC Address
-----
vs1
              10.238.0.2      40:55:39:25:27:c1
```

## Related Links

- [network arp active-entry show](#)

## network arp active-entry delete

Delete active ARP entry from a System or Admin Vserver

**Availability:** This command is available to *cluster* administrators at the *advanced* privilege level.

### Description

The `network arp active-entry delete` command deletes dynamically learned ARP entries from the network stack of a node. To delete statically configured ARP entries use the [network arp delete](#) command.

### Parameters

**-node {<nodename>|local} - Node**

Use this parameter to specify the name of the node in which the ARP entry is deleted.

**-vserver <vserver> - System or Admin Vserver Name**

Use this parameter to specify the name of the Vserver in which the ARP entry is deleted. Only Vservers with a type of Admin or System have dynamically learned ARP entries.

**-subnet-group <IP Address/Mask> - Subnet Group Name**

Use this parameter to specify the name of the routing group in which the ARP entry is deleted.

**-remotehost <text> - Remote IP Address**

Use this parameter to specify the IP address to be deleted from the active ARP entries.

**-port <text> - Port**

Use this parameter to specify the name of the Port to be deleted from the active ARP entries.

### Examples

The following example deletes the active ARP entry with an IP address of 10.224.64.1, subnet group of 0.0.0.0/0, port e0c on node node2 in the Admin Vserver cluster1:

```
cluster1::*> network arp active-entry delete -node cluster1-01 -vserver
cluster1 -subnet-group 0.0.0.0/0 -remotehost 10.224.64.1 -port e0c
```

## Related Links

- [network arp delete](#)

# network arp active-entry show

Display active ARP entries organized by Vserver

**Availability:** This command is available to *cluster* administrators at the *advanced* privilege level.

## Description

The `network arp active-entry show` command displays ARP entries present in the network stack of the node. The entries includes both dynamically learned ARP entries and user configured static ARP entries.

## Parameters

**{ [-fields <fieldname>,...]**

Use this parameter to display only certain fields of the active ARP table.

**| [-instance ] }**

Use this parameter to display all the fields of the active ARP table.

**[-node {<nodename>|local}] - Node**

Use this parameter to display active ARP entries that are specific to a given node.

**[-vserver <vserver>] - System or Admin Vserver Name**

Use this parameter to display active ARP entries that are specific to a given System or Admin Vserver. Data and Node Vservers will not have any active-arp entries.

**[-subnet-group <IP Address/Mask>] - Subnet Group Name**

Use this parameter to display active ARP entries that are specific to a given subnet group.

**[-remotehost <text>] - Remote IP Address**

Use this parameter to display active ARP entries for the specified IP address.

**[-port <text>] - Port**

Use this parameter to display active ARP entries for the specified Port name.

**[-mac <text>] - MAC Address**

Use this parameter to display the active ARP entry for the specified MAC address.

**[-ipspace <IPspace>] - IPspace**

Use this parameter to specify the IPspace associated with the System or Admin Vserver.

## Examples

The following example displays active ARP entries for the Admin Vserver cluster1:

```
cluster1::*> network arp active-entry show -vserver cluster1
```

```
Node: node-01
```

```
Vserver: cluster1
```

```
Subnet Group: 169.254.0.0/16
```

```
Remote IP Address  MAC Address          Port
```

```
-----  
169.254.106.95     0:55:39:27:d1:c1  lo
```

## Copyright Information

Copyright © 2022 NetApp, Inc. All rights reserved. Printed in the U.S. No part of this document covered by copyright may be reproduced in any form or by any means-graphic, electronic, or mechanical, including photocopying, recording, taping, or storage in an electronic retrieval system-without prior written permission of the copyright owner.

Software derived from copyrighted NetApp material is subject to the following license and disclaimer:

THIS SOFTWARE IS PROVIDED BY NETAPP "AS IS" AND WITHOUT ANY EXPRESS OR IMPLIED WARRANTIES, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE, WHICH ARE HEREBY DISCLAIMED. IN NO EVENT SHALL NETAPP BE LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO, PROCUREMENT OF SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA, OR PROFITS; OR BUSINESS INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE) ARISING IN ANY WAY OUT OF THE USE OF THIS SOFTWARE, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE.

NetApp reserves the right to change any products described herein at any time, and without notice. NetApp assumes no responsibility or liability arising from the use of products described herein, except as expressly agreed to in writing by NetApp. The use or purchase of this product does not convey a license under any patent rights, trademark rights, or any other intellectual property rights of NetApp.

The product described in this manual may be protected by one or more U.S. patents, foreign patents, or pending applications.

RESTRICTED RIGHTS LEGEND: Use, duplication, or disclosure by the government is subject to restrictions as set forth in subparagraph (c)(1)(ii) of the Rights in Technical Data and Computer Software clause at DFARS 252.277-7103 (October 1988) and FAR 52-227-19 (June 1987).

## Trademark Information

NETAPP, the NETAPP logo, and the marks listed at <http://www.netapp.com/TM> are trademarks of NetApp, Inc. Other company and product names may be trademarks of their respective owners.