



vserver nvme commands

ONTAP 9.5 commands

NetApp
August 29, 2024

Table of Contents

- vserver nvme commands 1
 - vserver nvme create 1
 - vserver nvme delete 1
 - vserver nvme modify 2
 - vserver nvme show-interface 2
 - vserver nvme show 4
 - vserver nvme feature show 5
 - vserver nvme namespace create 5
 - vserver nvme namespace delete 6
 - vserver nvme namespace modify 7
 - vserver nvme namespace show 8
 - vserver nvme subsystem create 9
 - vserver nvme subsystem delete 10
 - vserver nvme subsystem modify 11
 - vserver nvme subsystem show 12
 - vserver nvme subsystem controller show 13
 - vserver nvme subsystem host add 15
 - vserver nvme subsystem host remove 15
 - vserver nvme subsystem host show 16
 - vserver nvme subsystem map add 17
 - vserver nvme subsystem map remove 18
 - vserver nvme subsystem map show 18

vserver nvme commands

vserver nvme create

Create NVMe service configuration

Availability: This command is available to *cluster* and *Vserver* administrators at the *admin* privilege level.

Description

The `vserver nvme create` command creates an NVMe service for a Vserver.

When you create the NVMe service on a Vserver, the Vserver must have only *nvme* in the allowed-protocols list.

When you create the NVMe service on a Vserver, the administrative status of the service is *up* by default.

Parameters

-vserver <Vserver Name> - Vserver Name

Specifies the Vserver for the NVMe service.

[-status-admin {down|up}] - Administrative Status

Specifies the configured administrative status of a service.

Examples

```
cluster1::*> vserver nvme create -vserver vs_1
```

Creates an NVMe service on Vserver *vs_1*.

vserver nvme delete

Delete NVMe service configuration

Availability: This command is available to *cluster* and *Vserver* administrators at the *admin* privilege level.

Description

The `vserver nvme delete` command deletes an NVMe service of a Vserver. Before you can delete an NVMe service, the administrative status must be *down*. Use the [vserver nvme modify](#) command to change the administrative status.

Parameters

-vserver <Vserver Name> - Vserver Name

Specifies the Vserver for the NVMe service.

Examples

```
cluster1::*> vserver nvme delete -vserver vs_1
```

Deletes the NVMe service on Vserver *vs_1* .

Related Links

- [vserver nvme modify](#)

vserver nvme modify

Modify NVMe service configuration

Availability: This command is available to *cluster* and *Vserver* administrators at the *admin* privilege level.

Description

The `vserver nvme modify` command modifies an NVMe service configuration on a Vserver.

Parameters

-vserver <Vserver Name> - Vserver Name

Specifies the Vserver for the NVMe service.

[-status-admin {down|up}] - Administrative Status

Specifies the configured administrative status of a service. If you set this parameter to *down* , the Vserver will not serve NVMe traffic.

Examples

```
cluster1::*> vserver nvme modify -vserver vs_1 -status-admin down
```

Sets the administrative status of the NVMe service on Vserver *vs_1* to *down* .

vserver nvme show-interface

Display the NVMe over Fabrics LIF configuration

Availability: This command is available to *cluster* and *Vserver* administrators at the *admin* privilege level.

Description

The `vserver nvme show-interface` command displays the currently available interfaces to the NVMe protocol.

Parameters

{ [-fields <fieldname>,...]

If you specify the `-fields <fieldname>`, ... parameter, the command output also includes the specified field or fields. You can use `-fields ?` to display the fields to specify.

| [-instance] }

If you specify the `-instance` parameter, the command displays detailed information about all fields.

[-vserver <Vserver Name>] - Vserver Name

Use this parameter to display the NVMe interfaces that match the Vserver that you specify.

[-lif <lif-name>] - Logical Interface

Use this parameter to display the NVMe interfaces that match the LIF that you specify.

[-vserver-uuid <UUID>] - Vserver UUID

Use this parameter to display the NVMe interfaces that match the Vserver UUID that you specify.

[-home-node <nodename>] - Home Node

Use this parameter to display the NVMe interfaces that match the home node that you specify.

[-home-port {<netport>|<ifgrp>}] - Home Port

Use this parameter to display the NVMe interfaces that match the home port that you specify.

[-status-admin {up|down}] - Status Admin

Use this parameter to display the NVMe interfaces that match the administrative status that you specify.

[-physical-protocol <fibre-channel>] - Physical Protocol

Use this parameter to display the NVMe interfaces that match the physical protocol that you specify.

[-transport-protocol {fc-nvme|rdma-nvme}] - Transport Protocol

Use this parameter to display the NVMe interfaces that match the transport protocol that you specify.

[-transport-address <text>] - Transport Address

Use this parameter to display the NVMe interfaces that match the transport address that you specify.

[-comment <text>] - Comment

Use this parameter to display the NVMe interfaces that match the textual comment that you specify.

[-fc-wwnn <FC WWN>] - FC WWNN

Use this parameter to display the NVMe interfaces that match the FC WWNN that you specify.

[-fc-wwpn <FC WWN>] - FC WWPN

Use this parameter to display the NVMe interfaces that match the FC WWPN that you specify.

[-lif-id <integer>] - LIF ID

Use this parameter to display the NVMe interfaces that match the LIF ID that you specify.

`[-lif-uuid <UUID>] - LIF UUID`

Use this parameter to display the NVMe interfaces that match the LIF UUID that you specify.

Examples

```
cluster1::*> vsver nvme show-interface
Vserver Logical Interface      Home Node:Port      Transport Protocols
-----
vs_1
      nvme1                  node1:1a              fc-nvme
      Transport Address: nn-0x2000005056b45113:pn-0x2001005056b45113
```

vsver nvme show

Show NVMe service configuration

Availability: This command is available to *cluster* and *Vserver* administrators at the *admin* privilege level.

Description

The `vsver nvme show` command displays the current status of the NVMe service in a cluster.

Parameters

`{ [-fields <fieldname>, ...]`

If you specify the `-fields <fieldname>`, ... parameter, the command output also includes the specified field or fields. You can use `'-fields ?'` to display the fields to specify.

`| [-instance] }`

If you specify the `-instance` parameter, the command displays detailed information about all fields.

`[-vserver <Vserver Name>] - Vserver Name`

Use this parameter to display the NVMe services that match the Vserver that you specify.

`[-status-admin {down|up}] - Administrative Status`

Use this parameter to display the NVMe services that match the administrative status that you specify.

Examples

```
cluster1::*> vserver nvme show
Vserver      Status Admin
-----
vs1          up
vs2          up
2 entries were displayed.
```

vserver nvme feature show

Display NVMe target features

Availability: This command is available to *cluster* administrators at the *advanced* privilege level.

Description

Displays the list of currently enabled NVMe over Fabrics features and limits.

Examples

```
cluster1::*> vserver nvme feature show
      Enabled Features: nvmf, fc-nvme, multi-path, multi-node
Maximum Namespace Size: 15.97TB
      Maximum NSID: 512
      Maximum ANAGRPID: 512
```

vserver nvme namespace create

Create NVMe namespace

Availability: This command is available to *cluster* and *Vserver* administrators at the *admin* privilege level.

Description

The `vserver nvme namespace create` command creates a new NVMe namespace of a specific size. You must create NVMe namespaces at the root of a volume or qtree.

When you create an NVMe namespace, it is non-space reserved.



This command is not supported for FlexGroups or Vservers with Infinite Volumes.

Parameters

-vserver <Vserver Name> - Vserver Name

Specifies the Vserver.

-path <path> - Namespace Path

Specifies the path of the NVMe namespace. Examples of correct NVMe namespace paths are `/vol/vol1/ns1` and `/vol/vol1/mtree1/ns1`.

-size {<integer>[KB|MB|GB|TB|PB]} - Size

Specifies the size of the NVMe namespace in bytes. You can specify a multiplier suffix:

- KB (1024 bytes)
- MB (KB*KB bytes)
- GB (KB*MB bytes)
- TB (MB*MB bytes)

-ostype {vmware|hyper_v|windows|linux|xen} - OS Type

Specifies the operating system type of the NVMe namespace. The OS types are:

- hyper_v - the NVMe namespace stores Windows Hyper-V file system data.
- linux - the NVMe namespace stores Linux file system data.
- vmware - the NVMe namespace stores VMware file system data.
- windows - the NVMe namespace stores Windows file system data.
- xen - the NVMe namespace stores Xen file system data.

[-comment <text>] - Comment

Contains a textual description of the NVMe namespace.

Examples

```
cluster1::*> vsserver nvme namespace create -vsserver vs_1 -path
/vol/nsvol/namespace1 -size 100g -ostype linux
```

Creates an NVMe namespace at path `/vol/ns/vol/namespace1` on Vserver `vs_1`.

vsserver nvme namespace delete

Delete the namespace

Availability: This command is available to *cluster* and *Vserver* administrators at the *admin* privilege level.

Description

The `vsserver nvme namespace delete` command deletes an NVMe namespace from a specified Vserver and volume.

Parameters

-vserver <Vserver Name> - Vserver Name

Specifies the Vserver.

-path <path> - Namespace Path

Specifies the path of the NVMe namespace. Examples of correct NVMe namespace paths are `/vol/vol1/ns1` and `/vol/vol1/mtree1/ns1`.

[-skip-mapped-check <true>] - Skip Mapped Check

This option is required to delete an NVMe namespace that is attached to a subsystem.

Examples

```
cluster1::*> vserver nvme namespace delete -vserver vs1 -path  
/vol/nsvol/ns1
```

Deletes the NVMe namespace at path `/vol/nsvol/ns1` on Vserver `vs1`.

vserver nvme namespace modify

Modify NVMe namespace

Availability: This command is available to *cluster* and *Vserver* administrators at the *admin* privilege level.

Description

The `vserver nvme namespace modify` command modifies NVMe namespace attributes.

Parameters

-vserver <Vserver Name> - Vserver Name

Specifies the Vserver.

-path <path> - Namespace Path

Specifies the path of the NVMe namespace. Examples of correct NVMe namespace paths are `/vol/vol1/ns1` and `/vol/vol1/mtree1/ns1`.

[-comment <text>] - Comment

Contains a textual description of the NVMe namespace.

Examples

```
cluster1::*> vserver nvme namespace modify -path /vol/nsvol/ns1 -vserver  
vs_1 -comment "Comment text."
```

Modifies the value of the comment field for the NVMe namespace at path `/vol/nsvol/ns1` on Vserver `vs_1`.

vserver nvme namespace show

Display NVMe namespaces

Availability: This command is available to *cluster* and *Vserver* administrators at the *admin* privilege level.

Description

The `vserver nvme namespace show` command displays information for NVMe namespaces.

Parameters

{ [-fields <fieldname>,...]

If you specify the `-fields <fieldname>`, ... parameter, the command output also includes the specified field or fields. You can use `'-fields ?'` to display the fields to specify.

| [-instance] }

If you specify the `-instance` parameter, the command displays detailed information about all fields.

[-vserver <Vserver Name>] - Vserver Name

Use this parameter to display the NVMe namespaces that match the Vserver that you specify.

[-path <path>] - Namespace Path

Use this parameter to display the NVMe namespace that matches the path that you specify.

[-size {<integer>[KB|MB|GB|TB|PB]}] - Size

Use this parameter to display the NVMe namespaces that match the size that you specify.

[-block-size {<integer>[KB|MB|GB|TB|PB]}] - Block Size

Use this parameter to display the NVMe namespaces that match this parameter value.

[-size-used {<integer>[KB|MB|GB|TB|PB]}] - Size Used

Use this parameter to display the NVMe namespaces that match this parameter value.

[-ostype {vmware|hyper_v|windows|linux|xen}] - OS Type

Use this parameter to display the NVMe namespaces that match this parameter value.

[-comment <text>] - Comment

Use this parameter to display the NVMe namespaces that match this parameter value.

[-state {online|offline|nvfail|space-error}] - State

Use this parameter to display the NVMe namespaces that match this parameter value.

[-is-read-only {true|false}] - Is Read Only

Use this parameter to display the NVMe namespaces that match this parameter value.

[-creation-timestamp <MM/DD/YYYY HH:MM:SS>] - Creation Time

Use this parameter to display the NVMe namespaces that match this parameter value.

[`-uuid <UUID>`] - Namespace UUID

Use this parameter to display the NVMe namespaces that match this parameter value.

[`-restore-inaccessible {true|false}`] - Restore Inaccessible

Use this parameter to display the NVMe namespaces that match this parameter value.

[`-node <nodename>`] - Node Hosting the Namespace

Use this parameter to display the NVMe namespaces that match this parameter value.

[`-volume <volume name>`] - Volume Name

Use this parameter to display the NVMe namespaces that match this parameter value.

[`-qtree <qtree name>`] - Qtree Name

Use this parameter to display the NVMe namespaces that match this parameter value.

[`-subsystem <text>`] - Attached Subsystem

Use this parameter to display the NVMe namespaces that are attached to a Subsystem that matches this parameter value.

[`-nsid <Hex Integer>`] - Namespace ID

Use this parameter to display the NVMe namespaces that match this parameter value.

[`-anagrpid <Hex Integer>`] - ANA Group ID (privilege: advanced)

Use this parameter to display the NVMe namespaces that match Asymmetric Namespace Access (ANA) group identifier that you specify.

[`-vserver-id <integer>`] - Vserver ID

Use this parameter to display the NVMe namespaces that match this parameter value.

Examples

```
cluster::*> vservers nvme namespace show -vserver vs1
```

Vserver	Path	State	Size	Subsystem	NSID
vs1	/vol/test_1_vol/ns1	online	10GB	subsys1	1
vs1	/vol/test_1_vol/ns2	online	500MB	subsys1	2
vs1	/vol/test_1_vol/ns3	online	1TB	-	-

3 entries were displayed.

vserver nvme subsystem create

Create an NVMe target subsystem

Availability: This command is available to *cluster* and *Vserver* administrators at the *admin* privilege level.

Description

The `vserver nvme subsystem create` command creates a new NVMe target subsystem.

When you create an NVMe subsystem on a Vserver, the Vserver must meet the following pre-conditions:

- The Vserver must have an NVMe service created.
- The Vserver must not already have an NVMe subsystem by the same name.



The NVMe subsystem identifiers are assigned by the system. The NQN is derived from the Vserver UUID and subsystem name and may not be specified or modified by the user.

Parameters

-vserver <Vserver Name> - Vserver Name

Specifies the Vserver.

-subsystem <text> - Subsystem

Specifies the NVMe target subsystem.

-ostype {windows|linux|vmware|xen|hyper_v} - OS Type

Specifies the operating system type of the NVMe subsystem. The OS types are:

- `hyper_v` - the initiators belong to a Hyper-V parent host.
- `linux` - the initiators belong to a Linux host.
- `vmware` - the initiators belong to a VMware ESX host.
- `windows` - the initiators belong to a Windows host.
- `xen` - the initiators belong to a Xen hypervisor host.

[-comment <text>] - Comment

Contains a textual description of the NVMe subsystem.

Examples

```
cluster1::*> vserver nvme subsystem create -vserver vs_1 -subsystem sub_1  
-ostype linux
```

Creates a subsystem named `sub_1` on Vserver `vs_1`.

vserver nvme subsystem delete

Delete the subsystem

Availability: This command is available to *cluster* and *Vserver* administrators at the *admin* privilege level.

Description

The `vserver nvme subsystem delete` command deletes an NVMe subsystem from a specified Vserver.

Parameters

-vserver <Vserver Name> - Vserver Name

Specifies the Vserver.

-subsystem <text> - Subsystem

Specifies the NVMe target subsystem.

[-skip-mapped-check <true>] - Skip Mapped Namespace Check

Required to delete an NVMe subsystem with attached NVMe namespaces.

[-skip-host-check <true>] - Skip Host Check

Required to delete an NVMe subsystem with associated hosts.

Examples

```
cluster1::*> vserver nvme subsystem delete -vserver vs_1 -subsystem sub_1
```

Deletes the NVMe subsystem `sub_1` on Vserver `vs_1`.

vserver nvme subsystem modify

Modify an NVMe target subsystem

Availability: This command is available to *cluster* and *Vserver* administrators at the *admin* privilege level.

Description

The `vserver nvme subsystem modify` command modifies an existing NVMe target subsystem.

Parameters

-vserver <Vserver Name> - Vserver Name

Specifies the Vserver.

-subsystem <text> - Subsystem

Specifies the NVMe target subsystem.

[-comment <text>] - Comment

Contains a textual description of the NVMe subsystem.

Examples

```
cluster1::*> vservers nvme subsystem modify -vservers vs_1 -subsystem sub_1
-comment "Example Comment"
```

Modifies the comment on the subsystem named *sub_1* on Vserver *vs_1*.

vserver nvme subsystem show

Display NVMe target subsystems

Availability: This command is available to *cluster* and *Vserver* administrators at the *admin* privilege level.

Description

The `vserver nvme subsystem show` command displays information for NVMe subsystems.

Parameters

{ [-fields <fieldname>,...]

If you specify the `-fields <fieldname>, ...` parameter, the command output also includes the specified field or fields. You can use `'-fields ?'` to display the fields to specify.

| [-instance] }

If you specify the `-instance` parameter, the command displays detailed information about all fields.

[-vservers <Vserver Name>] - Vserver Name

Use this parameter to display the NVMe subsystems that match the Vserver that you specify.

[-subsystem <text>] - Subsystem

Use this parameter to display the NVMe subsystem that matches the name that you specify.

[-ostype {windows|linux|vmware|xen|hyper_v}] - OS Type

Use this parameter to display the NVMe subsystems that match this parameter value.

[-comment <text>] - Comment

Use this parameter to display the NVMe subsystems that match this parameter value.

[-target-nqn <text>] - Target NQN

Use this parameter to display the NVMe subsystems that match this parameter value.

[-serial-number <text>] - Serial Number

Use this parameter to display the NVMe subsystems that match this parameter value.

[-default-io-queue-count <integer>] - Default Number of Host I/O Queue Pairs

Specifies the default maximum IO queue count inherited by hosts added to this subsystem.

[`-default-io-queue-depth` <integer>] - Default Host I/O Queue Depth

Specifies the default maximum IO queue depth inherited by hosts added to this subsystem.

Examples

```
cluster1::*> vserver nvme subsystem show -vserver vs_1
Vserver Subsystem      Target NQN
-----
vs_1
    ss1                nqn.1992-
08.netapp.com:sn.ccb5a7d5d9d311e7924e005056b45113:subsystem.ss1
    ss2                nqn.1992-
08.netapp.com:sn.ccb5a7d5d9d311e7924e005056b45113:subsystem.ss2
2 entries were displayed.
```

vserver nvme subsystem controller show

Display active NVMe controllers

Availability: This command is available to *cluster* and *Vserver* administrators at the *admin* privilege level.

Description

The `vserver nvme subsystem controller show` command displays information for established NVMe controllers. An NVMe controller is established upon each host connection to a subsystem.

Parameters

{ [`-fields` <fieldname>, ...]

If you specify the `-fields` <fieldname>, ... parameter, the command output also includes the specified field or fields. You can use '`-fields ?`' to display the fields to specify.

| [`-instance`] }

If you specify the `-instance` parameter, the command displays detailed information about all fields.

[`-vserver` <Vserver Name>] - Vserver Name

Use this parameter to display the NVMe controllers that match the Vserver that you specify.

[`-subsystem` <text>] - Subsystem

Use this parameter to display the NVMe controllers that match the subsystem that you specify.

[`-controller-id` <Hex 16bit Integer>] - Controller ID

Use this parameter to display the NVMe controllers that match the controller ID that you specify. The controller ID is the identifier assigned by the NVMe subsystem upon host login and controller creation.

[-lif <text>] - Logical Interface

Use this parameter to display the NVMe controllers that match the LIF that you specify.

[-node <nodename>] - Node

Use this parameter to display the NVMe controllers that match the cluster node that you specify.

[-host-nqn <text>] - Host NQN

Use this parameter to display the NVMe controllers that match the host NQN that you specify. The host NQN is the NVMe identifier assigned to a specific host.

[-transport-protocol {fc-nvme|rdma-nvme}] - Transport Protocol

Use this parameter to display the NVMe controllers that match the transport protocol that you specify.

[-initiator-transport-address <text>] - Initiator Transport Address

Use this parameter to display the NVMe controllers that match the initiator transport address that you specify. The initiator transport address format depends on the transport protocol in use.

[-host-id <Hex String>] - Host Identifier

Use this parameter to display the NVMe controllers that match the host identifier that you specify. The host identifier is a 128-bit identifier assigned to a specific host.

[-io-queue-count <integer>] - Number of I/O Queues

Use this parameter to display the NVMe controllers that match the I/O queue count that you specify.

[-io-queue-depth <integer>,...] - I/O Queue Depths

Use this parameter to display the NVMe controllers that match the I/O queue depth that you specify.

[-admin-queue-depth <integer>] - Admin Queue Depth

Use this parameter to display the NVMe controllers that match the administrative queue depth that you specify.

Examples

```
cluster1::*> vserver nvme subsystem controller show -vserver vs_1
-subsystem ss1
Vserver Subsystem ID   LIF      Host NQN
-----
vs_1      ss1
          3 lif1     nqn.2001-08.example.com:nvme:host1
          4 lif1     nqn.2001-08.example.com:nvme:host2
          9 lif2     nqn.2001-08.example.com:nvme:host1
          a lif2     nqn.2001-08.example.com:nvme:host2
4 entries were displayed.
```


vserver nvme subsystem host add

Add a host to a subsystem

Availability: This command is available to *cluster* and *Vserver* administrators at the *admin* privilege level.

Description

The `vserver nvme subsystem host add` command adds an FC-NVMe host to an NVMe subsystem on a Vserver.

Parameters

-vserver <Vserver Name> - Vserver Name

Specifies the Vserver.

-subsystem <text> - Subsystem

Specifies the NVMe target subsystem.

-host-nqn <text> - Host NQN

Specifies the NVMe subsystem host NQN.

Examples

```
cluster::*> vserver nvme subsystem host add -vserver vs_1 -subsystem sub_1  
-host-nqn nqn.2001-01.com.example:nvme-host1
```

Adds a host with the specified NQN to the NVMe subsystem *sub_1* on Vserver *vs_1*.

vserver nvme subsystem host remove

Remove a host from a subsystem

Availability: This command is available to *cluster* and *Vserver* administrators at the *admin* privilege level.

Description

The `vserver nvme subsystem host remove` command removes an FC-NVMe host from an NVMe subsystem on a Vserver.

Parameters

-vserver <Vserver Name> - Vserver Name

Specifies the Vserver.

-subsystem <text> - Subsystem

Specifies the NVMe target subsystem.

-host-nqn <text> - Host NQN

Specifies the NVMe subsystem host NQN.

Examples

```
cluster::*> vserver nvme subsystem host remove -vserver vs_1 -subsystem
sub_1 -host-nqn nqn.2001-01.com.example:host1
```

Removes the host with the specified NQN from NVMe subsystem *sub_1* on Vserver *vs_1*.

vserver nvme subsystem host show

Display NVMe hosts configured to the subsystem

Availability: This command is available to *cluster* and *Vserver* administrators at the *admin* privilege level.

Description

The `vserver nvme subsystem host show` command displays information for the NVMe subsystem hosts.

Parameters

{ [-fields <fieldname>,...]

If you specify the `-fields <fieldname>, ...` parameter, the command output also includes the specified field or fields. You can use `'-fields ?'` to display the fields to specify.

| [-instance] }

If you specify the `-instance` parameter, the command displays detailed information about all fields.

[-vserver <Vserver Name>] - Vserver Name

Use this parameter to display the NVMe subsystem hosts that match the Vserver that you specify.

[-subsystem <text>] - Subsystem

Use this parameter to display the NVMe subsystem hosts that match the subsystem that you specify.

[-host-nqn <text>] - Host NQN

Use this parameter to display the NVMe subsystem host that matches the subsystem host NQN that you specify.

[-io-queue-count <integer>] - Number of I/O Queue Pairs

Use this parameter to display the NVMe subsystem hosts that match the maximum IO queue count that you specify.

[-io-queue-depth <integer>] - I/O Queue Depth

Use this parameter to display the NVMe subsystem hosts that match the maximum IO queue depth that you specify.

Examples

```
cluster::*> vsriver nvme subsystem host show -vsriver vs_1 -subsystem
sub_1
Vserver Subsystem Host NQN
-----
vs_1      sub_1      nqn.2001-08.com.example:nvme:host1
              nqn.2001-08.com.example:nvme:host2
              nqn.2001-08.com.example:nvme:host3
3 entries were displayed.
```

vsriver nvme subsystem map add

Add a namespace map

Availability: This command is available to *cluster* and *Vserver* administrators at the *admin* privilege level.

Description

The `vsriver nvme subsystem map add` command creates an association on an NVMe namespace to an NVMe subsystem.

When you add an NVMe subsystem map, the following pre-conditions must hold:

- The NVMe namespace must not be already mapped to a different subsystem.
- There must be an FC-NVMe LIF on the NVMe namespace owning node.

Parameters

-vsriver <Vserver Name> - Vserver Name

Specifies the Vserver.

-subsystem <text> - Subsystem

Specifies the NVMe target subsystem.

-path <path> - Namespace Path

Specifies the path of the NVMe namespace. Examples of correct NVMe namespace paths are `/vol/vol1/ns1` and `/vol/vol1/qtree1/ns1`.

Examples

```
cluster::*> vsriver nvme subsystem map add -vsriver vs_1 -subsystem sub_1
-path /vol/nsvol/namespace1
```

Adds an association on the NVMe namespace at the specified path to NVMe subsystem `sub_1` on Vserver `vs_1`.

vserver nvme subsystem map remove

Remove a namespace map

Availability: This command is available to *cluster* and *Vserver* administrators at the *admin* privilege level.

Description

The `vserver nvme subsystem map remove` command deletes an association on an NVMe namespace to an NVMe subsystem.

Parameters

-vserver <Vserver Name> - Vserver Name

Specifies the Vserver.

-subsystem <text> - Subsystem

Specifies the NVMe target subsystem.

-path <path> - Namespace Path

Specifies the path of the NVMe namespace. Examples of correct NVMe namespace paths are `/vol/vol1/ns1` and `/vol/vol1/qtree1/ns1`.

Examples

```
cluster::*> vserver nvme subsystem map remove -vserver vs_1 -subsystem  
sub_1 -path /vol/nsvol/namespace1
```

Removes the association on the NVMe namespace at the specified path to NVMe subsystem `sub_1` on Vserver `vs_1`.

vserver nvme subsystem map show

Display namespace maps within the subsystem

Availability: This command is available to *cluster* and *Vserver* administrators at the *admin* privilege level.

Description

The `vserver nvme subsystem map show` command displays information about NVMe subsystem maps.

Parameters

{ [-fields <fieldname>,...]

If you specify the `-fields <fieldname>, ...` parameter, the command output also includes the specified field or fields. You can use `'-fields ?'` to display the fields to specify.

| [-instance] }

If you specify the `-instance` parameter, the command displays detailed information about all fields.

[-vserver <Vserver Name>] - Vserver Name

Use this parameter to display the NVMe subsystem maps that match the Vserver that you specify.

[-subsystem <text>] - Subsystem

Use this parameter to display the NVMe subsystem maps that match the subsystem that you specify.

[-nsid <Hex 32bit Integer>] - NSID

Use this parameter to display the NVMe subsystem maps that match the NVMe namespace NSID that you specify.

[-path <path>] - Namespace Path

Use this parameter to display the NVMe subsystem maps that match the NVMe namespace path that you specify.

[-anagrpid <Hex 32bit Integer>] - ANA Group ID (privilege: advanced)

Use this parameter to display the NVMe namespaces that match the Asymmetric Namespace Access (ANA) group identifier that you specify.

[-namespace-uuid <UUID>] - Namespace UUID

Use this parameter to display the NVMe subsystem maps that match the NVMe namespace UUID that you specify.

Examples

```
cluster-1::*> vsystem nvme subsystem map show -vserver vs_1
Vserver      Subsystem NSID    Namespace Path
-----
vs_1         sub_1
              1 /vol/nsvol1/ns1
              2 /vol/nsvol1/ns2
2 entries were displayed.
```

Copyright information

Copyright © 2024 NetApp, Inc. All Rights Reserved. Printed in the U.S. No part of this document covered by copyright may be reproduced in any form or by any means—graphic, electronic, or mechanical, including photocopying, recording, taping, or storage in an electronic retrieval system—without prior written permission of the copyright owner.

Software derived from copyrighted NetApp material is subject to the following license and disclaimer:

THIS SOFTWARE IS PROVIDED BY NETAPP “AS IS” AND WITHOUT ANY EXPRESS OR IMPLIED WARRANTIES, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE, WHICH ARE HEREBY DISCLAIMED. IN NO EVENT SHALL NETAPP BE LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO, PROCUREMENT OF SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA, OR PROFITS; OR BUSINESS INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE) ARISING IN ANY WAY OUT OF THE USE OF THIS SOFTWARE, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE.

NetApp reserves the right to change any products described herein at any time, and without notice. NetApp assumes no responsibility or liability arising from the use of products described herein, except as expressly agreed to in writing by NetApp. The use or purchase of this product does not convey a license under any patent rights, trademark rights, or any other intellectual property rights of NetApp.

The product described in this manual may be protected by one or more U.S. patents, foreign patents, or pending applications.

LIMITED RIGHTS LEGEND: Use, duplication, or disclosure by the government is subject to restrictions as set forth in subparagraph (b)(3) of the Rights in Technical Data -Noncommercial Items at DFARS 252.227-7013 (FEB 2014) and FAR 52.227-19 (DEC 2007).

Data contained herein pertains to a commercial product and/or commercial service (as defined in FAR 2.101) and is proprietary to NetApp, Inc. All NetApp technical data and computer software provided under this Agreement is commercial in nature and developed solely at private expense. The U.S. Government has a non-exclusive, non-transferrable, nonsublicensable, worldwide, limited irrevocable license to use the Data only in connection with and in support of the U.S. Government contract under which the Data was delivered. Except as provided herein, the Data may not be used, disclosed, reproduced, modified, performed, or displayed without the prior written approval of NetApp, Inc. United States Government license rights for the Department of Defense are limited to those rights identified in DFARS clause 252.227-7015(b) (FEB 2014).

Trademark information

NETAPP, the NETAPP logo, and the marks listed at <http://www.netapp.com/TM> are trademarks of NetApp, Inc. Other company and product names may be trademarks of their respective owners.