



## **nvdimm events**

### ONTAP EMS reference

NetApp  
November 18, 2025

# Table of Contents

nvdimm events .....	1
nvdimm.excessive events .....	1
nvdimm.excessive.cecc.errs .....	1
nvdimm.flash events .....	1
nvdimm.flash.lifetime.low .....	1
nvdimm.fw events .....	1
nvdimm.fw.upgrade.failure .....	2
nvdimm.fw.upgrade.succeed .....	2
nvdimm.nvmem events .....	2
nvdimm.nvmem.checkfail .....	2
nvdimm.nvmem.destage.failure .....	3
nvdimm.nvmem.destage.succeed .....	3
nvdimm.nvmem.initfail .....	4
nvdimm.nvmem.restage.failure .....	4
nvdimm.nvmem.restage.succeed .....	5

# **nvdimm events**

## **nvdimm.excessive events**

### **nvdimm.excessive.cecc.errs**

#### **Severity**

ALERT

#### **Description**

This message occurs when excessive correctable error-correcting code (ECC) memory errors are reported by the NVDIMM controller.

#### **Corrective Action**

Use the "system environment sensors show -hidden true" clustershell command to view the current "NV Correctable ECC Count" value. Contact NetApp technical support for further assistance.

#### **Syslog Message**

Excessive correctable ECC errors in the NVDIMM in slot-%d. Count: %d.

#### **Parameters**

**slot** (INT): NVDIMM slot location.

**count** (INT): CECC count.

# **nvdimm.flash events**

## **nvdimm.flash.lifetime.low**

#### **Severity**

ALERT

#### **Description**

This message occurs when the NVDIMM device exceeds its warning threshold. This issue typically indicates that the NVDIMM hardware is approaching the end of its service life and should be replaced soon.

#### **Corrective Action**

Contact NetApp technical support for assistance with replacing the NVDIMM hardware.

#### **Syslog Message**

Service lifetime of NVDIMM device in slot-%d is low at %d%%.

#### **Parameters**

**slot** (INT): NVDIMM slot location.

**percent** (INT): Lifetime percentage.

# **nvdimm.fw events**

## **nvdimm.fw.upgrade.failure**

### **Severity**

ERROR

### **Description**

This message occurs when NVDIMM controller firmware failed to upgrade.

### **Corrective Action**

Power-cycle the controller and reboot ONTAP to attempt the firmware update again. If the error persists, contact NetApp technical support for assistance.

### **Syslog Message**

NVDIMM controller in slot-%d failed to upgrade firmware because of %s.

### **Parameters**

**slot** (INT): NVDIMM slot location.

**error** (STRING): Reason for upgrade failure, which could be: 1. the image file does not exist or is corrupted 2. it is unable to enter update mode 3. it is unable to clear update mode 3. the firmware image transfer failed 4. of a CRC mismatch with the transferred image 5. it failed to validate or commit the image 6. it failed to restart after the image upgrade

## **nvdimm.fw.upgrade.succeed**

### **Severity**

NOTICE

### **Description**

This message occurs when the NVDIMM controller successfully upgrades its own firmware image..

### **Corrective Action**

(None).

### **Syslog Message**

NVDIMM controller firmware in slot-%d was upgraded to %s.

### **Parameters**

**slot** (INT): NVDIMM slot location.

**version** (STRING): New firmware version.

## **nvdimm.nvmem events**

### **nvdimm.nvmem.checkfail**

### **Severity**

EMERGENCY

### **Description**

This message occurs when NVDIMM-based NVMEM checks fail.

## Corrective Action

For all errors, check that the right type of NVDIMM is properly installed at the designated DIMM slot.

## Syslog Message

NVMEM subsystem configuration check failed because %s. To prevent NVMEM data loss, halt the system.

## Parameters

**error** (STRING): Description of the error, which could be: 1 device in slot-N is not accessible. 2. device in slot-N is missing. 3. device in slot-N is not NVDIMM. 4. device in slot-N is the wrong size (N); expected size (N)

## **nvdimm.nvmem.destage.failure**

### Severity

ALERT

### Description

This message occurs when NVDIMM fails to copy nonvolatile data to the flash on the NVDIMM-device.

### Corrective Action

This type of error indicates that the volatile data on the local NVMEM has been lost. A storage system in an HA configuration might recover the NVMEM content from its partner. To prevent future possible data loss, take the appropriate actions based on the error: 1. If the failure is caused by a malfunctioning battery, contact NetApp technical support for assistance with battery replacement. 2. If the failure is caused by an NVDIMM intermittent hardware failure, contact NetApp technical support for assistance.

## Syslog Message

NVMEM subsystem failed to copy nonvolatile data to flash memory on NVDIMM device because %s.

## Parameters

**error** (STRING): Reason for destage failure could be: (1) SDRAM is not in self-refresh mode (2) energy source (battery) is not functioning properly (3) of insufficient battery (4) destage process timeout (5) an intermittent hardware error results partial data saved (6) of a hardware error (7) of a firmware error (8) of a flash error

## **nvdimm.nvmem.destage.succeed**

### Severity

NOTICE

### Description

This message occurs when all NVDIMM devices have copied nonvolatile data to flash memory.

### Corrective Action

(None).

## Syslog Message

NVMEM subsystem successfully copied nonvolatile data to flash memory on NVDIMM device in %ld seconds.

## Parameters

**seconds** (INT): Time taken by the destage operation.

## **nvdimm.nvmmem.initfail**

### Severity

EMERGENCY

### Description

This message occurs when the nvdimm-based NVMMEM subsystem is not initialized successfully.

### Corrective Action

For all errors, check if the error is persistent or intermittent by power cycling the controller and rebooting ONTAP. Note: If the last reboot is a dirty shutdown, set the bootarg.init.battery\_override to force system to replay the NVLOG first when booting. Then, gracefully shut down and power cycle the controller.. If the failure is persistent: (a) For error (1) (2) (3) (5) (6) (7) (8), contact NetApp technical support for assistance with replacement of NVDIMM or upgrade NVDIMM firmware. (b) For error (4), b.1 If failure cause is battery, contact NetApp technical support for assistance with replacement of the battery. b.2 For other failures, contact NetApp technical support for assistance with replacement of NVDIMM. (c) For error (9), contact NetApp technical support for assistance with replacement of the controller. (d) For error (10), verify the NVDIMM is installed properly and check if the correct BIOS is installed.

### Syslog Message

NVMM subsystem initialization failed because %s. To prevent NVMM data loss, halt the system.

## Parameters

**error** (STRING): Description of the error, which could be: 1.NVDIMM device in slot-N not accessible. 2.NVDIMM device in slot-N not ready. 3.NVDIMM device in slot-N is busy. 4.NVDIMM device in slot-N lost persistence due to [reason] 5.NVDIMM device in slot-N has worn-out flash (N percent remaining) 6.NVDIMM device in slot-N failed to configure energy source 7.NVDIMM device in slot-N failed to configure saveNPin. 8.NVDIMM device in slot-N failed to enable data preservation. 9.failed to enable battery. 10.NVDIMM memory address not mapped contiguously.

## **nvdimm.nvmmem.restage.failure**

### Severity

ALERT

### Description

This message occurs when nonvolatile data on the NVDIMM is either corrupt or not accessible. Because these errors cannot be corrected, nonvolatile data in flash memory is lost.

### Corrective Action

Frequent occurrence of these errors indicates that the NVDIMM is experiencing persistent intermittent hardware failure. Contact NetApp technical support for assistance with replacement.

### Syslog Message

NVMM subsystem failed to restore nonvolatile data from flash memory on the NVDIMM module because of %s.

## Parameters

**error** (STRING): Reason for restage failure could be: (1) SDRAM is not in self-refresh mode (2) of SDRAM uncorrectable error (3) restage process timeout (4) of a hardware error

## **nvdimm.nvmem.restage.succeed**

### Severity

NOTICE

### Description

This message occurs when all NVDIMM devices have restored nonvolatile data from flash memory.

### Corrective Action

(None).

### Syslog Message

NVMEM subsystem successfully restored nonvolatile data from flash memory on NVDIMM device in %ld seconds.

## Parameters

**seconds** (INT): Time taken by the restage operation.

## Copyright information

Copyright © 2025 NetApp, Inc. All Rights Reserved. Printed in the U.S. No part of this document covered by copyright may be reproduced in any form or by any means—graphic, electronic, or mechanical, including photocopying, recording, taping, or storage in an electronic retrieval system—with prior written permission of the copyright owner.

Software derived from copyrighted NetApp material is subject to the following license and disclaimer:

THIS SOFTWARE IS PROVIDED BY NETAPP “AS IS” AND WITHOUT ANY EXPRESS OR IMPLIED WARRANTIES, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE, WHICH ARE HEREBY DISCLAIMED. IN NO EVENT SHALL NETAPP BE LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO, PROCUREMENT OF SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA, OR PROFITS; OR BUSINESS INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE) ARISING IN ANY WAY OUT OF THE USE OF THIS SOFTWARE, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE.

NetApp reserves the right to change any products described herein at any time, and without notice. NetApp assumes no responsibility or liability arising from the use of products described herein, except as expressly agreed to in writing by NetApp. The use or purchase of this product does not convey a license under any patent rights, trademark rights, or any other intellectual property rights of NetApp.

The product described in this manual may be protected by one or more U.S. patents, foreign patents, or pending applications.

**LIMITED RIGHTS LEGEND:** Use, duplication, or disclosure by the government is subject to restrictions as set forth in subparagraph (b)(3) of the Rights in Technical Data -Noncommercial Items at DFARS 252.227-7013 (FEB 2014) and FAR 52.227-19 (DEC 2007).

Data contained herein pertains to a commercial product and/or commercial service (as defined in FAR 2.101) and is proprietary to NetApp, Inc. All NetApp technical data and computer software provided under this Agreement is commercial in nature and developed solely at private expense. The U.S. Government has a non-exclusive, non-transferrable, nonsublicensable, worldwide, limited irrevocable license to use the Data only in connection with and in support of the U.S. Government contract under which the Data was delivered. Except as provided herein, the Data may not be used, disclosed, reproduced, modified, performed, or displayed without the prior written approval of NetApp, Inc. United States Government license rights for the Department of Defense are limited to those rights identified in DFARS clause 252.227-7015(b) (FEB 2014).

## Trademark information

NETAPP, the NETAPP logo, and the marks listed at <http://www.netapp.com/TM> are trademarks of NetApp, Inc. Other company and product names may be trademarks of their respective owners.