



Manage storage tape devices

ONTAP 9.10.1 REST API Documentation

NetApp
April 02, 2024

Table of Contents

- Manage storage tape devices 1
 - Storage tape-devices endpoint overview 1
 - Retrieve tape devices 6
 - Retrieve a tape device 14

Manage storage tape devices

Storage tape-devices endpoint overview

Retrieving storage tape information

The storage tape GET API retrieves all of the tapes in the cluster.

Examples

1) Retrieving a list of tapes from the cluster

The following example returns the list of tapes in the cluster:

```
# The API:
/api/storage/tape-devices

# The call:
curl -X GET "https://<mgmt-ip>/api/storage/tape-devices" -H "accept:
application/hal+json"

# The response:
{
  "records": [
    {
      "node": {
        "uuid": "4083be52-5315-11eb-a839-00a0985ebbe7",
        "name": "st-8020-1-01",
        "_links": {
          "self": {
            "href": "/api/cluster/nodes/4083be52-5315-11eb-a839-
00a0985ebbe7"
          }
        }
      },
      "device_id": "2d.0",
      "_links": {
        "self": {
          "href": "/api/storage/tape-devices/4083be52-5315-11eb-a839-
00a0985ebbe7/2d.0"
        }
      }
    }
  ],
}
```

```

{
  "node": {
    "uuid": "4083be52-5315-11eb-a839-00a0985ebbe7",
    "name": "st-8020-1-01",
    "_links": {
      "self": {
        "href": "/api/cluster/nodes/4083be52-5315-11eb-a839-00a0985ebbe7"
      }
    }
  },
  "device_id": "2d.0L1",
  "_links": {
    "self": {
      "href": "/api/storage/tape-devices/4083be52-5315-11eb-a839-00a0985ebbe7/2d.0L1"
    }
  }
},
{
  "node": {
    "uuid": "4083be52-5315-11eb-a839-00a0985ebbe7",
    "name": "st-8020-1-01",
    "_links": {
      "self": {
        "href": "/api/cluster/nodes/4083be52-5315-11eb-a839-00a0985ebbe7"
      }
    }
  },
  "device_id": "qeg-tape-brocade2-8g:0.126",
  "_links": {
    "self": {
      "href": "/api/storage/tape-devices/4083be52-5315-11eb-a839-00a0985ebbe7/qeg-tape-brocade2-8g%3A0.126"
    }
  }
},
{
  "node": {
    "uuid": "4083be52-5315-11eb-a839-00a0985ebbe7",
    "name": "st-8020-1-01",
    "_links": {
      "self": {
        "href": "/api/cluster/nodes/4083be52-5315-11eb-a839-00a0985ebbe7"
      }
    }
  }
}

```

```

    }
  },
  "device_id": "stsw-broc6510-01:11.126",
  "_links": {
    "self": {
      "href": "/api/storage/tape-devices/4083be52-5315-11eb-a839-00a0985ebbe7/stsw-broc6510-01%3A11.126"
    }
  }
},
{
  "node": {
    "uuid": "4083be52-5315-11eb-a839-00a0985ebbe7",
    "name": "st-8020-1-01",
    "_links": {
      "self": {
        "href": "/api/cluster/nodes/4083be52-5315-11eb-a839-00a0985ebbe7"
      }
    }
  },
  "device_id": "stsw-broc6510-01:15.126",
  "_links": {
    "self": {
      "href": "/api/storage/tape-devices/4083be52-5315-11eb-a839-00a0985ebbe7/stsw-broc6510-01%3A15.126"
    }
  }
},
{
  "node": {
    "uuid": "4083be52-5315-11eb-a839-00a0985ebbe7",
    "name": "st-8020-1-01",
    "_links": {
      "self": {
        "href": "/api/cluster/nodes/4083be52-5315-11eb-a839-00a0985ebbe7"
      }
    }
  },
  "device_id": "stsw-broc6510-01:15.126L1",
  "_links": {
    "self": {
      "href": "/api/storage/tape-devices/4083be52-5315-11eb-a839-00a0985ebbe7/stsw-broc6510-01%3A15.126L1"
    }
  }
}

```

```

    }
  },
  {
    "node": {
      "uuid": "4083be52-5315-11eb-a839-00a0985ebbe7",
      "name": "st-8020-1-01",
      "_links": {
        "self": {
          "href": "/api/cluster/nodes/4083be52-5315-11eb-a839-00a0985ebbe7"
        }
      }
    },
    "device_id": "stsw-broc6510-01:22.126",
    "_links": {
      "self": {
        "href": "/api/storage/tape-devices/4083be52-5315-11eb-a839-00a0985ebbe7/stsw-broc6510-01%3A22.126"
      }
    }
  },
  {
    "node": {
      "uuid": "4083be52-5315-11eb-a839-00a0985ebbe7",
      "name": "st-8020-1-01",
      "_links": {
        "self": {
          "href": "/api/cluster/nodes/4083be52-5315-11eb-a839-00a0985ebbe7"
        }
      }
    },
    "device_id": "stsw-broc6510-01:23.126",
    "_links": {
      "self": {
        "href": "/api/storage/tape-devices/4083be52-5315-11eb-a839-00a0985ebbe7/stsw-broc6510-01%3A23.126"
      }
    }
  },
],
"num_records": 7,
"_links": {
  "self": {
    "href": "/api/storage/tape-devices"
  }
}

```

```
}  
}  
}
```

2) Retrieving a specific tape device from the cluster

The following example returns the requested tape device. If there is no tape with the requested UID, an error is returned.

```
# The API:  
/api/storage/tape-devices/{node.uuid}/{device_id}  
  
# The call:  
curl -X GET "https://<mgmt-ip>/api/storage/tape-devices/5f5275eb-5315-11eb-8ac4-00a0985e0dcf/2d.0" -H "accept: application/hal+json"  
  
# The response:  
{  
  "node": {  
    "uuid": "5f5275eb-5315-11eb-8ac4-00a0985e0dcf",  
    "name": "st-8020-1-02",  
    "_links": {  
      "self": {  
        "href": "/api/cluster/nodes/5f5275eb-5315-11eb-8ac4-00a0985e0dcf"  
      }  
    }  
  },  
  "device_id": "2d.0",  
  "type": "tape",  
  "description": "IBM LTO-6 ULT3580",  
  "alias": {  
    "name": "st7",  
    "mapping": "SN[1068000245]"  
  },  
  "wwnn": "5001697722ee0010",  
  "wwpn": "5001697722ee0011",  
  "serial_number": "1068000245",  
  "interface": "sas",  
  "device_state": "offline",  
  "formats": [  
    "LTO-4/5 Native Density",  
    "LTO-4/5 Compressed",  
    "LTO-6 2.5TB",  
  ]  
}
```

```

    "LTO-6 6.25TB Compressed"
  ],
  "storage_port": {
    "name": "2d"
  },
  "file_number": -1,
  "block_number": -1,
  "residual_count": 0,
  "device_names": [
    {
      "rewind_device": "rst0l",
      "no_rewind_device": "nrst0l",
      "unload_reload_device": "urst0l"
    },
    {
      "rewind_device": "rst0m",
      "no_rewind_device": "nrst0m",
      "unload_reload_device": "urst0m"
    },
    {
      "rewind_device": "rst0h",
      "no_rewind_device": "nrst0h",
      "unload_reload_device": "urst0h"
    },
    {
      "rewind_device": "rst0a",
      "no_rewind_device": "nrst0a",
      "unload_reload_device": "urst0a"
    }
  ],
  "reservation_type": "off",
  "_links": {
    "self": {
      "href": "/api/storage/tape-devices/5f5275eb-5315-11eb-8ac4-00a0985e0dcf/2d.0"
    }
  }
}

```

Retrieve tape devices

GET /storage/tape-devices

Introduced In: 9.9

Retrieves a collection of tape devices.

Related ONTAP commands

- `storage tape show`

Learn more

- [DOC /storage/tape-devices](#)

Parameters

Name	Type	In	Required	Description
block_number	integer	query	False	Filter by block_number
interface	string	query	False	Filter by interface
storage_port.name	string	query	False	Filter by storage_port.name
wwpn	string	query	False	Filter by wwpn
device_names.rewind_device	string	query	False	Filter by device_names.rewind_device
device_names.unload_reload_device	string	query	False	Filter by device_names.unload_reload_device
device_names.no_rewind_device	string	query	False	Filter by device_names.no_rewind_device
file_number	integer	query	False	Filter by file_number
node.uuid	string	query	False	Filter by node.uuid
node.name	string	query	False	Filter by node.name
reservation_type	string	query	False	Filter by reservation_type
serial_number	string	query	False	Filter by serial_number

Name	Type	In	Required	Description
device_state	string	query	False	Filter by device_state
residual_count	integer	query	False	Filter by residual_count
alias.name	string	query	False	Filter by alias.name
alias.mapping	string	query	False	Filter by alias.mapping
type	string	query	False	Filter by type
device_id	string	query	False	Filter by device_id
description	string	query	False	Filter by description
wwnn	string	query	False	Filter by wwnn
formats	string	query	False	Filter by formats
fields	array[string]	query	False	Specify the fields to return.
max_records	integer	query	False	Limit the number of records returned.
return_records	boolean	query	False	<p>The default is true for GET calls. When set to false, only the number of records is returned.</p> <ul style="list-style-type: none"> • Default value: 1

Name	Type	In	Required	Description
return_timeout	integer	query	False	<p>The number of seconds to allow the call to execute before returning. When iterating over a collection, the default is 15 seconds. ONTAP returns earlier if either max records or the end of the collection is reached.</p> <ul style="list-style-type: none"> • Default value: 1 • Max value: 120 • Min value: 0
order_by	array[string]	query	False	Order results by specified fields and optional [asc

Response

Status: 200, Ok

Name	Type	Description
_links	_links	
num_records	integer	Number of records
records	array[tape_device]	

Example response

```
{
  "_links": {
    "next": {
      "href": "/api/resourcelink"
    },
    "self": {
      "href": "/api/resourcelink"
    }
  },
  "records": {
    "alias": {
      "mapping": "SN[10WT000933]",
      "name": "st6"
    },
    "block_number": 0,
    "description": "QUANTUM LTO-8 ULTRIUM",
    "device_id": "1a.0",
    "device_names": {
      "no_rewind_device": "nrst6l",
      "rewind_device": "rst6l",
      "unload_reload_device": "urst6l"
    },
    "device_state": "read_write_enabled",
    "file_number": 0,
    "formats": [
      "LTO-7 6TB",
      "LTO-7 15TB Compressed",
      "LTO-8 12TB",
      "LTO-8 30TB Compressed"
    ],
    "interface": "sas",
    "node": {
      "_links": {
        "self": {
          "href": "/api/resourcelink"
        }
      },
      "name": "node1",
      "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"
    },
    "reservation_type": "off",
    "residual_count": 0,
    "serial_number": "10WT00093",
    "storage_port": {
```

```
    "name": "2b"
  },
  "type": "tape",
  "wwnn": "500507631295741c",
  "wwpn": "500507631295741c"
}
```

Error

Status: Default, Error

Name	Type	Description
error	error	

Example error

```
{
  "error": {
    "arguments": {
      "code": "string",
      "message": "string"
    },
    "code": "4",
    "message": "entry doesn't exist",
    "target": "uuid"
  }
}
```

Definitions

See Definitions

href

Name	Type	Description
href	string	

_links

Name	Type	Description
next	href	
self	href	

alias

Name	Type	Description
mapping	string	Alias mapping.
name	string	Alias name.

device_names

Name	Type	Description
no_rewind_device	string	Device name for no rewind.
rewind_device	string	Device name for rewind.
unload_reload_device	string	Device name for unload or reload operations.

_links

Name	Type	Description
self	href	

node

Name	Type	Description
_links	_links	
name	string	
uuid	string	

storage_port

Name	Type	Description
name	string	Initiator port.

tape_device

Name	Type	Description
alias	alias	
block_number	integer	Block number.
description	string	
device_id	string	
device_names	array[device_names]	
device_state	string	Operational state of the device.
file_number	integer	File number.
formats	array[string]	Tape cartridge format.
interface	string	Device interface type.
node	node	
reservation_type	string	
residual_count	integer	Residual count of the last I/O operation.
serial_number	string	
storage_port	storage_port	
type	string	Device type.
wwnn	string	World Wide Node Name.
wwpn	string	World Wide Port Name.

error_arguments

Name	Type	Description
code	string	Argument code
message	string	Message argument

error

Name	Type	Description
arguments	array[error_arguments]	Message arguments
code	string	Error code
message	string	Error message
target	string	The target parameter that caused the error.

Retrieve a tape device

GET /storage/tape-devices/{node.uuid}/{device_id}

Introduced In: 9.9

Retrieves a specific tape.

Related ONTAP commands

- `storage tape show`

Learn more

- [DOC /storage/tape-devices](#)

Parameters

Name	Type	In	Required	Description
node.uuid	string	path	True	Node UUID
device_id	string	path	True	Device ID
fields	array[string]	query	False	Specify the fields to return.

Response

Status: 200, Ok

Name	Type	Description
alias	alias	

Name	Type	Description
block_number	integer	Block number.
description	string	
device_id	string	
device_names	array[device_names]	
device_state	string	Operational state of the device.
file_number	integer	File number.
formats	array[string]	Tape cartridge format.
interface	string	Device interface type.
node	node	
reservation_type	string	
residual_count	integer	Residual count of the last I/O operation.
serial_number	string	
storage_port	storage_port	
type	string	Device type.
wwnn	string	World Wide Node Name.
wwpn	string	World Wide Port Name.

Example response

```
{
  "alias": {
    "mapping": "SN[10WT000933]",
    "name": "st6"
  },
  "block_number": 0,
  "description": "QUANTUM LTO-8 ULTRIUM",
  "device_id": "1a.0",
  "device_names": {
    "no_rewind_device": "nrst6l",
    "rewind_device": "rst6l",
    "unload_reload_device": "urst6l"
  },
  "device_state": "read_write_enabled",
  "file_number": 0,
  "formats": [
    "LTO-7 6TB",
    "LTO-7 15TB Compressed",
    "LTO-8 12TB",
    "LTO-8 30TB Compressed"
  ],
  "interface": "sas",
  "node": {
    "_links": {
      "self": {
        "href": "/api/resourcelink"
      }
    },
    "name": "node1",
    "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"
  },
  "reservation_type": "off",
  "residual_count": 0,
  "serial_number": "10WT00093",
  "storage_port": {
    "name": "2b"
  },
  "type": "tape",
  "wwnn": "500507631295741c",
  "wwpn": "500507631295741c"
}
```

Error

Status: Default, Error

Name	Type	Description
error	error	

Example error

```
{
  "error": {
    "arguments": {
      "code": "string",
      "message": "string"
    },
    "code": "4",
    "message": "entry doesn't exist",
    "target": "uuid"
  }
}
```

Definitions

See Definitions

alias

Name	Type	Description
mapping	string	Alias mapping.
name	string	Alias name.

device_names

Name	Type	Description
no_rewind_device	string	Device name for no rewind.
rewind_device	string	Device name for rewind.
unload_reload_device	string	Device name for unload or reload operations.

href

Name	Type	Description
href	string	

_links

Name	Type	Description
self	href	

node

Name	Type	Description
_links	_links	
name	string	
uuid	string	

storage_port

Name	Type	Description
name	string	Initiator port.

error_arguments

Name	Type	Description
code	string	Argument code
message	string	Message argument

error

Name	Type	Description
arguments	array[error_arguments]	Message arguments
code	string	Error code
message	string	Error message
target	string	The target parameter that caused the error.

Copyright information

Copyright © 2024 NetApp, Inc. All Rights Reserved. Printed in the U.S. No part of this document covered by copyright may be reproduced in any form or by any means—graphic, electronic, or mechanical, including photocopying, recording, taping, or storage in an electronic retrieval system—without prior written permission of the copyright owner.

Software derived from copyrighted NetApp material is subject to the following license and disclaimer:

THIS SOFTWARE IS PROVIDED BY NETAPP “AS IS” AND WITHOUT ANY EXPRESS OR IMPLIED WARRANTIES, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE, WHICH ARE HEREBY DISCLAIMED. IN NO EVENT SHALL NETAPP BE LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO, PROCUREMENT OF SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA, OR PROFITS; OR BUSINESS INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE) ARISING IN ANY WAY OUT OF THE USE OF THIS SOFTWARE, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE.

NetApp reserves the right to change any products described herein at any time, and without notice. NetApp assumes no responsibility or liability arising from the use of products described herein, except as expressly agreed to in writing by NetApp. The use or purchase of this product does not convey a license under any patent rights, trademark rights, or any other intellectual property rights of NetApp.

The product described in this manual may be protected by one or more U.S. patents, foreign patents, or pending applications.

LIMITED RIGHTS LEGEND: Use, duplication, or disclosure by the government is subject to restrictions as set forth in subparagraph (b)(3) of the Rights in Technical Data -Noncommercial Items at DFARS 252.227-7013 (FEB 2014) and FAR 52.227-19 (DEC 2007).

Data contained herein pertains to a commercial product and/or commercial service (as defined in FAR 2.101) and is proprietary to NetApp, Inc. All NetApp technical data and computer software provided under this Agreement is commercial in nature and developed solely at private expense. The U.S. Government has a non-exclusive, non-transferrable, nonsublicensable, worldwide, limited irrevocable license to use the Data only in connection with and in support of the U.S. Government contract under which the Data was delivered. Except as provided herein, the Data may not be used, disclosed, reproduced, modified, performed, or displayed without the prior written approval of NetApp, Inc. United States Government license rights for the Department of Defense are limited to those rights identified in DFARS clause 252.227-7015(b) (FEB 2014).

Trademark information

NETAPP, the NETAPP logo, and the marks listed at <http://www.netapp.com/TM> are trademarks of NetApp, Inc. Other company and product names may be trademarks of their respective owners.