



Manage security-related operations

REST API reference

NetApp
September 09, 2025

This PDF was generated from https://docs.netapp.com/us-en/ontap-restapi-9161/security_endpoint_overview.html on September 09, 2025. Always check docs.netapp.com for the latest.

Table of Contents

Manage security-related operations	1
Security endpoint overview	1
Overview	1
"onboard_key_manager_configurable_status" object	1
"software_data_encryption" object	1
"fips" object	1
"tls" object	2
"management_protocols" object	2
GET Examples	2

Manage security-related operations

Security endpoint overview

Overview

You can use this API for various cluster-wide security-related operations.

"onboard_key_manager_configurable_status" object

Use this API to retrieve details of whether or not the Onboard Key Manager can be configured on the cluster.

– GET /api/security

– GET /api/security?fields=onboard_key_manager_configurable_status

"software_data_encryption" object

Contains software data encryption related information.

The following APIs can be used to enable or disable and obtain default software data at rest encryption values:

– PATCH /api/security -d '{ "software_data_encryption.disabled_by_default" : true }'

– PATCH /api/security -d '{ "software_data_encryption.disabled_by_default" : false }'

– GET /api/security

– GET /api/security?fields=software_data_encryption

Platform Specifics

Unified ONTAP

A PATCH request on this API using the parameter "software_data_encryption.conversion_enabled" triggers the conversion of all non-encrypted metadata volumes to encrypted metadata volumes and all non-NAE aggregates to NAE aggregates. For the conversion to start, the cluster must have either Onboard Key Manager or an external key manager set up and the aggregates should either be empty or have only metadata volumes. No data volumes should be present in any of the aggregates. For MetroCluster configurations, the PATCH request will fail if the cluster is in the switchover state.

"fips" object

Contains FIPS mode information.

A PATCH request on this API using the parameter "fips.enabled" switches the system from using the default cryptographic module software implementations to validated ones or vice versa, where applicable. If the value of the parameter is "true" and unapproved algorithms are configured as permitted in relevant subsystems, those algorithms will be disabled in the relevant subsystem configurations. If "false", there will be no implied change to the relevant subsystem configurations.

– GET /api/security

– GET /api/security?fields=fips
– PATCH /api/security -d '{ "fips.enabled" : true }'
– PATCH /api/security -d '{ "fips.enabled" : false }'

"tls" object

Contains TLS configuration information.

A PATCH request on this API using the parameter "tls.cipher_suites" and/or "tls.protocol_versions" configures the permissible cipher suites and/or protocol versions for all TLS-enabled applications in the system. All protocol versions at or above the lowest version level specified are enabled, including those that are not explicitly specified.

– GET /api/security

– GET /api/security?fields=tls

– PATCH /api/security -d '{ "tls" : { "protocol_versions" : ["TLSv1.3", "TLSv1.2"], "cipher_suites" : ["TLS_ECDHE_RSA_WITH_AES_256_GCM_SHA384", "TLS_ECDHE_RSA_WITH_AES_128_GCM_SHA256"] } }'

"management_protocols" object

Contains Security Protocols information.

This security protocols endpoint is used to retrieve and configure security protocols.

– GET /api/security

– GET /api/security?fields=management_protocols

– PATCH /api/security -d '{ "management_protocols" : { "rsh_enabled" : true } }'

– PATCH /api/security -d '{ "management_protocols" : { "rsh_enabled" : false } }'

– PATCH /api/security -d '{ "management_protocols" : { "telnet_enabled" : true } }'

– PATCH /api/security -d '{ "management_protocols" : { "telnet_enabled" : false } }'

– PATCH /api/security -d '{ "management_protocols" : { "rsh_enabled" : true, "telnet_enabled" : true } }'

GET Examples

Retrieving information about the security configured on the cluster

The following example shows how to retrieve the configuration of the cluster.

```
# The API:  
GET /api/security:  
  
# The call:
```

```

curl -X GET 'https://<mgmt-ip>/api/security?fields=' -H 'accept: application/hal+json'

# The response:
{
  "onboard_key_manager_configurable_status": {
    "supported": false,
    "message": "Onboard Key Manager cannot be configured on the cluster. There are no self-encrypting disks in the cluster, and the following nodes do not support volume granular encryption: ntap-vsim2.",
    "code": 65537300
  },
  "software_data_encryption": {
    "conversion_enabled": false,
    "disabled_by_default": false,
    "encryption_state": "unencrypted"
  },
  "fips": {
    "enabled": false
  },
  "tls": {
    "cipher_suites": [
      "TLS_RSA_WITH_AES_128_CCM",
      "TLS_RSA_WITH_AES_128_CCM_8",
      "TLS_RSA_WITH_AES_128_GCM_SHA256",
      "TLS_RSA_WITH_AES_128_CBC_SHA",
      "TLS_RSA_WITH_AES_128_CBC_SHA256",
      "TLS_RSA_WITH_AES_256_CCM",
      "TLS_RSA_WITH_AES_256_CCM_8",
      "TLS_RSA_WITH_AES_256_GCM_SHA384",
      "TLS_RSA_WITH_AES_256_CBC_SHA",
      "TLS_RSA_WITH_AES_256_CBC_SHA256",
      "TLS_RSA_WITH_ARIA_128_GCM_SHA256",
      "TLS_RSA_WITH_ARIA_256_GCM_SHA384",
      "TLS_RSA_WITH_CAMELLIA_128_CBC_SHA",
      "TLS_RSA_WITH_CAMELLIA_128_CBC_SHA256",
      "TLS_RSA_WITH_CAMELLIA_256_CBC_SHA",
      "TLS_RSA_WITH_CAMELLIA_256_CBC_SHA256",
      "TLS_DHE_DSS_WITH_AES_128_GCM_SHA256",
      "TLS_DHE_DSS_WITH_AES_128_CBC_SHA",
      "TLS_DHE_DSS_WITH_AES_128_CBC_SHA256",
      "TLS_DHE_DSS_WITH_AES_256_GCM_SHA384",
      "TLS_DHE_DSS_WITH_AES_256_CBC_SHA",
      "TLS_DHE_DSS_WITH_AES_256_CBC_SHA256",
      "TLS_DHE_DSS_WITH_ARIA_128_GCM_SHA256",
      "TLS_DHE_DSS_WITH_ARIA_256_GCM_SHA384",
      "TLS_DHE_DSS_WITH_ARIA_256_GCM_SHA384",
      "TLS_DHE_DSS_WITH_ARIA_256_CBC_SHA"
    ]
  }
}

```

```
"TLS_DHE_DSS_WITH_CAMELLIA_128_CBC_SHA",
"TLS_DHE_DSS_WITH_CAMELLIA_128_CBC_SHA256",
"TLS_DHE_DSS_WITH_CAMELLIA_256_CBC_SHA",
"TLS_DHE_DSS_WITH_CAMELLIA_256_CBC_SHA256",
"TLS_DHE_PSK_WITH_AES_128_CBC_SHA",
"TLS_DHE_PSK_WITH_AES_128_CBC_SHA256",
"TLS_DHE_PSK_WITH_AES_128_CCM",
"TLS_PSK_DHE_WITH_AES_128_CCM_8",
"TLS_DHE_PSK_WITH_AES_128_GCM_SHA256",
"TLS_DHE_PSK_WITH_AES_256_CBC_SHA",
"TLS_DHE_PSK_WITH_AES_256_CBC_SHA384",
"TLS_DHE_PSK_WITH_AES_256_CCM",
"TLS_PSK_DHE_WITH_AES_256_CCM_8",
"TLS_DHE_PSK_WITH_AES_256_GCM_SHA384",
"TLS_DHE_PSK_WITH_ARIA_128_GCM_SHA256",
"TLS_DHE_PSK_WITH_ARIA_256_GCM_SHA384",
"TLS_DHE_PSK_WITH_CAMELLIA_128_CBC_SHA256",
"TLS_DHE_PSK_WITH_CAMELLIA_256_CBC_SHA384",
"TLS_DHE_PSK_WITH_CHACHA20_POLY1305_SHA256",
"TLS_DHE_RSA_WITH_AES_128_CCM",
"TLS_DHE_RSA_WITH_AES_128_CCM_8",
"TLS_DHE_RSA_WITH_AES_128_GCM_SHA256",
"TLS_DHE_RSA_WITH_AES_128_CBC_SHA",
"TLS_DHE_RSA_WITH_AES_128_CBC_SHA256",
"TLS_DHE_RSA_WITH_AES_256_CCM",
"TLS_DHE_RSA_WITH_AES_256_CCM_8",
"TLS_DHE_RSA_WITH_AES_256_GCM_SHA384",
"TLS_DHE_RSA_WITH_AES_256_CBC_SHA",
"TLS_DHE_RSA_WITH_AES_256_CBC_SHA256",
"TLS_DHE_RSA_WITH_ARIA_128_GCM_SHA256",
"TLS_DHE_RSA_WITH_ARIA_256_GCM_SHA384",
"TLS_DHE_RSA_WITH_CAMELLIA_128_CBC_SHA",
"TLS_DHE_RSA_WITH_CAMELLIA_128_CBC_SHA256",
"TLS_DHE_RSA_WITH_CAMELLIA_256_CBC_SHA",
"TLS_DHE_RSA_WITH_CAMELLIA_256_CBC_SHA256",
"TLS_DHE_RSA_WITH_CHACHA20_POLY1305_SHA256",
"TLS_ECDHE_RSA_WITH_ARIA_128_GCM_SHA256",
"TLS_ECDHE_RSA_WITH_ARIA_256_GCM_SHA384",
"TLS_ECDHE_ECDSA_WITH_AES_128_CCM",
"TLS_ECDHE_ECDSA_WITH_AES_128_CCM_8",
"TLS_ECDHE_ECDSA_WITH_AES_128_GCM_SHA256",
"TLS_ECDHE_ECDSA_WITH_AES_128_CBC_SHA",
"TLS_ECDHE_ECDSA_WITH_AES_128_CBC_SHA256",
"TLS_ECDHE_ECDSA_WITH_AES_256_CCM",
"TLS_ECDHE_ECDSA_WITH_AES_256_CCM_8",
"TLS_ECDHE_ECDSA_WITH_AES_256_GCM_SHA384",
```

```
"TLS_ECDHE_ECDSA_WITH_AES_256_CBC_SHA",
"TLS_ECDHE_ECDSA_WITH_AES_256_CBC_SHA384",
"TLS_ECDHE_ECDSA_WITH_ARIA_128_GCM_SHA256",
"TLS_ECDHE_ECDSA_WITH_ARIA_256_GCM_SHA384",
"TLS_ECDHE_ECDSA_WITH_CAMELLIA_128_CBC_SHA256",
"TLS_ECDHE_ECDSA_WITH_CAMELLIA_256_CBC_SHA384",
"TLS_ECDHE_ECDSA_WITH_CHACHA20_POLY1305_SHA256",
"TLS_ECDHE_PSK_WITH_AES_128_CBC_SHA",
"TLS_ECDHE_PSK_WITH_AES_128_CBC_SHA256",
"TLS_ECDHE_PSK_WITH_AES_256_CBC_SHA",
"TLS_ECDHE_PSK_WITH_AES_256_CBC_SHA384",
"TLS_ECDHE_PSK_WITH_CAMELLIA_128_CBC_SHA256",
"TLS_ECDHE_PSK_WITH_CAMELLIA_256_CBC_SHA384",
"TLS_ECDHE_PSK_WITH_CHACHA20_POLY1305_SHA256",
"TLS_ECDHE_RSA_WITH_AES_128_GCM_SHA256",
"TLS_ECDHE_RSA_WITH_AES_128_CBC_SHA",
"TLS_ECDHE_RSA_WITH_AES_128_CBC_SHA256",
"TLS_ECDHE_RSA_WITH_AES_256_GCM_SHA384",
"TLS_ECDHE_RSA_WITH_AES_256_CBC_SHA",
"TLS_ECDHE_RSA_WITH_AES_256_CBC_SHA384",
"TLS_ECDHE_RSA_WITH_CAMELLIA_128_CBC_SHA256",
"TLS_ECDHE_RSA_WITH_CAMELLIA_256_CBC_SHA384",
"TLS_ECDHE_RSA_WITH_CHACHA20_POLY1305_SHA256",
"TLS_PSK_WITH_AES_128_CBC_SHA",
"TLS_PSK_WITH_AES_128_CBC_SHA256",
"TLS_PSK_WITH_AES_128_CCM",
"TLS_PSK_WITH_AES_128_CCM_8",
"TLS_PSK_WITH_AES_128_GCM_SHA256",
"TLS_PSK_WITH_AES_256_CBC_SHA",
"TLS_PSK_WITH_AES_256_CBC_SHA384",
"TLS_PSK_WITH_AES_256_CCM",
"TLS_PSK_WITH_AES_256_CCM_8",
"TLS_PSK_WITH_AES_256_GCM_SHA384",
"TLS_PSK_WITH_ARIA_128_GCM_SHA256",
"TLS_PSK_WITH_ARIA_256_GCM_SHA384",
"TLS_PSK_WITH_CAMELLIA_128_CBC_SHA256",
"TLS_PSK_WITH_CAMELLIA_256_CBC_SHA384",
"TLS_PSK_WITH_CHACHA20_POLY1305_SHA256",
"TLS_RSA_PSK_WITH_AES_128_CBC_SHA",
"TLS_RSA_PSK_WITH_AES_128_CBC_SHA256",
"TLS_RSA_PSK_WITH_AES_128_GCM_SHA256",
"TLS_RSA_PSK_WITH_AES_256_CBC_SHA",
"TLS_RSA_PSK_WITH_AES_256_CBC_SHA384",
"TLS_RSA_PSK_WITH_AES_256_GCM_SHA384",
"TLS_RSA_PSK_WITH_ARIA_128_GCM_SHA256",
"TLS_RSA_PSK_WITH_ARIA_256_GCM_SHA384",
```

```

    "TLS_RSA_PSK_WITH_CAMELLIA_128_CBC_SHA256",
    "TLS_RSA_PSK_WITH_CAMELLIA_256_CBC_SHA384",
    "TLS_RSA_PSK_WITH_CHACHA20_POLY1305_SHA256",
    "TLS_SRPSHA_WITH_AES_128_CBC_SHA",
    "TLS_SRPSHA_WITH_AES_256_CBC_SHA",
    "TLS_SRPSHA_DSS_WITH_AES_128_CBC_SHA",
    "TLS_SRPSHA_DSS_WITH_AES_256_CBC_SHA",
    "TLS_SRPSHA_RSA_WITH_AES_128_CBC_SHA",
    "TLS_SRPSHA_RSA_WITH_AES_256_CBC_SHA",
    "TLS_AES_128_GCM_SHA256",
    "TLS_AES_256_GCM_SHA384",
    "TLS_CHACHA20_POLY1305_SHA256"
],
"protocol_versions": [
    "TLSv1.3",
    "TLSv1.2"
]
},
"management_protocols": {
    "rsh_enabled": false,
    "telnet_enabled": false
}
}

```

```

''''

== PATCH Examples

==== Enabling software encryption conversion in the cluster

The following example shows how to enable software encryption conversion
in the cluster.

= The API:

PATCH /api/security

= The call

curl -X PATCH "https://++<mgmt_ip>++/api/security" -d '{
"software_data_encryption.conversion_enabled" : true }'++</mgmt_ip>++

= The response:

```

```
{
  "job": {
    "uuid": "ebcbd82d-1cd4-11ea-8f75-005056ac4adc",
    "_links": {
      "self": {
        "href": "/api/cluster/jobs/ebcbd82d-1cd4-11ea-8f75-005056ac4adc"
      }
    }
  }
}
```

This returns a job UUID. A subsequent GET for this job UUID returns details of the job.

= The call

```
curl -X GET "https://++<mgmt_ip>++/api/cluster/jobs/ebcbd82d-1cd4-11ea-8f75-005056ac4adc"++</mgmt_ip>++
```

= The response:

```
{
  "uuid": "ebcbd82d-1cd4-11ea-8f75-005056ac4adc",
  "description": "PATCH /api/security",
  "state": "success",
  "message": "success",
  "code": 0,
  "start_time": "2019-12-12T06:45:40-05:00",
  "end_time": "2019-12-12T06:45:40-05:00",
  "_links": {
    "self": {
      "href": "/api/cluster/jobs/ebcbd82d-1cd4-11ea-8f75-005056ac4adc"
    }
  }
}
```

[discrete]

==== Enabling FIPS mode in the cluster

The following example shows how to enable FIPS mode in the cluster.

= The API:

PATCH /api/security

= The call

```
curl -X PATCH "https://+++<mgmt_ip>++/api/security" -d '{ "fips.enabled": true }'+++</mgmt_ip>+++
```

= The response:

```
{  
  "job": {  
    "uuid": "8e7f59ee-a9c4-4faa-9513-bef689bbf2c2",  
    "_links": {  
      "self": {  
        "href": "/api/cluster/jobs/8e7f59ee-a9c4-4faa-9513-bef689bbf2c2"  
      }  
    }  
  }  
}
```

This returns a job UUID. A subsequent GET for this job UUID returns details of the job.

= The call

```
curl -X GET "https://+++<mgmt_ip>++/api/cluster/jobs/8e7f59ee-a9c4-4faa-9513-bef689bbf2c2"+++</mgmt_ip>+++
```

= The response:

```
{  
  "uuid": "8e7f59ee-a9c4-4faa-9513-bef689bbf2c2",  
  "description": "PATCH /api/security",  
  "state": "success",  
  "message": "success",  
  "code": 0,  
  "start_time": "2020-04-28T06:55:40-05:00",  
  "end_time": "2020-04-28T06:55:41-05:00",  
  "_links": {  
    "self": {  
      "href": "/api/cluster/jobs/8e7f59ee-a9c4-4faa-9513-bef689bbf2c2"  
    }  
  }  
}
```

[discrete]

==== Configuring permissible TLS protocols and cipher suites in the cluster

The following example shows how to configure the cluster to only allow TLSv1.3 & TLSv1.2 with selected cipher suites.

= The API:

```
PATCH /api/security
```

= The call

```
curl -X PATCH "https://++<mgmt_ip>++/api/security" -d '{ "tls" : { "protocol_versions" : ["TLSv1.3", "TLSv1.2"], "cipher_suites" : ["TLS_ECDHE_RSA_WITH_AES_256_GCM_SHA384", "TLS_AES_256_GCM_SHA384"] } }'++</mgmt_ip>++
```

= The response:

```
{
  "job": {
    "uuid": "b45b6290-f4f2-442a-aa0e-4d3ffefe5e0d",
    "_links": {
      "self": {
        "href": "/api/cluster/jobs/b45b6290-f4f2-442a-aa0e-4d3ffefe5e0d"
      }
    }
  }
}
```

This returns a job UUID. A subsequent GET for this job UUID returns details of the job.

= The call

```
curl -X GET "https://++<mgmt_ip>++/api/cluster/jobs/b45b6290-f4f2-442a-aa0e-4d3ffefe5e0d"++</mgmt_ip>++
```

= The response:

```
{
  "uuid": "b45b6290-f4f2-442a-aa0e-4d3ffefe5e0d",
  "description": "PATCH /api/security",
  "state": "success",
  "message": "success",
  "code": 0,
  "start_time": "2021-03-22T08:52:50-05:00",
  "end_time": "2021-03-22T08:52:51-05:00",
  "_links": {
    "self": {
      "href": "/api/cluster/jobs/b45b6290-f4f2-442a-aa0e-4d3ffefe5e0d"
    }
  }
}
```

```

}

}

[discrete]
==== Enabling security protocols in the cluster

The following example shows how to enable the security protocol rsh in the
cluster.

= The API:

PATCH /api/security

= The call

curl -X PATCH "https://+++<mgmt_ip>+++/api/security" -d '{
"management_protocols" : { "rsh_enabled" : true } }'+++</mgmt_ip>+++

= The response

{
"job": {
"uuid": "2980ba28-adab-11eb-8fa3-005056bbfa84",
"_links": {
"self": {
"href": "/api/cluster/jobs/2980ba28-adab-11eb-8fa3-005056bbfa84"
}
}
}
}

= The call:

curl -H "accept: application/hal+json" -X GET "https://+++<mgmt-
ip>+++/api/security/?fields=management_protocols"+++</mgmt-ip>+++

= The response:

{
"management_protocols": {
"rsh_enabled": false,
"telnet_enabled": false
},
"_links": {
"self": {
"href": "/api/security"
}
}
}

```

```
}

}

'''



[[ID46c01f871b2ae21427caca115df8221b]]
= Retrieve information about security configured on the cluster

[.api-doc-operation .api-doc-operation-get]#GET# [.api-doc-code-
block]#/security`#



*Introduced In:* 9.7

Retrieves information about the security configured on the cluster.

== Related ONTAP commands

* `security config show`


== Parameters

[cols=5*,options=header]
|===
| Name
| Type
| In
| Required
| Description

| fields
| array[string]
| query
| False
a|Specify the fields to return.

|===
== Response
```

Status: 200, Ok

```
[cols=3*,options=header]
|===
|Name
|Type
|Description

|_links
|link:#_links[_links]
a|fips
|link:#fips[fips]
a|Cluster-wide Federal Information Processing Standards (FIPS) mode
information.

|management_protocols
|link:#management_protocols[management_protocols]
a|Cluster-wide security protocols related information.

|onboard_key_manager_configurable_status
|link:#onboard_key_manager_configurable_status[onboard_key_manager_configurable_status]
a|Indicates whether the Onboard Key Manager can be configured in the
cluster.

|software_data_encryption
|link:#software_data_encryption[software_data_encryption]
a|Cluster-wide software data encryption related information.

|tls
|link:#tls[tls]
a|Cluster-wide Transport Layer Security (TLS) configuration information

|===
.Example response
[%collapsible%closed]
=====
[source,json,subs=+macros]
{
  "_links": {
```

```

"self": {
  "href": "/api/resourcelink"
}
},
"onboard_key_manager_configurable_status": {
  "code": 65537300,
  "message": "No platform support for volume encryption in following
nodes - node1, node2."
},
"software_data_encryption": {
  "encryption_state": "string"
},
"tls": {
  "cipher_suites": [
    "TLS_ECDHE_RSA_WITH_AES_256_GCM_SHA384"
  ],
  "protocol_versions": [
    "string"
  ]
}
}
=====

== Error

```

Status: Default, Error

```

[cols=3*,options=header]
| ====
| Name
| Type
| Description

| error
| link:#returned_error[returned_error]
a|
| ====

.Example error
[%collapsible%closed]
=====

[source,json,subs=+macros]
{

```

```

"error": {
  "arguments": [
    {
      "code": "string",
      "message": "string"
    }
  ],
  "code": "4",
  "message": "entry doesn't exist",
  "target": "uuid"
}
}

=====

== Definitions

[.api-def-first-level]
. See Definitions
[%collapsible%closed]
//Start collapsible Definitions block
=====

[#href]
[.api-collapsible-fifth-title]
href

[cols=3*,options=header]
| ====
| Name
| Type
| Description

| href
| string
a|
| ====

[_links]
[.api-collapsible-fifth-title]
_links

[cols=3*,options=header]
| ====
| Name
| Type

```

```
| Description
```

```
| self
| link:#href[href]
a|
```

```
| ===
```

```
[#fips]
[.api-collapsible-fifth-title]
fips
```

Cluster-wide Federal Information Processing Standards (FIPS) mode information.

```
[cols=3*,options=header]
```

```
| ===
```

```
| Name
```

```
| Type
```

```
| Description
```

```
| enabled
```

```
| boolean
```

a| Indicates whether or not the software FIPS mode is enabled on the cluster. Our FIPS compliance involves configuring the use of only approved algorithms in applicable contexts (for example TLS), as well as the use of formally validated cryptographic module software implementations, where applicable. The US government documents concerning FIPS 140-2 outline the relevant security policies in detail.

```
| ===
```

```
[#management_protocols]
```

```
[.api-collapsible-fifth-title]
```

```
management_protocols
```

Cluster-wide security protocols related information.

```
[cols=3*,options=header]
```

```
| ===
```

```
| Name
```

```
| Type
```

| Description

| rsh_enabled

| boolean

a| Indicates whether or not security protocol rsh is enabled on the cluster.

| telnet_enabled

| boolean

a| Indicates whether or not security protocol telnet is enabled on the cluster.

| ===

[#onboard_key_manager_configurable_status]

[.api-collapsible-fifth-title]

onboard_key_manager_configurable_status

Indicates whether the Onboard Key Manager can be configured in the cluster.

[cols=3*, options=header]

| ===

| Name

| Type

| Description

| code

| integer

a| Code corresponding to the status message. Returns a 0 if the Onboard Key Manager can be configured in the cluster.

| message

| string

a| Reason that Onboard Key Manager cannot be configured in the cluster.

| supported

| boolean

a| Set to true if the Onboard Key Manager can be configured in the cluster.

|====

```
[#software_data_encryption]
[.api-collapsible-fifth-title]
software_data_encryption
```

Cluster-wide software data encryption related information.

```
[cols=3*,options=header]
```

|====

| Name

| Type

| Description

|conversion_enabled

|boolean

a|Indicates whether or not software encryption conversion is enabled on the cluster. A PATCH request initiates the conversion of all non-encrypted metadata volumes in the cluster to encrypted metadata volumes and all non-NAE aggregates to NAE aggregates. For the PATCH request to start, the cluster must have either an Onboard or an external key manager set up and the aggregates should either be empty or have only metadata volumes. No data volumes should be present in any of the aggregates in the cluster. For MetroCluster configurations, a PATCH request enables conversion on all the aggregates and metadata volumes of both local and remote clusters and is not allowed when the MetroCluster is in switchover state.

|disabled_by_default

|boolean

a|Indicates whether or not default software data at rest encryption is disabled on the cluster.

|encryption_state

|string

a|Software data encryption state.

encrypted ‐ All the volumes are encrypted.

encrypting ‐ Encryption conversion operation is in progress.

partial ‐ Some volumes are encrypted, and others remains in plain text.

rekeying ‐ All volumes are currently being encrypted with a new key.

unencrypted ‐ None of the volumes are encrypted.

conversion_paused ‐ Encryption conversion operation is paused on one or more volumes.

```
rekey_paused &dash; Encryption rekey operation is paused on one or more volumes.
```

```
| rekey  
| boolean  
a|
```

```
| ===
```

```
[#tls]  
.api-collapsible-fifth-title]  
tls
```

Cluster-wide Transport Layer Security (TLS) configuration information

```
[cols=3*,options=header]  
| ===  
| Name  
| Type  
| Description
```

```
| cipher_suites  
| array[string]  
a|Names a cipher suite that the system can select during TLS handshakes. A list of available options can be found on the Internet Assigned Number Authority (IANA) website.
```

```
| protocol_versions  
| array[string]  
a|Names a TLS protocol version that the system can select during TLS handshakes. The use of SSLv3 or TLSv1 is discouraged.
```

```
| ===
```

```
[#error_arguments]  
.api-collapsible-fifth-title]  
error_arguments
```

```
[cols=3*,options=header]  
| ===  
| Name
```

```
| Type
| Description

| code
| string
a|Argument code

| message
| string
a|Message argument

| ===

[#returned_error]
[.api-collapsible-fifth-title]
returned_error

[cols=3*, options=header]
| ===
| Name
| Type
| Description

| arguments
| array[link:#error_arguments[error_arguments]]
a|Message arguments

| code
| string
a|Error code

| message
| string
a|Error message

| target
| string
a|The target parameter that caused the error.

| ===
```

```
//end collapsible .Definitions block
=====

[[ID1a5d3038b88973c1fbe3a75939de16e8]]
= Update the software FIPS mode or enable conversion of non-encrypted
metadata volumes non-NAE aggregates

[.api-doc-operation .api-doc-operation-patch]#PATCH# [.api-doc-code-
block]#`/security`#
```

Introduced In: 9.8

Updates the software FIPS mode or modifies software data encryption.

== Platform Specifics

== Unified ONTAP

The PATCH request can be used to enable conversion of non-encrypted metadata volumes to encrypted metadata volumes and non-NAE aggregates to NAE aggregates.

== Related ONTAP commands

* `security config modify`

== Parameters

```
[cols=5*,options=header]
|===
| Name
| Type
| In
| Required
| Description

|return_timeout
|integer
|query
|False
a|The number of seconds to allow the call to execute before returning.
```

When doing a POST, PATCH, or DELETE operation on a single record, the default is 0 seconds. This means that if an asynchronous operation is started, the server immediately returns HTTP code 202 (Accepted) along with a link to the job. If a non-zero value is specified for POST, PATCH, or DELETE operations, ONTAP waits that length of time to see if the job completes so it can return something other than 202.

```
* Default value: 1
* Max value: 120
* Min value: 0
```

|====

== Request Body

```
[cols=3*,options=header]
|====
| Name
| Type
| Description

|fips
|link:#fips[fips]
a|Cluster-wide Federal Information Processing Standards (FIPS) mode
information.

|management_protocols
|link:#management_protocols[management_protocols]
a|Cluster-wide security protocols related information.

|software_data_encryption
|link:#software_data_encryption[software_data_encryption]
a|Cluster-wide software data encryption related information.

|tls
|link:#tls[tls]
a|Cluster-wide Transport Layer Security (TLS) configuration information

|====
```

```
.Example request
[%collapsible%closed]
=====
[source, json, subs=+macros]
{
  "software_data_encryption": {
    "encryption_state": "string"
  },
  "tls": {
    "cipher_suites": [
      "TLS_ECDHE_RSA_WITH_AES_256_GCM_SHA384"
    ],
    "protocol_versions": [
      "string"
    ]
  }
}
=====

== Response
```

Status: 200, Ok

```
[cols=3*,options=header]
| ====
| Name
| Type
| Description

| job
| link:#job_link[job_link]
a| a

| ====

.Example response
[%collapsible%closed]
=====

[source, json, subs=+macros]
{
  "job": {
    "uuid": "string"
  }
}
=====

== Response
```

Status: 202, Accepted

```
== Error
```

Status: Default

ONTAP Error Response Codes

```
| ====
| Error Code | Description
| 5636142
| This operation is not supported in a mixed-release cluster.

| 5636145
| This operation is not supported when cluster security is configured with
FIPS mode.
```

- | 52428817
 - | SSLv3 is not supported when FIPS is enabled.
- | 52428824
 - | TLSv1 is not supported when FIPS is enabled.
- | 52428830
 - | Cannot enable FIPS-compliant mode because the configured minimum security strength for certificates is not compatible.
- | 52428832
 - | TLSv1.1 is not supported when FIPS is enabled.
- | 52559974
 - | Cannot enable FIPS-compliant mode because a certificate that is not FIPS-compliant is in use.
- | 65536987
 - | One or more key servers are unavailable.
- | 196608047
 - | Operation is not allowed when volume move is in progress.
- | 196608070
 - | Key manager is not configured on the cluster. Configure either an external Key Management Server or an onboard key manager.
- | 196608081
 - | Cannot start software encryption conversion while there are data volumes in the cluster.
- | 196608082
 - | The operation is not valid when the MetroCluster is in switchover mode.
- | 196608368
 - | Failed to perform the requested operation. One or more data volume in offline state.
- | 196608369
 - | Conversion cannot be enabled because the cluster contains read-only or primordial logical data-protection volumes. Retry the patch operation after deleting those volumes.
- | 196608370
 - | The PATCH request to enable conversion failed because one or more volumes are already queued for the encryption conversion operation.

```
| 196608372
| An automated ONTAP update is in progress, retry the PATCH request after
it is completed.

| 196608373
| Unable to perform the encryption operation because of a mixed-release
cluster. Complete the upgrade or revert operation, then try the PATCH
request again.

| 196608374
| Failed to perform the requested operation. One or more SVMs not in admin
running state.

| 196608375
| Failed to perform the requested operation. One or more volume is of
temporary type.

| 196608376
| Internal error. Could not get volume encryption information.

| 196608377
| Internal error. The Volume Location Database (VLDB) is inconsistent.
Contact support personnel to resolve this issue.

| 196608378
| Failed to perform the requested operation. Data SVM Key manager
configuration is in mixed state.

| 196608379
| Internal error. The encryption metadata for the volume is inconsistent.
Contact technical support for assistance.

| 196608380
| Failed to perform the requested operation. Wafliron is currently active.

| 196608381
| Failed to perform the requested operation. A clone split operation is in
progress.

| 196608382
| Failed to perform the requested operation. A volume rehost operation is
in progress.

| 196608383
| Failed to perform the requested operation. The cluster contains one or
more SnapLock volume.
```

```
| 196608384
| The PATCH request to start rekey failed because the cluster contains one
or more plain text volumes. Retry the PATCH request after converting the
existing plain text volumes to encrypted volumes.

| 196608385
| Failed to perform the requested operation. Keystore configuration is
being switched. Wait until the keystore is in the active state and then
try the PATCH request again.

| 196608386
| Failed to perform the requested operation. Rekey operation for one or
more SVMs is in progress. Wait until the keystore is in the active state
and then try the PATCH request again.

| 196608387
| "software_data_encryption.conversion_enabled" cannot be set to "false"
in a PATCH request.

| 196608388
| Both "software_data_encryption.conversion_enabled" and
"software_data_encryption.disabled_by_default" cannot be set to "true" in
a single PATCH request.

| 196608389
| Both "software_data_encryption.conversion_enabled" and
"software_data_encryption.rekey" cannot be set to "true" in a single PATCH
request.

| 196608390
| "software_data_encryption.rekey" cannot be set to "false" in a PATCH
request.

| 196608391
| Both "software_data_encryption.rekey" and
"software_data_encryption.disabled_by_default" cannot be set to "true" in
a single PATCH request.

| 196608392
| The PATCH request for cluster level rekey requires an effective cluster
version of 9.16.1 or later.

| 196608393
| The PATCH request for cluster level rekey is not supported on this
platform.

| ===
```

Also see the table of common errors in the [xref:{relative_path}getting_started_with_the_ontap_rest_api.html#Response_body](#) [Response body] overview section of this documentation.

== Definitions

[.api-def-first-level]

.See Definitions

[%collapsible%closed]

//Start collapsible Definitions block

====

[#href]

[.api-collapsible-fifth-title]

href

[cols=3*, options=header]

|====

| Name

| Type

| Description

| href

| string

a|

|====

[#_links]

[.api-collapsible-fifth-title]

_links

[#fips]

[.api-collapsible-fifth-title]

fips

Cluster-wide Federal Information Processing Standards (FIPS) mode information.

[cols=3*, options=header]

|====

| Name

| Type

| Description

| enabled

```
|boolean
a|Indicates whether or not the software FIPS mode is enabled on the
cluster. Our FIPS compliance involves configuring the use of only approved
algorithms in applicable contexts (for example TLS), as well as the use of
formally validated cryptographic module software implementations, where
applicable. The US government documents concerning FIPS 140-2 outline the
relevant security policies in detail.
```

```
|====
```

```
[#management_protocols]
[.api-collapsible-fifth-title]
management_protocols
```

Cluster-wide security protocols related information.

```
[cols=3*,options=header]
```

```
|====
```

```
|Name
```

```
|Type
```

```
|Description
```

```
|rsh_enabled
```

```
|boolean
```

a|Indicates whether or not security protocol rsh is enabled on the cluster.

```
|telnet_enabled
```

```
|boolean
```

a|Indicates whether or not security protocol telnet is enabled on the cluster.

```
|====
```

```
[#onboard_key_manager_configurable_status]
[.api-collapsible-fifth-title]
onboard_key_manager_configurable_status
```

Indicates whether the Onboard Key Manager can be configured in the cluster.

```
[cols=3*,options=header]
|===
|Name
|Type
|Description

|code
|integer
a|Code corresponding to the status message. Returns a 0 if the Onboard Key Manager can be configured in the cluster.
```

```
|message
|string
a|Reason that Onboard Key Manager cannot be configured in the cluster.
```

```
|supported
|boolean
a|Set to true if the Onboard Key Manager can be configured in the cluster.
```

```
|===
```

```
[#software_data_encryption]
[.api-collapsible-fifth-title]
software_data_encryption
```

Cluster-wide software data encryption related information.

```
[cols=3*,options=header]
```

```
|===
```

```
|Name
```

```
|Type
```

```
|Description
```

```
|conversion_enabled
```

```
|boolean
```

```
a|Indicates whether or not software encryption conversion is enabled on the cluster. A PATCH request initiates the conversion of all non-encrypted metadata volumes in the cluster to encrypted metadata volumes and all non-NAE aggregates to NAE aggregates. For the PATCH request to start, the cluster must have either an Onboard or an external key manager set up and the aggregates should either be empty or have only metadata volumes. No
```

data volumes should be present in any of the aggregates in the cluster. For MetroCluster configurations, a PATCH request enables conversion on all the aggregates and metadata volumes of both local and remote clusters and is not allowed when the MetroCluster is in switchover state.

```
|disabled_by_default
|boolean
a|Indicates whether or not default software data at rest encryption is
disabled on the cluster.

|encryption_state
|string
a|Software data encryption state.
encrypted &dash; All the volumes are encrypted.
encrypting &dash; Encryption conversion operation is in progress.
partial &dash; Some volumes are encrypted, and others remains in plain
text.
rekeying &dash; All volumes are currently being encrypted with a new key.
unencrypted &dash; None of the volumes are encrypted.
conversion_paused &dash; Encryption conversion operation is paused on one
or more volumes.
rekey_paused &dash; Encryption rekey operation is paused on one or more
volumes.
```

```
|rekey
|boolean
a|
|===
[#tls]
[.api-collapsible-fifth-title]
tls

Cluster-wide Transport Layer Security (TLS) configuration information
```

```
[cols=3*,options=header]
|===
|Name
|Type
|Description
```

```
|cipher_suites
|array[string]
a|Names a cipher suite that the system can select during TLS handshakes. A
list of available options can be found on the Internet Assigned Number
Authority (IANA) website.

|protocol_versions
|array[string]
a|Names a TLS protocol version that the system can select during TLS
handshakes. The use of SSLv3 or TLSv1 is discouraged.

| ===

[#security_config]
[.api-collapsible-fifth-title]
security_config

[cols=3*,options=header]
| ===
|Name
|Type
|Description

|fips
|link:#fips[fips]
a|Cluster-wide Federal Information Processing Standards (FIPS) mode
information.

|management_protocols
|link:#management_protocols[management_protocols]
a|Cluster-wide security protocols related information.

|software_data_encryption
|link:#software_data_encryption[software_data_encryption]
a|Cluster-wide software data encryption related information.

|tls
|link:#tls[tls]
a|Cluster-wide Transport Layer Security (TLS) configuration information
```

```
| ====

[#job_link]
[.api-collapsible-fifth-title]
job_link

[cols=3*,options=header]
| ====
| Name
| Type
| Description

| uuid
| string
a|The UUID of the asynchronous job that is triggered by a POST, PATCH, or
DELETE operation.

| ====

[#error_arguments]
[.api-collapsible-fifth-title]
error_arguments

[cols=3*,options=header]
| ====
| Name
| Type
| Description

| code
| string
a|Argument code

| message
| string
a|Message argument

| ====

[#returned_error]
[.api-collapsible-fifth-title]
```

```

returned_error

[cols=3*,options=header]
|===
| Name
| Type
| Description

| arguments
| array[link:#error_arguments[error_arguments]]
a|Message arguments

| code
| string
a|Error code

| message
| string
a|Error message

| target
| string
a|The target parameter that caused the error.

|===
//end collapsible .Definitions block
=====

:leveloffset: -1

:leveloffset: -1

<<<
*Copyright information*


```

Copyright © 2025 NetApp, Inc. All Rights Reserved. Printed in the U.S. No part of this document covered by copyright may be reproduced in any form or by any means—graphic, electronic, or mechanical, including

photocopying, recording, taping, or storage in an electronic retrieval system—without prior written permission of the copyright owner.

Software derived from copyrighted NetApp material is subject to the following license and disclaimer:

THIS SOFTWARE IS PROVIDED BY NETAPP "AS IS" AND WITHOUT ANY EXPRESS OR IMPLIED WARRANTIES, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE, WHICH ARE HEREBY DISCLAIMED. IN NO EVENT SHALL NETAPP BE LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO, PROCUREMENT OF SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA, OR PROFITS; OR BUSINESS INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE) ARISING IN ANY WAY OUT OF THE USE OF THIS SOFTWARE, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE.

NetApp reserves the right to change any products described herein at any time, and without notice. NetApp assumes no responsibility or liability arising from the use of products described herein, except as expressly agreed to in writing by NetApp. The use or purchase of this product does not convey a license under any patent rights, trademark rights, or any other intellectual property rights of NetApp.

The product described in this manual may be protected by one or more U.S. patents, foreign patents, or pending applications.

LIMITED RIGHTS LEGEND: Use, duplication, or disclosure by the government is subject to restrictions as set forth in subparagraph (b) (3) of the Rights in Technical Data -Noncommercial Items at DFARS 252.227-7013 (FEB 2014) and FAR 52.227-19 (DEC 2007).

Data contained herein pertains to a commercial product and/or commercial service (as defined in FAR 2.101) and is proprietary to NetApp, Inc. All NetApp technical data and computer software provided under this Agreement is commercial in nature and developed solely at private expense. The U.S. Government has a non-exclusive, non-transferrable, nonsublicensable, worldwide, limited irrevocable license to use the Data only in connection with and in support of the U.S. Government contract under which the Data was delivered. Except as provided herein, the Data may not be used, disclosed, reproduced, modified, performed, or displayed without the prior written approval of NetApp, Inc. United States Government license rights for the Department of Defense are limited to those rights identified in DFARS clause 252.227-7015(b) (FEB 2014).

Trademark information

NETAPP, the NETAPP logo, and the marks listed at
link:<http://www.netapp.com/TM> are trademarks of
NetApp, Inc. Other company and product names may be trademarks of their
respective owners.