



## **Manage shelves**

### **ONTAP 9.7 REST API reference**

NetApp  
August 29, 2024

# Table of Contents

- Manage shelves ..... 1
  - Storage shelves endpoint overview ..... 1
  - Retrieve shelves ..... 10
  - Retrieve a shelf ..... 21

# Manage shelves

## Storage shelves endpoint overview

### Retrieving storage shelf information

The storage shelf GET API retrieves all of the shelves in the cluster.

### Examples

#### 1) Retrieve a list of shelves from the cluster

The following example shows the response with a list of shelves in the cluster:

```
# The API:
/api/storage/shelves

# The call:
curl -X GET "https://<mgmt-ip>/api/storage/shelves" -H "accept:
application/hal+json"

# The response:
{
  "records": [
    {
      "uid": "3109174803597886800",
      "_links": {
        "self": {
          "href": "/api/storage/shelves/3109174803597886800"
        }
      }
    },
    {
      "uid": "9237728366621690448",
      "_links": {
        "self": {
          "href": "/api/storage/shelves/9237728366621690448"
        }
      }
    },
    {
      "uid": "9946762738829886800",
      "_links": {
```

```

    "self": {
      "href": "/api/storage/shelves/9946762738829886800"
    }
  },
  {
    "uid": "10318311901725526608",
    "_links": {
      "self": {
        "href": "/api/storage/shelves/10318311901725526608"
      }
    }
  },
  {
    "uid": "13477584846688355664",
    "_links": {
      "self": {
        "href": "/api/storage/shelves/13477584846688355664"
      }
    }
  }
],
"num_records": 5,
"_links": {
  "self": {
    "href": "/api/storage/shelves/"
  }
}
}
}

```

## 2) Retrieve a specific shelf from the cluster

The following example shows the response of the requested shelf. If there is no shelf with the requested uid, an error is returned.

```

# The API:
/api/storage/shelves/{uid}

# The call:
curl -X GET "https://<mgmt-ip>/api/storage/shelves/3109174803597886800" -H
"accept: application/hal+json"

# The response:

```

```

{
  "uid": "3109174803597886800",
  "name": "6.10",
  "id": "10",
  "serial_number": "SHU0954292N0HAH",
  "model": "DS4246",
  "module_type": "iom6",
  "internal": false,
  "state": "ok",
  "connection_type": "sas",
  "disk_count": 24,
  "paths": [
    {
      "name": "0e",
      "node": {
        "uuid": "0530d6c1-8c6d-11e8-907f-00a0985a72ee",
        "name": "node-1",
        "_links": {
          "self": {
            "href": "/api/cluster/nodes/0530d6c1-8c6d-11e8-907f-00a0985a72ee"
          }
        }
      },
      "_links": {
        "self": {
          "href": "/api/storage/ports/0530d6c1-8c6d-11e8-907f-00a0985a72ee/0e"
        }
      }
    },
    {
      "name": "0g",
      "node": {
        "uuid": "0530d6c1-8c6d-11e8-907f-00a0985a72ee",
        "name": "node-1",
        "_links": {
          "self": {
            "href": "/api/cluster/nodes/0530d6c1-8c6d-11e8-907f-00a0985a72ee"
          }
        }
      },
      "_links": {
        "self": {
          "href": "/api/storage/ports/0530d6c1-8c6d-11e8-907f-

```

```
00a0985a72ee/0g"
  }
}
],
"bays": [
  {
    "id": 0,
    "has_disk": true,
    "type": "single_disk",
    "state": "ok"
  },
  {
    "id": 1,
    "has_disk": true,
    "type": "single_disk",
    "state": "ok"
  },
  {
    "id": 2,
    "has_disk": true,
    "type": "single_disk",
    "state": "ok"
  },
  {
    "id": 3,
    "has_disk": true,
    "type": "single_disk",
    "state": "ok"
  },
  {
    "id": 4,
    "has_disk": true,
    "type": "single_disk",
    "state": "ok"
  },
  {
    "id": 5,
    "has_disk": true,
    "type": "single_disk",
    "state": "ok"
  },
  {
    "id": 6,
    "has_disk": true,
    "type": "single_disk",
```

```
    "state": "ok"
  },
  {
    "id": 7,
    "has_disk": true,
    "type": "single_disk",
    "state": "ok"
  },
  {
    "id": 8,
    "has_disk": true,
    "type": "single_disk",
    "state": "ok"
  },
  {
    "id": 9,
    "has_disk": true,
    "type": "single_disk",
    "state": "ok"
  },
  {
    "id": 10,
    "has_disk": true,
    "type": "single_disk",
    "state": "ok"
  },
  {
    "id": 11,
    "has_disk": true,
    "type": "single_disk",
    "state": "ok"
  },
  {
    "id": 12,
    "has_disk": true,
    "type": "single_disk",
    "state": "ok"
  },
  {
    "id": 13,
    "has_disk": true,
    "type": "single_disk",
    "state": "ok"
  },
  {
    "id": 14,
```

```
"has_disk": true,
"type": "single_disk",
"state": "ok"
},
{
  "id": 15,
  "has_disk": true,
  "type": "single_disk",
  "state": "ok"
},
{
  "id": 16,
  "has_disk": true,
  "type": "single_disk",
  "state": "ok"
},
{
  "id": 17,
  "has_disk": true,
  "type": "single_disk",
  "state": "ok"
},
{
  "id": 18,
  "has_disk": true,
  "type": "single_disk",
  "state": "ok"
},
{
  "id": 19,
  "has_disk": true,
  "type": "single_disk",
  "state": "ok"
},
{
  "id": 20,
  "has_disk": true,
  "type": "single_disk",
  "state": "ok"
},
{
  "id": 21,
  "has_disk": true,
  "type": "single_disk",
  "state": "ok"
},
},
```



```
{
  "id": 22,
  "has_disk": true,
  "type": "single_disk",
  "state": "ok"
},
{
  "id": 23,
  "has_disk": true,
  "type": "single_disk",
  "state": "ok"
}
],
"frus": [
  {
    "type": "module",
    "id": 0,
    "state": "ok",
    "part_number": "111-00690+B2",
    "serial_number": "8001900099",
    "firmware_version": "0191"
  },
  {
    "type": "module",
    "id": 1,
    "state": "ok",
    "part_number": "111-00190+B0",
    "serial_number": "7903785183",
    "firmware_version": "0191"
  },
  {
    "type": "psu",
    "id": 1,
    "state": "ok",
    "part_number": "0082562-12",
    "serial_number": "PMW82562007513E",
    "firmware_version": "0311"
  },
  {
    "type": "psu",
    "id": 2,
    "state": "ok",
    "part_number": "0082562-12",
    "serial_number": "PMW825620075138",
    "firmware_version": "0311"
  },
],
```

```

{
  "type": "psu",
  "id": 3,
  "state": "ok",
  "part_number": "0082562-12",
  "serial_number": "PMW8256200750BA",
  "firmware_version": "0311"
},
{
  "type": "psu",
  "id": 4,
  "state": "ok",
  "part_number": "0082562-12",
  "serial_number": "PMW8256200750A2",
  "firmware_version": "0311"
}
],
"ports": [
  {
    "id": 0,
    "module_id": "a",
    "designator": "square",
    "state": "connected",
    "internal": false,
    "wwn": "500A098000C9EDBF",
    "cable": {
      "identifier": "5001086000702488-500a098000c9edbf",
      "part_number": "112-00430+A0",
      "length": "2m",
      "serial_number": "APF16510229807"
    },
    "remote": {
      "wwn": "5001086000702488",
      "phy": "08"
    }
  },
  {
    "id": 1,
    "module_id": "a",
    "designator": "circle",
    "state": "connected",
    "internal": false,
    "wwn": "500A098000C9EDBF",
    "cable": {
      "identifier": "500a098000d5c4bf-500a098000c9edbf",
      "part_number": "112-00176+A0",

```

```

    "length": "0.5-1.0m",
    "serial_number": "APF133917610YT"
  },
  "remote": {
    "wwn": "500A098000D5C4BF",
    "phy": "00"
  }
},
{
  "id": 2,
  "module_id": "b",
  "designator": "square",
  "state": "connected",
  "internal": false,
  "wwn": "500A098004F208BF",
  "cable": {
    "identifier": "5001086000702648-500a098004f208bf",
    "part_number": "112-00430+A0",
    "length": "2m",
    "serial_number": "APF16510229540"
  },
  "remote": {
    "wwn": "5001086000702648",
    "phy": "08"
  }
},
{
  "id": 3,
  "module_id": "b",
  "designator": "circle",
  "state": "connected",
  "internal": false,
  "wwn": "500A098004F208BF",
  "cable": {
    "identifier": "500a0980062ba33f-500a098004f208bf",
    "part_number": "112-00176+20",
    "length": "0.5-1.0m",
    "serial_number": "832210017"
  },
  "remote": {
    "wwn": "500A0980062BA33F",
    "phy": "00"
  }
}
],
"_links": {

```

```
"self": {
  "href": "/api/storage/shelves/3109174803597886800"
}
}
```

## Retrieve shelves

GET /storage/shelves

Retrieves a collection of shelves.

### Related ONTAP commands

- storage shelf show
- storage shelf port show
- storage shelf drawer show

### Learn more

- [DOC /storage/shelves](#)

### Parameters

Name	Type	In	Required	Description
uid	string	query	False	Filter by uid
connection_type	string	query	False	Filter by connection_type
drawers.id	integer	query	False	Filter by drawers.id
drawers.serial_number	string	query	False	Filter by drawers.serial_number
drawers.part_number	string	query	False	Filter by drawers.part_number
drawers.error	string	query	False	Filter by drawers.error

Name	Type	In	Required	Description
drawers.closed	boolean	query	False	Filter by drawers.closed
drawers.state	string	query	False	Filter by drawers.state
drawers.disk_count	integer	query	False	Filter by drawers.disk_count
module_type	string	query	False	Filter by module_type
bays.state	string	query	False	Filter by bays.state
bays.has_disk	boolean	query	False	Filter by bays.has_disk
bays.type	string	query	False	Filter by bays.type
bays.id	integer	query	False	Filter by bays.id
model	string	query	False	Filter by model
serial_number	string	query	False	Filter by serial_number
state	string	query	False	Filter by state
disk_count	integer	query	False	Filter by disk_count
frus.state	string	query	False	Filter by frus.state
frus.part_number	string	query	False	Filter by frus.part_number
frus.firmware_version	string	query	False	Filter by frus.firmware_version
frus.type	string	query	False	Filter by frus.type
frus.serial_number	string	query	False	Filter by frus.serial_number
frus.id	integer	query	False	Filter by frus.id

<b>Name</b>	<b>Type</b>	<b>In</b>	<b>Required</b>	<b>Description</b>
ports.module_id	string	query	False	Filter by ports.module_id
ports.wwn	string	query	False	Filter by ports.wwn
ports.cable.identifier	string	query	False	Filter by ports.cable.identifier
ports.cable.length	string	query	False	Filter by ports.cable.length
ports.cable.part_number	string	query	False	Filter by ports.cable.part_number
ports.cable.serial_number	string	query	False	Filter by ports.cable.serial_number
ports.state	string	query	False	Filter by ports.state
ports.remote.phy	string	query	False	Filter by ports.remote.phy
ports.remote.wwn	string	query	False	Filter by ports.remote.wwn
ports.remote.port	string	query	False	Filter by ports.remote.port
ports.remote.mac_address	string	query	False	Filter by ports.remote.mac_address
ports.remote.chassis	string	query	False	Filter by ports.remote.chassis
ports.mac_address	string	query	False	Filter by ports.mac_address
ports.internal	boolean	query	False	Filter by ports.internal
ports.designator	string	query	False	Filter by ports.designator

<b>Name</b>	<b>Type</b>	<b>In</b>	<b>Required</b>	<b>Description</b>
ports.id	integer	query	False	Filter by ports.id
internal	boolean	query	False	Filter by internal
name	string	query	False	Filter by name
paths.name	string	query	False	Filter by paths.name
paths.node.uuid	string	query	False	Filter by paths.node.uuid
paths.node.name	string	query	False	Filter by paths.node.name
id	string	query	False	Filter by id
fields	array[string]	query	False	Specify the fields to return.
max_records	integer	query	False	Limit the number of records returned.
return_records	boolean	query	False	The default is true for GET calls. When set to false, only the number of records is returned.
return_timeout	integer	query	False	The number of seconds to allow the call to execute before returning. When iterating over a collection, the default is 15 seconds. ONTAP returns earlier if either max records or the end of the collection is reached.
order_by	array[string]	query	False	Order results by specified fields and optional [asc

## Response

Status: 200, Ok

Name	Type	Description
_links	<a href="#">_links</a>	
num_records	integer	Number of records
records	array[ <a href="#">shelf</a> ]	



## Example response

```
{
  "_links": {
    "next": {
      "href": "/api/resourcelink"
    },
    "self": {
      "href": "/api/resourcelink"
    }
  },
  "records": [
    {
      "bays": [
        {
          "id": 0,
          "state": "ok",
          "type": "single_disk"
        }
      ],
      "connection_type": "sas",
      "disk_count": 12,
      "drawers": [
        {
          "disk_count": 12,
          "error": "string",
          "part_number": "111-03071",
          "serial_number": "021604008263",
          "state": "ok"
        }
      ],
      "frus": [
        {
          "firmware_version": "0191",
          "part_number": "111-00690+A2",
          "serial_number": 8000166294,
          "state": "error",
          "type": "module"
        }
      ],
      "id": 1,
      "model": "DS2246",
      "module_type": "iom6",
      "name": 1.1,
      "paths": [
        {
```

```

    "_links": {
      "self": {
        "href": "/api/resourcelink"
      }
    },
    "name": "2a",
    "node": {
      "_links": {
        "self": {
          "href": "/api/resourcelink"
        }
      },
      "name": "node1",
      "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"
    }
  ],
  "ports": [
    {
      "cable": {
        "identifier": "500a0980000b6c3f-50000d1703544b80",
        "length": "2m",
        "part_number": "112-00431+A0",
        "serial_number": 616930439
      },
      "designator": "square",
      "id": 0,
      "mac_address": "string",
      "module_id": "a",
      "remote": {
        "chassis": "string",
        "mac_address": "string",
        "phy": 12,
        "port": "string",
        "wwn": "50000D1703544B80"
      },
      "state": "connected",
      "wwn": "500A0980000B6C3F"
    }
  ],
  "serial_number": "SHFMS1514000895",
  "state": "ok",
  "uid": 7777841915827391056
}
]
}

```

## Error

Status: Default, Error

Name	Type	Description
error	error	

### Example error

```
{
  "error": {
    "arguments": [
      {
        "code": "string",
        "message": "string"
      }
    ],
    "code": "4",
    "message": "entry doesn't exist",
    "target": "uuid"
  }
}
```

## Definitions

## See Definitions

href

Name	Type	Description
href	string	

\_links

Name	Type	Description
next	<a href="#">href</a>	
self	<a href="#">href</a>	

bays

Name	Type	Description
has_disk	boolean	
id	integer	
state	string	
type	string	

drawers

Name	Type	Description
closed	boolean	
disk_count	integer	
error	string	
id	integer	
part_number	string	
serial_number	string	
state	string	

frus

Name	Type	Description
firmware_version	string	
id	integer	
part_number	string	
serial_number	string	
state	string	

Name	Type	Description
type	string	

\_links

Name	Type	Description
self	<a href="#">href</a>	

node

Name	Type	Description
_links	<a href="#">_links</a>	
name	string	
uuid	string	

paths

Storage port

Name	Type	Description
_links	<a href="#">_links</a>	
name	string	
node	<a href="#">node</a>	

cable

Name	Type	Description
identifier	string	
length	string	
part_number	string	
serial_number	string	

remote

Name	Type	Description
chassis	string	
mac_address	string	
phy	string	
port	string	
wwn	string	

ports

Name	Type	Description
cable	<a href="#">cable</a>	
designator	string	
id	integer	
internal	boolean	
mac_address	string	
module_id	string	
remote	<a href="#">remote</a>	
state	string	
wwn	string	

#### shelf

Name	Type	Description
bays	array[ <a href="#">bays</a> ]	
connection_type	string	
disk_count	integer	
drawers	array[ <a href="#">drawers</a> ]	
frus	array[ <a href="#">frus</a> ]	
id	string	
internal	boolean	
model	string	
module_type	string	
name	string	
paths	array[ <a href="#">paths</a> ]	
ports	array[ <a href="#">ports</a> ]	
serial_number	string	
state	string	
uid	string	

#### error\_arguments

Name	Type	Description
code	string	Argument code
message	string	Message argument

error

Name	Type	Description
arguments	array[ <a href="#">error_arguments</a> ]	Message arguments
code	string	Error code
message	string	Error message
target	string	The target parameter that caused the error.

## Retrieve a shelf

GET /storage/shelves/{uid}

Retrieves a specific shelf.

### Related ONTAP commands

- `storage shelf show`
- `storage shelf port show`
- `storage shelf drawer show`

### Learn more

- [DOC /storage/shelves](#)

### Parameters

Name	Type	In	Required	Description
uid	string	path	True	Shelf UID
fields	array[string]	query	False	Specify the fields to return.

### Response

Status: 200, Ok

Name	Type	Description
bays	array[ <a href="#">bays</a> ]	

Name	Type	Description
connection_type	string	
disk_count	integer	
drawers	array[drawers]	
frus	array[frus]	
id	string	
internal	boolean	
model	string	
module_type	string	
name	string	
paths	array[paths]	
ports	array[ports]	
serial_number	string	
state	string	
uid	string	



## Example response

```
{
  "bays": [
    {
      "id": 0,
      "state": "ok",
      "type": "single_disk"
    }
  ],
  "connection_type": "sas",
  "disk_count": 12,
  "drawers": [
    {
      "disk_count": 12,
      "error": "string",
      "part_number": "111-03071",
      "serial_number": "021604008263",
      "state": "ok"
    }
  ],
  "frus": [
    {
      "firmware_version": "0191",
      "part_number": "111-00690+A2",
      "serial_number": 8000166294,
      "state": "error",
      "type": "module"
    }
  ],
  "id": 1,
  "model": "DS2246",
  "module_type": "iom6",
  "name": 1.1,
  "paths": [
    {
      "_links": {
        "self": {
          "href": "/api/resourcelink"
        }
      },
      "name": "2a",
      "node": {
        "_links": {
          "self": {
            "href": "/api/resourcelink"
          }
        }
      }
    }
  ]
}
```

```

    }
  },
  "name": "node1",
  "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"
}
],
"ports": [
  {
    "cable": {
      "identifier": "500a0980000b6c3f-50000d1703544b80",
      "length": "2m",
      "part_number": "112-00431+A0",
      "serial_number": 616930439
    },
    "designator": "square",
    "id": 0,
    "mac_address": "string",
    "module_id": "a",
    "remote": {
      "chassis": "string",
      "mac_address": "string",
      "phy": 12,
      "port": "string",
      "wwn": "50000D1703544B80"
    },
    "state": "connected",
    "wwn": "500A0980000B6C3F"
  }
],
"serial_number": "SHFMS1514000895",
"state": "ok",
"uid": 7777841915827391056
}

```

## Error

Status: Default, Error

Name	Type	Description
error	error	

## Example error

```
{
  "error": {
    "arguments": [
      {
        "code": "string",
        "message": "string"
      }
    ],
    "code": "4",
    "message": "entry doesn't exist",
    "target": "uuid"
  }
}
```

## Definitions

## See Definitions

bays

Name	Type	Description
has_disk	boolean	
id	integer	
state	string	
type	string	

drawers

Name	Type	Description
closed	boolean	
disk_count	integer	
error	string	
id	integer	
part_number	string	
serial_number	string	
state	string	

frus

Name	Type	Description
firmware_version	string	
id	integer	
part_number	string	
serial_number	string	
state	string	
type	string	

href

Name	Type	Description
href	string	

\_links

Name	Type	Description
self	<a href="#">href</a>	

## node

Name	Type	Description
_links	<a href="#">_links</a>	
name	string	
uuid	string	

## paths

### Storage port

Name	Type	Description
_links	<a href="#">_links</a>	
name	string	
node	<a href="#">node</a>	

## cable

Name	Type	Description
identifier	string	
length	string	
part_number	string	
serial_number	string	

## remote

Name	Type	Description
chassis	string	
mac_address	string	
phy	string	
port	string	
wwn	string	

## ports

Name	Type	Description
cable	<a href="#">cable</a>	
designator	string	
id	integer	
internal	boolean	
mac_address	string	

Name	Type	Description
module_id	string	
remote	<a href="#">remote</a>	
state	string	
wwn	string	

#### error\_arguments

Name	Type	Description
code	string	Argument code
message	string	Message argument

#### error

Name	Type	Description
arguments	array[ <a href="#">error_arguments</a> ]	Message arguments
code	string	Error code
message	string	Error message
target	string	The target parameter that caused the error.

## Copyright information

Copyright © 2024 NetApp, Inc. All Rights Reserved. Printed in the U.S. No part of this document covered by copyright may be reproduced in any form or by any means—graphic, electronic, or mechanical, including photocopying, recording, taping, or storage in an electronic retrieval system—without prior written permission of the copyright owner.

Software derived from copyrighted NetApp material is subject to the following license and disclaimer:

THIS SOFTWARE IS PROVIDED BY NETAPP "AS IS" AND WITHOUT ANY EXPRESS OR IMPLIED WARRANTIES, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE, WHICH ARE HEREBY DISCLAIMED. IN NO EVENT SHALL NETAPP BE LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO, PROCUREMENT OF SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA, OR PROFITS; OR BUSINESS INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE) ARISING IN ANY WAY OUT OF THE USE OF THIS SOFTWARE, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE.

NetApp reserves the right to change any products described herein at any time, and without notice. NetApp assumes no responsibility or liability arising from the use of products described herein, except as expressly agreed to in writing by NetApp. The use or purchase of this product does not convey a license under any patent rights, trademark rights, or any other intellectual property rights of NetApp.

The product described in this manual may be protected by one or more U.S. patents, foreign patents, or pending applications.

LIMITED RIGHTS LEGEND: Use, duplication, or disclosure by the government is subject to restrictions as set forth in subparagraph (b)(3) of the Rights in Technical Data -Noncommercial Items at DFARS 252.227-7013 (FEB 2014) and FAR 52.227-19 (DEC 2007).

Data contained herein pertains to a commercial product and/or commercial service (as defined in FAR 2.101) and is proprietary to NetApp, Inc. All NetApp technical data and computer software provided under this Agreement is commercial in nature and developed solely at private expense. The U.S. Government has a non-exclusive, non-transferrable, nonsublicensable, worldwide, limited irrevocable license to use the Data only in connection with and in support of the U.S. Government contract under which the Data was delivered. Except as provided herein, the Data may not be used, disclosed, reproduced, modified, performed, or displayed without the prior written approval of NetApp, Inc. United States Government license rights for the Department of Defense are limited to those rights identified in DFARS clause 252.227-7015(b) (FEB 2014).

## Trademark information

NETAPP, the NETAPP logo, and the marks listed at <http://www.netapp.com/TM> are trademarks of NetApp, Inc. Other company and product names may be trademarks of their respective owners.