



Manage

ONTAP 9.8 REST API reference

NetApp
August 29, 2024

Table of Contents

- Manage 1
 - Private manage event-remediations 1
 - Event remediation and management action..... 6
 - Perform an event management action 10

Manage

Private manage event-remediations

Private manage event-remediations endpoint overview

Overview

Event remediations is the initial implementation of ONTAP self healing proof of concept.

This endpoint supports GET calls. GET is used to retrieve details about the event.

Event remediation and management action collection get

learn more

- [\[doc /private/manage/event-remediations\]\(#docs-manage-private_manage_event-remediations\)](#)

GET /private/manage/event-remediations

Introduced In: 9.8

Event remediation and management action collection GET

Learn more

- [DOC /private/manage/event-remediations](#)

Parameters

Name	Type	In	Required	Description
max_records	integer	query	False	Limit the number of records returned.
return_records	boolean	query	False	The default is true for GET calls. When set to false, only the number of records is returned. <ul style="list-style-type: none">• Default value: 1

Name	Type	In	Required	Description
return_timeout	integer	query	False	<p>The number of seconds to allow the call to execute before returning. When iterating over a collection, the default is 15 seconds. ONTAP returns earlier if either max records or the end of the collection is reached.</p> <ul style="list-style-type: none"> • Default value: 1 • Max value: 120 • Min value: 0
order_by	array[string]	query	False	Order results by specified fields and optional [asc
desc] direction. Default direction is 'asc' for ascending.	fields	array[string]	query	False

Response

Status: 200, Ok

Name	Type	Description
_links	_links	
num_records	integer	Number of records
records	array[event_remediations]	List of event remediations

Example response

```
{
  "_links": {
    "next": {
      "href": "/api/resourcelink"
    },
    "self": {
      "href": "/api/resourcelink"
    }
  },
  "num_records": "3",
  "records": [
    {
      "cluster": {
        "name": "cluster1",
        "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"
      },
      "completion_time": "string",
      "description": "Disable Telnet",
      "event_remediation_action": "string",
      "event_remediation_action_type": "string",
      "event_remediation_state": "string",
      "event_type_name": "cluster_telnet_enabled",
      "id": "198",
      "solution": "Continue to disable telnet on the selected cluster using the 'security protocol modify -application telnet -enabled false' ontap cli command.",
      "source": {
        "object_id": "5666",
        "object_type": "inventory.ontap.fas.Cluster"
      },
      "source_full_name": "shrey-vsimg1",
      "source_resource_type": "cluster",
      "start_time": "string"
    }
  ]
}
```

Error

Status: Default, Error

Name	Type	Description
error	error	

Example error

```
{
  "error": {
    "arguments": [
      {
        "code": "string",
        "message": "string"
      }
    ],
    "code": "4",
    "message": "entry doesn't exist",
    "target": "uuid"
  }
}
```

Definitions

See Definitions

href

Name	Type	Description
href	string	

_links

Name	Type	Description
next	href	
self	href	

cluster

Name	Type	Description
name	string	
uuid	string	

source

Name	Type	Description
object_id	integer	
object_type	string	

event_remediations

Name	Type	Description
cluster	cluster	
completion_time	string	Completion time of the event
description	string	Description for the event
event_remediation_action	string	Event remediation action
event_remediation_action_type	string	Type of remediation action
event_remediation_state	string	State of the event remediation
event_type_name	string	Type of the event
id	integer	Event Identifier

Name	Type	Description
solution	string	Corrective action for the event
source	source	
source_full_name	string	Source of the event
source_resource_type	string	Type of source of the event
start_time	string	Start time of the event

error_arguments

Name	Type	Description
code	string	Argument code
message	string	Message argument

error

Name	Type	Description
arguments	array[error_arguments]	Message arguments
code	string	Error code
message	string	Error message
target	string	The target parameter that caused the error.

Event remediation and management action

learn more

- [\[doc /private/manage/event-remediations\]\(#docs-manage-private_manage_event-remediations\)](#)

GET /private/manage/event-remediations/{id}

Introduced In: 9.8

Event remediation and management action

Learn more

- [DOC /private/manage/event-remediations](#)

Parameters

Name	Type	In	Required	Description
id	integer	path	True	• Default value: 1
fields	array[string]	query	False	Specify the fields to return.

Response

Status: 200, Ok

Name	Type	Description
cluster	cluster	
completion_time	string	Completion time of the event
description	string	Description for the event
event_remediation_action	string	Event remediation action
event_remediation_action_type	string	Type of remediation action
event_remediation_state	string	State of the event remediation
event_type_name	string	Type of the event
id	integer	Event Identifier
solution	string	Corrective action for the event
source	source	
source_full_name	string	Source of the event
source_resource_type	string	Type of source of the event
start_time	string	Start time of the event

Example response

```
{
  "cluster": {
    "name": "cluster1",
    "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"
  },
  "completion_time": "string",
  "description": "Disable Telnet",
  "event_remediation_action": "string",
  "event_remediation_action_type": "string",
  "event_remediation_state": "string",
  "event_type_name": "cluster_telnet_enabled",
  "id": "198",
  "solution": "Continue to disable telnet on the selected cluster using the 'security protocol modify -application telnet -enabled false' on tap cli command.",
  "source": {
    "object_id": "5666",
    "object_type": "inventory.ontap.fas.Cluster"
  },
  "source_full_name": "shrey-vsimg1",
  "source_resource_type": "cluster",
  "start_time": "string"
}
```

Error

Status: Default, Error

Name	Type	Description
error	error	

Example error

```
{
  "error": {
    "arguments": [
      {
        "code": "string",
        "message": "string"
      }
    ],
    "code": "4",
    "message": "entry doesn't exist",
    "target": "uuid"
  }
}
```

Definitions

See Definitions

cluster

Name	Type	Description
name	string	
uuid	string	

source

Name	Type	Description
object_id	integer	
object_type	string	

error_arguments

Name	Type	Description
code	string	Argument code
message	string	Message argument

error

Name	Type	Description
arguments	array[error_arguments]	Message arguments
code	string	Error code
message	string	Error message
target	string	The target parameter that caused the error.

Perform an event management action

learn more

- [\[doc /private/manage/event-remediations\]\(#docs-manage-private_manage_event-remediations\)](#)

PATCH `/private/manage/event-remediations/{id}`

Introduced In: 9.8

Perform an event management action.

Learn more

- [DOC /private/manage/event-remediations](#)

Parameters

Name	Type	In	Required	Description
id	integer	path	True	<ul style="list-style-type: none">• Default value: 1
return_timeout	integer	query	False	<p>The number of seconds to allow the call to execute before returning. When doing a POST, PATCH, or DELETE operation on a single record, the default is 0 seconds. This means that if an asynchronous operation is started, the server immediately returns HTTP code 202 (Accepted) along with a link to the job. If a non-zero value is specified for POST, PATCH, or DELETE operations, ONTAP waits that length of time to see if the job completes so it can return something other than 202.</p> <ul style="list-style-type: none">• Default value: 1• Max value: 120• Min value: 0

Request Body

Name	Type	Description
cluster	cluster	
completion_time	string	Completion time of the event

Name	Type	Description
description	string	Description for the event
event_remediation_action	string	Event remediation action
event_remediation_action_type	string	Type of remediation action
event_remediation_state	string	State of the event remediation
event_type_name	string	Type of the event
id	integer	Event Identifier
solution	string	Corrective action for the event
source	source	
source_full_name	string	Source of the event
source_resource_type	string	Type of source of the event
start_time	string	Start time of the event

Example request

```
{
  "cluster": {
    "name": "cluster1",
    "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"
  },
  "completion_time": "string",
  "description": "Disable Telnet",
  "event_remediation_action": "string",
  "event_remediation_action_type": "string",
  "event_remediation_state": "string",
  "event_type_name": "cluster_telnet_enabled",
  "id": "198",
  "solution": "Continue to disable telnet on the selected cluster using the 'security protocol modify -application telnet -enabled false' on tap cli command.",
  "source": {
    "object_id": "5666",
    "object_type": "inventory.ontap.fas.Cluster"
  },
  "source_full_name": "shrey-vsimg1",
  "source_resource_type": "cluster",
  "start_time": "string"
}
```

Response

Status: 202, Accepted

Name	Type	Description
job	job_link	

Example response

```
{
  "job": {
    "_links": {
      "self": {
        "href": "/api/resourcelink"
      }
    },
    "uuid": "string"
  }
}
```

Error

Status: Default, Ontap error response codes

Name	Type	Description
error	error	

Example error

```
{
  "error": {
    "arguments": [
      {
        "code": "string",
        "message": "string"
      }
    ],
    "code": "4",
    "message": "entry doesn't exist",
    "target": "uuid"
  }
}
```

Definitions

See Definitions

cluster

Name	Type	Description
name	string	
uuid	string	

source

Name	Type	Description
object_id	integer	
object_type	string	

event_remediations

Name	Type	Description
cluster	cluster	
completion_time	string	Completion time of the event
description	string	Description for the event
event_remediation_action	string	Event remediation action
event_remediation_action_type	string	Type of remediation action
event_remediation_state	string	State of the event remediation
event_type_name	string	Type of the event
id	integer	Event Identifier
solution	string	Corrective action for the event
source	source	
source_full_name	string	Source of the event
source_resource_type	string	Type of source of the event
start_time	string	Start time of the event

href

Name	Type	Description
href	string	

_links

Name	Type	Description
self	href	

job_link

Name	Type	Description
_links	_links	
uuid	string	The UUID of the asynchronous job that is triggered by a POST, PATCH, or DELETE operation.

error_arguments

Name	Type	Description
code	string	Argument code
message	string	Message argument

error

Name	Type	Description
arguments	array[error_arguments]	Message arguments
code	string	Error code
message	string	Error message
target	string	The target parameter that caused the error.

Copyright information

Copyright © 2024 NetApp, Inc. All Rights Reserved. Printed in the U.S. No part of this document covered by copyright may be reproduced in any form or by any means—graphic, electronic, or mechanical, including photocopying, recording, taping, or storage in an electronic retrieval system—without prior written permission of the copyright owner.

Software derived from copyrighted NetApp material is subject to the following license and disclaimer:

THIS SOFTWARE IS PROVIDED BY NETAPP "AS IS" AND WITHOUT ANY EXPRESS OR IMPLIED WARRANTIES, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE, WHICH ARE HEREBY DISCLAIMED. IN NO EVENT SHALL NETAPP BE LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO, PROCUREMENT OF SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA, OR PROFITS; OR BUSINESS INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE) ARISING IN ANY WAY OUT OF THE USE OF THIS SOFTWARE, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE.

NetApp reserves the right to change any products described herein at any time, and without notice. NetApp assumes no responsibility or liability arising from the use of products described herein, except as expressly agreed to in writing by NetApp. The use or purchase of this product does not convey a license under any patent rights, trademark rights, or any other intellectual property rights of NetApp.

The product described in this manual may be protected by one or more U.S. patents, foreign patents, or pending applications.

LIMITED RIGHTS LEGEND: Use, duplication, or disclosure by the government is subject to restrictions as set forth in subparagraph (b)(3) of the Rights in Technical Data -Noncommercial Items at DFARS 252.227-7013 (FEB 2014) and FAR 52.227-19 (DEC 2007).

Data contained herein pertains to a commercial product and/or commercial service (as defined in FAR 2.101) and is proprietary to NetApp, Inc. All NetApp technical data and computer software provided under this Agreement is commercial in nature and developed solely at private expense. The U.S. Government has a non-exclusive, non-transferrable, nonsublicensable, worldwide, limited irrevocable license to use the Data only in connection with and in support of the U.S. Government contract under which the Data was delivered. Except as provided herein, the Data may not be used, disclosed, reproduced, modified, performed, or displayed without the prior written approval of NetApp, Inc. United States Government license rights for the Department of Defense are limited to those rights identified in DFARS clause 252.227-7015(b) (FEB 2014).

Trademark information

NETAPP, the NETAPP logo, and the marks listed at <http://www.netapp.com/TM> are trademarks of NetApp, Inc. Other company and product names may be trademarks of their respective owners.