



View iSCSI sessions

ONTAP 9.14.1 REST API reference

NetApp
April 02, 2024

This PDF was generated from https://docs.netapp.com/us-en/ontap-restapi/ontap/protocols_san_iscsi_sessions_endpoint_overview.html on April 02, 2024. Always check docs.netapp.com for the latest.

Table of Contents

| | |
|---|----|
| View iSCSI sessions | 1 |
| Protocols SAN iSCSI sessions endpoint overview..... | 1 |
| Retrieve iSCSI sessions | 5 |
| Retrieve an iSCSI session | 15 |

View iSCSI sessions

Protocols SAN iSCSI sessions endpoint overview

Overview

An iSCSI session is one or more TCP connections that link an iSCSI initiator with an iSCSI target. TCP connections can be added and removed from an iSCSI session by the iSCSI initiator. Across all TCP connections within an iSCSI session, an initiator sees one and the same target. After the connection is established, iSCSI control, data, and status messages are communicated over the session.

The iSCSI sessions REST API provides information about iSCSI initiators that have successfully logged in to ONTAP.

Examples

Retrieving all iSCSI sessions

```
# The API:  
GET /api/protocols/san/iscsi/sessions  
  
# The call:  
curl -X GET "https://<mgmt-ip>/api/protocols/san/iscsi/sessions" -H  
"Accept: application/hal+json"  
  
# The response:  
{  
  "records": [  
    {  
      "svm": {  
        "uuid": "a009a9e7-4081-b576-7575-ada21efcaf16",  
        "name": "svml",  
        "_links": {  
          "self": {  
            "href": "/api/svm/svms/a009a9e7-4081-b576-7575-ada21efcaf16"  
          }  
        }  
      },  
      "target_portal_group": "iscsi_lif1",  
      "tsih": 10,  
      "_links": {  
        "self": {  
          "href": "/api/protocols/san/iscsi/sessions/a009a9e7-4081-b576-7575-ada21efcaf16/iscsi_lif1/10"  
        }  
      }  
    },  
  ]}
```

```
{
  "svm": {
    "uuid": "b009a9e7-4081-b576-7575-ada21efcaf16",
    "name": "svm2",
    "_links": {
      "self": {
        "href": "/api/svm/svms/b009a9e7-4081-b576-7575-ada21efcaf16"
      }
    },
    "target_portal_group": "iscsi_lif2",
    "tsih": 11,
    "_links": {
      "self": {
        "href": "/api/protocols/san/iscsi/sessions/b009a9e7-4081-b576-7575-ada21efcaf16/iscsi_lif2/11"
      }
    }
  }
},
"num_records": 2,
"_links": {
  "self": {
    "href": "/api/protocols/san/iscsi/sessions"
  }
}
}
```

Retrieving all of the iSCSI sessions under the target portal group *iscsi_lif1*

The `tpgroup` query parameter is used to perform the query.

```

# The API:
GET /api/protocols/san/iscsi/sessions

# The call:
curl -X GET "https://<mgmt-
ip>/api/protocols/san/iscsi/sessions?tpgroup=iscsi_lif1" -H "Accept:
application/hal+json"

# The response:
{
  "records": [
    {
      "svm": {
        "uuid": "a009a9e7-4081-b576-7575-ada21efcaf16",
        "name": "svm1",
        "_links": {
          "self": {
            "href": "/api/svm/svms/a009a9e7-4081-b576-7575-ada21efcaf16"
          }
        }
      },
      "target_portal_group": "iscsi_lif1",
      "tsih": 10,
      "_links": {
        "self": {
          "href": "/api/protocols/san/iscsi/sessions/a009a9e7-4081-b576-
7575-ada21efcaf16/iscsi_lif1/10"
        }
      }
    }
  ],
  "num_records": 1,
  "_links": {
    "self": {
      "href": "/api/protocols/san/iscsi/sessions"
    }
  }
}

```

Retrieving an iSCSI session

```

# The API:
GET

```

```

/api/protocols/san/iscsi/sessions/{svm.uuid}/{target_portal_group}/{tsih}

# The call:
curl -X GET "https://<mgmt-ip>/api/protocols/san/iscsi/sessions/a009a9e7-
4081-b576-7575-ada21efcaf16/iscsi_lif1/10" -H "Accept:
application/hal+json"

# The response:
{
  "svm": {
    "uuid": "a009a9e7-4081-b576-7575-ada21efcaf16",
    "name": "svm1",
    "_links": {
      "self": {
        "href": "/api/svm/svms/a009a9e7-4081-b576-7575-ada21efcaf16"
      }
    },
    "target_portal_group": "iscsi_lif1",
    "tsih": 10,
    "initiator": {
      "name": "iqn.1994-05.com.example:string",
      "comment": "Example information about this initiator"
    },
    "isid": "61:62:63:64:65:00",
    "target_portal_group_tag": 1027,
    "connections": [
      {
        "cid": 1,
        "authentication_type": "chap",
        "initiator_address": {
          "address": "10.224.123.85",
          "port": 43827
        },
        "interface": {
          "name": "iscsi_lif1",
          "uuid": "c15439b4-dbb4-11e8-90ac-005056bba882",
          "ip": {
            "address": "192.168.0.1",
            "port": 3260
          },
          "_links": {
            "self": {
              "href": "/api/network/ip/interfaces/c15439b4-dbb4-11e8-90ac-
005056bba882"
            }
          }
        }
      }
    ]
  }
}

```

```

        }
    }
}
],
"igroups": [
{
    "uuid": "af7838cd-f993-4faf-90b7-5524787ae1e8",
    "name": "igroup1",
    "_links": {
        "self": {
            "href": "/api/protocols/san/igroups/af7838cd-f993-4faf-90b7-5524787ae1e8"
        }
    }
},
{
    "uuid": "bf7838cd-f993-4faf-90b7-5524787ae1e8",
    "name": "igroup2",
    "_links": {
        "self": {
            "href": "/api/protocols/san/igroups/bf7838cd-f993-4faf-90b7-5524787ae1e8"
        }
    }
},
"_links": {
    "self": {
        "href": "/api/protocols/san/iscsi/sessions/a009a9e7-4081-b576-7575-ada21efcaf16/iscsi_lif1/10"
    }
}
}
]
,
```

Retrieve iSCSI sessions

GET /protocols/san/iscsi/sessions

Introduced In: 9.6

Retrieves iSCSI sessions.

Related ONTAP commands

- vserver iscsi connection show
- vserver iscsi session parameter show

- `vserver iscsi session show`

Learn more

- [DOC /protocols/san/iscsi/sessions](#)

Parameters

| Name | Type | In | Required | Description |
|----------------------------------|---------|-------|----------|--|
| target_portal_group_tag | integer | query | False | Filter by target_portal_group_tag |
| initiator.alias | string | query | False | Filter by initiator.alias |
| initiator.name | string | query | False | Filter by initiator.name |
| initiator.comment | string | query | False | Filter by initiator.comment <ul style="list-style-type: none"> • Introduced in: 9.9 |
| svm.uuid | string | query | False | Filter by svm.uuid |
| svm.name | string | query | False | Filter by svm.name |
| isid | string | query | False | Filter by isid |
| connections.interface.name | string | query | False | Filter by connections.interface.name |
| connections.interface.uuid | string | query | False | Filter by connections.interface.uuid |
| connections.interface.ip.address | string | query | False | Filter by connections.interface.ip.address |

| Name | Type | In | Required | Description |
|---------------------------------------|---------------|-------|----------|--|
| connections.interface.ip.port | integer | query | False | Filter by connections.interface.ip.port <ul style="list-style-type: none"> • Max value: 65536 • Min value: 1 |
| connections.cid | integer | query | False | Filter by connections.cid |
| connections.authentication_type | string | query | False | Filter by connections.authentication_type |
| connections.initiator_address.port | integer | query | False | Filter by connections.initiator_address.port |
| connections.initiator_address.address | string | query | False | Filter by connections.initiator_address.address |
| igroups.uuid | string | query | False | Filter by igroups.uuid |
| igroups.name | string | query | False | Filter by igroups.name <ul style="list-style-type: none"> • maxLength: 96 • minLength: 1 |
| target_portal_group | string | query | False | Filter by target_portal_group |
| tsih | integer | query | False | Filter by tsih |
| fields | array[string] | query | False | Specify the fields to return. |
| max_records | integer | query | False | Limit the number of records returned. |

| Name | Type | In | Required | Description |
|----------------|---------------|-------|----------|--|
| return_records | boolean | query | False | <p>The default is true for GET calls. When set to false, only the number of records is returned.</p> <ul style="list-style-type: none"> • Default value: 1 |
| return_timeout | integer | query | False | <p>The number of seconds to allow the call to execute before returning. When iterating over a collection, the default is 15 seconds. ONTAP returns earlier if either max records or the end of the collection is reached.</p> <ul style="list-style-type: none"> • Max value: 120 • Min value: 0 • Default value: 1 |
| order_by | array[string] | query | False | Order results by specified fields and optional [asc] |

Response

```
Status: 200, Ok
```

| Name | Type | Description |
|-------------|--|--|
| _links | _links | |
| num_records | integer | The number of records in the response. |
| records | array[iscsi_session] | |

Example response

```
{  
    "_links": {  
        "next": {  
            "href": "/api/resourcelink"  
        },  
        "self": {  
            "href": "/api/resourcelink"  
        }  
    },  
    "num_records": 1,  
    "records": {  
        "_links": {  
            "self": {  
                "href": "/api/resourcelink"  
            }  
        },  
        "connections": {  
            "_links": {  
                "next": {  
                    "href": "/api/resourcelink"  
                },  
                "self": {  
                    "href": "/api/resourcelink"  
                }  
            },  
            "authentication_type": "chap",  
            "cid": 0,  
            "initiator_address": {  
                "address": "10.10.10.7",  
                "port": 55432  
            },  
            "interface": {  
                "_links": {  
                    "self": {  
                        "href": "/api/resourcelink"  
                    }  
                },  
                "ip": {  
                    "address": "10.10.10.7",  
                    "port": 3260  
                },  
                "name": "lif1",  
                "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
            }  
        }  
    }  
}
```

```

},
"igroups": {
  "_links": {
    "self": {
      "href": "/api/resourcelink"
    }
  },
  "name": "igroup1",
  "uuid": "4ea7a442-86d1-11e0-ae1c-123478563412"
},
"initiator": {
  "alias": "initiator_alias1",
  "comment": "This is an iSCSI initiator for host 5",
  "name": "iqn.1992-01.example.com:string"
},
"isid": "61:62:63:64:65:00",
"svm": {
  "_links": {
    "self": {
      "href": "/api/resourcelink"
    }
  },
  "name": "svml1",
  "uuid": "02c9e252-41be-11e9-81d5-00a0986138f7"
},
"target_portal_group": "tpgroup1",
"target_portal_group_tag": 0,
"tsih": 0
}
}

```

Error

Status: Default, Error

| Name | Type | Description |
|-------|----------------|-------------|
| error | returned_error | |

Example error

```
{  
  "error": {  
    "arguments": {  
      "code": "string",  
      "message": "string"  
    },  
    "code": "4",  
    "message": "entry doesn't exist",  
    "target": "uuid"  
  }  
}
```

Definitions

See Definitions

href

| Name | Type | Description |
|------|--------|-------------|
| href | string | |

_links

| Name | Type | Description |
|------|----------------------|-------------|
| next | href | |
| self | href | |

_links

| Name | Type | Description |
|------|----------------------|-------------|
| self | href | |

initiator_address

The TCP socket information for the initiator end of the connection. This is useful for network packet debugging.

| Name | Type | Description |
|---------|---------|--|
| address | string | The TCP IPv4 or IPv6 address of the initiator end of the iSCSI connection. |
| port | integer | The TCP port number of the initiator end of the iSCSI connection. |

ip

The IP information. ONTAP only supports port 3260.

| Name | Type | Description |
|---------|---------|---|
| address | string | IPv4 or IPv6 address |
| port | integer | The TCP port number of the iSCSI access endpoint. |

interface

The network interface information for the target end of the connection.

| Name | Type | Description |
|--------|------------------------|--|
| _links | _links | |
| ip | ip | The IP information. ONTAP only supports port 3260. <ul style="list-style-type: none"> • readOnly: 1 • Introduced in: 9.6 |
| name | string | The name of the interface. |
| uuid | string | The UUID that uniquely identifies the interface. |

iscsi_connection

An active iSCSI connection.

| Name | Type | Description |
|---------------------|-----------------------------------|--|
| _links | _links | |
| authentication_type | string | The iSCSI authentication type used to establish the connection. |
| cid | integer | The identifier of the connection within the session. |
| initiator_address | initiator_address | The TCP socket information for the initiator end of the connection. This is useful for network packet debugging. |
| interface | interface | The network interface information for the target end of the connection. |

igroups

| Name | Type | Description |
|--------|------------------------|---|
| _links | _links | |
| name | string | The name of the initiator group. |
| uuid | string | The unique identifier of the initiator group. |

initiator

The initiator that created the session.

| Name | Type | Description |
|---------|--------|--|
| alias | string | The initiator alias. |
| comment | string | A comment available for use by the administrator. This is modifiable from the initiator REST endpoint directly. See PATCH /protocols/san/igroups/{igroup.uuid}/initiators/{name} . |
| name | string | The world wide unique name of the initiator. |

svm

SVM, applies only to SVM-scoped objects.

| Name | Type | Description |
|--------|------------------------|---|
| _links | _links | |
| name | string | The name of the SVM. This field cannot be specified in a PATCH method. |
| uuid | string | The unique identifier of the SVM. This field cannot be specified in a PATCH method. |

iscsi_session

An iSCSI session is one or more TCP connections that link an iSCSI initiator with an iSCSI target. TCP connections can be added and removed from an iSCSI session by the iSCSI initiator. Across all TCP connections within an iSCSI session, an initiator sees one and the same target. After the connection is established, iSCSI control, data, and status messages are communicated over the session.

| Name | Type | Description |
|-------------|---|--|
| _links | _links | |
| connections | array[iscsi_connection] | The iSCSI connections that make up the iSCSI session. |
| igroups | array[igroups] | The initiator groups in which the initiator is a member. |
| initiator | initiator | The initiator that created the session. |

| Name | Type | Description |
|-------------------------|---------|--|
| isid | string | The initiator portion of the session identifier specified by the initiator during login. |
| svm | svm | SVM, applies only to SVM-scoped objects. |
| target_portal_group | string | The target portal group to which the session belongs. |
| target_portal_group_tag | integer | The target portal group tag of the session. |
| tsih | integer | The target session identifier handle (TSIH) of the session. |

error_arguments

| Name | Type | Description |
|---------|--------|------------------|
| code | string | Argument code |
| message | string | Message argument |

returned_error

| Name | Type | Description |
|-----------|------------------------|---|
| arguments | array[error_arguments] | Message arguments |
| code | string | Error code |
| message | string | Error message |
| target | string | The target parameter that caused the error. |

Retrieve an iSCSI session

GET /protocols/san/iscsi/sessions/{svm.uuid}/{tpgroup}/{tsih}

Introduced In: 9.6

Retrieves an iSCSI session.

Related ONTAP commands

- vserver iscsi connection show
- vserver iscsi session parameter show
- vserver iscsi session show

Learn more

- [DOC /protocols/san/iscsi/sessions](#)

Parameters

| Name | Type | In | Required | Description |
|----------|---------------|-------|----------|--|
| svm.uuid | string | path | True | The unique identifier of the SVM of the iSCSI session. |
| tpgroup | string | path | True | The target portal group of the iSCSI session. |
| tsih | integer | path | True | The target session identifying handle. |
| fields | array[string] | query | False | Specify the fields to return. |

Response

```
Status: 200, Ok
```

| Name | Type | Description |
|-------------|---|--|
| _links | _links | |
| connections | array[iscsi_connection] | The iSCSI connections that make up the iSCSI session. |
| igroups | array[igroups] | The initiator groups in which the initiator is a member. |
| initiator | initiator | The initiator that created the session. |

| Name | Type | Description |
|-------------------------|---------------------|--|
| isid | string | The initiator portion of the session identifier specified by the initiator during login. |
| svm | svm | SVM, applies only to SVM-scoped objects. |
| target_portal_group | string | The target portal group to which the session belongs. |
| target_portal_group_tag | integer | The target portal group tag of the session. |
| tsih | integer | The target session identifier handle (TSIH) of the session. |

Example response

```
{  
    "_links": {  
        "self": {  
            "href": "/api/resourcelink"  
        }  
    },  
    "connections": {  
        "_links": {  
            "next": {  
                "href": "/api/resourcelink"  
            },  
            "self": {  
                "href": "/api/resourcelink"  
            }  
        },  
        "authentication_type": "chap",  
        "cid": 0,  
        "initiator_address": {  
            "address": "10.10.10.7",  
            "port": 55432  
        },  
        "interface": {  
            "_links": {  
                "self": {  
                    "href": "/api/resourcelink"  
                }  
            },  
            "ip": {  
                "address": "10.10.10.7",  
                "port": 3260  
            },  
            "name": "lif1",  
            "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"  
        }  
    },  
    "igroups": {  
        "_links": {  
            "self": {  
                "href": "/api/resourcelink"  
            }  
        },  
        "name": "igroup1",  
        "uuid": "4ea7a442-86d1-11e0-ae1c-123478563412"  
    },  
}
```

```

"initiator": {
    "alias": "initiator_alias1",
    "comment": "This is an iSCSI initiator for host 5",
    "name": "iqn.1992-01.example.com:string"
},
"isid": "61:62:63:64:65:00",
"svm": {
    "_links": {
        "self": {
            "href": "/api/resourcelink"
        }
    },
    "name": "svm1",
    "uuid": "02c9e252-41be-11e9-81d5-00a0986138f7"
},
"target_portal_group": "tpgroup1",
"target_portal_group_tag": 0,
"tsih": 0
}

```

Error

Status: Default

ONTAP Error Response Codes

| Error Code | Description |
|------------|--|
| 2621462 | An SVM with the specified UUID does not exist. |

Also see the table of common errors in the [Response body](#) overview section of this documentation.

| Name | Type | Description |
|-------|--------------------------------|-------------|
| error | returned_error | |

Example error

```
{  
  "error": {  
    "arguments": {  
      "code": "string",  
      "message": "string"  
    },  
    "code": "4",  
    "message": "entry doesn't exist",  
    "target": "uuid"  
  }  
}
```

Definitions

See Definitions

href

| Name | Type | Description |
|------|--------|-------------|
| href | string | |

_links

| Name | Type | Description |
|------|------|-------------|
| self | href | |

_links

| Name | Type | Description |
|------|------|-------------|
| next | href | |
| self | href | |

initiator_address

The TCP socket information for the initiator end of the connection. This is useful for network packet debugging.

| Name | Type | Description |
|---------|---------|--|
| address | string | The TCP IPv4 or IPv6 address of the initiator end of the iSCSI connection. |
| port | integer | The TCP port number of the initiator end of the iSCSI connection. |

ip

The IP information. ONTAP only supports port 3260.

| Name | Type | Description |
|---------|---------|---|
| address | string | IPv4 or IPv6 address |
| port | integer | The TCP port number of the iSCSI access endpoint. |

interface

The network interface information for the target end of the connection.

| Name | Type | Description |
|--------|------------------------|--|
| _links | _links | |
| ip | ip | The IP information. ONTAP only supports port 3260. <ul style="list-style-type: none"> • readOnly: 1 • Introduced in: 9.6 |
| name | string | The name of the interface. |
| uuid | string | The UUID that uniquely identifies the interface. |

iscsi_connection

An active iSCSI connection.

| Name | Type | Description |
|---------------------|-----------------------------------|--|
| _links | _links | |
| authentication_type | string | The iSCSI authentication type used to establish the connection. |
| cid | integer | The identifier of the connection within the session. |
| initiator_address | initiator_address | The TCP socket information for the initiator end of the connection. This is useful for network packet debugging. |
| interface | interface | The network interface information for the target end of the connection. |

igroups

| Name | Type | Description |
|--------|------------------------|---|
| _links | _links | |
| name | string | The name of the initiator group. |
| uuid | string | The unique identifier of the initiator group. |

initiator

The initiator that created the session.

| Name | Type | Description |
|---------|--------|--|
| alias | string | The initiator alias. |
| comment | string | A comment available for use by the administrator. This is modifiable from the initiator REST endpoint directly. See PATCH /protocols/san/igroups/{igroup.uuid}/initiators/{name} . |
| name | string | The world wide unique name of the initiator. |

svm

SVM, applies only to SVM-scoped objects.

| Name | Type | Description |
|--------|------------------------|---|
| _links | _links | |
| name | string | The name of the SVM. This field cannot be specified in a PATCH method. |
| uuid | string | The unique identifier of the SVM. This field cannot be specified in a PATCH method. |

error_arguments

| Name | Type | Description |
|---------|--------|------------------|
| code | string | Argument code |
| message | string | Message argument |

returned_error

| Name | Type | Description |
|-----------|--|-------------------|
| arguments | array[error_arguments] | Message arguments |
| code | string | Error code |
| message | string | Error message |

| Name | Type | Description |
|--------|--------|---|
| target | string | The target parameter that caused the error. |

Copyright information

Copyright © 2024 NetApp, Inc. All Rights Reserved. Printed in the U.S. No part of this document covered by copyright may be reproduced in any form or by any means—graphic, electronic, or mechanical, including photocopying, recording, taping, or storage in an electronic retrieval system—with prior written permission of the copyright owner.

Software derived from copyrighted NetApp material is subject to the following license and disclaimer:

THIS SOFTWARE IS PROVIDED BY NETAPP “AS IS” AND WITHOUT ANY EXPRESS OR IMPLIED WARRANTIES, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE, WHICH ARE HEREBY DISCLAIMED. IN NO EVENT SHALL NETAPP BE LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO, PROCUREMENT OF SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA, OR PROFITS; OR BUSINESS INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE) ARISING IN ANY WAY OUT OF THE USE OF THIS SOFTWARE, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE.

NetApp reserves the right to change any products described herein at any time, and without notice. NetApp assumes no responsibility or liability arising from the use of products described herein, except as expressly agreed to in writing by NetApp. The use or purchase of this product does not convey a license under any patent rights, trademark rights, or any other intellectual property rights of NetApp.

The product described in this manual may be protected by one or more U.S. patents, foreign patents, or pending applications.

LIMITED RIGHTS LEGEND: Use, duplication, or disclosure by the government is subject to restrictions as set forth in subparagraph (b)(3) of the Rights in Technical Data -Noncommercial Items at DFARS 252.227-7013 (FEB 2014) and FAR 52.227-19 (DEC 2007).

Data contained herein pertains to a commercial product and/or commercial service (as defined in FAR 2.101) and is proprietary to NetApp, Inc. All NetApp technical data and computer software provided under this Agreement is commercial in nature and developed solely at private expense. The U.S. Government has a non-exclusive, non-transferrable, nonsublicensable, worldwide, limited irrevocable license to use the Data only in connection with and in support of the U.S. Government contract under which the Data was delivered. Except as provided herein, the Data may not be used, disclosed, reproduced, modified, performed, or displayed without the prior written approval of NetApp, Inc. United States Government license rights for the Department of Defense are limited to those rights identified in DFARS clause 252.227-7015(b) (FEB 2014).

Trademark information

NETAPP, the NETAPP logo, and the marks listed at <http://www.netapp.com/TM> are trademarks of NetApp, Inc. Other company and product names may be trademarks of their respective owners.