



# **Guidelines for using the storage delete command**

## **Snapdrive for Unix**

NetApp  
August 30, 2024

This PDF was generated from [https://docs.netapp.com/us-en/snapdrive-unix/solaris/concept\\_guidelines\\_for\\_storage\\_deletion\\_in\\_a\\_host\\_cluster\\_environment.html](https://docs.netapp.com/us-en/snapdrive-unix/solaris/concept_guidelines_for_storage_deletion_in_a_host_cluster_environment.html) on August 30, 2024. Always check docs.netapp.com for the latest.

# Table of Contents

- Guidelines for using the storage delete command ..... 1
  - Guidelines for storage deletion in a host cluster environment ..... 1

# Guidelines for using the storage delete command

The `snapdrive storage delete` command has some restrictions in SnapDrive for UNIX.

- When you delete a file system, SnapDrive for UNIX always removes the file system's mount point.
- If you use the `-lun` option to specify the name of a LUN that is a member of either a host disk group or a file system, the `snapdrive storage delete` command fails.
- If you use `-lun` option to specify the name of the LUN that is not discovered by multipathing software on the host, the `snapdrive storage delete` command fails.

For example, on Solaris hosts, the LUN has to be under DMP control. In other words, the LUN has to have a corresponding `/dev/vx/dmp` device.

## Guidelines for storage deletion in a host cluster environment

You must be aware of some guidelines for using the `snapdrive storage delete` command in a host cluster environment.

- If you initiate the `snapdrive storage delete` command with `-devicetype shared` option from any nonmaster node in the host cluster, the command is sent to the master node and executed. For this to happen, you have to ensure that the `rsh` or `ssh access-without-password-prompt` is allowed on all the host cluster nodes.
- The `snapdrive storage delete` command can be executed from any node in the host cluster.
- For the storage delete operation to be successful, neither should be false:
  - The storage entities have to be shared.
  - The LUNs should be mapped to all the nodes in the host cluster.
- You can delete a storage entity on a specific node either by using the `-devicetype dedicated` option or by omitting the `-devicetype` option in the command line syntax, altogether because the default value is `dedicated`.
- The `snapdrive storage delete` command gives an error message if a shared storage entity or LUN is deleted with `-devicetype dedicated` option, or if a dedicated storage entity or LUN is deleted with `shared` option.
- The storage delete operation fails, if one of the following happens:
  - If any error occurs during the process of deleting a storage entity.

SnapDrive for UNIX deletes the storage entities, disconnect the LUNs from all the nonmaster nodes and then disconnect and delete the LUNs from the master node in the host cluster.

- If a node in the host cluster shuts down and reboots before the `snapdrive storage delete` command is executed.

This happens because the LUNs are still be mapped to the non-existing node. To avoid this, use the

-force option.

## Copyright information

Copyright © 2024 NetApp, Inc. All Rights Reserved. Printed in the U.S. No part of this document covered by copyright may be reproduced in any form or by any means—graphic, electronic, or mechanical, including photocopying, recording, taping, or storage in an electronic retrieval system—without prior written permission of the copyright owner.

Software derived from copyrighted NetApp material is subject to the following license and disclaimer:

THIS SOFTWARE IS PROVIDED BY NETAPP “AS IS” AND WITHOUT ANY EXPRESS OR IMPLIED WARRANTIES, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE, WHICH ARE HEREBY DISCLAIMED. IN NO EVENT SHALL NETAPP BE LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO, PROCUREMENT OF SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA, OR PROFITS; OR BUSINESS INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE) ARISING IN ANY WAY OUT OF THE USE OF THIS SOFTWARE, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE.

NetApp reserves the right to change any products described herein at any time, and without notice. NetApp assumes no responsibility or liability arising from the use of products described herein, except as expressly agreed to in writing by NetApp. The use or purchase of this product does not convey a license under any patent rights, trademark rights, or any other intellectual property rights of NetApp.

The product described in this manual may be protected by one or more U.S. patents, foreign patents, or pending applications.

LIMITED RIGHTS LEGEND: Use, duplication, or disclosure by the government is subject to restrictions as set forth in subparagraph (b)(3) of the Rights in Technical Data -Noncommercial Items at DFARS 252.227-7013 (FEB 2014) and FAR 52.227-19 (DEC 2007).

Data contained herein pertains to a commercial product and/or commercial service (as defined in FAR 2.101) and is proprietary to NetApp, Inc. All NetApp technical data and computer software provided under this Agreement is commercial in nature and developed solely at private expense. The U.S. Government has a non-exclusive, non-transferrable, nonsublicensable, worldwide, limited irrevocable license to use the Data only in connection with and in support of the U.S. Government contract under which the Data was delivered. Except as provided herein, the Data may not be used, disclosed, reproduced, modified, performed, or displayed without the prior written approval of NetApp, Inc. United States Government license rights for the Department of Defense are limited to those rights identified in DFARS clause 252.227-7015(b) (FEB 2014).

## Trademark information

NETAPP, the NETAPP logo, and the marks listed at <http://www.netapp.com/TM> are trademarks of NetApp, Inc. Other company and product names may be trademarks of their respective owners.