



XCP event logs

XCP

NetApp
June 11, 2024

Table of Contents

- XCP event logs 1
- XCP NFS event logs 1
- XCP SMB event logs 13

XCP event logs

XCP NFS event logs

Review example event logs for XCP NFS.

The following table shows event logs for XCP NFS.

Event ID	Event template	Event example
401	Mounted on NFS export <mount path> with maximum read block size <read block size> bytes, maximum write block size <write block size> bytes. Mount point has mode value<mode bits> and type: <fattr3 type>.	2020-07-14 03:53:59,811 - INFO {"Event ID":401, "Event Category": "Mounting unmounting file system", "Event Type": "Mount file system information", "ExecutionId": 408249379415, "Event Source": "NETAPP-01", "Description": "Mounted on NFS export <IPaddress of NFS server>:/test1 with maximum read block size 65536 bytes, maximum write block size 65536 bytes. Mount point has mode value 493 and type : Directory"}
181	This license is issued to <username>of <company name>,license type is <license type> with <license status> status, license will expire on <expire date>	2020-07-14 03:53:59,463 - INFO {"Event ID": 181, "Event Category": "Authentication and authorization", "Event Type": "License information", "ExecutionId": 408249379415, "Event Source": "NETAPP-01", "Description": "This license is issued to NetApp User of Network Appliance, Inc, license type is SANDBOX with ACTIVE status, license will expire on Thu Jul 1 00:00:00 2021"}

Event ID	Event template	Event example
183	The license issued to <username> of <company name> will expire in less than one week	2020-07-14 04:02:55,151 - WARNING {"Event ID": 183, "Event Category": "Authentication and authorisation", "Event Type": "License warning", "ExecutionId": 408249519546, "Event Source": "NETAPP-01", "Description": "The license issued to NetApp User of Network Appliance, Inc will expire in less than one week"}
581	Catalog path <catalog volume path> to store catalog directory is not accessible. Refer user guide for configuring catalog volume.	2020-07-14 04:05:00,857 - ERROR {"Event ID": 581, "Event Category": "Catalog and indexing", "Event Type": "Catalog exporting error", "ExecutionId": 408249552351, "Event Source": "NETAPP-01", "Description": "Catalog path <IP address of NFS server>:/test11 to store catalog directory is not accessible. Refer user guide for configuring catalog volume."}
582	Failed creating catalog directory in catalog volume path <catalog volume path>	2020-07-14 04:10:12,895 - ERROR {"Event ID": 582, "Event Category": "Catalog and indexing", "Event Type": "Catalog directory creation error", "ExecutionId": 408249630498, "Event Source": "NETAPP-01", "Description": "Failed creating catalog directory in catalogvolume path 10.234.104.250:/cat_vol"}

Event ID	Event template	Event example
584	Error in creating index directory <index id> for <command>	2020-07-14 04:52:15,918 - ERROR {"Event ID":584, "Event Category": "Catalog and indexing", "Event Type": "Error in index creation", "ExecutionId": 408250278214, "Event Source": "NETAPP-01", "Description": "Error in creating index directory abc7 for scan"}
586	Failed to create index <index id> in catalog volume while executing command : <command>	2020-07-14 04:45:46,275 - ERROR {"Event ID": 586, "Event Category": "Catalog and indexing", "Event Type": "Error in index creation", "ExecutionId": 408250177021, "Event Source": "NETAPP-01", "Description": "Failed to create index abc6 in catalog volume while executing command : scan {- newid: 'abc6'}"}
351	System resources available while executing xcp command: <command>, are : <CPU info>, <memory info>	2020-07-14 05:08:35,393 - INFO {"Event ID":351, "Event Category": "System resource utilization", "Event Type": "Resources available for scan", "ExecutionId": 408250529264, "Event Source": "NETAPP-01", "Description": "System resources available while executing xcp command : scan , are : CPU: count 4, load avg (1/5/15m) 0.0, 0.0, 0.0, System memory (GiB): avail 7.3, total 7.8, free 6.6, buffer 0.1, cache 0.5"}

Event ID	Event template	Event example
13	XCP <command> is running on platform <platform info> for source <source info>	2020-07-14 05:08:35,478 - INFO {"Event ID": 13, "Event Category": "XCP job status", "Event Type": "Starting xcp scan operation", "ExecutionId": 408250529264, "Event Source": "NETAPP-01", "Description": "XCP command : scan {-newid: 'abc7'} is running on platform Linux-2.6.26-2-amd64-x86_64-with-debian- 5.0.10 for source 10.234.104.250:/test1"}
14	XCP scan completed successfully after scanning <scan item count> items. Source : <source scanned>	2020-07-14 05:08:35,653 - INFO {"Event ID": 14, "Event Category": "XCP job status", "Event Type": "XCP scan completion", "ExecutionId": 408250529264, "Event Source": "NETAPP-01", "Description": "XCP scan completed successfully after scanning 479 items. Source : 10.234.104.250:/test1"}
354	System resources available while executing xcp command: <command>, are : <CPU info>, <memory info>	2020-07-14 05:15:13,562 - INFO {"Event ID": 354, "Event Category": "System resource utilization", "Event Type": "Resources available for copy", "ExecutionId": 408250596708, "Event Source": "NETAPP-01", "Description": "System resources available while executing xcp command : copy , are : CPU: count 4, load avg (1/5/15m) 0.0, 0.0, 0.0, System memory (GiB): avail 7.3, total 7.8, free 6.6, buffer 0.1, cache 0.5"}

Event ID	Event template	Event example
25	XCP <command> is running on platform <platform info> for source <copy source> and destination <copy destination/target>	2020-07-14 05:15:13,647 - INFO {"Event ID": 25, "Event Category": "XCP job status", "Event Type": "Starting xcp copy operation", "ExecutionId": 408250596708, "Event Source": "NETAPP-01", "Description": "XCP command : copy {} is running on platform Linux-2.6.26- 2-amd64-x86 64-with-debian-5.0.10 for source <IP address of NFS server>:/source_vol and destination <NFS destination source>:/test1"}
26	XCP copy completed successfully after scanning <scanned item count> of which <matched item count> are matched and <copied item count> items are copied to the destination. Source : <copy source>, destination :<copy destination/target	2020-07-14 05:15:13,885 - INFO {"Event ID":26, "Event Category": "XCP job status", "Event Type": "XCP copy completion", "ExecutionId": 408250596708, "Event Source": "NETAPP-01", "Description": "XCP copy completed successfully after scanning 3 of which 0 are matched and 2 items are copied to the destination. Source : <IP address of NFS server>:/source_vol, destination : <NFS destination source>:/test1"}

Event ID	Event template	Event example
16	XCP <command> is running on platform <platform info> for source <sync source> and destination <sync destination>	2020-07-14 06:41:20,145 - INFO {"Event ID": 16, "Event Category": "XCP job status", "Event Type": "Starting xcp sync operation", "ExecutionId": 408251920146, "Event Source": "NETAPP-01", "Description": "XCP command : sync {-id: 'autoname_copy_2020-07-14_06.22.07.233271'} is running on platform Linux-2.6.26-2-amd64-x86_64-with-debian-5.0.10 for source <IP address of NFS server>:/src_vol and destination <NFS destination source>:/dest_vol"}
352	System resources available while executing xcp command: <command>, are : <CPU info>, <memory info>	2020-07-14 06:41:28,728 - INFO {"Event ID": 352, "Event Category": "System resource utilization", "Event Type": "Resource available for sync", "ExecutionId": 408251920146, "Event Source": "NETAPP-01", "Description": "System resources available while executing xcp command : sync {-id: 'autoname_copy_2020-07-14_06.22.07.233271'} , are : CPU: count 4, load avg (1/5/15m) 0.1, 0.0, 0.0, System memory (GiB): avail 7.2, total 7.8, free 6.6, buffer 0.1, cache 0.5"}

Event ID	Event template	Event example
17	XCP sync is completed. Total scanned <scanned item count>, copied <copied item count>, modification <modification item count>, new file <new file count>, delete item <delete item count>. Command executed : <command>	2020-07-14 06:41:29,245 - INFO {"Event ID":17, "Event Category": "XCP job status", "Event Type": "XCP sync completion", "ExecutionId": 408251920146, "Event Source": "NETAPP-01", "Description": "XCP sync is completed. Total scanned 66, copied 0, modification 1, new file 0, delete item 0. Command executed : sync {-id: 'autoname_copy_2020-07-14_06.22.07.233271'}"}}
19	XCP <command> is running on platform <platform info> for source <verify source> and destination <verify destination>	2020-07-14 06:54:59,084 - INFO {"Event ID": 19, "Event Category": "XCP job status", "Event Type": "Starting xcp verify operation", "ExecutionId": 408252130477, "Event Source": "NETAPP-01", "Description": "XCP command : verify {} is running on platform Linux-2.6.26-2-amd64-x86_64-with- debian-5.0.10 for source <IP address of NFS server>:/src_vol and destination <IP address of NFS destination server>:/dest_vol"}}
353	System resources available while executing xcp command: <command>, are : <CPU info>, <memory info>	2020-07-14 06:54:59,085 - INFO {"Event ID": 353, "Event Category": "System resource utilization", "Event Type": "Resources available for verify", "ExecutionId": 408252130477, "Event Source": "NETAPP-01", "Description": "System resources available while executing xcp command : verify , are : CPU: count 4, load avg (1/5/15m) 0.0, 0.0, 0.0, System memory (GiB): avail 7.3, total 7.8, free 6.6, buffer 0.1, cache 0.5"}}

Event ID	Event template	Event example
211	log file path : <file path> , severity filter level <severity level>, log message sanitization is set as <sanitization value>	2020-07-14 06:40:59,104 - INFO {"Event ID": 211, "Event Category": "Logging and supportability", "Event Type": "XCP logging information", "ExecutionId": 408251920146, "Event Source": "NETAPP-01", "Description": "Log file path : /opt/NetApp/xFiles/xcp/xcplogs/xcp.log, severity filter level INFO, log message sanitization is set as False"}
215	Event file path: <file path>, severity filter level <severity level>, event message sanitization is set as <sanitization value>	2020-07-14 06:40:59,105 - INFO {"Event ID": 215, "Event Category": "Logging and supportability", "Event Type": "XCP event information", "ExecutionId": 408251920146, "Event Source": "NETAPP-01", "Description": "Event file path : /opt/NetApp/xFiles/xcp/xcplogs/xcp_event.log, severity filter level INFO, event message sanitization is set as False"}
54	Catalog volume is left with no free space please increase the size of catalog volume <catalog volume running out of space>	2020-07-14 04:10:12,897 - ERROR {"Event ID":54, "Event Category": "Application failure", "Event Type": "No space left on Catalog volume error", "ExecutionId": 408249630498, "Event Source": "NETAPP-01", "Description": "Catalog volume is left with no free space. Please increase the size of catalog volume<IP address of NFS destination server>:/cat_vol"}

Event ID	Event template	Event example
53	Catalog volume <catalog volume> is left with no free space to store index <index id> while executing <command>. Please increase the size of the catalog volume <catalog volume running out of space>	2020-07-14 04:52:15,922 - ERROR {"Event ID": 53, "Event Category": "Application failure", "Event Type": "No space left for catalog volume error", "ExecutionId": 408250278214, "Event Source": "NETAPP-01", "Description": "Catalog volume 10.234.104.250:/cat_vol is left with no free space to store index abc7 while executing : scan {-newid: 'abc7'}. Please increase the size of the catalog volume <IP address of NFS destination server>:/cat_vol"}
61	NFS LIF <LIF IP> is not reachable for path <volume path without IP> while executing <command>. Please check volume is not offline and is reachable.	2020-07-14 07:38:20,100 - ERROR {"Event ID":61, "Event Category": "Application failure", "Event Type": "NFS mount has failed", "ExecutionId": 408252799101, "Event Source": "NETAPP-01", "Description": "NFS LIF <IP address of NFS destination server> is not reachable for path /test11 while executing : scan {}. Please check volume is not offline and is reachable"}
71	TCP connection could not be established for IP address <IP>. Check network setting and configuration.	2020-07-14 07:44:44,578 - ERROR {"Event ID": 71, "Event Category": "Application failure", "Event Type": "IP is not active", "ExecutionId": 408252889541, "Event Source": "NETAPP-01", "Description": "TCP connection could not be established to the address <IP address of NFS destination server>. Check network setting and configuration."} (UT done)

Event ID	Event template	Event example
51	Target volume is left with no free space while executing: <command>. Please increase the size of target volume <volume running out of space>.	2020-07-14 07:07:07,286 - ERROR {"Event ID": 51, "Event Category": "Application failure", "Event Type": "No space left on destination error", "ExecutionId": 408252316712, "Event Source": "NETAPP-01", "Description": "Target volume is left with no free space while executing : copy {}. Please increase the size of target volume <IP address of NFS destination server>:/cat_vol"}
76	Index id {} is already present . Use new index id and rerun command : <command>	2020-07-14 09:18:41,441 - ERROR {"Event ID": 76, "Event Category": "Application failure", "Event Type": "Index ID problem", "ExecutionId": null, "Event Source": "NETAPP-01", "Description": "Index id asd is already present . Use new index id and rerun command: scan {-newid: 'asd'} "}
362	CPU usage has crossed <percentage CPU used>%	2020-06-16 00:17:28,294 - ERROR {"Event ID": 362, "Event Category": "System resource utilization", "Event Type": "resources available for xcp", "Event Source": "NETAPP- 01 ", "Description": "CPU Usage has crossed 90.07%"}
363	Memory Usage has crossed <percentage memory used>%	2020-06-16 00:17:28,300 - ERROR {"Event ID": 363, "Event Category": "System resource utilization", "Event Type": "resources available for xcp", "Event Source": "NETAPP- 01", "Description": "Memory Usage has crossed 95%"}

Event ID	Event template	Event example
22	XCP <command> is running on platform <platform information> for source <resume source> and destination <resume destination>	<pre>2020-07-14 06:24:26,768 - INFO {"Event ID": 22, "Event Category": "XCP job status", "Event Type": "Starting xcp resume operation", "ExecutionId": 408251663404, "Event Source": "NETAPP-01", "Description": "XCP command : resume {-id: 'autoname_copy_2020-07-14_06.22.07.233271'} is running on platform Linux-2.6.26-2-amd64- x86_64-with-debian-5.0.10 for source <IP address for NFS sever>:/src_vol and destination <IP address of NFS destination server>:/dest_vol"} </pre>
356	System resources available while executing xcp command: <command> , are : <CPU info>, <memory information>	<pre>2020-07-14 06:24:26,837 - INFO {"Event ID": 356, "Event Category": "System resource utilization", "Event Type": "Resource available for resume", "ExecutionId": 408251663404, "Event Source": "NETAPP-01", "Description": "System resources available while executing xcp command : resume {-id: 'autoname_copy_2020-07-14_06.22.07.233271'} , are : CPU: count 4, load avg (1/5/15m) 0.1, 0.1, 0.0, System memory (GiB): avail 7.2, total 7.8, free 6.6, buffer 0.1, cache 0.5"} </pre>

Event ID	Event template	Event example
23	XCP resume is completed. Total scanned items <scanned item count>, total copied items <copied item count>. Command executed :<command>	2020-07-14 06:26:15,608 - INFO {"Event ID": 23, "Event Category": "XCP job status", "Event Type": "XCP resume completion", "ExecutionId": 408251663404, "Event Source": "NETAPP-01", "Description": "XCP resume is completed. Total scanned items 5982, total copied items 5973. Command executed : resume {-id: 'autoname_copy_2020-07-14_06.22.07.233271'} "}
76	Index id <index id> is already present. Use new index id and rerun command : <command>	2020-07-14 09:43:08,381 - ERROR {"Event ID": 76, "Event Category": "Application failure", "Event Type": "Index ID problem", "ExecutionId": null, "Event Source": "NETAPP-01", "Description": "Index id asd is already present . Use new index id and rerun command : scan {-newid: 'asd'} "}
82	Index id <index id> used while executing sync is incomplete. Try resume on the existing index id <index id>	2020-07-14 10:33:09,307 - ERROR {"Event ID": 82, "Event Category": "Application failure", "Event Type": "Incomplete index used for sync", "ExecutionId": null, "Event Source": "NETAPP-01", "Description": "Index id autoname_copy_2020-07-14_10.28.22.323897 used while executing sync is incomplete. Try resume on the existing index id autoname_copy_2020-07-14_10.28.22.323897."}

Event ID	Event template	Event example
365	CPU utilization reduced to <CPU percentage used>%	2020-07-14 09:43:08 381 - ERROR {"Event ID": 364, "Event Category": "System resource utilization", "Event Type": "Resources available for xcp", "ExecutionId": 408251663404, "Event Source": "NETAPP-01", "Description": " CPU utilization reduced to 26%"}
364	Memory utilization reduced to <CPU percentage used>%	2020-07-14 09:43:08,381 - INFO {"Event ID": 364, "Event Category": " Resources available for xcp", "Event Type": "Resources available for xcp", "ExecutionId": 408351663478, "Event Source": "NETAPP-01", "Description": " Memory utilization reduced to 16.2%"}
10	XCP command <command> has failed	2020-07-14 09:43:08,381 - INFO {"Event ID": 10, "Event Category": " Xcp job status", "Event Type": "XCP command failure", "ExecutionId":4082516634506, "Event Source": "NETAPP-01", "Description": " XCP command verify has failed"

XCP SMB event logs

Review example event logs for XCP SMB.

The following table shows event logs for XCP SMB.

Event ID	Event template	Event example
355	CPU usage has crossed <CPU percentage use>%	2020-06-23 12:42:02,705 - INFO {"Event ID": 355, "Event Category": "System resource utilization", "Event Type": "CPU usage for xcp", "Event Source": "NETAPP-01", "Description": "CPU usage has crossed 96%"}

Event ID	Event template	Event example
356	Memory usage has crossed <memory percentage use>%	2020-06-23 12:42:02,705 - INFO { "Event ID": 356, "Event Category": "System resource utilization", "Event Type": "Memory usage for xcp", "Event Source": "NETAPP-01", "Description": "CPU usage has crossed92.5%" }
61	Address was not found: <complete address over which command is fired>	2020-07-15 02:57:06,466 - ERROR { "Event ID": 61, "Event Category": "Application Failure", "Event Type": "Address was not found", "ExecutionId": 408264113696, "Event Source": "NETAPP-01", "Description": "Address was not found: '\\\\<IP address of SMB server>\\cifs1\""} }
62	Interface cannot be found: < complete address over which command is fired >	2020-07-15 02:52:00,603 - ERROR { "Event ID": 62, "Event Category": "Application Failure", "Event Type": "Interface was not found", "ExecutionId": 408264071616, "Event Source": "NETAPP-01", "Description": "Interface cannot be found: '\\\\<IP address of SMB server>\\cifs11\""} }
63	Invalid Address. Please make sure that the Address starts with '\\'	2020-07-15 03:00:10,422 - ERROR { "Event ID": 63, "Event Category": "Application Failure", "Event Type": "Invalid Address", "ExecutionId": 408264197308, "Event Source": "NETAPP-01", "Description": "Invalid Address. Please make sure that the Address starts with '\\'" }

Event ID	Event template	Event example
41	Destination volume is left with no free space please increase the size target volume:<destination volume>	2020-06-15 17:12:46,413 - ERROR { "Event ID": 41, "Event Category": "Application Failure", "Event Type": "No space left on destination error", "Event Source": "NETAPP-01", "Description": "Destination volume is left with no free space please increase the size of target volume: <IP address of SMB server>\\to" }
211	Log file path : <file path>, severity filter level <severity level>, log message sanitization is set as <value of sanitization option>	{ "Event ID": 211, "Event Category": "Logging and supportability", "Event Type": "XCP logging information", "ExecutionId": 408252673852, "Event Source": "NETAPP-01", "Description": "Log file path : C:\\NetApp\\XCP\\Logs\\xcp.log, severity filter level DEBUG, log message sanitization is set as False" }
215	Event file path : <file path>, severity filter level <severity level>, Event message sanitization is set as <sanitization option>	{ "Event ID": 215, "Event Category": "Logging and supportability", "Event Type": "XCP event information", "ExecutionId": 408252673852, "Event Source": "NETAPP-01", "Description": "Event file path : C:\\NetApp\\XCP\\Logs\\xcp_event.log, severity filter level INFO, Event message sanitization is set as False" }

Event ID	Event template	Event example
181	This license is issued to <user name> of <company name>, license type is <license type> with <status> status, license will expire expires on <expiration date>	{"Event ID": 181, "Event Category": "Authentication and authorization", "Event Type": "license information", "ExecutionId": 408252673852, "Event Source": "NETAPP-01", "Description": "This license is issued to calin of NetApp Inc, license type is SANDBOX with ACTIVE status, license will expire on Mon Dec 31 00:00:00 2029"}
13	XCP <command> is running on platform <platform information> for source <scan source>	2020-07-15 02:12:56,917 - INFO {"Event ID": 13, "Event Category": "XCP job status", "Event Type": "Starting xcp scan operation", "ExecutionId": 408263470688, "Event Source": "NETAPP-01", "Description": "XCP {scan} is running on platform Windows- 8.1-6.3.9600-SP0 for source \\\\<IP address of SMB server>\\cifs"}
351	System resources available while command : <command>, are : cpu <CPU information>, total memory <total memory on system>, available memory	2020-07-15 02:12:56,917 - INFO {"Event ID": 351, "Event Category": "System resource utilization", "Event Type": "Resources available for scan", "ExecutionId": 408263470688, "Event Source": "NETAPP-01", "Description": "System resources available while executing xcp command : scan, are : cpu 4, total memory 8.00GiB, available memory 6.81GiB"}

Event ID	Event template	Event example
14	XCP scan completed successfully after scanning <scanned items count> items. Source :<scan source>	2020-07-15 02:12:57,932 - INFO {"Event ID": 14, "Event Category": "XCP job status", "Event Type": "XCP scan completion", "ExecutionId": 408263470688, "Event Source": "NETAPP-01", "Description": "XCP scan completed successfully after scanning 29 items. Source : \\ \\ \\ <IP address of SMB server> \\ \cifs"}
25	XCP <command> is running on platform <platform information> for source <copy source> and destination <copy destination>	2020-07-15 02:19:06,562 - INFO {"Event ID": 25, "Event Category": "XCP job status", "Event Type": "Starting xcp copy operation", "ExecutionId": 408263563552, "Event Source": "NETAPP-01", "Description": "XCP {copy} is running on platform Windows- 8.1-6.3.9600-SP0 for source \\ \\ \\ <IP address of SMB server> \\ \cifs and destination \\ \\ \\ <IP address of SMB destination server> \\ \source_vol"}
352	System resources available while executing command :<command>, are : cpu <CPU information>, total memory <Total memory>, available memory <memory available for execution>	2020-07-15 02:19:06,562 - INFO {"Event ID": 352, "Event Category": "System resource utilization", "Event Type": "Resources available for copy", "ExecutionId": 408263563552, "Event Source": "NETAPP-01", "Description": "System resources available while executing xcp command : copy, are : cpu 4, total memory 8.00GiB, available memory 6.82GiB"}

Event ID	Event template	Event example
26	XCP copy completed successfully after copying <copied items count> items. Source :<copy source>, destination : <copy destination>	2020-07-15 02:19:14,500 - INFO {"Event ID": 26, "Event Category": "XCP job status", "Event Type": "XCP copy completion", "ExecutionId": 408263563552, "Event Source": "NETAPP-01", "Description": "XCP copy completed successfully after copying 0 items. Source :
16	XCP <command> is running on platform <platform> for source <sync source> and destination <sync destination>	2020-07-15 02:27:10,490 - INFO {"Event ID": 16, "Event Category": "XCP job status", "Event Type": "Starting xcp sync operation", "ExecutionId": 408263688308, "Event Source": "NETAPP-01", "Description": "XCP {sync} is running on platform Windows- 8.1-6.3.9600-SP0 for source \\<IP address of SMB server>\\cifs and destination \\<IP address of SMB destination server>\\source_vol"}
353	System resources available while executing xcp command: <command>, are : cpu <CPU information>, total memory <total memory>, available memory <available memory>	2020-07-15 02:27:10,490 - INFO {"Event ID": 353, "Event Category": "System resource utilization", "Event Type": "Resources available for sync", "ExecutionId": 408263688308, "Event Source": "NETAPP-01", "Description": "System resources available while executing xcp command : sync, are : cpu 4, total memory 8.00GiB, available memory 6.83GiB"}

Event ID	Event template	Event example
17	XCP sync completed successfully after scanning <scanned item count> items, copying <copied item count> items, comparing <compared item count> items, removing <removed item count> items. Source : <sync source>, destination : <sync destination>	2020-07-15 03:04:14,269 - INFO {"Event ID": 17, "Event Category": "XCP job status", "Event Type": "XCP sync completion", "ExecutionId": 408264256392, "Event Source": "NETAPP-01", "Description": "XCP sync completed successfully after scanning30 items, copying 20 items, comparing 30 items, removing 0 items. Source : \\\\<IP address of SMB server>\\cifs, destination :\\\\<IP address of SMB destination server>\\source_vol"}
19	XCP <command> is running on platform <platform information> for source <verify source> and destination <verify destination>	2020-07-15 03:14:04,854 - INFO {"Event ID": 19, "Event Category": "XCP job status", "Event Type": "Starting xcp verify operation", "ExecutionId": 408264409944, "Event Source": "NETAPP-01", "Description": "XCP {verify -noacl} is running on platform Windows-8.1-6.3.9600-SP0 for source \\\\<IP address of SMB server>\\cifs and destination \\\\<IP address of SMB destination server>\\source_vol"}
354	System resources available for command : <command>, are : cpu <CPU information>, total memory <total memory>, available memory <available memory for execution>	2020-07-15 03:14:04,854 - INFO {"Event ID": 354, "Event Category": "System resource utilization", "Event Type": "Resources available for verify", "ExecutionId": 408264409944, "Event Source": "NETAPP-01", "Description": "System resources available while executing xcp command : verify, are : cpu 4, total memory 8.00GiB, available memory 6.80GiB"}

Event ID	Event template	Event example
20	XCP verify is completed by scanning <scanned item count> items, comparing <compared item count> items	{"Event ID": 20, "Event Category": "XCP job status", "Event Type": "XCP verify completion", "command Id": 408227440800, "Event Source": "NETAPP-01", "Description": "XCP verify is completed by scanning 59 items, comparing 0 items"}
357	CPU utilization reduced to <CPU utilization percentage>%	{"Event ID": 357, "Event Category": "System resource utilization", "Event Type": "CPU usage for xcp", "Event Source": "NETAPP- 01", "Description": "CPU utilization reduced to 8.2%"}
358	Memory utilization reduced to <memory utilization percentage>%	{"Event ID": 358, "Event Category": "System resource utilization", "Event Type": "Memory usage for xcp", "Event Source": "NETAPP-01", "Description": "Memory utilization reduced to 19%"}
10	XCP command <command> has failed	2020-07-14 09:43:08,381 - INFO {"Event ID": 10, "Event Category": " Xcp job status", "Event Type": "XCP command failure", "Event Source": "NETAPP-01", "Description": " XCP command H:\console_msg\xcp_cifs\xcp\ main .py verify \\\<IP address of SMB server>\cifs \\\<IP address of SMB destination server>\source_vol has failed"

Copyright information

Copyright © 2024 NetApp, Inc. All Rights Reserved. Printed in the U.S. No part of this document covered by copyright may be reproduced in any form or by any means—graphic, electronic, or mechanical, including photocopying, recording, taping, or storage in an electronic retrieval system—without prior written permission of the copyright owner.

Software derived from copyrighted NetApp material is subject to the following license and disclaimer:

THIS SOFTWARE IS PROVIDED BY NETAPP “AS IS” AND WITHOUT ANY EXPRESS OR IMPLIED WARRANTIES, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE, WHICH ARE HEREBY DISCLAIMED. IN NO EVENT SHALL NETAPP BE LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO, PROCUREMENT OF SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA, OR PROFITS; OR BUSINESS INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE) ARISING IN ANY WAY OUT OF THE USE OF THIS SOFTWARE, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE.

NetApp reserves the right to change any products described herein at any time, and without notice. NetApp assumes no responsibility or liability arising from the use of products described herein, except as expressly agreed to in writing by NetApp. The use or purchase of this product does not convey a license under any patent rights, trademark rights, or any other intellectual property rights of NetApp.

The product described in this manual may be protected by one or more U.S. patents, foreign patents, or pending applications.

LIMITED RIGHTS LEGEND: Use, duplication, or disclosure by the government is subject to restrictions as set forth in subparagraph (b)(3) of the Rights in Technical Data -Noncommercial Items at DFARS 252.227-7013 (FEB 2014) and FAR 52.227-19 (DEC 2007).

Data contained herein pertains to a commercial product and/or commercial service (as defined in FAR 2.101) and is proprietary to NetApp, Inc. All NetApp technical data and computer software provided under this Agreement is commercial in nature and developed solely at private expense. The U.S. Government has a non-exclusive, non-transferrable, nonsublicensable, worldwide, limited irrevocable license to use the Data only in connection with and in support of the U.S. Government contract under which the Data was delivered. Except as provided herein, the Data may not be used, disclosed, reproduced, modified, performed, or displayed without the prior written approval of NetApp, Inc. United States Government license rights for the Department of Defense are limited to those rights identified in DFARS clause 252.227-7015(b) (FEB 2014).

Trademark information

NETAPP, the NETAPP logo, and the marks listed at <http://www.netapp.com/TM> are trademarks of NetApp, Inc. Other company and product names may be trademarks of their respective owners.