



使用将新的 MetroCluster 控制器接到有 FC 网

ONTAP MetroCluster

Thom Illingworth, Ivana Devine, Megan Bock
August 15, 2021

This PDF was generated from https://docs.netapp.com/zh-cn/ontap-metrocluster/install-fc/task_fmc_mcc_transition_cable_the_new_mcc_controllers_to_the_exist_fc_fabrics.html on August 31, 2021. Always check docs.netapp.com for the latest.



使用□□将新的 MetroCluster 控制器□接到□有 FC 网□□□ 1

使用□□将新的 MetroCluster 控制器□接到□有 FC 网□□□

在集群模式 ONTAP MetroCluster 配置中的□个控制器上，必□使用□□将 FC-VI □配器和 HBA □接到□有 FC 交□机上的特定端口。

□□

1. 按照下表□ FC-VI 和 HBA 端口布□：

| 站点 A | | 站点 B | |
|---------------------------|----------------------|---------------------------|----------------------|
| □接此站点 A □件和端口 ... | FC_switch_A_1 端口 ... | □接此站点 B □件和端口 ... | FC_switch_B_1 端口 ... |
| controller_A_1 FC-VI 端□ 1 | 32 | controller_B_1 FC-VI 端□ 1 | 32 |
| controller_A_1 HBA 端□ 1 | 33 | controller_B_1 HBA 端□ 1 | 33 |
| controller_A_1 HBA 端□ 2 | 34 | controller_B_1 HBA 端□ 2 | 34 |
| controller_A_2 FC-VI 端□ 1 | 35 | controller_B_2 FC-VI 端□ 1 | 35 |
| controller_A_2 HBA 1 | 36 | controller_B_2 HBA 1 | 36 |
| controller_A_2 HBA 2. | 37 | controller_B_2 HBA 2. | 37 |

2. 使用□□将第一个交□机网□□□中的□个 FC-SAS 网□□接到 FC 交□机。

网□数量因 SAS 存□堆□数量而□。

| 站点 A | | 站点 B | |
|--------------------|----------------------|--------------------|----------------------|
| 使用□□□接此站点 A 网□ ... | FC_switch_A_1 端口 ... | 使用□□□接此站点 B 网□ ... | FC_switch_B_1 端口 ... |
| bridge_A_1_38 | 38 | Bridge_B_1_38 | 38 |
| bridge_A_1_39 | 39 | Bridge_B_1_39 | 39 |

3. 使用□□将第二个交□机网□□□中的□个网□□接到 FC 交□机。

网□数量因 SAS 存□堆□数量而□。

| 站点 A | | 站点 B | |
|-----------------------|----------------------|-----------------------|----------------------|
| 使用□□□接此站点 A 网□ ... | FC_switch_A_2 端口 ... | 使用□□□接此站点 B 网□ ... | FC_switch_B_2 端口 ... |
| Bridge_A_2_38 | 38 | Bridge_B_2_38 | 38 |
| Bridge_A_2_39 | 39 | Bridge_B_2_39 | 39 |

Copyright Information

Copyright © 2021 NetApp, Inc. All rights reserved. Printed in the U.S. No part of this document covered by copyright may be reproduced in any form or by any means-graphic, electronic, or mechanical, including photocopying, recording, taping, or storage in an electronic retrieval system- without prior written permission of the copyright owner.

Software derived from copyrighted NetApp material is subject to the following license and disclaimer:

THIS SOFTWARE IS PROVIDED BY NETAPP "AS IS" AND WITHOUT ANY EXPRESS OR IMPLIED WARRANTIES, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE, WHICH ARE HEREBY DISCLAIMED. IN NO EVENT SHALL NETAPP BE LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO, PROCUREMENT OF SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA, OR PROFITS; OR BUSINESS INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE) ARISING IN ANY WAY OUT OF THE USE OF THIS SOFTWARE, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE.

NetApp reserves the right to change any products described herein at any time, and without notice. NetApp assumes no responsibility or liability arising from the use of products described herein, except as expressly agreed to in writing by NetApp. The use or purchase of this product does not convey a license under any patent rights, trademark rights, or any other intellectual property rights of NetApp.

The product described in this manual may be protected by one or more U.S. patents, foreign patents, or pending applications.

RESTRICTED RIGHTS LEGEND: Use, duplication, or disclosure by the government is subject to restrictions as set forth in subparagraph (c)(1)(ii) of the Rights in Technical Data and Computer Software clause at DFARS 252.277-7103 (October 1988) and FAR 52-227-19 (June 1987).

Trademark Information

NETAPP, the NETAPP logo, and the marks listed at <http://www.netapp.com/TM> are trademarks of NetApp, Inc. Other company and product names may be trademarks of their respective owners.