



XCP 事件記錄

XCP

NetApp
May 21, 2024

目錄

XCP 事件記錄	1
XCP NFS 事件記錄	1
XCP SMB 事件記錄	13

XCP 事件記錄

XCP NFS 事件記錄

檢閱 XCP NFS 的事件記錄範例。

下表顯示 XCP NFS 的事件記錄。

事件ID	事件範本	事件範例
401	Mounted on NFS export <mount path> with maximum read block size <read block size> bytes, maximum write block size <write block size> bytes. Mount point has mode value<mode bits> and type: <fattr3 type>.	2020-07-14 03:53:59,811 - INFO {"Event ID":401, "Event Category": "Mounting unmounting file system", "Event Type": "Mount file system information", "ExecutionId": 408249379415, "Event Source": "NETAPP-01", "Description": "Mounted on NFS export <IPaddress of NFS server>:/test1 with maximum read block size 65536 bytes, maximum write block size 65536 bytes. Mount point has mode value 493 and type : Directory"}
181	This license is issued to <username>of <company name>,license type is <license type> with <license status> status, license will expire on <expire date>	2020-07-14 03:53:59,463 - INFO {"Event ID": 181, "Event Category": "Authentication and authorization", "Event Type": "License information", "ExecutionId": 408249379415, "Event Source": "NETAPP-01", "Description": "This license is issued to NetApp User of Network Appliance, Inc, license type is SANDBOX with ACTIVE status, license will expire on Thu Jul 1 00:00:00 2021"}

事件ID	事件範本	事件範例
183	The license issued to <username> of <company name> will expire in less than one week	2020-07-14 04:02:55,151 - WARNING {"Event ID": 183, "Event Category": "Authentication and authorisation", "Event Type": "License warning", "ExecutionId": 408249519546, "Event Source": "NETAPP-01", "Description": "The license issued to NetApp User of Network Appliance, Inc will expire in less than one week"}
581	Catalog path <catalog volume path> to store catalog directory is not accessible. Refer user guide for configuring catalog volume.	2020-07-14 04:05:00,857 - ERROR {"Event ID": 581, "Event Category": "Catalog and indexing", "Event Type": "Catalog exporting error", "ExecutionId": 408249552351, "Event Source": "NETAPP-01", "Description": "Catalog path <IP address of NFS server>:/test11 to store catalog directory is not accessible. Refer user guide for configuring catalog volume."}
582	Failed creating catalog directory in catalog volume path <catalog volume path>	2020-07-14 04:10:12,895 - ERROR {"Event ID": 582, "Event Category": "Catalog and indexing", "Event Type": "Catalog directory creation error", "ExecutionId": 408249630498, "Event Source": "NETAPP-01", "Description": "Failed creating catalog directory in catalogvolume path 10.234.104.250:/cat_vol"}

事件ID	事件範本	事件範例
584	Error in creating index directory <index id> for <command>	2020-07-14 04:52:15,918 - ERROR {"Event ID":584, "Event Category": "Catalog and indexing", "Event Type": "Error in index creation", "ExecutionId": 408250278214, "Event Source": "NETAPP-01", "Description": "Error in creating index directory abc7 for scan"}
586	Failed to create index <index id> in catalog volume while executing command : <command>	2020-07-14 04:45:46,275 - ERROR {"Event ID": 586, "Event Category": "Catalog and indexing", "Event Type": "Error in index creation", "ExecutionId": 408250177021, "Event Source": "NETAPP-01", "Description": "Failed to create index abc6 in catalog volume while executing command : scan {- newid: 'abc6'}"}
351	System resources available while executing xcp command: <command>, are : <CPU info>, <memory info>	2020-07-14 05:08:35,393 - INFO {"Event ID":351, "Event Category": "System resource utilization", "Event Type": "Resources available for scan", "ExecutionId": 408250529264, "Event Source": "NETAPP-01", "Description": "System resources available while executing xcp command : scan , are : CPU: count 4, load avg (1/5/15m) 0.0, 0.0, 0.0, System memory (GiB): avail 7.3, total 7.8, free 6.6, buffer 0.1, cache 0.5"}

事件ID	事件範本	事件範例
13.	XCP <command> is running on platform <platform info> for source <source info>	2020-07-14 05:08:35,478 - INFO {"Event ID": 13, "Event Category": "XCP job status", "Event Type": "Starting xcp scan operation", "ExecutionId": 408250529264, "Event Source": "NETAPP-01", "Description": "XCP command : scan {-newid: 'abc7'} is running on platform Linux-2.6.26-2-amd64-x86_64-with-debian- 5.0.10 for source 10.234.104.250:/test1"}
14.	XCP scan completed successfully after scanning <scan item count> items. Source : <source scanned>	2020-07-14 05:08:35,653 - INFO {"Event ID": 14, "Event Category": "XCP job status", "Event Type": "XCP scan completion", "ExecutionId": 408250529264, "Event Source": "NETAPP-01", "Description": "XCP scan completed successfully after scanning 479 items. Source : 10.234.104.250:/test1"}
354	System resources available while executing xcp command: <command>, are : <CPU info>, <memory info>	2020-07-14 05:15:13,562 - INFO {"Event ID": 354, "Event Category": "System resource utilization", "Event Type": "Resources available for copy", "ExecutionId": 408250596708, "Event Source": "NETAPP-01", "Description": "System resources available while executing xcp command : copy , are : CPU: count 4, load avg (1/5/15m) 0.0, 0.0, 0.0, System memory (GiB): avail 7.3, total 7.8, free 6.6, buffer 0.1, cache 0.5"}

事件ID	事件範本	事件範例
25.	XCP <command> is running on platform <platform info> for source <copy source> and destination <copy destination/target>	2020-07-14 05:15:13,647 - INFO {"Event ID": 25, "Event Category": "XCP job status", "Event Type": "Starting xcp copy operation", "ExecutionId": 408250596708, "Event Source": "NETAPP-01", "Description": "XCP command : copy {} is running on platform Linux-2.6.26- 2-amd64-x86 64-with-debian-5.0.10 for source <IP address of NFS server>:/source_vol and destination <NFS destination source>:/test1"}
26	XCP copy completed successfully after scanning <scanned item count> of which <matched item count> are matched and <copied item count> items are copied to the destination. Source : <copy source>, destination :<copy destination/target	2020-07-14 05:15:13,885 - INFO {"Event ID":26, "Event Category": "XCP job status", "Event Type": "XCP copy completion", "ExecutionId": 408250596708, "Event Source": "NETAPP-01", "Description": "XCP copy completed successfully after scanning 3 of which 0 are matched and 2 items are copied to the destination. Source : <IP address of NFS server>:/source_vol, destination : <NFS destination source>:/test1"}

事件ID	事件範本	事件範例
16.	XCP <command> is running on platform <platform info> for source <sync source> and destination <sync destination>	2020-07-14 06:41:20,145 - INFO {"Event ID": 16, "Event Category": "XCP job status", "Event Type": "Starting xcp sync operation", "ExecutionId": 408251920146, "Event Source": "NETAPP-01", "Description": "XCP command : sync {-id: 'autoname_copy_2020-07-14_06.22.07.233271'} is running on platform Linux-2.6.26-2-amd64-x86_64-with-debian-5.0.10 for source <IP address of NFS server>:/src_vol and destination <NFS destination source>:/dest_vol"}
352	System resources available while executing xcp command: <command>, are : <CPU info>, <memory info>	2020-07-14 06:41:28,728 - INFO {"Event ID": 352, "Event Category": "System resource utilization", "Event Type": "Resource available for sync", "ExecutionId": 408251920146, "Event Source": "NETAPP-01", "Description": "System resources available while executing xcp command : sync {-id: 'autoname_copy_2020-07-14_06.22.07.233271'} , are : CPU: count 4, load avg (1/5/15m) 0.1, 0.0, 0.0, System memory (GiB): avail 7.2, total 7.8, free 6.6, buffer 0.1, cache 0.5"}

事件ID	事件範本	事件範例
17.	XCP sync is completed. Total scanned <scanned item count>, copied <copied item count>, modification <modification item count>, new file <new file count>, delete item <delete item count>. Command executed : <command>	2020-07-14 06:41:29,245 - INFO {"Event ID":17, "Event Category": "XCP job status", "Event Type": "XCP sync completion", "ExecutionId": 408251920146, "Event Source": "NETAPP-01", "Description": "XCP sync is completed. Total scanned 66, copied 0, modification 1, new file 0, delete item 0. Command executed : sync {-id: 'autoname_copy_2020-07-14_06.22.07.233271'}"}}
19	XCP <command> is running on platform <platform info> for source <verify source> and destination <verify destination>	2020-07-14 06:54:59,084 - INFO {"Event ID": 19, "Event Category": "XCP job status", "Event Type": "Starting xcp verify operation", "ExecutionId": 408252130477, "Event Source": "NETAPP-01", "Description": "XCP command : verify {} is running on platform Linux-2.6.26-2-amd64-x86_64-with- debian-5.0.10 for source <IP address of NFS server>:/src_vol and destination <IP address of NFS destination server>:/dest_vol"}}
353	System resources available while executing xcp command: <command>, are : <CPU info>, <memory info>	2020-07-14 06:54:59,085 - INFO {"Event ID": 353, "Event Category": "System resource utilization", "Event Type": "Resources available for verify", "ExecutionId": 408252130477, "Event Source": "NETAPP-01", "Description": "System resources available while executing xcp command : verify , are : CPU: count 4, load avg (1/5/15m) 0.0, 0.0, 0.0, System memory (GiB): avail 7.3, total 7.8, free 6.6, buffer 0.1, cache 0.5"}}

事件ID	事件範本	事件範例
211	log file path : <file path> , severity filter level <severity level>, log message sanitization is set as <sanitization value>	2020-07-14 06:40:59,104 - INFO { "Event ID": 211, "Event Category": "Logging and supportability", "Event Type": "XCP logging information", "ExecutionId": 408251920146, "Event Source": "NETAPP-01", "Description": "Log file path : /opt/NetApp/xFiles/xcp/xcplogs/xcp.log, severity filter level INFO, log message sanitization is set as False" }
2..	Event file path: <file path>, severity filter level <severity level>, event message sanitization is set as <sanitization value>	2020-07-14 06:40:59,105 - INFO { "Event ID": 215, "Event Category": "Logging and supportability", "Event Type": "XCP event information", "ExecutionId": 408251920146, "Event Source": "NETAPP-01", "Description": "Event file path : /opt/NetApp/xFiles/xcp/xcplogs/xcp_event.log, severity filter level INFO, event message sanitization is set as False" }
54	Catalog volume is left with no free space please increase the size of catalog volume <catalog volume running out of space>	2020-07-14 04:10:12,897 - ERROR { "Event ID": 54, "Event Category": "Application failure", "Event Type": "No space left on Catalog volume error", "ExecutionId": 408249630498, "Event Source": "NETAPP-01", "Description": "Catalog volume is left with no free space. Please increase the size of catalog volume<IP address of NFS destination server>:/cat_vol" }

事件ID	事件範本	事件範例
53.	Catalog volume <catalog volume> is left with no free space to store index <index id> while executing <command>. Please increase the size of the catalog volume <catalog volume running out of space>	2020-07-14 04:52:15,922 - ERROR {"Event ID": 53, "Event Category": "Application failure", "Event Type": "No space left for catalog volume error", "ExecutionId": 408250278214, "Event Source": "NETAPP-01", "Description": "Catalog volume 10.234.104.250:/cat_vol is left with no free space to store index abc7 while executing : scan {-newid: 'abc7'}. Please increase the size of the catalog volume <IP address of NFS destination server>:/cat_vol"}
61.	NFS LIF <LIF IP> is not reachable for path <volume path without IP> while executing <command>. Please check volume is not offline and is reachable.	2020-07-14 07:38:20,100 - ERROR {"Event ID":61, "Event Category": "Application failure", "Event Type": "NFS mount has failed", "ExecutionId": 408252799101, "Event Source": "NETAPP-01", "Description": "NFS LIF <IP address of NFS destination server> is not reachable for path /test11 while executing : scan {}. Please check volume is not offline and is reachable"}
71	TCP connection could not be established for IP address <IP>. Check network setting and configuration.	2020-07-14 07:44:44,578 - ERROR {"Event ID": 71, "Event Category": "Application failure", "Event Type": "IP is not active", "ExecutionId": 408252889541, "Event Source": "NETAPP-01", "Description": "TCP connection could not be established to the address <IP address of NFS destination server>. Check network setting and configuration."} (UT done)

事件ID	事件範本	事件範例
51	Target volume is left with no free space while executing: <command>. Please increase the size of target volume <volume running out of space>.	2020-07-14 07:07:07,286 - ERROR {"Event ID": 51, "Event Category": "Application failure", "Event Type": "No space left on destination error", "ExecutionId": 408252316712, "Event Source": "NETAPP-01", "Description": "Target volume is left with no free space while executing : copy {}. Please increase the size of target volume <IP address of NFS destination server>:/cat_vol"}
76	Index id {} is already present . Use new index id and rerun command : <command>	2020-07-14 09:18:41,441 - ERROR {"Event ID": 76, "Event Category": "Application failure", "Event Type": "Index ID problem", "ExecutionId": null, "Event Source": "NETAPP-01", "Description": "Index id asd is already present . Use new index id and rerun command: scan {-newid: 'asd'} "}
363.62	CPU usage has crossed <percentage CPU used>%	2020-06-16 00:17:28,294 - ERROR {"Event ID": 362, "Event Category": "System resource utilization", "Event Type": "resources available for xcp", "Event Source": "NETAPP- 01 ", "Description": "CPU Usage has crossed 90.07%"}
363	Memory Usage has crossed <percentage memory used>%	2020-06-16 00:17:28,300 - ERROR {"Event ID": 363, "Event Category": "System resource utilization", "Event Type": "resources available for xcp", "Event Source": "NETAPP- 01", "Description": "Memory Usage has crossed 95%"}

事件ID	事件範本	事件範例
22	XCP <command> is running on platform <platform information> for source <resume source> and destination <resume destination>	2020-07-14 06:24:26,768 - INFO {"Event ID": 22, "Event Category": "XCP job status", "Event Type": "Starting xcp resume operation", "ExecutionId": 408251663404, "Event Source": "NETAPP-01", "Description": "XCP command : resume {-id: 'autoname_copy_2020-07-14_06.22.07.233271'} is running on platform Linux-2.6.26-2-amd64- x86_64-with-debian-5.0.10 for source <IP address for NFS sever>:/src_vol and destination <IP address of NFS destination server>:/dest_vol"}
356	System resources available while executing xcp command: <command> , are : <CPU info>, <memory information>	2020-07-14 06:24:26,837 - INFO {"Event ID": 356, "Event Category": "System resource utilization", "Event Type": "Resource available for resume", "ExecutionId": 408251663404, "Event Source": "NETAPP-01", "Description": "System resources available while executing xcp command : resume {-id: 'autoname_copy_2020-07-14_06.22.07.233271'} , are : CPU: count 4, load avg (1/5/15m) 0.1, 0.1, 0.0, System memory (GiB): avail 7.2,total 7.8, free 6.6, buffer 0.1, cache 0.5"}

事件ID	事件範本	事件範例
23	XCP resume is completed. Total scanned items <scanned item count>, total copied items <copied item count>. Command executed :<command>	2020-07-14 06:26:15,608 - INFO {"Event ID": 23, "Event Category": "XCP job status", "Event Type": "XCP resume completion", "ExecutionId": 408251663404, "Event Source": "NETAPP-01", "Description": "XCP resume is completed. Total scanned items 5982, total copied items 5973. Command executed : resume {-id: 'autoname_copy_2020-07-14_06.22.07.233271'} "}
76	Index id <index id> is already present. Use new index id and rerun command : <command>	2020-07-14 09:43:08,381 - ERROR {"Event ID": 76, "Event Category": "Application failure", "Event Type": "Index ID problem", "ExecutionId": null, "Event Source": "NETAPP-01", "Description": "Index id asd is already present . Use new index id and rerun command : scan {-newid: 'asd'} "}
82	Index id <index id> used while executing sync is incomplete. Try resume on the existing index id <index id>	2020-07-14 10:33:09,307 - ERROR {"Event ID": 82, "Event Category": "Application failure", "Event Type": "Incomplete index used for sync", "ExecutionId": null, "Event Source": "NETAPP-01", "Description": "Index id autoname_copy_2020-07-14_10.28.22.323897 used while executing sync is incomplete. Try resume on the existing index id autoname_copy_2020-07-14_10.28.22.323897."}

事件ID	事件範本	事件範例
365	CPU utilization reduced to <CPU percentage used>%	2020-07-14 09:43:08 381 - ERROR {"Event ID": 364, "Event Category": "System resource utilization", "Event Type": "Resources available for xcp", "ExecutionId": 408251663404, "Event Source": "NETAPP-01", "Description": " CPU utilization reduced to 26%}
364	Memory utilization reduced to <CPU percentage used>%	2020-07-14 09:43:08,381 - INFO {"Event ID": 364, "Event Category": " Resources available for xcp", "Event Type": "Resources available for xcp", "ExecutionId": 408351663478, "Event Source": "NETAPP-01", "Description": " Memory utilization reduced to 16.2%"}
10.	XCP command <command> has failed	2020-07-14 09:43:08,381 - INFO {"Event ID": 10, "Event Category": " Xcp job status", "Event Type": "XCP command failure", "ExecutionId":4082516634506, "Event Source": "NETAPP-01", "Description": " XCP command verify has failed"

XCP SMB 事件記錄

檢閱 XCP SMB 的事件記錄範例。

下表顯示 XCP SMB 的事件記錄。

事件ID	事件範本	事件範例
355	CPU usage has crossed <CPU percentage use>%	2020-06-23 12:42:02,705 - INFO {"Event ID": 355, "Event Category": "System resource utilization", "Event Type": "CPU usage for xcp", "Event Source": "NETAPP-01", "Description": "CPU usage has crossed 96%"}

事件ID	事件範本	事件範例
356	Memory usage has crossed <memory percentage use>%	2020-06-23 12:42:02,705 - INFO { "Event ID": 356, "Event Category": "System resource utilization", "Event Type": "Memory usage for xcp", "Event Source": "NETAPP-01", "Description": "CPU usage has crossed92.5%" }
61.	Address was not found: <complete address over which command is fired>	2020-07-15 02:57:06,466 - ERROR { "Event ID": 61, "Event Category": "Application Failure", "Event Type": "Address was not found", "ExecutionId": 408264113696, "Event Source": "NETAPP-01", "Description": "Address was not found: '\\\\<IP address of SMB server>\\cifs1\""} }
62.	Interface cannot be found: < complete address over which command is fired >	2020-07-15 02:52:00,603 - ERROR { "Event ID": 62, "Event Category": "Application Failure", "Event Type": "Interface was not found", "ExecutionId": 408264071616, "Event Source": "NETAPP-01", "Description": "Interface cannot be found: '\\\\<IP address of SMB server>\\cifs11\""} }
63.	Invalid Address. Pleased make sure that the Address starts with '\\'	2020-07-15 03:00:10,422 - ERROR { "Event ID": 63, "Event Category": "Application Failure", "Event Type": "Invalid Address", "ExecutionId": 408264197308, "Event Source": "NETAPP-01", "Description": "Invalid Address. Please make sure that the Address starts with '\\'" }

事件ID	事件範本	事件範例
41	Destination volume is left with no free space please increase the size target volume:<destination volume>	2020-06-15 17:12:46,413 - ERROR { "Event ID": 41, "Event Category": "Application Failure", "Event Type": "No space left on destination error", "Event Source": "NETAPP-01", "Description": "Destination volume is left with no free space please increase the size of target volume: <IP address of SMB server>\\to" }
211	Log file path : <file path>, severity filter level <severity level>, log message sanitization is set as <value of sanitization option>	{ "Event ID": 211, "Event Category": "Logging and supportability", "Event Type": "XCP logging information", "ExecutionId": 408252673852, "Event Source": "NETAPP-01", "Description": "Log file path : C:\\NetApp\\XCP\\Logs\\xcp.log, severity filter level DEBUG, log message sanitization is set as False" }
2..	Event file path : <file path>, severity filter level <severity level>, Event message sanitization is set as <sanitization option>	{ "Event ID": 215, "Event Category": "Logging and supportability", "Event Type": "XCP event information", "ExecutionId": 408252673852, "Event Source": "NETAPP-01", "Description": "Event file path : C:\\NetApp\\XCP\\Logs\\xcp_event.log, severity filter level INFO, Event message sanitization is set as False" }

事件ID	事件範本	事件範例
181	This license is issued to <user name> of <company name>, license type is <license type> with <status> status, license will expire expires on <expiration date>	{"Event ID": 181, "Event Category": "Authentication and authorization", "Event Type": "license information", "ExecutionId": 408252673852, "Event Source": "NETAPP-01", "Description": "This license is issued to calin of NetApp Inc, license type is SANDBOX with ACTIVE status, license will expire on Mon Dec 31 00:00:00 2029"}
13.	XCP <command> is running on platform <platform information> for source <scan source>	2020-07-15 02:12:56,917 - INFO {"Event ID": 13, "Event Category": "XCP job status", "Event Type": "Starting xcp scan operation", "ExecutionId": 408263470688, "Event Source": "NETAPP-01", "Description": "XCP {scan} is running on platform Windows- 8.1-6.3.9600-SP0 for source \\\\ <ip address="" of="" server="" smb="">\cifs"}</ip>
351	System resources available while command : <command>, are : cpu <CPU information>, total memory <total memory on system>, available memory	2020-07-15 02:12:56,917 - INFO {"Event ID": 351, "Event Category": "System resource utilization", "Event Type": "Resources available for scan", "ExecutionId": 408263470688, "Event Source": "NETAPP-01", "Description": "System resources available while executing xcp command : scan, are : cpu 4, total memory 8.00GiB, available memory 6.81GiB"}

事件ID	事件範本	事件範例
14.	XCP scan completed successfully after scanning <scanned items count> items. Source :<scan source>	2020-07-15 02:12:57,932 - INFO {"Event ID": 14, "Event Category": "XCP job status", "Event Type": "XCP scan completion", "ExecutionId": 408263470688, "Event Source": "NETAPP-01", "Description": "XCP scan completed successfully after scanning 29 items. Source : \\ \\ \\ <IP address of SMB server> \\ \cifs"}
25.	XCP <command> is running on platform <platform information> for source <copy source> and destination <copy destination>	2020-07-15 02:19:06,562 - INFO {"Event ID": 25, "Event Category": "XCP job status", "Event Type": "Starting xcp copy operation", "ExecutionId": 408263563552, "Event Source": "NETAPP-01", "Description": "XCP {copy} is running on platform Windows- 8.1-6.3.9600-SP0 for source \\ \\ \\ <IP address of SMB server> \\ \cifs and destination \\ \\ \\ <IP address of SMB destination server> \\ \source_vol"}
352	System resources available while executing command :<command>, are : cpu <CPU information>, total memory <Total memory>, available memory <memory available for execution>	2020-07-15 02:19:06,562 - INFO {"Event ID": 352, "Event Category": "System resource utilization", "Event Type": "Resources available for copy", "ExecutionId": 408263563552, "Event Source": "NETAPP-01", "Description": "System resources available while executing xcp command : copy, are : cpu 4, total memory 8.00GiB, available memory 6.82GiB"}

事件ID	事件範本	事件範例
26	XCP copy completed successfully after copying <copied items count> items. Source :<copy source>, destination : <copy destination>	2020-07-15 02:19:14,500 - INFO {"Event ID": 26, "Event Category": "XCP job status", "Event Type": "XCP copy completion", "ExecutionId": 408263563552, "Event Source": "NETAPP-01", "Description": "XCP copy completed successfully after copying 0 items. Source :
16.	XCP <command> is running on platform <platform> for source <sync source> and destination <sync destination>	2020-07-15 02:27:10,490 - INFO {"Event ID": 16, "Event Category": "XCP job status", "Event Type": "Starting xcp sync operation", "ExecutionId": 408263688308, "Event Source": "NETAPP-01", "Description": "XCP {sync} is running on platform Windows- 8.1-6.3.9600-SP0 for source \\<IP address of SMB server>\\cifs and destination \\<IP address of SMB destination server>\\source_vol"}
353	System resources available while executing xcp command: <command>, are : cpu <CPU information>, total memory <total memory>, available memory <available memory>	2020-07-15 02:27:10,490 - INFO {"Event ID": 353, "Event Category": "System resource utilization", "Event Type": "Resources available for sync", "ExecutionId": 408263688308, "Event Source": "NETAPP-01", "Description": "System resources available while executing xcp command : sync, are : cpu 4, total memory 8.00GiB, available memory 6.83GiB"}

事件ID	事件範本	事件範例
17.	XCP sync completed successfully after scanning <scanned item count> items, copying <copied item count> items, comparing <compared item count> items, removing <removed item count> items. Source : <sync source>, destination : <sync destination>	2020-07-15 03:04:14,269 - INFO {"Event ID": 17, "Event Category": "XCP job status", "Event Type": "XCP sync completion", "ExecutionId": 408264256392, "Event Source": "NETAPP-01", "Description": "XCP sync completed successfully after scanning30 items, copying 20 items, comparing 30 items, removing 0 items. Source : \\\\<IP address of SMB server>\\cifs, destination :\\\\<IP address of SMB destination server>\\source_vol"}
19	XCP <command> is running on platform <platform information> for source <verify source> and destination <verify destination>	2020-07-15 03:14:04,854 - INFO {"Event ID": 19, "Event Category": "XCP job status", "Event Type": "Starting xcp verify operation", "ExecutionId": 408264409944, "Event Source": "NETAPP-01", "Description": "XCP {verify -noacl} is running on platform Windows-8.1-6.3.9600-SP0 for source \\\\<IP address of SMB server>\\cifs and destination \\\\<IP address of SMB destination server>\\source_vol"}
354	System resources available for command : <command>, are : cpu <CPU information>, total memory <total memory>, available memory <available memory for execution>	2020-07-15 03:14:04,854 - INFO {"Event ID": 354, "Event Category": "System resource utilization", "Event Type": "Resources available for verify", "ExecutionId": 408264409944, "Event Source": "NETAPP-01", "Description": "System resources available while executing xcp command : verify, are : cpu 4, total memory 8.00GiB, available memory 6.80GiB"}

事件ID	事件範本	事件範例
20.	XCP verify is completed by scanning <scanned item count> items, comparing <compared item count> items	{"Event ID": 20, "Event Category": "XCP job status", "Event Type": "XCP verify completion", "command Id": 408227440800, "Event Source": "NETAPP-01", "Description": "XCP verify is completed by scanning 59 items, comparing 0 items"}
357	CPU utilization reduced to <CPU utilization percentage>%	{"Event ID": 357, "Event Category": "System resource utilization", "Event Type": "CPU usage for xcp", "Event Source": "NETAPP- 01", "Description": "CPU utilization reduced to 8.2%"}
358	Memory utilization reduced to <memory utilization percentage>%	{"Event ID": 358, "Event Category": "System resource utilization", "Event Type": "Memory usage for xcp", "Event Source": "NETAPP-01", "Description": "Memory utilization reduced to 19%"}
10.	XCP command <command> has failed	2020-07-14 09:43:08,381 - INFO {"Event ID": 10, "Event Category": " Xcp job status", "Event Type": "XCP command failure", "Event Source": "NETAPP-01", "Description": " XCP command H:\console_msg\xcp_cifs\xcp\ \ main .py verify \\\\ address of SMB server>\cifs \\\<IP address of SMB destination server>\source_vol has failed"

版權資訊

Copyright © 2024 NetApp, Inc. 版權所有。台灣印製。非經版權所有人事先書面同意，不得將本受版權保護文件的任何部分以任何形式或任何方法（圖形、電子或機械）重製，包括影印、錄影、錄音或儲存至電子檢索系統中。

由 NetApp 版權資料衍伸之軟體必須遵守下列授權和免責聲明：

此軟體以 NETAPP「原樣」提供，不含任何明示或暗示的擔保，包括但不限於有關適售性或特定目的適用性之擔保，特此聲明。於任何情況下，就任何已造成或基於任何理論上責任之直接性、間接性、附隨性、特殊性、懲罰性或衍生性損害（包括但不限於替代商品或服務之採購；使用、資料或利潤上的損失；或企業營運中斷），無論是在使用此軟體時以任何方式所產生的契約、嚴格責任或侵權行為（包括疏忽或其他）等方面，NetApp 概不負責，即使已被告知有前述損害存在之可能性亦然。

NetApp 保留隨時變更本文所述之任何產品的權利，恕不另行通知。NetApp 不承擔因使用本文所述之產品而產生的責任或義務，除非明確經過 NetApp 書面同意。使用或購買此產品並不會在依據任何專利權、商標權或任何其他 NetApp 智慧財產權的情況下轉讓授權。

本手冊所述之產品受到一項（含）以上的美國專利、國外專利或申請中專利所保障。

有限權利說明：政府機關的使用、複製或公開揭露須受 DFARS 252.227-7013（2014 年 2 月）和 FAR 52.227-19（2007 年 12 月）中的「技術資料權利 - 非商業項目」條款 (b)(3) 小段所述之限制。

此處所含屬於商業產品和 / 或商業服務（如 FAR 2.101 所定義）的資料均為 NetApp, Inc. 所有。根據本協議提供的所有 NetApp 技術資料和電腦軟體皆屬於商業性質，並且完全由私人出資開發。美國政府對於該資料具有非專屬、非轉讓、非轉授權、全球性、有限且不可撤銷的使用權限，僅限於美國政府為傳輸此資料所訂合約所允許之範圍，並基於履行該合約之目的方可使用。除非本文另有規定，否則未經 NetApp Inc. 事前書面許可，不得逕行使用、揭露、重製、修改、履行或展示該資料。美國政府授予國防部之許可權利，僅適用於 DFARS 條款 252.227-7015(b)（2014 年 2 月）所述權利。

商標資訊

NETAPP、NETAPP 標誌及 <http://www.netapp.com/TM> 所列之標章均為 NetApp, Inc. 的商標。文中所涉及的所有其他公司或產品名稱，均為其各自所有者的商標，不得侵犯。